NUTS & VOLTS
MAGAZINE

OUR 18th YEAR

$3.50
VOL. 18 NO. 12
DECEMBER 1997

Exploring Electronics And Technology For The Hobbyist And Professional

Merry Christmas from Nuts & Volts

12>
0 74470 89295 3

CLONE, FORMAT, REPAIR AND TEST ANY DISK DRIVE.

STAND ALONE DRIVE DUPE-IT CLONES ENTIRE DRIVES

Copy entire hard drives with ease. Why spend hours installing and formatting drives when you can do it instantly with Drive Dupe-It! Set up any SCSI or IDE drive with all your original software. Connect blank drives and press start. You'll copy entire drives instantly!

With our combo IDE/SCSI model, you can copy entire hard disk images from IDE to SCSI or vice-versa.

HOT NEW TECHNOLOGY REPAIRS DRIVES

Don't throw those used drives away! Breathe new life into old drives with Drive Dupe-It! Reassign and eliminate bad SCSI blocks and IDE defects. Put the built-in drive repair system to work for you. Here's how it works: First, a precise analysis system scans the disk surfaces for errors. Defects are then mapped around and effectively "erased". The built-in error correcting system "trains" the drive to permanently avoid defective areas. Your data is stored only on safe areas of the disk. Capacity is reduced by an insignificant amount, and the drive works flawlessly once again.

Get the technology used by major repair shops and data recovery centers. Drive Dupe-It repairs all disk defects caused by normal wear. Drives with excessive mechanical damage may not be repairable.

PRO MODEL INCLUDES FACTORY TEST SYSTEM

Choose the Dupe-It Pro, and you'll also have an entire factory drive test system for under $1000. The Pro model gives you the ability to copy, reformat, repair, translate, and test any hard disk drive. Use the Pro to put any hard drive through its paces. A full factory final test and performance analysis is performed. Complete test and repair reports are sent to any standard printer.

STAND ALONE IDE DRIVE DUPE-IT
P/N IDI ..... $395.

IDE DRIVE DUPE-IT WITH DRIVE MECHANIC
P/N IDI2 ..... $495.

COMBO IDE AND SCSI DRIVE DUPE-IT WITH TRANSLATOR
P/N SDI ..... $595.

IDE AND SCSI DUPE-IT WITH TRANSLATOR AND DRIVE MECHANIC
P/N SDI2 ..... $795.

PRO MODEL LOADED WITH IDE AND SCSI INTERFACES, TRANSLATOR, DRIVE MECHANIC, AND DRIVE DIAGNOSTIC TEST SOFTWARE WITH PRINTER PORT
P/N SDIPRO ..... $995.

CORPORATE SYSTEMS CENTER
www.corpsys.com

ORDER FACTORY DIRECT:

408-743-8739

CD DUPE-IT! IS SOLD AND INTENDED FOR BACKUP AND IN-HOUSE DUPLICATION PURPOSES ONLY. COPYRIGHT LAWS MUST BE OBSERVED. CALL FOR RACK MOUNT AND MULTI-DRIVE COPIERS.

Write in 211 on Reader Service Card.

COPY ANY CD INSTANTLY!

CD DUPE-IT!

Instantly duplicate CD-ROM disks for software distribution. Make spare backup copies of your favorite software on rugged, permanent media. Produce disks quickly and economically. No mastering or multimedia experience is required.

ONE BUTTON OPERATION. NO PC NEEDED.

Insert your original disk and press "start". The multimedia processor quickly copies any disk to the internal A/V hard drive. Insert blank disks and make as many copies as you like. You'll produce identical, bit-for-bit duplicates. The system is totally self contained — no connection to a PC or Mac is required. Just plug it in and press "start". You'll get perfect copies of audio and CD-ROM disks.

BUILD YOUR OWN CUSTOM AUDIO DISKS!

You can even make your own custom audio disks without a PC! Insert your original CD's, select the tracks you want, and copy them to the internal hard drive. Then insert a blank CD-R, and you'll have a custom audio disk with just the songs you want.

With the included CD mastering software, CD Dupe-It will work overtime. Just attach a SCSI cable to your PC or Mac, and you're ready to design and create your own original CD's.

CD DUPE-IT!.....$1295
CASE OF 100 BLANK DISKS.....$159

HSC Electronic Supply

Serving Silicon Valley since 1964!

...brings you a potpourri of high-tech goodies for the techno-tinkerer!
For thirty years we have been your source for Silicon Valley exotica!

Sound Card Spectacular!

Four styles to choose from:

MediaVision ProAudio Wavetable Sound Card
- IDE interface for CD/ROM drive
- Full featured sound capability, incl. Wavetable, 24 voice
- Win 3.XX, Win '95 compatible, accepts Korg Pro upgrade
- New in retail box, 90-day HSC warranty

HSC#17034 **$29.95**

MediaVision Premium 3D Sound Card
- 16-bit audio, 44.1KHz digitized stereo sound
- MPU 401 MIDI, Soundblaster compat., SRS 3-D circuitry
- Internal SCSI-2 CD-ROM port, microphone jack (mike not included), line-in & speaker jacks, joystick port
- Includes driver disks, photocopied book
- OEM package (no box), 90-day HSC warranty
- We had these and ran out...New stock at Lower Price!

HSC#17035 **$29.95**

MediaVision ProZonic Sound Card
- IDE interface for CD/ROM drive
- 16-bit audio, 44.1KHz digitized stereo sound
- MPU 401 MIDI, Soundblaster compat., MPC1 & MPC2
- Plug n' Play Windows '95 compatible
- New in OEM package (no box), 90-day HSC warranty
- Includes driver disks, photocopied book

HSC#17028 **$13.95**

Media Vision ProAudio Spectrum Sound Card
- 16-bit audio, 44.1KHz stereo sound
- MPU 401 MIDI emulation, Soundblaster compatible
- Internal SCSI CD-ROM port, microphone jack (mike not included), line-in, speaker jack, joystick port
- Includes driver disk, information sheet (no book)
- OEM package (no box), 90-day warranty

HSC#17049 **$19.95**

Media Vision PCMCIA Sound!

- Great for Portables, Laptops with PCMCIA Slot
- External pod has joystick port, mic. input, line in & line out jacks, volume control.
- Installation software, instructions included
- Windows 3.x, Windows 95 compatible
- New in OEM packaging (no box), 90-day HSC warranty
- We had these before at $39.95 and they went fast!

HSC#17036 **$29.95**

4X Multimedia Blowout!

- MediaVision 4X Multimedia Kit has everything!
- SCSI CD-ROM Drive, Wavetable Sound card with SCSI controller, small external speakers, eight CD titles!
- Full retail kit, all cables, installation software included
- Spanish language manuals and installation video, but installation disks are multilingual.
- New in box (Spanish language labels)- 90 day warranty
- Hurry, they will go fast at this price!

HSC#17055 **$59.95**

Low Price, High Quality!

- Superior quality in a PS-2 compatible keyboard!
- Hewlett Packard part #A2840-60207
- 102-key keyboard has standard QWERTY layout with additional French characters (Hey, Canadians!)
- PS/2 style connector (mini-DIN)
- New in box, 90-day warranty
- Similar to illustration



HSC#17030 **$14.95**

Stereo Keyboard!

- Multimedia Stereo Keyboard by SC&T International
- Built-in high power stereo speakers & amplifier
- Full range 4" bass enhanced, hi-fidelity 16 watt speakers
- Works with all sound cards & CD-ROM drives
- Or use with portable radio, cassette or CD player
- Separate Volume, Bass, Treble & Balance slide controls
- Built-in LED volume level bar-graph display
- Built-in omnidirectional microphone, plus mic. jack
- Headphone jack for private listening (headphones incl.)
- New in box, 90-day HSC warranty

HSC#17027 **$37.50**

Phone Voice Scrambler

- Privacy at the push of a button -- SecureTalk by GRE!
- Advanced circuitry encrypts telephone conversations from casual eavesdropping, including scanners!
- Small, portable units operate off AC adapter (Land-line model) or cigarette lighter plug (Cellular model).
- Measures 7" x 4" x 1.5", operates on 9 -12 VDC
- Provides a choice of 32 different scrambling codes over 4 channels. Can be bypassed by pressing "Normal" button.
- Sold in pairs, choose AC operation, mobile, or one of each.
- Unit inserts between handset and base of phone (Note, will not work with slim-line or other all-in-one-piece phones!)
- Unit has DB-9 connectors, you will need to fabricate an adapter cable set (DB-9 male & female to mini-modular connectors, diagram provided, ask about parts kit for land-line unit)
- Both styles are identical except for power adapter and one jumper.
- Units are new in box, 90-day warranty - exchange

HSC# 16909 Land-Line Phone Scrambler
HSC# 16910 Cellular Phone Scrambler
Your Choice - any two, any style for $29.95/pr.

Son of SwapBox!

- Just in time...we ran out of the regular SwapBoxes!
- IBM Compatible Reader/Writer for PCMCIA Cards with built-in 1.44 MB Floppy drive...fits in standard floppy bay!
- SwapBox Combo by SCM Microsystems for ISA bus
- Convenient front access for slots (not in rear of system)
- Dual slot, Type I, II or III, hot swappable
- Perfect for transferring data or hardware from laptops, notebooks or other PCMCIA peripherals to desktop PC's
- Directly supported by Windows 95 - no drivers needed!
- Includes DOS driver disk, manuals, cable, internal card
- New in OEM package (white box), 90-day warranty



HSC#16819 **$99.95**

PCI Video Accelerator Cards from Media Vision!

MEDIA VISION PROAxcel

- Blazing fast 64-bit graphic & video card
- PCI Bus card with 1MB RAM, expandable to 2MB
- Uses proprietary chipset (Alliance Semi ProMotion 6410)
- Resolutions up to 800 x 600, 64K colors with 1MB
- Up to 1600 x 1200, 256 colors, 800 x 600, 16M colors (requires 2MB) -- Upgrade chipset available, $7.50
- Supports MPEG, AVI, and other full-motion video formats
- Up to 30 fps full-screen video playback possible (requires 90MHz or better Pentium)
- Win95, NT & 3.1 drivers and full manual on CD-ROM
- If you can not read CD's, diskettes are available, $2 extra
- New in box and have a 90-day HSC Warranty

HSC#16807 Now--Lower Price! $19.95

Hand Scanner Bargain

- Relisys Model HS410G 256 Grayscale Hand Scanner
- Up to 800 dpi (dithered) resolution available
- Brand new OEM pack (styrofoam tray)
- Includes manual, interface card, diskette with TWAIN drivers
- Note: Previous ads in error..no application software is included!
- New, 90 day warranty -- unit is similar to illustration

HSC#17009 **$14.95**

Absolute Last of the Red Hot Reno!

- Now at clearance price -- Media Vision ***Reno***:
  - Consists of new external Reno CD/ROM drive,docking bay with SCSI2 port, AC Adapter, cable kit, travel pouch, headphones
  - Late Model version Uses AC adaptor (included) or AA alkaline batteries (not included)
  - Double-speed 180mS drive is lightning fast!
  - Drive detaches from docking bay, use with headphones as a portable personal audio CD player
  - Great for Mac or IBM (adaptor bracket included)
  - Mac software included
  - SCSI Controller & software required for IBM use
  - Brand new, 90-day warran*

A.

Now - $59.00

Available Separately:
A. Macintosh Powerbook SCSI Adapter (HDI-30 to 25-pin D connector) **HSC#15704 $12.50** if purchased alone, or with purchase of Reno Kit,**$5.00**

Super Sounding Speakers!

Tired of the cheesy sound coming from those give-away speakers in your multimedia kit? Try upgrading to these sonic wonders...you'll have to hear them to appreciate the difference these will make without blowing your budget!

GNT2002 2-way Bass-Reflex speakers
- 3.25" woofer, 1" piezo tweeter, ported enclosure
- 15W built-in amplifiers, 80W peak, 5.4W RMS
- 40 - 20,000 Hz, built-in SRS 3-D stereo
- Measure approx. 3.75" x 6.125" x 9.25" tall
- AC adaptor, audio cables included
- On-off switch, 3-D switch, bass, treble & volume controls
- Attractive off-white finish with grey grille-cloth

HSC#16884 **$34.95**



GNT3500 3-way Bass-Reflex speakers
- 4" woofer, 2" midrange, 1" piezo tweeter
- 23W built-in amplifiers, 120W peak, 20W RMS
- 20 - 20,000 Hz, built-in SRS 3-D stereo
- Measure approx. 6.25" x 6.5" x 9.75" tall
- AC adaptor, audio cables included
- On-off switch, 3-D switch, bass, treble & volume controls
- Attractive off-white finish with grey grille-cloth

HSC#16671 **$39.95**

SCSI Device Cases



16185 16559 16575 16960

- Horizontal style case, 9.5" x 2.5" x 10.5", 30 watt power supply, fan cooled, room for 5.25" drive, front access

HSC#16185 **$29.95**

- Upright Case, 3.5" x 5.5" x 8.125", has front opening for 3.5" drive, 20 watt power supply, no fan

HSC#16559 **$24.95**

- Deluxe quality case, 7" x 4.5" x 10.75", made for Olympus Optical, has 5.25" open front bay, SCSI diagnostic indicator on rear panel, 30 watt fan-cooled power supply, IEC power cord included. Assembled in USA.

HSC#16575 **$49.95**

- Small horizontal case, 6.5" x 2" x 8.5", for 3.5" drives, small 17 watt fan-cooled power supply (5V @ 1A, 12V @ 1A)

HSC#16960 **$37.95**

All cases are new, and feature 50-pin Centronics-style daisy-chain connectors, internal 50-pin cable and SCSI ID switch.

Bargain Game Controller!

- Quickshot QS-191 Game pad for IBM Compatibles
- Faster action, less fatigue than a joystick
- Why pay more for a game device?
- Brand new, plugs into 15-pin game port

HSC#17033 **$3.95**

Skinny SCSI 2X CD-ROM!

- 1" high SCSI 2x (double speed) CD-ROM drive by Toshiba
- Model Number XM-4101B made for Sun Microsystems
- Mounts in regular 5.25" drive bay (with a gap at top of bezel)
- Lavender colored faceplate -- made for laptop computer?
- Meets MPC-2 level specifications, rugged high quality drive!
- Standard SCSI interface, with drive select jumpers on rear
- New, in plain white box, 90-day warranty

HSC#16870 **$29.95**

Infrared Connections!

- IBM "Options" series ISA-Bus and PCMCIA card adaptors will add industry standard infrared communications capability to your desktop PC (with ISA slots) or notebook computer! (Win95 driver available from Microsoft website)
- Allows wireless connection to compatible notebooks, workstations, printers, and other peripherals supporting the Infrared Data Association (IrDA) standard.
- Also will emulate a COM port for cable-less hook-ups
- Communicates up to 115KBps, or up to 1.152MBps with the included TranXit Software.
- Operates over distances up to 3 meters (10 ft.)
- Includes Card, transceiver module, driver disk & book
- Both styles new in box, 90-day warranty

HSC#16483 PCMCIA Version $19.95
HSC#16813 ISA-Bus Version $19.95
***Or a package deal...get both for* $29.95**

Halted specialties co. HSC Electronic Supply

Toll Free (Orders Only) 1-800-4 HALTED (1-800-442-5833)
Internet World Wide Web: http://www.halted.com
3500 Ryder St., Santa Clara, CA 95051 (408) 732-1573 -or-
4837 Amber Ln., Sacramento, CA 95841 (916) 338-2545 *FAX your orders to:*
5681 Redwood Dr., Rohnert Park, CA 94928 (707) 585-7344 *(408) 732-6428*

Visit HSC's Website!

- Pay us a virtual visit on the World Wide Web!
- Simply point your browser to *http://www.halted.com*
- Site is constantly being revised, please visit often!
- Check out the amazing "Gizmo of the Week" feature!

New HSC Catalog !

- Hot off the presses! First one in four years! The wait is over!
- Seventy-six pages of electronics, from ordinary to exotic!
- Phone, fax, write or email to get your copy
- Or drop on by and pick one up...we'd love to see you!

Terms: Some quantities limited; all items subject to prior sale. **Minimum order: $10.00 plus shipping.** Orders under $20.00 subject to $2.00 handling fee, in addition to shipping. All orders shipped FOB Santa Clara, CA (this means you pay freight!) by UPS Surface (no P.O. Boxes) unless otherwise specified, in which case prevailing carrier rate plus $5.00 handling fee applies. Prepaid orders that don't include shipping charges will be shipped freight COD. There is a $4.75 UPS charge added to shipping charges for COD shipments. If you have questions about your order, please call Customer Service at (408) 732-1854 M-F 9AM to 5PM PST.

NUTS & VOLTS MAGAZINE

Published Monthly By
T & L Publications, Inc.
430 Princeland Court
Corona, CA 91719
(909) 371-8497
FAX (909) 371-3052

E-Mail
editor@nutsvolts.com
URL
http://www.nutsvolts.com

Subscription Order ONLY Line
1-800-783-4624

Publisher
Jack Lemieux
N6ZTD
—
Editor
Larry Lemieux
KD6UWV
—
Managing Editor
Robin Nelson
KD6UWS
—
On-The-Road Exhibit Coordinator
Audrey Lemieux
N6VXW
—
Subscriptions
Abby Madain
—
Classified Ads
Natalie Sigafus
—

Copyright 1997
by T & L Publications, Inc.
All Rights Reserved

NOTICE TO ADVERTISERS

All advertising is subject to publisher's approval. We are not responsible for mistakes, misprints or typographical errors. Nuts & Volts Magazine assumes no responsibility for the availability or condition of advertised items or for the honesty of the advertiser. The publisher makes no claims for the legality of any item advertised in Nuts & Volts. This is the sole responsibility of the advertiser. Advertisers and their agencies agree to indemnify and protect the publisher from any and all claims, action or expense arising from advertising placed in Nuts & Volts.

Please send all subscription orders, correspondence, UPS, overnight mail and artwork to: 430 Princeland Court, Corona, CA 91719.

The closing date for each issue is the 10th of the prior month, e.g., the closing date for the June issue is May 10th. Ad copy to be typeset by Nuts & Volts should be received one week prior to the closing date.

Call or write for current advertising rates.

CONTENTS

VOLUME 18 NO. 12 DECEMBER 1997

ARTICLES

RS-232 RELAYS *Ryan Sheldon* **12**
Simplify the task of hardware and software design by learning what tools can get the job done quickly and effectively.

INEXPENSIVE POWER INVERTER CONVERSION PROJECT *Kenton Chun* **18**
With the set-up cost for solar energy being far from free, this project suggests a low-cost solar alternative that produces quality modified sinewave power for your household appliances.

USER'S GUIDE TO AUDIO POWER AMPLIFIER ICs — PART 5 *Ray Marston* **23**
Practical IC-based audio power amplifier circuit design techniques are described in the final episode of this five-part series.

ROBOT WARS 1997: PRETTY HATE MACHINE *Dan Danknick* **34**
Take a look at one of the more novel entries from this year's contest.

BOATERS SEE BIG IMPROVEMENTS IN RADARS *Gordon West* **45**
Although mariners don't have the sophisticated transponders that private pilots now have, it appears that marine radar and radar systems are now getting more sophisticated for the water.

BUILD YOUR OWN MIDI-TO-SYNTHESIZER INTERFACE *Thomas Henry* **52**
Miss the richer and warmer sound of your favorite instruments of yesteryear? Well, with the MTS-100, it's a snap to connect a modern music keyboard, or a personal computer running sequencer software, to your dinosaurs.

ENCYCLOPEDIA OF ELECTRONIC CIRCUITS: PCB LAYOUT — PART 3 *TJ Byers* **103**
In this next installment, the karaoke schematic is converted into a printed circuit board.

COLUMNS

AMATEUR ROBOTICS *Karl Lunt* **61**
Take a brief look at both the Forth language and the powerful Time Processing Unit built into the Motorola 68332.

OPEN CHANNEL *Joseph J. Carr K4IPV* **69**
More radio direction finding, with a look at some additional types of antenna and receiver systems used for RDF activity.

RESOURCE BIN *Don Lancaster* **92**
My secrets of web-based research.

STAMP APPLICATIONS *Jon Williams* **79**
It's time to get real — Part 2. Create an alarm clock using the Pocket Watch B.

DEPARTMENTS

ADVERTISER'S INDEX **112**
CLASSIFIED AD INFO **112**
DEALER DIRECTORY **83**
EVENTS CALENDAR **38**
NEW PRODUCT NEWS **98**
NV ADMART **74-75**
ELECTRONICS Q & A **85**
READER FEEDBACK **5**
TECH FORUM **90**

To Subscribe to NUTS & VOLTS
Send payment to the address below or call 1-800-783-4624 and use your Visa or MasterCard.

USA ONLY
$19.00 — One Year **$35.00 — Two Years**

MAILED FIRST CLASS — FOREIGN ONLY
$37.00 — Canada/Mexico **$100.00 — Foreign/Air Mail**
$50.00 — Foreign/Surface

Nuts & Volts Magazine, 430 Princeland Court, Corona, CA 91719

EDITORIAL CONTRIBUTIONS

Nuts & Volts Magazine encourages article submissions and queries. Send a SASE for a copy of our writer's guidelines.

All submissions should be on 5-1/4 or 3-1/2 inch diskettes and include hard copy as well. If return of materials is requested, include a SASE with your submission.

Deadlines should be discussed in advance with the editor, but generally all material should be submitted by the 1st of the month for the next month's issue.

CHANGE OF ADDRESS

If you are moving, notify us AS SOON AS POSSIBLE so we can continue your subscription without interruption.

Your magazine WILL NOT automatically be forwarded to you by the post office, so it's important to submit your change of address directly to Nuts & Volts.

We will not be able to replace missed issues of the magazine due to unreported address changes.

When you send in your new address, include a current mailing label from the magazine with your account number on it. If you do not have a mailing label, be sure to include your old address and the name(s) under which the subscription was submitted.

INDEX TO CLASSIFIED ADS

10. Ham Gear for Sale 6
20. Ham Gear Wanted 8
30. CB/Scanners 8
40. Music & Accessories 9
50. Computer Hardware 9
60. Computer Software 15
70. Computer Equip. Wanted 17
80. Test Equipment 17
85. Security 50
90. Satellite Equipment 50
95. Military Surplus Electronics 57
100. Audio/Video/Laser 57
110. Cable TV 60
115. Telephone/Fax 66
120. Components 67
125. Microcontrollers 68
130. Antique Electronics 68
135. Aviation Electronics 72
140. Publications 72
145. Robotics 73
150. Plans/Kits/Schematics 76
155. Manuals/Schematics Wanted 84
160. Misc. Electronics For Sale 84
170. Misc. Electronics Wanted 88
175. BBS & Online Services 89
180. Education 89
190. Business Opportunities 89
200. Repairs/Services 96

Nuts & Volts Magazine is published monthly for $19.00 per year by T&L Publications, Inc., 430 Princeland Court, Corona, CA. Application to mail at 2nd class postage rates is pending at Corona and San Diego. POSTMASTER: Send address changes to Nuts & Volts Magazine, 430 Princeland Court, Corona, CA 91719.

EPROM+

The Professionals Choice!

A DEVICE PROGRAMMER FOR BENCH AND FIELD

FIRST GENERATION EPROMS (24 PIN) 2708, TMS2716*, 1702*
SECOND GENERATION EPROMS (24,28,32 PIN) 2516,32,64,68764/66
2716,32,64,128,256,512,513,011,010,101,1001,020,2001,040,4001,080,8001
(40,42 PIN*) 27C210,1024,220,2048,240,4002,4096,27C400,800, **27C160 (16MEG)**
EEPROMS/NVRAMS (18-32 PIN) X2210/12,2804,16,17,64,65,256,512,010,**ER5901**,12XXX
FLASH EPROMS (28,32 PIN) **[28F]** **[29C]** **[29EE]** **[29F]** 256,257,512,001BX,010,101,020,040
*SERIAL EEPROMS** (8 PIN INCLUDES C,CS,LC,E) **[2401]** 02,04,08,16,2►32,44,64,65,256 **[25010]**020,040,080,160,320,640,128
[59C11]13,22 **[8572]**82,92 **[9306]**16,46,56,66,86 **[95010]** 020,040,080 **[35C102]**104,108 (14 PIN) ER1400, M58657
*BIPOLAR PROMS** (16 THROUGH 24 PIN) 82SXXX AND 74SXXX FAMILIES *FPGA CONFIGURATORS* **[17C65]** 128,256
*PIC MICROS** **[12C5XX]** **[16C54]** 55,56,57,58,55X **[16C61]** 62,63,64,65,62X **[16C71]** 73,74,71X **[16C84]** **[16F8X]** **[14000]**
*MICROCONTROLLERS** (8 BIT) **[8741]**,42,48,49 **[8751]** C51,5X,C5XX **[87C75X]** **[89C51]** 52,55 **[89C1051]** 2051
*MOTOROLA MICROS** **[68705P3]** U3,R3 **[68HC705C8]** C9,J2,P9 **[68HC711E9]** D3
* REQUIRES SNAP-IN ADAPTER (DIAGRAMS INCLUDED) OR PURCHASE ASSEMBLED AND TESTED)

- READ, PROGRAM, COPY, COMPARE, DISK FILE LOAD & SAVE (PLUS MORE!)
- FULL SCREEN BUFFER EDITOR WITH 25 COMMANDS PLUS BYTE & WORD MODES
- READS INTEL HEX/EXTENDED HEX, MOTOROLA S-RECORD AND BINARY FILES
- SOFTWARE RUNS UNDER DOS, WINDOWS 3.1 OR 95 ON ANY SPEED MACHINE
- PARALLEL PRINTER CABLE AND POWER PACK STORE INSIDE UNIT (9"X6"X3")
- MADE IN THE USA ▫ 30 DAY MONEY BACK GUARANTEE ▫ 1 YR. WARRANTY

COMPLETE SYSTEM INCLUDES: PROGRAMMING UNIT, SOFTWARE PRINTER PORT CABLE, POWER PACK AND PRINTED MANUAL

$289

$5.00 SHIPPING ▫ $5.00 C.O.D.
VISA • MASTERCARD • AMEX

ANDROMEDA RESEARCH, P.O. BOX 222, MILFORD, OHIO 45150
(513) 831-9708 FAX (513) 831-7562

reader *FeedBack*

Dear Nuts & Volts:

I just wanted to thank Don Pomery for the debug routine (Reader's Tip in "Electronics Q & A," Nov. '97 issue). I was able to recover a HD that I thought was a gonner for sure. I had done "Fdisk /mbr" twice on the drive each time with a different CMOS setting then written "FUBAR" in pencil on the drive when it wouldn't respond to Fdisk or Format. The drive was headed for the trash when I read Don's Reader's Tip. What did I have to lose? It worked! Thanks Don and thanks *Nuts & Volts*. That more than paid for a year's subscription.

jhonett@pacbell.net

Dear Nuts & Volts:

I like your magazine, but it would be nice if you had more "Ham Radio" stuff. There are a lot of ham radio operators out here.

73 KB0UJC
West Plains, MO

Dear Nuts & Volts:

I have been following the "User's Guide to Audio Power Amplifiers" written by Ray Marston. Ray has written a very good series of articles about audio power amplifier ICs. However, I have difficulty understanding abbreviations of some schematic component values. For example: 510R, is this 510 ohms? Why the R? 100N, is this 100 uF? Why the N? 2R7, I can't guess what resistance value this means. 4R7, same as above. 8R0, from the text I know this means an eight-ohm impedance speaker.

Scattered throughout the many schematic drawings are other puzzling component values.

Perhaps Mr. Marston can be kind enough to help an old tube technician who has not kept pace with solid-state terminology.

James Brendage
Orangevale, CA

Response:

Thanks for your comments about my articles. Regarding the abbreviations commonly used to define schematic component values, these are designed to be as compact as possible, containing no superfluous information and taking up a minimum of schematic space.

When defining the value of a schematic's 47 µF (47 microfarad) capacitor, for example, the 'F' (Farad) part of the notation is obviously superfluous, since the component is clearly drawn as a capacitor and as such inevitably has a value that is related to the Farad; this particular component value can thus be adequately notated as '47µ.'

Similarly, it is usually wasteful to have an 'ohms' notation on a schematic resistor value, or a 'Henrys' notation on a schematic inductor value.

In most modern electronic schematics, resistor values

Continued on page 109

ICM "The Bible" of the IC Industry

EEM is the Largest Component Parts Directory available. All the Major Parts Manufacturers display Entire Product Lines with Pictures & Data sheets. Cabinets, Transformers, Pots, Semi's, Resistors, Capacitors, Crystals, Coils, Connectors, Wire, Heat sinks, Switches, Fuses, Speakers, Displays, an Endless list !

$78 97 EEM 4 Vol Set + 2 Vol EITD
Very Few
23 lbs
Shipping's Cheap

ICM has 150,000 IC's of EVERY KIND from EVERY Manufacturer. Specifications, Selected Data Sheets, Every known Cross-reference, Alternate Sources, Manufacturer Profiles & Distributors.

Contains Most Current Production ICs
For Light Design or Service

$139 97 ICM 3 Vol + 2 Vol EITD
For Advanced Design Work

$67! ICM 3 Vol Set Back Issue + EITD

EITD Electronic Industry's Yellow & White Pages

Find any Component -or- Service in a Snap the Way the Pro's Do
The EITD is a Reference you'll use Constantly !
Contains sources for everything from Semiconductors to Foreign Assembly Services. Locate Distributors, Manufacturers and Service providers for **Products, Services or ANY Component Parts imaginable !** 2 Vol Set 5lbs

"REFEREE" Semiconductor & Directory Software

Cross-REFERENCE ALL types of
Transistors, IC's & Diodes
Over 250,000 Devices Listed
Extremely easy to use. You'll be Navigating in Seconds
The Most Comprehensive Cross-REFERENCE Software available
Any Selection typically yields 75 to 250 potential replacements
Case Drawings, Lead Config. and Pin-outs for many Devices
Coverage of Replacement Numbers is Very Impressive.
Also Lists ECG, NTE, SK & GE, Includes "In House Numbers"
7 Disk Set with MODULAR Databases:
Install all the Databases (17 Meg), or just a few
Includes 4 Consumer Electronics Industry Directories
For Service, Engineering and Purchasing.
- Consumer Electronics Parts Sources (Service)
- Consumer Electronics Manufacturers
- The Entire Computer Industry
- Semiconductor Manufactures

Helpful extras included:
Conversion Utils, Formulas, Resistor Library
FREE REFEREE Mouse Pad

Netcom 800-881-6247 ext 6300 516-826-1808 x 6300 9am-9pm EST 7Days

"EXPERIENCED" TEST EQUIPMENT

(You Wouldn't Want "In-Experienced" Equipment, Would You?)

AC/DC EL300 300 Watt Electronic Load.....$250
AC/DC EL301B Load Controller.....$250
ANRITSU MS610B Spectrum Analyzer.....$4500
ANRITSU MW9040A/MW0947A Optical TDR.....$4500
ASSOCIATED RESEARCH 5400DT Hypot.....$1250
BK PRECISION 1611A Power Supply.....$200
BK PRECISION 1711 DC Power Supply.....$210
FLUKE 1953A Frequency Counter.....$695
FLUKE 2190A Digital Thermometer.....$500
FLUKE 6071A Synthesized RF Sig Gen.....$7995
FLUKE 7261A Universal Counter/Timer.....$895
FLUKE 8000A 3+ Digit Multimeter.....$125
FLUKE 8050A 4+ Digit Multimeter.....$350
FLUKE 8520A 5+ Digit System Multimeter.....$1200
FLUKE 8800A Digital Multimeter.....$300
FLUKE 8810A Digital Voltmeter.....$225
FLUKE 8860A Digital Multimeter.....$650
FLUKE 8921A True RMS Voltmeter.....$450
FLUKE 97 50 MHz Scopemeter.....$1495
GEORATOR 901-1403-2 AC Power Source.....$5000
GIGATRONICS 1026/18 Synthesized Sig Gen.....$7995
GIGATRONICS 6061A Synthesized RF Sig Gen.....$4500
GIGATRONICS 80301A Power Sensor.....$295
GIGATRONICS 8541 Digital Power Meter.....$1175
HONEYWELL 1858 18 Channel Recorder.....$2200
HONEYWELL 1881HGD High Gain Differential Amp.....$125
HONEYWELL 1883AMPD Med. Gain Differential Amp.....$125
HP 141T/8552B/8553B Spectrum Analyzer.....$2400
HP 1630D Logic Analyzer.....$1450
HP 1980B Automatic Scope Measurement System.....$1495
HP 2225A ThinkJet Printer.....$295
HP 3312A Function Generator.....$725
HP 3325A Synthesized Function Generator.....$1800
HP 3330B Frequency Synthesizer.....$1450
HP 334A Distortion Analyzer.....$895
HP 339A Distortion Analyzer.....$1900
HP 3400A True RMS Voltmeter.....$195
HP 3478A Digital Multimeter.....$795
HP 3488A HP-IB Switch/Control Unit.....$1250
HP 3562A Dynamic Signal Analyzer.....$12,750
HP 3575A Gain Phase Meter.....$1400
HP 3581A Wave Analyzer.....$1200
HP 3764A Digital Transmission Analyzer.....$5000
HP 3852A Data Acquisition/Control Unit.....$3000
HP 400EL AC Voltmeter.....$200
HP 4191A RF Impedance Analyzer.....$14,500
HP 4192A Impedance Analyzer.....$14,000
HP 4260A Universal Bridge.....$1100
HP 4274A Multi Frequency LCR Meter.....$5995
HP 4328A Milliohmmeter.....$1200
HP 435B RF Power Meter.....$850
HP 436A RF Power Meter.....$1525
HP 478A Coaxial Thermistor Mount.....$195
HP 4972A LAN Protocol Analyzer.....$3975
HP 5315A Universal Counter.....$625
HP 5328A Universal Counter.....$550
HP 5334A 100 MHz Universal Counter.....$2400

HP 8901B
Modulation Analyzer, 150 kHz to 1300 MHz



Super Value Priced $5,500

HP 5334B Universal Counter.....$1450
HP 5342A 18 GHz Frequency Counter.....$3950
HP 5345A Electronic Counter.....$1200
HP 5385A 1 GHz Frequency Counter.....$1900
HP 54100A 1 GHz Digitizing Oscilloscope.....$3500
HP 59501A Isolated DAC/Power Supply Programmer.....$250
HP 6177C DC Current Source.....$650
HP 6181C Precision Current Source.....$400
HP 6207B DC Power Supply.....$200
HP 6217A DC Power Supply.....$175
HP 6236B Triple Output Power Supply.....$675
HP 6253A Dual Output DC Power Supply.....$550
HP 6261B DC Power Supply.....$800
HP 6266B DC Power Supply.....$495
HP 6282A DC Power Supply.....$395
HP 6289A DC Power Supply.....$395
HP 6294A General Purpose Power Supply.....$150
HP 6299A DC Power Supply.....$400
HP 6456B DC Power Supply.....$2500
HP 7475A RS-232C Graphics Plotter.....$550
HP 8011A Pulse Generator.....$500
HP 8012B Pulse Generator.....$595
HP 8111A Pulse/Function Generator.....$2200
HP 8152A Optical Average Power Meter.....$1000
HP 8157A Optical Attenuator.....$1500
HP 8175A Digital Signal Generator.....$6500
HP 8181A Data Generator Extender.....$1995
HP 8182A Data Analyzer.....$1995
HP 8444A 500 kHz-1250 MHz Tracking Generator.....$1600
HP 8484A Power Sensor.....$650
HP 8501A Storage Normalizer.....$1100
HP 8503A 50/ S-Parameter Test Set.....$1300
HP 8559A 10MHz-21GHz Spectrum Analyzer Plug-In.....$3500
HP 8560E Portable Spectrum Analyzer.....$22,500
HP 8561B Spectrum Analyzer.....$21,000
HP 85685A RF Preselector.....$17,995
HP 8590B Portable Spectrum Analyzer.....$7900
HP 8591A Spectrum Analyzer.....$9600
HP 8591E/10/21 Spectrum Analyzer.....$13,500
HP 8640B VHF Signal Generator.....$2800
HP 8656B Synthesized Signal Generator.....$4500
HP 8657A Synthesized Signal Generator.....$6200
HP 8657B Synthesized Signal Generator.....$12,500
HP 86602B RF Plug-In.....$500
HP 86634A Phase Modulation Plug-In.....$750
HP 86635A Modulation Plug-In for 8660x.....$500
HP 8673H/618 Synthesized Signal Generator.....$8995
HP 8683B Microwave Signal Generator.....$5800
HP 8754A Network Analyzer.....$4100
HP 8770A Arbitrary Waveform Synthesizer.....$9000
HP 8900B Peak Power Calibrator.....$450
HP 8901A Modulation Analyzer.....$4500
HP 8901B Modulation Analyzer.....$6500
HP 8903A Audio Analyzer.....$4200
HP 8903B Audio Analyzer.....$5500
HP 8904A Multifunction Synthesizer.....$3100
HP 8958A Cellular Radio Interface.....$4800
HP 8970A Noise Figure Meter.....$6500
KEITHLEY 228 Voltage/Current Source.....$2995
KEITHLEY 480 Picoammeter.....$695
KEITHLEY 706 Scanner Mainframe.....$1400
KEPCO ATE75-1.5M DC Power Supply.....$250
KEPCO JQE150-3.5M DC Power Supply.....$400
KEPCO JQE36-8M DC Power Supply.....$400
KIKUSUI PLZ50-15A DC Power Supply.....$300
KROHN-HITE 3202 Dual Channel Tunable Filter.....$695
KROHN-HITE 4141R Programmable Oscillator.....$600
LAMBDA LH127S.....$200
LAMBDA LP414AFM.....$200
LAMBDA LP521FM.....$350
LAMBDA LP532FM.....$395
LAMBDA LPD414AFM.....$300
LAMBDA LPD423AFM.....$395
LAMBDA LPT7202FM Triple Output DC Power Supply.....$625
MARCONI 2955/2957 Cellular Radio Test Set.....$5995
MARCONI 2955/2960 Cellular Radio Test Set.....$8000

TekMeter®
RMS Multimeter/Digital Storage Oscilloscope

Super Value Priced $695

NARDA 4322-4 Power Divider.....$75
NARDA 766-10 Attenuator.....$195
NARDA 768-30 Attenuator.....$290
NAVTEL 9470 Protocol Analyzer.....$5500
PHILIPS PM2534 System Multimeter.....$695
PHILIPS PM5712 1 Hz To 50 MHz Pulse Generator.....$650
POWER DESIGN 5015T DC Power Supply.....$225
POWER DESIGN TW6050A DC Power Supply.....$500
SCHAFFNER NSG200E Simulator Mainframe.....$1400
SCHAFFNER NSG203A AC Interruptions Plug-In.....$2100
SCHAFFNER NSG222 Fast Pulses Plug-In.....$1250
SCHAFFNER NSG223 Pulses with High Energy Plug-In.....$950
SCHAFFNER NSG224 Interference Pulse Plug-In.....$1400
SENSITIVE RESEARCH ESH 21 kV Static Voltmeter.....$600
SORENSON DCR150-3B DC Power Supply.....$625
SORENSON DCR40-70B DC Power Supply.....$1150
SORENSON SRL40-50 DC Power Supply.....$1100
SORENSON SRL60-4 DC Power Supply.....$1080
T-COM 440B Digital Communications Test Set.....$3995
TEK 1410 NTSC Generator Mainframe.....$3800
TEK 1485C/1480R Waveform Monitor.....$3750
TEK 1910 NTSC Digital Generator/Inserter.....$5495
TEK 2205 Oscilloscope.....$450
TEK 2215A Oscilloscope.....$825
TEK 2235 100 MHz Oscilloscope.....$1195
TEK 2430 Digital Storage Oscilloscope.....$4100
TEK 2445A 150 MHz Oscilloscope.....$2695
TEK 466 Portable Storage Oscilloscope.....$1195
TEK 485 350 MHz Oscilloscope.....$1200
TEK 7704A 250 MHz Mainframe.....$400
TEK 7834 400 MHz Storage Oscilloscope.....$1025
TEK 7844 400 MHz Dual Beam Scope Mainframe.....$1000
TEK 7A18 Vertical Amplifier.....$175
TEK 7A22 Differential Amplifier.....$125
TEK 7A26 Vertical Amplifier.....$225
TEK 7B53A Dual Timebase.....$250
TEK 7B85 Delayed Timebase.....$250
TEK 7B92A Delayed Timebase.....$350
TEK 7D20 Programmable Digitizer.....$825
TEK 7S14 Sampling.....$795
TEK 7T11A Sampling Timebase.....$495
TEK AA5001 Distortion Analyzer.....$1500
TEK AA501 Distortion Analyzer.....$2295
TEK AM503 Current Probe Amplifier.....$750
TEK DC5009 Frequency Counter.....$1100
TEK DC503 Digital Counter Plug-In.....$250
TEK DM5010 Digital Multimeter.....$975
TEK DSA602 Digitizing Signal Analyzer.....$5995
TEK FG501A 2 MHz Function Generator Plug-In.....$450
TEK FG504 Function Generator Plug-In.....$725
TEK P6202A Active FET Probe.....$495
TEK P6701 Optical-to-Electrical Converter.....$300
TEK PG505 Pulse Generator Plug-In.....$375
TEK PS503A Triple Power Supply.....$225
TEK S4 Sampling Head.....$925
TEK T935A 35 MHz Oscilloscope.....$200
TEK THM565 Handheld 2 MHz DSO/Multimeter.....$695
TEK TM5006 Power Module/Mainframe.....$500
TEK TM503 Power Module.....$195
TEK VM700A/01/40 Video Measurement Set.....$19,995
TEKELEC CHAMELEON 32 Development System.....$4500
TELECO TECHNIQUES 224 T1 Channel Access Tester.....$6500
TELECO TECHNIQUES 4000 Communications Analyzer.....$4500
WAVETEK 20 2 MHz Function Generator.....$3995
WAVETEK 278 Synthesized Function Generator.....$1800
WAVETEK 442 Dual HI/LO Variable Filter.....$445

Turn Your Surplus Test Equipment into Cash — *Call Wade Miller for details*

ValueTronics International, Inc

1925 South Wright Boulevard • Schaumburg, Illinois 60193 • USA
847-584-8258 • 1-800-552-8258 • 847-584-4329 FAX

HAM GEAR FOR SALE

WANTED: ROCKWELL-Collins HF-80 equipment, 851S-1, 237B-3 log periodic, Collins literature. Jim Stitzinger 805-259-2011, 805-259-3830 (fax), bfl-jfs@smartlink.net

THE ALC245M AUTOMATIC VOLUME CONTROLLER will keep your transceiver or scanner's volume constant from a whisper to a scream. $22.95 S&H $5. Other models also available. **FREE BROCHURE**. C&S Electronics, PO Box 2142, Norwalk, CT 06852-2142. Phone: 203-866-3208 Fax: 203-854-5036. E-Mail: CANDSELECT@worldnet.att.net

HR2510: 10M amateur mobile radio's **"NEW,"** 1250 IC $275 ea. COD, S&H extra. Free S&H if prepaid. D&R Electronics, 10 Park St., Thomaston, CT 06787, 860-283-9492 phone.

VACUUM TUBES, thousands in stock NOS, (new old stock) and high quality low mileage pre-owned tubes. All used tubes cleaned, tested, and boxed before shipment. LynTec 408-274-3559 http://www.lyntec.com Lynn@lyntec.com

FOR MOON bounce and radio astronomy auto-track antenna mount pedestal precision heavy duty formerly used on SCR 584 radar. Cheap. Tucson, AZ. 520-747-0507.

WATTMETERS BIRD 43 w/6 slugs, 100-5000 watts, leather case $400; B & K 0-1500 watt dummy load, metered $100. Bird slug 4410.4, 0-30 meg 10KW $75. As new. Psitech Plus 707-745-4804, Fax 707-747-5277 E-Mail: apeas@ix.netcom.com

THE SMART BATTERY CHARGER for lead acid or gel cell batteries. Can be left connected to the battery **INDEFINITELY**, will not overcharge! Standard kit is 12V @ 1 amp. This kit is 100% complete, including a custom-made, pre-punched, painted and lettered enclosure. For the kit order #150-KIT at $59.95. For an assembled and tested unit, order #150-ASY at $79.95. CA residents add 7.75% sales tax. Add $6.50 per unit shipping. MC/VISA accepted. A&A Engineering, 2521 W. La Palma #K, Anaheim, CA 92801. 714-952-2114, FAX 714-952-3280.

USED TESTED Midland UHF 70-1530B $175, MVP UHF $75, Mitrec UHF $30, Maxor 80 UHF $50. Scanners & CB, power supplies & ham gear too! Free catalog! Call 909-873-1319 fax on demand 24 hrs. 909-820-1885 E-Mail: HRH6@aol.com & LML, 424 E. Shamrock, Rialto, CA 92376

NEW PRODUCTS FROM S&S: UPGRADE YOUR OLD RIGS! Digital dial (counter) has 10Hz resolution HF, 100Hz VHF and frequency range 50KHz to 230MHz; kit $99.95; assembled $149.95. **NEW digital VFO** with 1Hz resolution to 54MHz; kit $169.95; assembled $219.95. S&H $7 (continental US). GUARANTEED TO WORK. For info send **SASE**. Call/write to order: S&S Engineering, 14102 Brown Road, Smithsburg, MD 21783. 301-416-0661. E-Mail: N3SAD@aol.com or see http://www.xmetric.com/sseng

REMOTES
Remote Control for Any Application

NEW NEW NEW NEW NEW

- 3 Channel Receiver
- Channel 1 - 5 amp Relay, N/O, N/C
- Channel 2 and 3 Digital Outputs
- Compatible with 2 Button or 4 Button Remote
- Code Hopping Receiver at 434 Mhz
- Compatible with All Garage Doors and Some Car Alarms

$69.95

- 6 Channel Receiver with Digital Outputs
- All Channels are Programmable for Momentary, Latched, Latched with Condition 30-60-90 Sec. Timed Outputs
- Code Hopping Receiver at 434 Mhz
- Compatible with 2 Button or 4 Button Remote
- Compatible with Some Car Alarms

$99.95

- 2 Button - 3 Channel Remote
- Extra Long Range 434 Mhz with S.A.W. Resonator
- Push Both Buttons together for Channel 3
- Compatible with Three and Six Channel Receivers.

$29.95

- 4 Button - 15 Channel
- Extra Long Range 434 Mhz S.A.W. Resonator
- Push Combination of Buttons together for Channel 5 through 15, i.e.: Push Button 1 and 2 together for Channel 5
- Compatible with Three and Six Channel Receivers.

$39.95

Street Smart Security ▪ 1-800-908-4737
7147 University Avenue • La Mesa, CA 91941
Send, Fax or Call Order In - Use Credit Card or Check. Fax (619) 462-0652

Write in 180 on Reader Service Card.



The HAPPIEST of HOLIDAYS to ALL

CHECK THIS OUT! ULTRA MINI and WEATHERPROOF,

"LIPSTICK" camera sets new standards. Sleek black anodized, aluminum, housing is O-Ring sealed and RAINPROOF. Adjustable tilting mount included. Specs: 1/3" CCD, 380 Lines resolution, 0.3 Lux sensitivity, AGC, Auto Shutter. Operates on 9 to 16VDC @100mA, 3.7mm, 78° FOV lens, A real glass lens. NTSC video out. 1/2 once! SENSITIVE to IR. Ultra small Size only: 23mm diam. X 50mm long. With 36" leads.

GM-200K-STD,..$129 power adapter .$4.95

"EMBEDABLE", "BULLET CAM" it's INCREDIBLE !

So tiny you can install it right into a door with merely an 0.9" diameter hole. Sleek black anodized, extruded aluminum housing. Similar construction as the lipstick camera above only smaller! 1/3" CCD, 410 Lines Res., 0.3 Lux sens., AGC, Auto Shutter. Power from 9 to 16VDC @100mA, 250k PIXELS, 90° FOV Pinhole lens. A real glass lens. Std. NTSC video out. 1/2 once! SENSITIVE to IR. Size only 23mm Diam. x 35mm long. With 36" leads. Think of the places you could put this little jewel.

GM-200K-PINHOLE,..$129 power adapter .$4.95

NEW MODEL MICRO CAMERA, w/audio 1/3" CCD, 410 Lines

Res., 0.3 Lux sens., AGC, Auto Shutter. Power from 9 to 16VDC @100mA, 250k PIXELS, Std. model, 3.6mm, 92° FOV lens, Pinhole, 90° FOV. A real glass lens. Both focus from 10mm to infinity. Std. NTSC video out. 1/2 once! SENSITIVE to IR. Size Std: 1.25"sq. x 1"d. PH is 0.6"d, Both with 6" leads. **WARNING:** Don't confuse these models with LOW RESOLUTION, HIGH LUX C-MOS CAMERAS. **C-MOUNT** model now available. Only 0.9" d

GM-1000A-STD,.....$89	GM-1000ASTD/Audio,.....$109
GM-1000A-PH,.....$89	GM-1000A-PH/Audio.....$109
GM-1000A-CM.....$89	GM-1000A-CM/Audio.....$109

C-Mount f2.0 Lenses	Micro lenses for Board Cams
4mm, 80°.....$32	2.5mm, 150°.....$22
8mm, 40°.....$32	4.3mm, 78° fast.....$22
12mm, 28°.....$32	5mm, 70°PH.....$22

SEE in TOTAL DARKNESS! NOT 6 LED's, NOT 12, NOT 24! OUR IR FLOOD has 168 LED's !!

Powerful, not power hungry. Projects up to 50 feet. 24V wall adapter incl. Size: 4.5"Wx6.6"Hx1.5"d Commercially made and BRAND NEW! **IR FLOOD....$159ea.**

COVERT CAMERAS available with audio,

1/3" CCD, 410 Lines Res., 0.3 Lux sens., AGC, Auto Shutter. Pwr. from 9 to 16VDC @100mA, 90° FOV lens, All focus from 3 ft. to infinity. NTSC video out. SENSITIVE to IR. note: Smoke and Motion detectors are not functional, Clock and Exit operate normally. Dome is 3.5"H x 5.5"Diam.

Exit...$169 Clock, Smoke, Motion or Dome ...$149 add $12 for audio



UNIQUE LINEAR MOTION BASE, Origially intended as the motion drive for a high end desktop flat bed scanner.

These are new units removed from a dicontinued model. The movement is provided by a stepper motor with a toothed belt drive. This drives the carriage 12" accross two polished stainless steel rails. (the action that moves the lamp across the page.) The assembly is mounted to the scanner cover. We recommend removing it and mounting it on your base.Includes optical end of travel detector. Overall size: 16"L x 13"w x 2"H. Nicely made.

Model LMB-2..... $59ea. or 2 for $100

TIME LAPSE VCR, Records up to 720 HOURS!

Through a special deal we have obtained these used, depot refurbished , GYYR model TLC-1440 (Hitachi) time lapse recorders. We can offer them for 1/3 the regular price. Althouth not cosmetically perfect. They are in excellent working condition.

SPECIAL Limited Qty. TLC-1440...$499ea.

** WEB SITE UNDER CONSTRUCTION!*

WWW.resunltd4u.com

Brand New, Video Motion Sensor. Model VM10. Attach

to any standard video signal and you've got an electronic "watchman" diligently watching the entire scene. Or any adjustable sized area within the scene. Such as a doorway or even a drawer or cabinet. A state of the art security aid. The unit will close a contact when it senses a change. Use it to turn on a VCR or call the hounds. Auto or manual reset. Very compact, ac powered. Adjustable sensitivity. Video loop through jack.

NEW SPECIAL VM-10..... $179ea.

Exclusive "LAB STYLE" LASERS, 650nm and 635nm, Rugged, Dependable. One year warranty.

Adjustable X and Y beam position. Aircraft aluminum housing. Internal battery and on-off switch included. Makes a super pointer. .75d x 2.75"L

SALE..... 650nm $69, 635nm $99

AN/PVS-2, U.S. made Gen. 1, Starlight scope, complete depot refurbished

system includes: transit case, High gain 30K to 50K MIL spec, three stage, intensifier with automatic brightness control, Super, 95mm, 4 pwr, f1.2 "CAT" lens, 10.7 FOV, Operates up to 40 hours on 4 AA batteries, 17.5"L x 3.5"D, 7.7" at center. **.....$795ea.**

TWO MINI C-MOUNT CAMERAS, The super sensitive, GM410 or the general purpose GM412,

The GM-412 specs: B&W, size 1.5"sq. X 2.4"L, 250,000 Pixels, **380** Lines Resolution, Sensitivity **0.3** Lux, The GM410 specs: size only 1.5" SQ. x 1.6"L, >270,000 Pixels, **410** Lines Res., Sens. **0.05 LUX.**, Both cameras are 1/3" CCD with AGC & Electronic shutter. 12V @110mA power. NTSC out. IR SENSITIVE, GM 410 has RCA video connector, GM-412 has a BNC. Both use std. DC pwr. jack. Aluminum housings with dual threaded top and bottom mounting. True performance not hype! These cameras will outperform *ANY* camera in this magazine. Multi- lens options are available to exploit their superior performance.

GM412 less lens.....$139ea. GM410 less lens.....$169ea.

Ultra Fast Lenses for Low Light or Gen'l Purp. for Normal Light	
16mm, f1.6, 15° FOV .....$39ea.	4mm, 80° FOV .....$32ea.
8mm, f1.3, 30° FOV .....$49ea.	8mm, 40° FOV .....$32ea.
4mm, f1.4, 56° FOV .....$49ea.	12mm, 28° FOV .....$32ea.

WORLDS SMALLEST 100mW VIDEO TRANSMITTER, Incredibly



only 0.98" x 0.8" x 0.037" in size. Transmits crystal controlled hi-res. images with 100mW output! The transmitter you've been waiting for. **Shown actual size.** Much smaller than the 9V battery which powers it. Draws only 35mA! Factory tuned ready to receive on cable channel 59. Will work with color or B&W cameras. UHF Bow tie antenna with balun and 3' F cable for TV Included. Perfect with our GM1000A cameras. Both will fit in a cigarette pack.....with the battery!

TVX-100...$199. TVX-100 with GM-1000A-PH Camera...$288.

SCIENTIFIC, 1/2" COLOR CCD CAMERA

- *YC/SVHS output*
- *380K Pixels*
- *460 Lines*
- *1.5 Lux sensitivity*

All parameters adjustable from outside camera! Perfect for microscopy, inspection, capture or surveillance. Features internal or external sync, Interlaced or N/I, Adj. shutter, 1/60 to 1/10000 Sec., Auto White balance with three steps, Auto iris output, C or CS mount, Manual/auto gain or ext. variable gain. BNC video out, 12V@ 250mA pwr., via std. barrel jack. The GM470-C has it all! Aluminum housing. Size: 50mm W x 50mm H x 145mmL **New, GM470C, less lens.....$499ea.**

Super Batteries, *Feel the Power!*

6V @ 10 AH SEALED LEAD ACID Brand new

and tough to get at a discount. Very compact. Use two for a 12V@ 10AH pack. Perfect for robotics and other high drain applications. Size: 5.9"L x 3.7"H x 1.97"D

REG. $17ea. NOW 2 for $16, 8 for $50

10V @ 2.5 AH SEALED LEAD ACID Each pack consists of five, 2 Volt cells.

Each cell the size of a std. 'D' battery. They are arrainged as 1X5 cells. Enclosed in an ABS outer shell. (removed for photo) Mint condition. Perfect for robotics and other high drain applications. Buy several, make custom packs of any rating. Size: 7.5"L x 2.8"H x 1.5"D

5 for $20, 30 for $99

SEE the LIGHT, SEE the COLORS, Orphaned scanner industry color calibration source.

A stepper motor driven color wheel is sandwiched between two anodized black alum. plates. A 3/4" hole in the plates lines up with red, green, blue and neutral gray filters installed in the wheel. A "U" shaped mini fluorescent lamp provides illumination . The lamp is powered by a solid state, 12DC inverter board, supplied. As the wheel rotates a phototransistor detects it's position. A precision gadget that is waiting for a new home. Size: 4"W x 4" L x0.2" Deep

NEW, FLURO SOURCE $9ea. or 3 for $25

STEP RIGHT UP FOLKS, NEW STEPPER MOTOR with Belt Drive 'Pulley,

Assembly consists of a steel angle bracket 4.7" L x 2.6"H on which is mounted a 12V 0.4A stepper motor with a 1/2" removeable toothed pulley. This drives a belt which rotates a larger 1.8" diam. toothed pulley . Thus providing about a 3.6:1 drive reduction. The re is also a take off pulley as part of the hub of the larger pulley. Looks like it would be useful as a general pupose drive in many applications. New and priced right for experimentation.

BELT DRIVE.....$8ea. or 4 for $25

NEW LASER DIODE MODULES, operate from 4.5 to 9VDC !

SPECIFICATIONS:
DC Power: 4.5 - 9V, @65mA
Power out: 4.5mw max.
Range: 400-800 Meters
Glass Collimator
Size: 0.41"diam.x0.7"L

Shown Actual Size

650nm 5X Brighter...$45
635nm 10X Brighter...$69
***635F adj. focus...$79**

The best value for commercial, Subminiature, laser modules. Glass collimating lens provides 1.5mRad performance. (divergence comparable to HeNe lasers.) Wide input, internal surface mount, 4.5 to 9VDC power supply. Machined brass for excellent thermal characteristics.

DIGITAL COLOR CAMERA is a RARE FIND. PANASONIC WV-D5000.

- *2/3" CCD*
- *8X f1.4 Bayonet mnt. Lens*
- *Auto Focus*
- *Manual Zoom*
- *Stereo Mic Inputs*
- *Auto/Manual White Balance*
- *Auto/Manual Iris Control*
- *10.5 to 84mm W/ MACRO*
- *3 Step AGC*
- *Earphone Output*

Once again we find a special surprise. These are the finds that make it fun.These cameras are used in excellent condition.They provide 460 lines resolution. Minimum illumination is 3.5lux, S/N: 46dB, Auto tracing white balance. They were originally intended to connect to a high end portable deck. Sorry no decks. They operate from 12VDC @ 0.5 to 1.5A peak. Size including lens is 10.75L x 4.5"W x 4.5"H. Supplied with hookup info for PWR., Vid and Audio. We do not have the mating connector. I avail. from Panasonic) Simple to make a direct connection. A Very impressive camera.

Limited Quantity, D5000.....$499ea.

WEATHER RESISTANT Camera Enclosure

Solid, extruded aircraft aluminum. C Strain reliefs for cables. Size: 3.5"w x 3.7"h x14"L,

Sale Price.....$49ea.
with 110VHEATER....$69ea.

TCXO, 50MHz, 100PPM stabilty.

Hemetically sealed steel can protects a precision, temperature compensated, 50MHz, crystal oscillator.Operates from 12VDC @ 80mA. Perfect for home brew freq. reference. Size: 2W x 2" L x0.75"H

NEW, TCXO.....$10ea. or 3 for $25

The WILD model M7 Microscope,

A truly magnificent instrument. Once you use a WILD all others pale! Magnification with 10X wide field eyepiece smoothly zooms from 6X to 31X. Working distance is 91mm. With included 0.5 objective the working distance is 156mm. Includes base shown, Panasonic WV-CD50 B&W mini CCD camera and Fiber optic ring light. Complete video microscopy system with one of the worlds finest microscopes. Like new condition.Other camera options available. **$2295.00**

RESOURCES UN-LTD.

300 BEDFORD STREET , MANCHESTER, NH 03101

VISA, MC, AMEX, DISCOVER, COD. ORDER: 800-810-4070 TECH. 603-668-2499 ORDER FAX: 603-644-7825 E-MAIL unltd4u@tiac.net

Write in 130 on Reader Service Card.

HAM GEAR FOR SALE *cont.*

WW2 J-38 telegraph key. Unused. $39.95 ppd. Visit our Web site: http://www.arrowweb.com/surplus-Tubes, parts, misc. items. Lee Frank, PO Box 60011, Harrisburg, PA 17106-0011.

Looking for a great value? Subscriptions to *Nuts & Volts* are only $19 for a full year. Call *Toll Free* and use your Visa or MasterCard to order!

1-800-783-4624
http://www.nutsvolts.com

HAM GEAR WANTED

WANTED: ICOM IC-03AT 220MHz handhelds. Will consider non-functional radios. **Top dollar offered.** Contact Alan Sanders, Communications Specialists, Inc., 426 West Taft Avenue, Orange, CA 92865-4296. 1-800-854-0547, FAX 1-800-850-0547.

LOOKING FOR 88-108MHz broadband antenna to receive distant stations. Do you have a product to help me? ARRL antenna handbook designs for 144MHz don't have scaling info. Write: PO Box 7949, Alice Springs, Australia, E-Mail: WORRY @OZEMAIL.COM.AU

CB – SCANNERS

WANTED: WAWASEE MODEL JB 1001 SFC/M CB TEST STATION, 916-451-7530 10am-5pm PST.

"CB MODIFICATION SECRETS," new 200-page guide by author of "CB Radio Hacker's Guide." More easy AM/SSB CB upgrades & enhancements: Cobra, Realistic, Uniden, President, etc. Freq. expansion, VFO, clarifier unlock, VOX, Roger Beep, anti-theft device, receive preamp, more. Only $21.95, plus $5 S/H ($6 to Canada). CRB Research, Box 56, Commack, NY 11725. NYS res. add $2.22 tax. Visa/MC orders call: 516-543-9169.

RADIOS CB & 10 METER RECEIVE KITS, NOISE TOYS, MODULATION KITS, ANTENNAS, BRACKETS, RADIO PARTS FOR GALAXY, COBRA, RANGER, ETC., PLUS MUCH MORE. CALL FOR FREE CATALOG. 1-800-536-0109.

SECRET CB BOOKS, TUNE-UP MANUALS, SAMS PHOTOFACTS, SERVICE BOOKS, SCHEMATIC SETS, PLUS MORE. CALL FOR FREE CATALOG. 1-800-536-0109.

LORD/WYATT COMMUNICATIONS IMPORT/EXPORT RADIO HOBBYIST CATALOG. Everything for the **CB & RADIO HOBBYIST** from **SOUP TO NUTS.** Send $5 to **LWC**, PO Box 30128CBND, Brooklyn, NY 11203-0128. 718-789-7329 press ext. 1.

SCANNING USA - unique monthly magazine. Get the most enjoyment from your scanner. All the latest news, product reviews, what's new, written by the nation's top acclaimed hobbyists. Subscriptions $19.95, sample issues $3. 2054 Hawthorne, Joliet, IL 60435. 1-800-651-0922.

NEW GALAXY DX-2527 10M BASE AM/FM/SSB/CW 28-29.7MHz. (11M & clarifier info included), 30W variable, freq. counter, talk back, echo/robot voice, scan, split, mem, dim, 110V AC. **$569.95 ppd** (NYS add 8.25% tax) catalog **$3. MAX-TECH, BOX 8086, New York, NY 10150 USA 10150 718-547-8244.**

MIRAGE, RCI, Uniden scanners (trunking) Cobra, CB radios, power supplies, microphones, hard-to-get electronic stuff, more; catalog $1 (refundable). Galaxy, Box 1202, Akron, OH 44309. Here for over 10 years.

CB MODIFICATIONS! Frequencies, books, kits, high-performance accessories, plans, repairs, amplifiers, 10-meter conversions. The best since 1976! Catalog $3. CBCI, Box 31500NV, Phoenix, AZ 85046.

BLACK BOOK CB LINEARS. Repair notes, theory, specifications, 60 schematics. $25. KEN's, 2825 Lake, Kalamazoo, MI 49001 616-345-4609.

RED BOOK CB MODIFICATION. Audio, modulation, PLL/VCO, synthesis, crystals, sliders. $25. Ken's 2825 Lake, Kalamazoo, MI 49001. 616-345-4609.

SALES, SERVICE: CB equipment, radios, modifications, power mice, echo-reverb boxes, kits, meters, filters, antennas, noise toys, mounts, hard-to-find items. Partial list $1, complete list $4. D&R Electronics, 10 Park St., Thomaston, CT 06787. 860-283-9492.

SEC Sun Equipment Corporation
P. O. Box 97903, Raleigh, NC 27624-7903
Test Equipment for Cost-Minded People

LODESTAR Lodestar Electronics Corp. Since 1979
One Year Warranty. 15 Day Money Back Guarantee. OEM welcome.
School purchase order accepted. Bids accepted.
SALES REP./DISTRIBUTORS/OEM WANTED.
1-800-870-1955 or (919)870-1955 Fax:(919)870-5720

DC POWER SUPPLY

PS-303 $159.00 0-30VDC, 0-3A; 0.02%+2mV line regulation; 0.02%+3mV load regulation; 1mVrms noise & ripple; Short circuit/overload protection; constant current/voltage (CC/CV).
PS-303D $314.95 dual, tracking
PS-305 $219.95, 0-30VDC, 0-5A.
PS-305D $399.95, dual, tracking.

8110 $289.95 0-60VDC, 0-3A.
8112 $399.95 0-60VDC, 0-5A.
8108(8109) $549.95($699.95) 0-60VDC, 0-3A(5A), dual, independent tracking. Low ripple.
8102(8103) $399.95($489.95) triple outputs, 0-30V/0-3A(5A) x 2, fixed 5VDC/3A, independent & tracking operation, constant voltage and current. Slave/Master, Serial/Parallel connection.
PS-1610S(8107) $289.00($399.95) 0-16VDC(0-30VDC), 0-10A.
PS-2243(2245) $139.00($159.00) 0-12/0-24VDC,3A(5A).
8200(8201) $179.95($239.95) 0-30VDC(digital meter), 0-3A(5A).
8210(8211) $199.95($259.95) two digital meters.
8202(8203) $499.95($549.95) digital display; triple outputs -- dual 0-30VDC/0-3A(5A) & a fixed 5VDC/3A; independent tracking operation; constant current and constant voltage (CC/CV).

AM/FM SWEEMAR SCOPE

SM-6225B/C $1999.95
Freq Range: (AM)490KHz; (FM) 10-11.4MHz; *Accuracy*: ± 0.1%
Marker: (AM)455KHz, ±5KHz, ±10KHz; (FM)10.7MHz, ±7.5KHz, ±150KHz.
STEREO SCOPE OS-7505B $369.00 trigger, 0-10MHz.
ALIGNMENT SCOPE OS-7001A $369.00 0-200KHz.

AM/FM STD SIGNAL GEN.

SG-4110A $1799.00
Freq: 100KHz-110MHz
Display: 6-digit LED
Accuracy:
<±(5x10-E5 ±1 count)
Resolution: 100Hz (100-34.99MHz); 1KHz (35MHz-110MHz).
Output: -19dBu, -99dBu, 1dB steps. *Impedance*: 50Ω VSWR 1.2

NTSC TV COLOR BAR PAT. GEN.

CPG-1366A $159.95, VHF NTSC;
Freq.: 45.75, 175.25, 187.25 MHz;
RF Output: 10mV.
Impedance: 75 Ohm;
Video Output: BNC, 1Vp-p.
CPG-1367A $159.95, VHF PAL

SWR/RF/mW POWER METER

310 $89.95
Freq. Range: 1.8-150MHz.
RF Power: 0-4W/20W/200W
SWR Measure.:1.0 - ∞, 4W min.
Accuracy: 5%-10%; SO-239 plugs.
Insertion Loss: O.3dB.
Input/Output Imp.: 50Ω.

320 $89.95, 130-520MHz.
330 $119.95, 1.8-520MHz.
SWR-3P $26.95 1.7-150MHz;
RF Power: 0.5-10W, 0.5W-100W.
SWR-2P $22.95, 1.7-30MHz; *RF Power*: 0.5-10W.

mW RF Power Meter 340 $219.00
1.8-500MHz; RF power: 20mW/200mW/2W; Imp.: 50Ω; Accuracy: ±10% full scale; N-type connector. SWR <1.15

VHF/UHF ATTENUATORS



RT-8815 $199.00, VHF, 500MHz, 81dB, 50Ω, 0.5W.
RT-8815U $359.00, UHF, 950MHz, 81dB, 50Ω, 0.5W.
RT-8817 $199.00, VHF, 500MHz, 81dB, 75Ω, 0.5W.
RT-8817U $359.00, UHF, 950MHz, 81dB, 75Ω, 0.5W.
085E-2 $499.00, UHF, 950MHz, 61dB, 50Ω, 0.5W.
087E-2 $499.00, UHF, 950MHz, 61dB, 75Ω, 0.5W.

ON SALE - Power Supply
8102 ~~$399.95~~ $359.95 triple outputs, 0-30V/0-3A **x 2,** fixed 5VDC/3A, independent & tracking operation, constant voltage (CV) & constant current (CC), Slave/Master, Serial/Parallel connection.
PS-303D ~~$314.95~~ $282.95 dual outputs/tracking, CC&CV.
Limited quantity. Full one year warranty.

RF SIGNAL GENERATOR

SG-4160B $124.95
100KHz-150MHz up to 450MHz on 3rd harmonics; 6 ranges; AM modulation. *RF Output*: 100mVrms to 35 MHz. *Modulation*: Int. 1KHz AM, Ext. 50Hz-20KHz AM.
Audio Output: 1KHz, 1Vrms.
SG-4162AD $229.95, with Freq. Counter 1Hz-150MHz, 6 digits, for internal & external signals. Specification see SG-4160B.

AUDIO GENERATOR

AG-2601A $124.95
10Hz-1MHz, 5 ranges;
Output Level: sinewave 0-8Vrms, square 10Vp-p.
Output Impedance: 600 Ohm.
Distortion: <0.05% 500Hz-50KHz; <0.5% 50KHz-500KHz.
AG-2603AD $229.95, with Freq. Counter 1Hz-150MHz, 6 digits, for internal & external signals. Specification see AG-2601A above

FUNCTION GENERATOR

FG-2100A $169.95
0.2Hz-2MHz in 7 ranges; Sine, Square, Triangle, Pulse & Ramp
Output: 5mVp-p-20Vp-p, 1% distortion.
VCF: 0-10V control freq. to 1000:1.
FG-2102AD $229.95 generates signals same as FG-2100; 4-digit counter display, TTL & CMOS outputs, 30ppm ±1 count accuracy
FG-2020B $159.00 0.5Hz-500KHz; Sine, Square, Triangle.
(FG)2103 $329.95, Digital sweep generator, 0.5Hz-5MHz in 7 ranges. *Operating Mode*: sweep, AM, gated burst, VCG.
Freq. Counter: Int. 0.5Hz-5MHz, Ext. 5HZ-10MHz.
FG-513 $719.95, Digital sweep generator; Sine, Square, Triangle, Pulse, Ramp, TTL & DC; 2Hz-13MHz in 7 ranges; ±(.01%+1dgt).
Freq. Counter & TCXO: 5Hz-100MHz, 6.5 digits, x1 & x20 attntn.

FM STEREO MODULATOR

AG-2011A $549.00
RF SECTION:
Carrier: 98MHz ±2MHz;
Output: 10mV, 1mV & 0.1mV
COMPOSITE SIGNALS:
Pilot: 19KHz ±2Hz, 0.8Vrms
INT. MODULATION: 400KHz, 1KHz ±1%, 1Vrms, distortion < .5%; *L-R Separation*: >50dB.
EXT. MODULATION: *Freq.*: 50Hz-15KHz
L-R Separation: >45dB 100Hz-3KHz, >35dB 50Hz-15KHz.

AC MILLIVOLT METER

MV-3100A $159.95 wide band 5Hz~1MHz; 3 scales, mV, dB &dBm; 300μV~100V in 12 ranges, 10μV resolution; -70~40dB in 12 ranges, 0dB=1Vrms,0dBm=0.755V); ±3% accuracy; Input impedance 10MΩ; Noise <2%. **MV-3201B $309.95** dual channels, simultaneous measurement.

OSCILLOSCOPES

OS-7305B $249.00 DC~7MHz;
Vertical: 10mV/Div; Horizontal: 250mV/Div; 10Hz~100KHz in 4 ranges; 3" CRT; Internal and External Sync.; Input: 1MΩ/35pF.
OS-7010A ~~$369.0~~ $299.95 10MHz. 5" CRT, 10mV/cm~10V/cm, 1MΩ.
OS-622G $344.95 20MHz/dualtrace
OS-653 $699.95 50MHz, dual, delay sweep, ALT trigger, TV syn.
OS-6101$1499.95 100MHz, 4ch/8 trcs, delay swep,cursor readout

DIGITAL MULTIMETER

DMM-120 $24.95, 3½ digit, 600VDC/AC, 2ADC, 2MΩ, hFE/diode test.
DMM-123+Capacitance $44.95, 3½ digit, 600VDC/AC, 10ADC/AC, 2GΩ, 20μF, hFE/diode test, continuity beeper.
DMM-125 $54.95, Autorange/Bar Graph, 600VDC/AC, 2ADC/AC, 32MΩ, continuity beeper.
MIC-35 $59.95, Autorange, 3½ digit, LCD, 1000VDC/750VAC, 20MΩ, 20ADC/AC, diode/continuity check, data hold.
MIC-39 $149.95, Autorange/Bar Graph, True RMS, 3¾ digit, LCD, 40MΩ, 40μF, 1000VDC/750VAC, 20ADC/AC, 600KHz Freq. Counter, Data Hold, Drop-prove, Sleeping Mode, Memory, Read Functions.

GRID DIP METER

DM-4061 $89.95 1.5-250MHz, 6 bands; 6 plug-in coils, 2 transistor, and 1 diode.
Modulation: ≈ 2KHz Sinewave.
Crystal Oscillator: 1-15MHz.
Wave absorption meter. 9VDC battery.

AUTO DISTORTION METER

DM-3104A $799.95
MEASUREMENT:
Range: 0.01%-30%, 0.1/0.3/1/3/10/30% full scale.
Freq.: 400Hz±10%, 1000Hz±10%(HPF).
Input: 3mV-100V, ratio measuring 20dB.
Auto. Switching Ranges: Fundamental Freq. = (fo)±10%;
Fund. Rejection: >-80dB at (fo)±5%; >-70dB at (fo)±10%.
Harmonic Accuracy: ±0.5dB, 1.8(fo)-20KHz.
DM-3204 $1,599.00 dual channels.

FREQUENCY COUNTER

FC-5250C $119.95
Freq. Range: 10Hz-220MHz (HF)10Hz-20MHz, (VHF)10MHz-200MHz
Gate Time: 0.1 & 1sec.
Max. Input: 10Vp-p.
Input Sensitivity: 35mV 10Hz-200MHz. *Display*: 7-digit LEDs.
Input Impedance: (HF) 1MΩ, (VHF) 50Ω.

FC-5260A ~~$146.00~~ $129.95
10Hz-600MHz. 7-digit LEDs.
FC-5270 $149.95
10Hz-1.2GHz. 8-digit LEDs.
FC-5600B ~~$321.00~~ $299.95
10Hz-600MHz. 10-digit LEDs.
(FC)5700 $329.95 10Hz ~ 1.3GHz. 10-digit LEDs.

SIGNAL TRACER/INJECTOR

SE-6100 $134.95
TRACER: Gain Max. 60dB
Attenuation: 0/20/40/60dB
Input Impedance: 100KΩ;
Output Imped.: 600Ω;
Speaker: 8 Ω.
INJECTOR: *Freq.*: 1KHz Squarewave; *Output Level*: Continuously variable 0 - 4.5Vp-p.

AUTO. CAPACITANCE METER

CM3300A $139.00 10 ranges, 99.9pF ~ 99.9mF, fully automatic.
Resolution: 0.1pF lowest, 0.1% full scale.
Accuracy:
0.5% of full scale±1 digit to 99.9μF,
1% of full scale±1 digit to 99.9μF.
Display: 3 digit LED.
Unit indicator: pF, nF, μF, mF. Overrange indicator.

WOW-FLUTTER METER

WF-3103A $699.95
Freq. Range: 3KHz±10% JIS/CCIR; 3.15KHz±10% DIN.
Range: 0.03/.1/.3/3% full scale.
Accuracy: ±5%.
WF-3105A $799.95, digital;
Function: LIN/WOW/Flutter/WTD.
Freq Counter: 10Hz-9.99MHz.
Indication: CCIR/DIN/JIS.

ELECTRONIC/PC TOOL KITS

9Z45 $29.99 U.S. Patented, 45-pcs. Contents: IC Inserter, IC Extractor with securers & Bows, 3-prong part Retriever, #0 Phillips Screwdriver, 1/8" Flat Screwdriver, Self-hold Tweezers, Metal Tweezers, Extra Parts Tube, Soldering Iron, Solder, Crimping Tool, Long-nose Plier, Cutting Plier, Zipper vinyl Case. Bits include: *Phillips*: #0, #1, #2, & #3; *Flat*: 1/8", 3/16", 1/4", 9/32"; PZ1, PZ2; T8, T9, T10, T15, T20, T25, T27, T30, T40, T45; *Hex*: 5/64", 3/32", 1/8", 5/32", 3/16"; *Sockets*: 3/16" (5mm), 7/32" (5.5mm), 1/4" (6mm), 9/32" (7mm), 5/16" (8mm).
8G23 $34.99 U.S. Patented, 23-pcs. Contents: IC Inserter, IC Tweezers, IC Extractor with securers & Bows, 3-prong part Retriever, 3/16" Nutdriver, 1/4" Nutdriver, 3/16" Slotted Screwdriver, 1/8" Slotted Screwdriver, #0 & #1 Phillips, Reversible T10/T15 Bits, Reversible #2 Phillips/¼" Slotted Bits, Tweezers, Long-nose Plier, Cutting Plier, 6" adj. Wrench, Soldering Iron, Solder, Crimping Tool, Zipper vinyl Case, Manual.

MICROPROCESSOR TRAINER

$699.00 learn 8088 hardware design and software programming.

KONNEX DISTRIBUTING. Call 1-888-777-7874. PO Box 451372, Los Angeles, CA 90045. CBs, antennas, meters, transistors, microphones, accessories. Best prices.

HR2510: 10M amateur mobile radio's **"NEW,"** 1250 IC $275 ea. COD, S&H extra. Free S&H if prepaid. D&R Electronics, 10 Park St., Thomaston, CT 06787, 860-283-9492 phone.

240+ CHANNEL CB/HAM/COMMERCIAL radios: AM/FM/ISSB/CW export/domestic: RCI, Motorola, Uniden, Cobra, Alinco. Mics, antennas, linears, meter, books, night scopes, and tons more stuff! Catalog $3. MAXTECH, Box 8086, New York, NY 10150. 718-547-8244.

MUSIC & ACCESSORIES

TURNTABLE, RECORD player, phonograph repair parts. West-Tech, Box 1415, Sebring, FL 33871, 941-471-0922, FAX 941-471-3817.

COMPUTER HARDWARE

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.



19" RACKMOUNT PC chassis: Heavy duty, 4U, 8 slots expandable to 12, two (one hidden) 3.5"/two 5.25" drive bays, front panel fan, mini tower power supply not included, $209 with this ad! Monitor chassis $269, keyboard chassis $139. 8255-8253 I/O card with prototyping area $69, 12-bit ADDA card $89, both with software. **Computronics Technology,** 972-242-8087.

MILLIONS IN scrap gold are about to hit the market in the form of old computer junk. I'm making a bundle recycling this material and you can join me. Call 24-hour message: 603-645-4776.

FIX ANY PC in a flash with BUSPORT™ diagnostic card it fully tests all ISA, EISA, 80x86 Pentium systems. Call now! 702-677-9237 or write to: 4M Technology, POB 6949, Reno, NV 89513-6946 or E-Mail: buspost@4mtech.reno.nv.us Web: http://www.greatbasin.com/~4mtech

CRTs CHEAP. Buy direct from the manufacturer. Save money. Mfg. all CRT types since 1950. **3 year warranty**. Reg-Res 19" tubes $75; 25" $100; hi-res 13" tubes from $80. We specialize in **hi-resolution** video/computer CRTs. **T.M.C.** 215-226-0749/215-223-0388.

ROGER'S SYSTEMS SPECIALIST. SCSI fast wide cables, ten Base T cables and hubs, bi-directional 1284 I-EEE printer cables, micro-centronics type $1.50. 9 ft. modem cable $1 each. Pentium ball bearing fans $2 ea. Hundreds of items. Call for catalog. Most orders shipped same day. Visit our web site www.rogerssystems.com 1-800-366-0579.

TANDY/RADIO SHACK Model 1/3/4,1000 Support. Monthly magazine, software, parts, repair. Computer News, POB 50127, Casper, WY 82605-0127. 307-265-6483.

SVGA MONITOR $80; 486 computer, monitor $350; HP plotter 7475 $75; HP plotter 7550A $100; HP plotter 7470 $50; 386 computer $100; 286 computer $50; HP Think Jet printer $40; HP Paint Jet 3630A $75. Much more call 714-827-7345.

PC INTERFACE to controller area network using CANPORT. Powerful device connects to PC parallel port. Includes DLLs, libraries, application. Send $109: EMICROS, 25759 Ridgewood, Farmington Hills, MI 48336. 248-477-6639, www.emicros.com

PLOTTERS: HP 7090A measuring plotter $1,500. **HP 7595A** DraftMaster I (sizes A-E) $1,675. **HP 7475A** $220. Excellent condition, warranty. Pepper Systems, 214-353-0257 Fax: 214-902-9511.

MACINTOSH SYSTEMS, repairs, parts and peripherals. Low prices on new, refurb, and used Macs and peripherals and all Mac parts. Repairs of whole units or repair or exchange of parts. Mac Shack 716-377-9230, FAX 716-377-9573. Visa/MC accepted. www.vivanet.com/~macshack

RAINBOW KITS

Many of our kits are available completely built!

SUPER SENSITIVE 1.5w AMPLIFIER

Listen through walls, hear conversations across the room. Add a parabolic reflector and hear blocks away. Makes an ultra sensitive intercom. Can be used as a 1.5W AMP. We supply a mini-electret mike in the kit. Power requirement 6 to12v DC. SIZE:1.75"x 1"

AA-1 BUILT $29.95 KIT **10.95**

STROBE LIGHT

Do you need an attention getter, warning light,or flashing light for model airplanes? Then this kit is for you. Use it as an emergency light for your auto, radio tower, even use it on your bicycle. Has a variable flash rate.Power requirement 6 or 12v DC. Size 3.5"x1.9"

ST-1 KIT **$11.95**

WIDE BAND PRE-AMP



Teflon printed circuit board and surface mount technology for better performance.

Use the **WBA-6** amplifier for scanners, HT's, Frequency counters, Satellite Receivers. It amplifies low-level (weak) signals. If the signal is extremely low , two amplifiers can be used in a series.

- 1MHz to 2.5 GHz 2.8dB NF
- 1dB compression=0dBm
- Gain: 1MHz- 20dB to 2.5GHz-6dB
- Power requirement: 12v @ 6Ma

WBA-6 KIT **$19.95**

AUDIO PREAMP

Boost your microphones output to line level!

Plug your mic into our AP-1 and drive your amp. to full capacity. Connect an AP-1 to a pair of amplified speakers, plug your mic in and you have an instant PA system. Requires 6 to 12v DC Size: 1.75" X 1"

AP-1 KIT **$9.95**

FM STEREO TRANSMITTER



Own your own FM radio station. Any stereo signal you plug into the FMST-100 will be transmitted to any FM radio tuneable from 76 to 108MHz FM. Transmit a wireless link through an auditorium, from your car to your camper, listen to your CD's while mowing the lawn, Play music on one channel sing on the other. Clarity is excellent, aprox. 40dB stereo separation. Length of antenna determines the distance of transmission. Complete with stereo input level controls & crystal for stereo separation. 9v battery operation. SIZE: 1.5" x 2.5" x 3"

FMST-100 Cabinet **$8.95** KIT **$29.95**

He-Ne Laser Kit.



A Laser switching power supply kit

Input 12v Dc 1A, Output 2 to 12 KV at 3 to ma. Trigger voltage aprox. 8 to 10KV Complete with PC Board 6.25" x 2.25", schematic and all parts

LPS-1 KIT **$69.95**

B He-Ne Laser Tube

L1MW-1 KIT **$49.95**

C Mirror motor kit

Project Lissajous patterns on walls. Comes complete with 2 Motors, 2 Front Surface Mirrors, Mounting Brackets, and Speed Control.

MM-2 KIT **$34.95**

D Deluxe Case

LDIS-1 KIT **$49.95**

• Laser Tube	$49.95
• Power Supply	$69.95
• Mirror motor kit	$34.95
• Deluxe Case	$49.95
TOTAL	$204.80

Laser Special all for $189.95

$14.85 DISCOUNT



TV NOTCH FILTERS

FOR CHANNELS 2 thru 22 ONLY

Our TV filters eliminate unwanted TV channels or interference that alters both sound and video with a beep beep beep. Works on cable channels (2 thru 22) only.



NOTE: All TV Filter Kits are sold for educational purposes only. You must obtain permission from your local cable company before using these filters on your cable system.

DF-222 KIT **$14.95**

SWEET 16 TONE DECODER

Sweet 16 tone decoder operates great over phone lines, radios or scanners.

- 16 TTL Level Outputs
- DTMF Decoder Decodes 16 different touch tones using the phone, radios, or scanners.
- One relay & driver circuit on board.
- 9v battery powered. Size: 2 3/4" x 2 1/8"

TT-16 KIT **$34.95**

Project 5 different red beams

CONSTANT or BLINKING

- 3.5 mw • 645 nm
- 1600 ft range. • Class IIIA
- 10 hr continuous use
- Two "AAA" batteries included
- Includes 5 different Logo rings. 5 1/4" L x 7/16" diam.

LP-5 **$44.95**

DC VOLTAGE MONITOR



If battery status is important, you need this kit. This kit uses 7 LEDs to monitor 12v DC in 1v, 1/2v, or 1/4v steps. Monitor 8v or 5v in 1/4v steps. Great for boats, motor homes, model planes or race car ni-cads. All parts and instructions are included.

VM-1 SIZE: 1.3" x 2.7". KIT **$7.95**

VM-110 monitor 110v AC KIT **$10.95**

PHONE TONE GENIE

Control 4 separate devices with DTMF tones from anywhere in the world!

- Easy to operate.
- One push button programming.

Simply connect your Phone Tone Genie to your phone line and program in a security code using DTMF tones up to 16 digitsin length with your telephone. Any device connected to the Phone Tone Genie can then be turned on or off by entering your security code. Each device may operate off of 120 AC and up to 2 Amps ***Operates from 12 VDC Wall transformer which is included.*** Size 1.5"Hx5"Wx5"D

- **Turn a device ON or OFF, from anywhere in the world.**
- **Listen for any sounds in your house using the AA-1 Big Ear kit.**
- **Connect the Phone Tone Genie to the speaker of your scanner or ham radio to listen for a special tone code that can turn on an emergency radio for fireman or police.**

PTG-1 BUILT **$139.95** KIT **$99.95**

PTG-C Case **$12.95**

INFRARED ANALYZER

Connect to your computer, see the code pattern from your remote control or any other remote control device.

ALL SOFTWARE INCLUDED

- Will run on any 80386 or 80486 based machine equipped with VGA graphics and DOS 3.3 or higher.
- The computer reads a value every 15 Microseconds, total sampling time is approximately 2 seconds
- Zoom in on and view any 8 millisecond portion of the data, for instant comparison and analysis.
- Sampled data can be saved to Disk.

TIR-1 KIT **$89.95**

This Manual contains schematics, parts lists & P.C. board layouts for many of the Rainbow Kits. Use your own parts to construct our kits.

KIT BOOK $14.95

$9.95 with the purchase of any kit.

ELECTRONIC RAINBOW

Please add sufficient postage First lb $5.00 Canada $7.00 Additional LB. Add $1.00 US FUNDS ONLY We will accept telephone orders for Visa or Mastercard

7F

Electronic Rainbow Ind., Inc.
6227 Coffman Rd. Indianapolis, IN 46268

CALL 317-291-7262 FAX 317-291-7269
INTERNET:www.rainbowkits.com

VISA MasterCard

CALL TOLL FREE
(800) 292-7711 orders only
Se Habla Español

C&S SALES
EXCELLENCE IN SERVICE

CALL OR WRITE FOR OUR NEW FREE 64 PAGE CATALOG!
(800) 445-3201

NEW
XK-700 Digital / Analog Trainer
Elenco's newest advanced designed Digital / Analog Trainer is specially designed for school projects. It is built on a single PC board for maximum reliability. It includes 5 built-in power supplies, a function generator with continuously sine, triangular and square wave forms. 1560 tie point breadboard area. Tools and meter shown optional (Mounted in a professional tool case made of reinforced metal).

XK-700
Assembled and Tested
$189.95

XK-700-SEMI KIT
w/ Fully Assembled PC Board
$174.95

XK-700K - Kit
$159.95

Made in the USA

Elenco Scopes
Free Dust Cover and Probes



S-1325	25MHz		$325
S-1330	25MHz	Delayed Sweep	$439
S-1340	40MHz		$475
S-1345	40MHz	Delayed Sweep	$569
S-1360	60MHz	Delayed Sweep	$749
S-1390	100MHz	Delayed Sweep	$995
DS-303	40MHz/20Ms/s	Analog/Digital	$995
DS-603	60MHz/20Ms/s	Analog/Digital	$1295

Four Functions In One
Model MX-9300

$459.95

Features:
- One instrument with four test and measuring systems:
  - 1.3GHz Frequency Counter
  - 2MHz Sweep Function Generator
  - Digital Multimeter
  - Digital Triple Power Supply - 0-30V @ 3A, 15V @ 1A, 5V @2A

NEW
Tektronix DMMs
- 40,000 count
- High Accuracy
- Tektronix quality
- 3yr warranty

DMM 912 $189
DMM 914 $235
DMM 916 $275

20MHz Sweep / Function Generator with Frequency Counter
Model 4040

- 0.2Hz to 20MHz
- AM & FM modulation
- Burst Operation
- External Frequency counter to 30MHz
- Linear and Log sweep

10MHz Model 4017 $309
5MHz Model 4011 $239

$399

Fluke Scopemeters

123...NEW....$950
92B.....$1445
96B.....$1695
99B.....$2095
105B .NEW...$2495

ALL FLUKE PRODUCTS ON SALE

Technician Tool Kit
Model TK-1500

28 tools plus a DMM contained in a large flexible tool case with a handle ideal for everyone on the go.

$49.95

Fluke Multimeters

Model 10	$63	Model 12	$84
Model 70II	$75	Model 83	$235
Model 73II	$97	Model 85	$269
Model 75II	$129	Model 87	$289
Model 77II	$154	Model 863E	$475
Model 79II	$175	Model 867BE	$650

B&K Precision Multimeters

Model 389	$109	Model 388A	$99
Model 390	$127	Model 2707	$75
Model 391	$143	Model 2860A	$79
Model 5360	$195	Model 5370	$219
Model 5380	$265	Model 5390	$295

NEW
DIGITAL LCR METER
Model LCR-1810

- Capacitance .1pF to 20µF
- Inductance 1µH to 20H
- Resistance .01Ω to 2000MΩ
- Temperature -20°C to 750°C
- DC Volts 0 - 20V
- Frequency up to 15MHz
- Diode/Audible Continuity Test
- Signal Output Function
- 3 1/2 Digit Display

$99.95

B&K High Current DC Power Supply
- Variable 3-14 VDC
- Thermal Protection
- Current Limiting

Model 1686 12A
$159
Model 1688 28A
$239

B & K 13.8V Fixed DC/Power Supplies
Model 1680 6A $39
Model 1682 15A $75

Quad Power Supply
Model XP-4

4 Fully Regulated DC Power Supplies in One Unit
4 DC voltages: 3 fixed - +5V @ 1A, -5V @ 250mA, +12V @ 500A • 1 Variable 0-12V @ 500mA



$29.95

Digital Multimeter
Model M-1700

$39.95

11 functions including freq to 20MHz, cap to 20µF. Meets UL-1244 safety specs.

10% OFF ON ALL STANDARD AMATEUR RADIO PRODUCTS
Including Accessories

Simm Module Tester
Model 898

- Tests 72 and 30 pin SIMMs to 36 bits.
- Stands alone and portable. No other equipment required.
- Automatically identifies width, depth and speed of SIMMs.
- 10 built-in tests identify mosts memory defects Pre-heat cycle prior to tests.

$625

Model XP-581
4 Fully Regulated DC Power Supplies in One Unit
4 DC voltages: 3 fixed - +5V @ 3A, +12V @ 1A, -12V @ 1A
1 Variable - 2.5 - 20V @ 2A

$89.95

Portable Semiconductor Tester
- In or out-of-order circuit tests for transistor, FETs, SCRs and darlingtons.

Model 510

$199

Satellite Finder
Model SF-100A

- Aligns Satelite Dishes
- Range 950-2050MHz
- Audio Tone
- Compact Size
- Self Power Check

$99

Handheld Universal Counter

Model F-2850
10Hz - 2.8GHz
Dual Input
$149

NEW

Model F-2800
1MHz - 2.8GHz
$99

Features:
- Full range 10Hz - 2.8GHz (F-2850)
- 16 segment RF signal strength bargraph 1MHz - 2.8GHz (F-2800)
- Dual 50Ω/1MΩ inputs. (F-2850 only)
- 16 segment RF signal strength bargraph
- 10 digital LCD display with backlight. (F-2850 only)
- 6 hour NiCd battery operation.
- High speed 250MHz direct count for high resolution.
- Multifunctions: Frequency, Period and Auto Trigger & Hold. (F-2850).

Specifications
Input Sensitivity (Typical)

Amplifier	1MΩ (F-2850 only)	50Ω
Impedance	1MΩ (F-2850 only)	50Ω, VSWR<2:1
Range	10Hz - 50MHz (F-2850 only)	1MHz - 2.8GHz
Sensitivity	<10mV @ 10Hz - 10MHz <20mV @ 10MHz - 50MHz (F-2850 only)	<1.5mV @ 100MHz <5mV @ 250MHz <5mV @ 1GHz <100mV @ 2.4GHz
Maximum Input	100Vrms (F-2850 only)	15dBm

Guaranteed Lowest Prices
UPS SHIPPING: 48 STATES 5%
OTHERS CALL FOR DETAILS
IL Residents add 8.25% Sales Tax

C&S SALES, INC.
150 W. CARPENTER AVENUE
WHEELING, IL 60090
FAX: (847) 541-9904 (847) 541-0710
http://www.elenco.com/cs_sales

VISA MasterCard

15 DAY MONEY BACK GUARANTEE
FULL FACTORY WARRANTY

PRICES SUBJECT TO CHANGE WITHOUT NOTICE

Write in 197 on Reader Service Card.

COMPUTER HARDWARE *cont.*

SUPRCHIP© STAND-ALONE controller. Fully assembled & tested 2" square module with 89 pins. Fits 486 PGA socket or specify wire wrap version. Built-in command interpreter/debugger with over 40 commands. **72** I/O ports, used for **RS-232, RS-485**, printer, eight **A/D**, two **D/A**, two timer/counters, 6 int, **encoder**, two **PWM**, **memory expansion.** Requires only 5V/**10mA** & dumb terminal for operation. Use stand-alone or as remote data collection & control. **Free source code** for QB & VB virtual instrument programs. Optional EEPROM. Load & test 6502-type assembly code from RAM or connect EPROM. Manual, complete description and application notes available from our **web site**, www.divaautomation.com (Under construction). Check or MO for $99 + $5 S&H to: DIVA Automation, Inc., POB 461539, Escondido, CA 92046-1539.



WANTED: EXCESS ELECTRONIC INVENTORIES, ICs, MEMORY, EPROMs, PALs, LEDs, CIRCUIT BOARDS, DIODES, AND TRANSISTORS. CALL ACTIVE MICRO, 562-494-4851 OR FAX 562-494-4913.

PENTIUM MOTHERBOARDS, TX chipset, Plug-N-Play BIOS, 3 ISA/4 PCI, 512K Pipeline cache cache, 2-year warranty, runs everything up to 233 MHz, $89, **CPUs:** Pentium **MMX**:166/200/233 @ $179/239/359, **IBM/Cyrix 686** P200+ $86, **Cyrix** 200 **MX** $149, **AMD** K6 **MMX** 166/200/233 @ $169/209/369 24X **CD-ROM**. Audio button $79, 72-pin **SIMMs**, 60ns EDO, 16MB-$49, 8MB-$29. S3 **Virge** video card with 2MB/4MB $39. Call for current pricing, other parts and illustrated catalog. Minimum 1-year warranty, techspecialties, Inc., 5703 Heffernan, Houston, TX 77087-4113, 1-800-864-5391 for orders and tech support, fax: 713-307-0314.

INDUSTRIAL ELECTRONICS bonanza: Collection of brand new General Electric machine tool quality switches, pilot lights, proximity sensors, motor starters, etc., includes green PB, reflex photo limit switch, proximity switch, lever limit switch, relay contacts, red light, green light, spring switch, accessory kit, red light, black PB, photo sensing head, polarized retroreflector, selector switch, green light, magnetic starter, DPST relay, renewal parts, aux connector kit, amber light, pneumatic timer, capacitance sensor, red PB, big barrel proximity switch, mini prox switch, overload relay, black switch photo limit switch, limit level, amber lamp, limit switch, armored cable, aux connector kit, magnetic contactor, more. In original boxes at 19 cents on the dollar. $249 for the lot. Synergetics Surplus, 3860 West First Street, Box 809, Thatcher, AZ 85552. 520-428-4073. synergetics@tinaja.com VISA/MC.

APPLE DUAL 200 MHz 604E PPC card for 8600, 9500 or 9600MP $825. **Philips New PM9210** 1GHz HF probe for DC voltmeters $295. 415-842-3268.

MITSUBISHI COLOR PRINTERS, dye-sub, 8-1/2" x 11" output. 2 pcs. available @ $200 ea. Call Roger at GS&E 716-338-7001. VISA-MC available.

FLOPPY DRIVE REPAIRS $1-$25. PCs, PS2, Mac, Apple II, 8". Since 1983. 6 month warranty. 1-800-458-6778. ISR, 2217 Downing Ln., Leander, TX 78641.

SONY/AMIGA MULTISCANS 15" 00.26 DP 15.7 thru 36KHz (1024x768I). $150. Blem SVGAs $110. Others available. Expert Sony repair, parts available. **DEALER DISCOUNTS**. Refurbished Guaranteed. Pikul & Assoc., 101 Glenfield Dr., Festus, MO 63028. 314-937-0335.

486DX OPTI ISA motherboards, new w/manual, $24, 1.2 GIG IDE HD, $95, Turtle Beach Tropez sound card + Midisoft Studio $69.95. American Techna-Vision 510-352-3787.

COMPUTER EQUIPMENT: C64, C128, Amiga, disk drives, monitors, printers, software, etc. Bargain prices. Send a self-addressed stamped envelope and $1 for a complete listing to: LL Landucci, 3198 Shady Oak Lane, Verona, WI 53593. Money refunded with first order.

TRS-80 MODELS 1, 3, 4, 100, pocket computer, and COCO. #10 SASE, 54¢ stamp, to TRS-80 AGAIN, 100D W. Falls St., Kings Mountain, NC 28086-3664. E-Mail: petebum@aol.com

Quality Reconditioned
TEST EQUIPMENT

Hewlett-Packard 8341B

Synthesized Sweeper, 0.01 to 20.0 GHz, 1 to 4 Hz frequency resolution, low spurious and phase noise, complete analog sweeper. Opt 003, low harmonics, Opt 004, rear panel RF output with 90 dB programmable attenuator.

$26,000.00

Hewlett-Packard 8642B

Signal Generator, 100 kHz to 2115 MHz, +20 dBm max output level, <-134 dBc/Hz SSB phase noise at 20 kHz offset, am/fm,Φ M and pulse modulation. Opt 001, high stability time base, Opt 002, RF connectors on rear panel.

$32,500.00

Hewlett-Packard 8970B

Noise Figure Meter, 10 to 1600 MHz, accurate and simple, swept or CW measurements, second-stage correction, noise figure and gain display.

$11,750.00

Hewlett-Packard 8590B

Spectrum Analyzer, 9 kHz to 1.8 GHz, wide amplitude range extends from -115 dBm to +30 dBm, 32 Kbytes of user memory, Opt 021, HP-IB.

$8,000.00

Hewlett-Packard 5370B

Universal Time-Interval Counter, 11 digits/s freq. resolution, 20 ps single shot LSD, ±100 ps accuracy achievable, frequency and period to 100 MHz, 8000 measurements possible, built-in stats functions.

$2,750.00

Hewlett-Packard 1650A

Logic Analyzer, 80 channels of 25 MHz state/100 MHz timing, 1 kbit/channel,supports most 8, 16, and 32 bit microprocessors, HP-IB.

$1,995.00

Hewlett-Packard 1650B

Logic Analyzer, can be configured as a 1 or 2 state analyzer, 80 channels of 35 MHz state/100 MHz timing, 1 kbit/channel,supports most 8, 16, and 32 bit microprocessors, HP-IB.

$2,750.00

Hewlett-Packard 8642A

Synthesized Signal Generator, 100 kHz to 1057.5 MHz, <-134 dBc/Hz SSB phase noise at 20 kHz offset, -100 dBc nonharmonic spurious, +20 dBm max output level.

$19,995.00

Hewlett-Packard 5342A

Microwave Frequency Counter, 500 MHz to 18 GHz, 11 digit LED, sensitivity to -25dBm. Opt 001, high stability time base, 011, HP-IB.

Special $2,250.00

Hewlett-Packard 3582A

Spectrum Analyzer, .02 to 25.5 kHz, 0.02 Hz resolution, 70 dB dynamic range, transfer function, coherent function, phase spectrum, and frequency domain analysis, internal noise source, HP-IB.



Special $1,995.00

Hewlett-Packard 8568A

Spectrum Analyzer, 1000 Hz to 1500 MHz, -137 dBm to +30 dBm amplitude range, features frequency counter accuracy, digital display, store and recall control settings, HP-IB.

$13,000.00

Hewlett-Packard 8568B Opt. E96

Spectrum Analyzer, 100 Hz to 1500 MHz, resolution bw from 1 kHz to 3 MHz in a 1, 3, 10 sequence. Phase noise is 107 dBc. Amplitude is -135 to +30 dBm. Call for Special option info.

$19,750.00

Racal-Dana 9087

Synthesized Signal Generator, 10 kHz to 1.3 GHz, 1 Hz resolution, output -140 to +19 dBm, 0.1 dB resolution, non-volatile memory.

$2,500.00

Hewlett-Packard 3586B

Selective Level Meter, makes carrier measurements to 32.5 MHz, voice channel measurements from 50 Hz to 100 kHz. Can use 3336B level generator as an automatic tracking generator. Has opt 001, 003 & 004.



$850.00

Wavetek 3520 Signal Generator

1 to 2080 MHz, -137 to +10 dBm, frequency resolution is 100 Hz to 1040 MHz and 200 Hz to 2080 MHz, GPIB Programmability, 32 front panel stored settings.

Special $2,900.00

EIP Microwave 548A

Microwave Frequency Counter, 10 Hz to 26.5 GHz, 12 digit resolution, sensitivity Of 25 mV rms, has special option 91, extends frequency of 26.5 to 40.0 GHz, includes opt 05, time base osc, opt 06, extended freq. capability, 08, GP-IB interface. Includes freq. extension cable kit, like new.

$3,900.00

Tektronix 494P

Spectrum Analyzer,10 kHz to 21 GHz, (capable of up to 325 GHz with external waveguide mixers, not supplied), nonvolatile memory storage, direct plot capability, keypad data entry.

$12,500.00

Tektronix 492

Spectrum Analyzer, 50 kHz to 21 GHz, 80 dB dynamic range, amplitude comparison in 0.25 dB steps. Opt 01, internal preselector, 02, digital storage, 03, frequency stabilization.

$8,250.00

Also Tektronix 492P Opt 01, 02, 03

$9,750.00

(602) 483-6202 • Fax (602) 483-6403

14455 North 79th Street, Unit #C • Scottsdale, Arizona 85260

WANTED: USED TEST EQUIPMENT

DANBAR SALES COMPANY

by Ryan Sheldon

RS-232 Relays

Computer control of the outside world is a somewhat difficult task for many computer users. I have talked to many people who want to control something with their computer, but lack the knowledge or resources required to actually build the device they need. Like most computer users, I believe programming external devices should be as easy as possible. So, in this article, I intend to simplify the task of hardware and software design by showing what tools can get the job done quickly and effectively.

In the ideal computer-controlled utopia, the user could program external devices to perform simple tasks like opening doors, turning on lights, or just checking the temperature outside. While these needs are simple and the tools are becoming available, integrating these new developments can be an intimidating job. But I think I can show you some clever new tools that will greatly simplify these types of tasks.

RS-232 communications, as you probably know, is nothing new. And because it is so readily available, it only makes sense to use RS-232 for some complicated computer control applications. While RS-422 and other standards boast greater communication distances and speeds, RS-232 typically has the ability to operate over several hundred feet at low baud rates ... perfect for simple control applications like you are about to see.

Explaining RS-232 communications could take a while so I won't do that here ... in fact, I'm going to dodge that topic altogether. Many publications and articles are available on this topic. What is important to understand for our purposes is that you need only two wires to control the devices outlined in the schematic, and that you need only four lines of QBasic code to make these circuits work.

RS-232 Control Network

Have you ever heard of an RS-232 control network? If not, don't worry, it's kind of new. The concept is old and has been around for years. What's new about it is that it is being applied to RS-232 communications for use in low-speed industrial control applications.

An RS-232 control network allows several devices to be attached to a single RS-232/RS-422 serial port and each device can be controlled individually. National Control Devices is among the few companies supporting this type of control network. With it, you can control relays, LCD character displays, LCD graphics displays, hobby servos, and high-power DC motors, and several audio/video control devices ... all from a single RS-232 port.

What makes this type of control network possible is a series of interface processors programmed into common PIC microcontrollers. Here, I would like to introduce you to the NCD-110 interface processor. This processor is the basic element of the NCD RS-232 control network. This processor has a four-bit address that is set using jumpers J1-J4 (see schematic). This processor also has a four-bit data output.

The NCD-110 acts something like a serial-to-parallel converter chip, only instead of giving you eight output bits, it gives you four. It uses what would have been the other four output bits to determine its address.

When a byte of data is received from the serial port of your computer, the NCD-110 breaks the byte into two sections. Each section contains four bits called nibbles. The first nibble (most significant nibble, MSN) is used as the address, the other nibble (least significant nibble, LSN) is the data.

What this means to you is that you can connect 16 of the NCD-110 interface processors to a single RS-232 serial port and have 64 output bits from a single serial port.

Later in this article, I will show you how to interface this processor to a CMOS 4099. This will give you eight output bits for each NCD-110, providing a total of 128 individual output bits that can be controlled from a single RS-232 serial port.

RS-232 Transmission

The RS-232 serial port can send out a maximum of 256 characters. This is illustrated using the QBasic example program shown in Program 1. Note that this program assumes you are using COM2.

If you connected the LED as shown in the "RS-232 Connections" diagram, this program would cause the LED to flash. These flashes represent data traveling from the transmit line of your RS-232 port.

When an NCD-110 is set to address 0 (J1-J4 jumpers removed), the NCD-110B ignores all ASCII characters except for 0-15. See Table 1.

Table 2 tells you how to set the jumpers on the NCD-110. The address number will also be referred to as the device number. The range column is very important. This list shows what ASCII characters the NCD-110 will respond to, depending on the settings of the address jumpers J1-J4.

Controlling Relays with the NCD-110

I chose to control relays in this article because they have a practical application to real-world control systems and they are easy to understand. In the quad relay example, the NCD-110 is directly driving the relay buffer circuitry. And based on what you now know about the NCD-110, a single RS-232 character can be used to control all four relays simultaneously.

When controlling relays, I would advise the use of an optoisolated RS-232 input stage. We omitted this because it is not absolutely necessary and we wanted to simplify the communication to the NCD-110. Note that mechanical relays produce large flyback voltages that are clamped by the use of the 1N4007 diodes. A 47 uF capacitor should also be used across the power supply poles to help absorb the flyback voltages.

A 4 MHz ceramic resonator is used in this design to control the speed of the NCD-110 interface processor. The NCD-110 is based on a PIC 16C54A, and is programmed to operate at 9600 baud without a jumper installed on J5, and at 1200 baud with a jumper installed. High-speed versions of the NCD-110 will be available soon.

CMOS 4099

The NCD-110 can also be interfaced directly to a CMOS 4099 eight-bit addressable latch. When attached, the user loses the ability to set all the logic levels with a single ASCII character, but gains the ability to individually control eight output bits.

When the NCD-110 is set to address 0, sending ASCII characters 0 to 7 will turn off each of the output bits on the 4099, respectively. Sending ASCII characters 8 to 15 turns on each of the output bits, respectively. When interfaced to relays, a single ASCII character controls a single relay.




```
10 OPEN "com2:9600,N,8,1,CD0,CS0,DS0,OP0" FOR OUTPUT AS #1
20 FOR N = 0 TO 255
30 PRINT #1, CHR$(N);
40 NEXT N
```

PROGRAM 1

Remember, when an NCD-110 is set to address 0, it only listens to ASCII characters 0-15. And when it is set to address 1, the NCD-110 only listens to ASCII characters 16-31. This method of addressing continues up through ASCII character 255. If you are into programming, you can create powerful modules with just a few lines of code. Here are a couple of example relay driver subroutines that handle the entire

RS-232 Networkable Relays

By Ryan Sheldon, National Control Devices, (404) 244-2432, http://members.aol.com/ncdcat/

The schematic shows 3 NCD-110 interface processors connected in parallel to a single RS-232 serial port. Each NCD-110 has a set of 4 jumpers that determine its address. When set to address 0, the NCD-110 only responds to ASCII characters 0 to 15. When set to address 1, it only responds to characters 16 to 31. Each subsequent device number defines which set of ASCII characters the NCD-110 responds to.

For example, if you transmit ASCII characters 0 to 47, device 0 will respond first, then device 1, and finally device 2. Note that 255 ASCII characters can be transmitted from a single RS-232 serial port. This allows up 16 NCD-110 interface processors to share a single serial port. Take note of the address jumper setting (J1 to J4) on each device. Four address jumpers have 16 different possible combinations of settings. This method is used to determine each of the 16 addresses.

Device 0 is a quad relay driver that uses the NCD-110 to directly control the relays. This is the easiest type of relay driver to construct.

Device 1 is a simple 4-bit output processor. Using 16 NCD-110 processors enables the user to control 64 logic-level outputs.

Device 2 shows how easy it is to connect the NCD-110 to a CMOS 4099 8-bit addressable latch. This effectively doubles the output capacity of the NCD-110. In this mode, the user can only control the on/off status of the CMOS 4099 1-bit at a time.



The following ASCII characters only speak to device 1. The outputs present a binary number of 0 to 15 accordingly.

CHR$(16)	Turn Off All Outputs.
CHR$(17)	Turn On Output 1.
CHR$(18)	Turn On Output 2.
CHR$(19)	Turn On Outputs 1 and 2.
CHR$(20)	Turn On Output 3.
CHR$(21)	Turn On Output 1 and 3.
CHR$(22)	Turn On Output 2 and 3.
CHR$(23)	Turn On Outputs 1, 2, and 3.
CHR$(24)	Turn On Output 4.
CHR$(25)	Turn On Outputs 1 and 4.
CHR$(26)	Turn On Outputs 2 and 4.
CHR$(27)	Turn On Outputs 1, 2, and 4.
CHR$(28)	Turn On Outputs 3 and 4.
CHR$(29)	Turn On Outputs 1, 3, and 4.
CHR$(30)	Turn On Outputs 2, 3, and 4.
CHR$(31)	Turn On All Outputs.

The following ASCII characters only speak to device 2, the 8-relay driver.

CHR$(32)	Turn Off Relay 1.
CHR$(33)	Turn Off Relay 2.
CHR$(34)	Turn Off Relay 3.
CHR$(35)	Turn Off Relay 4.
CHR$(36)	Turn Off Relay 5.
CHR$(37)	Turn Off Relay 6.
CHR$(38)	Turn Off Relay 7.
CHR$(39)	Turn Off Relay 8.
CHR$(40)	Turn On Relay 1.
CHR$(41)	Turn On Relay 2.
CHR$(42)	Turn On Relay 3.
CHR$(43)	Turn On Relay 4.
CHR$(44)	Turn On Relay 5.
CHR$(45)	Turn On Relay 6.
CHR$(46)	Turn On Relay 7.
CHR$(47)	Turn On Relay 8.

The following ASCII characters only speak to device 0, the quad relay driver.

CHR$(0)	Turn Off All Relays.
CHR$(1)	Turn On Relay 1.
CHR$(2)	Turn On Relay 2.
CHR$(3)	Turn On Relays 1 and 2.
CHR$(4)	Turn On Relay 3.
CHR$(5)	Turn On Relays 1 and 3.
CHR$(6)	Turn On Relays 2 and 3.
CHR$(7)	Turn On Relays 1, 2, and 3.
CHR$(8)	Turn On Relay 4.
CHR$(9)	Turn On Relays 1 and 4.
CHR$(10)	Turn On Relays 2 and 4.
CHR$(11)	Turn On Relays 1, 2, and 4.
CHR$(12)	Turn On Relays 3 and 4.
CHR$(13)	Turn On Relays 1, 3, and 4.
CHR$(14)	Turn On Relays 2, 3, and 4.
CHR$(15)	Turn On All Relays.

Note: RS-232 ground MUST be tied to the ground of these circuits.

Diodes (D1) - 1N4007
Transistors (Q1) - 2N2222 NPN
CR - 4 MHz Ceramic Resonator
J5 - Baud Rate Select. Remove for 9600 baud, install for 1200 baud.

RS-232 Relay Driver Boards Available, Contact Ryan Sheldon (404) 244-2432

communication in one wack:

```
SUB RELAY4 (Device!, Pattern!)
   'Compute and send output for a four-relay controller.
   PRINT #1, CHR$((Device * 16) + Pattern);
END SUB
```

In the above example, the RELAY4 subroutine needs only a device number (from 0 to 15) and a pattern (also from 0 to 15). A pattern value of 0 will turn off all relays, while a pattern value of 15 will turn them all on. Other pattern values of 1-14 will actuate the relays in the equivalent binary pattern. So, if nine were transmitted as the pattern, the first and last relays would be on, and the middle 2 would turn off. This happens because the binary equivalent of 9 is 1001.

```
SUB RELAY8 (Device!, Relay!, Status!)
  'Send computed data to an eight-relay controller.
  PRINT #1, CHR$((Device * 16) + (Relay - 1 + (8 * Status)));
END SUB
```

In the above example program, the subroutine needs only three simple variables. A device number from 0 to 15 will tell the routine which NCD-110 to talk to. The relay variable should be a number from 1 to 8 corresponding to the relay that is to be switched. The status variable should be a 1 or a 0. If it's a 1, the selected relay will be turned on; a 0 will turn it off.

The NCD-110 is the easiest of the NCD processors to understand. Many NCD processors are fully compliant to this communications protocol. In future articles, I will show you how you can share this relay driver with our graphics display and many of our other devices ... all using a single serial port on your computer. **NV**

If you have any questions about this article, feel free to call me with your comments and ideas. Please leave a message for me if I'm not around; your call will be returned. Call Ryan Sheldon at (404) 244-2432 or E-Mail at ncdryan@aol.com
If you want to see our complete line of products, visit us at http://members.aol.com/ncdcat/
Visa and MasterCard welcome.

	O4	O3	O2	O1
When ASCII character 0 is received, outputs are	0	0	0	0
When ASCII character 1 is received, outputs are	0	0	0	1
When ASCII character 2 is received, outputs are	0	0	1	0
When ASCII character 3 is received, outputs are	0	0	1	1
When ASCII character 4 is received, outputs are	0	1	0	0
When ASCII character 5 is received, outputs are	0	1	0	1
When ASCII character 6 is received, outputs are	0	1	1	0
When ASCII character 7 is received, outputs are	0	1	1	1
When ASCII character 8 is received, outputs are	1	0	0	0
When ASCII character 9 is received, outputs are	1	0	0	1
When ASCII character 10 is received, outputs are	1	0	1	0
When ASCII character 11 is received, outputs are	1	0	1	1
When ASCII character 12 is received, outputs are	1	1	0	0
When ASCII character 13 is received, outputs are	1	1	0	1
When ASCII character 14 is received, outputs are	1	1	1	0
When ASCII character 15 is received, outputs are	1	1	1	1
		0 = Off	1 = On	

TABLE 1

Binary	Address	J1	J2	J3	J4	Range
0000	0	Remove	Remove	Remove	Remove	0-15
0001	1	Install	Remove	Remove	Remove	16-31
0010	2	Remove	Install	Remove	Remove	32-47
0011	3	Install	Install	Remove	Remove	48-63
0100	4	Remove	Remove	Install	Remove	64-79
0101	5	Install	Remove	Install	Remove	80-95
0110	6	Remove	Install	Install	Remove	96-111
0111	7	Install	Install	Install	Remove	112-127
1000	8	Remove	Remove	Remove	Install	128-143
1001	9	Install	Remove	Remove	Install	144-159
1010	10	Remove	Install	Remove	Install	160-175
1011	11	Install	Install	Remove	Install	176-191
1100	12	Remove	Remove	Install	Install	192-207
1101	13	Install	Remove	Install	Install	208-223
1110	14	Remove	Install	Install	Install	224-239
1111	15	Install	Install	Install	Install	240-255

TABLE 2

CAPITAL ELECTRONICS INC.

"QUALITY IS OUR CAPITAL CONCERN."

Complete On Site Electrical Engineering Lab

- Product Engineering
- Firmware Development
- Reverse Engineering
- RF Circuit Design & Manufacturing
- Micro Controller & EPROM Hardware & Software Development

From Auto-Routing to CNC Routing to Electronic Assemblies. . .
Capital Electronics is Your Best Route For Printed Circuit Boards.

Design/Layout
- CAD Layout Services
- Compatible With Almost All CAD Systems
- From Schematics or Sample PCB's
- Photoplotting Services
- 28,800 Baude Modem

Printed Circuit Boards
- Single & Double Sided
- Multi-Layer & Flexible PCB's
- From Quick Turn Protoypes to Scheduled Production Runs
- Fine Lines, SMT
- Electrical Testing
- Precious Metal Plating

Assembly Services
- Fast Turn Board Stuffing
- Wire Harnesses
- Wave Soldering
- Acquisition of Parts
- Final Testing
- Turnkey Services
- Custom Enclosures

For Quick & Competitive Pricing or More Information, Please Call Us Today!
303 Sherman Street • Ackley, Iowa 50601
(515) 847-3888
Fax (515) 847-3889 • Modem (515) 847-3890

VISA MasterCard American Express

Internet Access:
For Automated Info Response: INFO@capital-elec.com
E-Mail: Quote@capital-elec.com
Web Access: http://www.capital-elec.com

Write in 91 on Reader Service Card.

MONITOR TECHNICIANS! 10 step program for successful analysis; diagnosis, and repair of high voltage and power supply problems in computer monitors. Booklet available for $20 from Computer Vision, 6905 Indian Bay Rd., Montague, MI 49437.

MONITOR ADAPTERS. Convert OEM. (incl. PGA) 31.5KHz & above monitors with BNC connectors to PC use. Model VA10 VGA to RGB+ Sync $45. Model VA11 VGA to RG/Sync-B $55. VA12 VGA to PGA (DB9) $45. Rich, Pikul & Assoc., 101 Glenfield Dr., Festus, MO 63028. 314-937-0335.

LIQUIDATION! STOREROOM cleanout, obsolescent computer stuff, cheap! For list, E-Mail <armanmik@n-jcenter.com> or SASE to Box 785, Ormond Beach, FL 32175.

BUILD YOUR own IBM computer from available parts with the help of an easy to view 79 minute video tape. This award winning VHS shows you how to save money or start a small business by assembling any compatible 386 to Pentium MMX computer in a step by step easy to follow procedure. It's easy when you know how! Order your tape today, while supplies last, only $29 (reg. $59.95) plus $2.95 P&H. Send check to: **EVP, PO BOX 2201, Northlake, IL 60164-0201** or call: 1-800-754-5096 now!

CHEAP IBM PC PARTS! Disk controllers, cases and power supplies, floppy drives, CD-ROMs, motherboards, coprocessors, cables, video cards, fax modems, and more! Examples: NEW **Genuine Intel Pentium CPU** 60/66 MHz and PCI mainboard with 256K cache $75. Tape drive Archive 11250Q 250meg+ used drive, software and new tape $35. Call Under The Wire Electronics (UTWE) 626-930-1121 (or try 818-930-1121 10am-5pm PST) or fax 626-930-1123. UTWE, 235 E. Colorado Blvd. #211, Pasadena, CA 91101. E-Mail: JohnUTWE@aol.com

EXTERNAL SCSI cases with power supply for CD-ROM, tape, hard drive, etc. Includes 2 Centronics 50 pin connectors and internal cables, power LED, power cord, etc. Used but in good condition. Single device case $30, 4 device case $50. New cases also available! Call Under The Wire Electronics (UTWE) 626-930-1121 (or try 818-930-1121 10am-5pm PST) or fax 626-930-1123. UTWE, 235 E. Colorado Blvd. #211, Pasadena, CA 91101. E-Mail: JohnUTWE@aol.com

NEW "All-In-One" 486 mainboard with DX2-50 CPU (upgradeable) 128K cache 1Meg Video and IDE I/O (and all the cables) for $55 fits in a standard PC case. 16 30 pin SIMM sockets. Win95, OS/2 and Win3.XX video support. Uses 386, 486DLC, 486SX, 486DX and 486DX2 CPUs. Add 1*9 SIMMs for $4 each. Call Under The Wire Electronics (UTWE) 626-930-1121 (or try 818-930-1121 10am-5pm PST) or fax 626-930-1123 UTWE 235 E. Colorado Blvd. #211, Pasadena, CA 91101 E-Mail: johnUTWE@aol.com

GREAT 80486 bare bones system deal! New 486DX2-50 (or 66) CPU, 128K cache, 1 Meg VGA by Video 7, 16 30 pin, SIMM sockets, IDE and floppy controller, 2 serial ports and 1 parallel port, desktop case with 235 watt supply all for $80 (or $95 for 66MHz). New cheap keyboards available too! Call UTWE @ 626-930-1121 (or try 818-930-1121)10am-5pm PST or fax 626-930-1123. E-Mail: JohnUTWE @aol.com

Closing Date
For Next Issue – December 10th

COMPUTER SOFTWARE

PAGING/FAXING build low-cost data routing system for PC networks for alpha pagers or fax messaging. DOS/Windows/Web clients included. Complete system $39 on CD. More information: www.apin.com/datalink Orders only: 1-800-993-7447.

SHAREWARE CATALOG. Over 3,000 programs, free game on every catalog disk. Great prices, bonuses, free disks. Data Mate, Box 2811, Ronkonkoma, NY 11779.

CAM & MOTION SOFTWARE: Z-trace, PCB toolpath, $299. Plotcam motion, $149. cmheater@juno.com MSG/FAX 407-452-7197, 407-459-2729 http://www.megabits.net/ddt

LINUX! LINUX! LINUX! If you aren't purchasing your Linux products from us, you are paying too much! We offer the major distributions (Yggdrasil, Slackware, Red Hat, etc) at **great prices!** We also carry a full range of books. Contact us at **www.cheapbytes.com** and use our secured web server. E-Mail: sales@cheapbytes.com Fax: 209-367-8518. Cheap*Bytes, PO Box 2714, Lodi, CA 95241.

AMAZING PRODUCTS!
ELECTRONIC & SCIENTIFIC DEVICES

ALL NEW! LASER WINDOW BOUNCE SCIENCE PROJECTS *USES SCATTERED AND DIRECT REFLECTIONS*

Remarkable concept allows user to hear sounds within a premise over a beam of laser light reflected from a window or similar surface. Experimental device provide hours of interesting and educational use. Utilizes a visible red laser that simplifies alignment and discourages illegal use. Usable range will vary-expect about 20 to 50 meters. Optional lens will increase range 200 to 400 meters! Further range requires expensive optics. Requires a sturdy video tripod (not incl.) Caution-check local law in your state if planning to use for accessing oral communication.



LWB5 Plans.....*$20.00* *LWB5K* KIT/PLANS.....*$149.50*
LWB50 Ready to Use With Selected Laser Pointer.....*$199.50*
LWB70 Above With High Performance Laser Gun Sight, Long Range Extender Lens and Cushioned Headsets.....*$299.50*

$59.95 6 TRANSMITTER Projects
CAUTION: Check Public Law 90-352

1. *Super Sensitive Ultra Clear 1Mile+ Voice Transmitter*
2. *1 Mile + Telephone Transmitter*
3. *Telephone* DROP IN* Transmitter Line Powered- Needs No Batteries!!*
4. *Tracking/Homing Beacon "Beeping Transmitter"*
5. *Transmitter Rebroadcasts Video or Audio Outputs*
6. *Short Range TV/FM Disrupter "NEAT PRANK!!! Discretion Advised*

All 6 Above Kits Plus FREE Info Data Pack on "HELPFUL HINTS" Using Wireless Devices
COMBOX Kits and Plans.....$59.50

ULTRA BRIGHT LASERS
4 to 7x brighter 650-630 nm Radiation
ALL METAL CONSTRUCTION
1 YEAR WARRANTEE
BATTERIES INCLUDED
LAPN65 15mw equiv 2000 ft.....*$29.95*
LAPN63 30mw equiv 3000 ft.....*$69.95*

FOCUSABLE LASER POINTER From a Small Dot to a Large Spot!
LAPN65F Focusable Above *LAPN65*...*$59.95*

TRANSISTORIZED TESLA COIL
TURNS A LIGHT BULB INTO A SPECTACULAR PLASMA DISPLAY
Transmits Wireless Energy
Noiseless Operation
Pyrotechnic Effect
12 VDC/5 Amps or Battery
115 VAC Optional Converter
Adjustable Frequency
Control For Effect
TCL5 Plans.....*$8.00*
TCL5K Kit/Plans.....*$59.50*
TCL50 Ready to Use.....*$99.50*
12DC/7 12VDC@7Amps.....*$39.50*

NEW CYBERNETIC EAR!
Use For Courtesy Lowering of TV Volume Control etc. Detect Rattles and Other Mechanical Abnormalities, Leaking Gases, Air, or Corona. Great Safety Aid for Shop. Enhances Most Hearing 3 to 4 Times! Adjustable Volume Control, Fits Easily Into Either Ear. Many Many Uses!
CYBEREAR Ready to use...*$19.95*

3 MI TELEPHONE TRANSMITTER
Tunable On FM Broadcast. Excellent Telephone Project. Only Transmits When Phone is Used
VWPM7K Kit/Plans.....*$39.50*
BEEP1K BEEPER ALERT KIT.....*$19.95*

ELECTRIC CHARGE GUN
WITH 15 FOOT RANGE!!
Stuns and Immobilizes Attackers From a Distance. More Knockdown Power than a Handgun!! Check Your State Legality
FREE!! 100KV Stun Gun
ECG10 With STUN100.....*$249.50*

STUNGUNS SOLD SEPERATELY
STUN200 200KV StunGun....*$49.50*
STUN300 300KV StunGun....*$69.50*

JACOBS LADDER
Observe a pyrotechnical display of "traveling" fiery plasma. Starts off as 1/2" arc and expands to over 3" before evaporating into space. This is an excellent attention getting display as well as a winning science project!! With arc control.
JACK1 Plans.....*$8.00*
JACK1K Kit Minus Case.....*$129.50*
JACK10 Ready to Use.....*$249.50*
12KVGEN20 Pwr Supply Only.....*$99.50*
12KVGEN2K Kit of Pwr Supply.....*$79.50*

250KV TESLA COIL
10-14" of Explosive Bolts of Lightning
Transmit Wireless Energy
Strange and Bizarre pyrotechnical effects.
Ion Motors Anti-Gravity
Size 20" H x 8" Sq
Weight - 25 Pounds
115 Volts/2 Amps AC
Labeled "Use Caution"
BTC3 Plans.....*$15.00*
BTC3K Kit/Plans.....*$349.50*
BTC30 Ready to Use.....*$449.50*
BTC4 Plans, 500kv Unit.....*$20.00*

HIGH CRIME AREA SECURITY!
INFINITY+ TRANSMITTER
ROOM MONITOR/ LINE GRABBER/CONTROLLER
- *MONITOR YOUR PREMISES* Avoid ambushes and break ins.
- *ACCESS ON GOING CALLS* Longwinded teenagers!!
- *CONTROL 8 APPLIANCES* Remote control your home!!!
- *EXTRA ADDED FEATURE!!!* Redirect Those "COIN HUNGARY" Toll Calls Made From Pay Phones!!

TELCON3 Plans.....*$10.00*
TELCON3K Kit/Plans.....*$99.50*
TELCON30 Ready to Use.....*$149.50*
Programmed With built in BEEPER ALERT

PHASOR BLAST WAVE PISTOL
130 db of Directional Sonic Shock Waves Energy
Handheld and Battery Operated
PPP1 Plans.....*$8.00*
PPP1K Kit/Plans.....*$49.50*
PPP10 Ready to Use.....*$79.50*

ATTENTION! HIGH VOLTAGE EXPERIMENTERS
Battery Powered Mini Sized Modules for research in: HOVERCRAFT, ION GUNS FORCE FIELDS, SHOCKERS etc
MINIMAX4 4KV@10ma.....*$19.50*

BURNING LASER RAY GUN
UTILIZES LOSSLESS ENERGY CHARGING
All Parts Available
A FUTURISTIC CONCEPT!!
LAGUN2 Plans.....*$20.00*

BURNING CO2 BENCH LASER
HOTTER THAN MOST TORCHES!
All Parts Available
LC7 Plans.....*$20.00*

KINETIC ELECTRIC GUN
PIONEER A FUTURISTIC WEAPON!
DANGER HIGH VOLTAGE
500 Joules Energy Storage
Constant Current Charging
Triggered Spark Switch
Ballistic Velocities
Handheld Battery Operated
Labeled A Dangers product
PROTOTYPED IN OUR LABS JOIN THE RESEARCH!
EGUN1 Plans with Parts List.....*$20.00*
All Parts are Individually Available

3Mi FM BC TRANSMITTER
Safety Product Allows Listening to Children or Invalids in Hazardous Areas, Pools, Ponds etc. Great Security Intrusion Alert! Uses FM Table Top Radio.
FMV1K Kit/Plans.....*$39.50*

ION RAY GUN *PROJECTS ENERGY!*
Star Wars Technology Demonstrates Weapons Potential!
IOG7K Kit/Plans.....*$99.50*

GRAVITY GENERATOR
Demonstrates a unique phenomena of electrical reactions that produce the effect of "anti-gravity". You build and levitate a small mock space ship from simple materials. Excellent scientific demonstration of a fascinating method of levitation.
Levitate an Object!
GRA1 Plans and Book.....*$20.00*
GRA1K Pwr Sup Kit/Plans...*$99.50*
GRA10 Assbled Pwr Sup...*$149.50*

ELECTRONIC HYPNOSIS AND MIND CONTROL
Generates Highly Effective Audible and Visual Stimuli With Bio-Feedback That Can Induce Hypnotic as Well as ALPHA Relaxed States of the Mind. Place Subjects " Under" Your Control. Enhances Hidden PSYCHIC Ability in Many People!
MIND Plans.....*$15.00*
MIND2K Kit and Plans.....*$49.50*
MIND20 Assembled.....*$79.50*

TELEPHONE TAPING SYSTEM
EXTENDED X4 PLAY
Tapes Phone Conversation
20 Mega Input ZI Check Laws!
TAP30X Ready to Use.....*$84.50*
BEEP10 Beeper Alert.....*$29.95*

SHOCK FORCE FIELD/ VEHICLE OBJECT ELECTRIFIER
Hand Shock Balls, Wands. Electrify Objects. Great Payback for Those Wiseguys!
CAUTION Mantrapping is Illegal!!
SHK1K Kit of Pwr Module....*$19.50*

ATTENTION!! RAILGUN EXPERIMENTERS
HIGH ENERGY PULSER EXPERIMENTORS AND RESEARCHERS
RAIL GUN, COIL GUN, EXPLODING WATER, ANTIGRAVITY, MASS WARPING ,LEVITATION, PLASMA PROPULSION, LATTICE SNAPPING, EMP etc
- Lossless Energy Charging
- Programmable Voltage to 2 KV and Energy Control to 3 KJ
- Triggered Spark Switch [1KJ]
- Universal 12 VDC or 115 VAC
- 7.5 X 7.5 X 7" Light weight

UNIT IS SHOWN WITH OUR "DISTRIBUTED ENERGY SOURCE" LAB RAIL GUN
HEP3 Plans High Energy Pulser/Ignitor.....*$15.00*
HOTSHOT
HEP3K Kit/Plans (Minus Energy Storage).....*$199.50*
HEP30 Assembled (Minus Energy Storage).....*$299.50*
HEPCAP 800 Joules Energy Storage.....*$199.50*

INFORMATION UNLIMITED DEPT NV1097
BOX 716 AMHERST, N.H. 03031

24 Hr Toll FREE "Orders Only" Line 1-800-221-1705
Fax Your Order to 1-603-672-5406
9 to 5 pm EST Information Line 1-603-673-4730
See Our Web Site at http://www.amazing1.com

We Accept MC, VISA, Cash, MO, Checks. Please add $5.00 Shipping. COD Orders Add Additional $4.75.
REQUEST A FREE CATALOG!!

BRIGAR ELECTRONICS

7-9 ALICE ST.
BINGHAMTON, NY 13904

PHONE: (607) 723-3111
FAX: (607) 723-5202
E-MAIL: BRIGAR2@aol.com

Send for free catalogue

SERVICE

Most orders ship within 24 hours of placement.
$30.00 Min. Order

DISCOVER NOVUS · VISA · MasterCard

CREDIT CARD DISCOUNT

$ 0.00	- $ 99.99 NET
$100.00	- $249.99 LESS 10%
$250.00	- $499.99 LESS 15%
$500.00	- $999.99 LESS 20%
$1000.00 AND UP	LESS 25%

SERVING: • INDUSTRY • SCHOOLS • HOBBYISTS • EXPERIMENTORS • CONSUMERS

OPEN: MONDAY THRU FRIDAY 7:30AM TO 4:30 PM, SATURDAY 7:30AM TO NOON

CABLE CUTTERS

MFG: GB ELECTRICAL **PART # GC-73**
Precision ground, high strength steel blades Contoured cutting blades hold cable firmly while cutting Cushioned vinyl hand grips for high leverage cutting Cuts copper or aluminum electrical cables including battery cable, welding cable and control cable. Cuts tubing and hose.



DISPLAY PACKAGED
..... $9.95

ULTRASONIC LIGHT SWITCH MFG: LITRONIC
Replaces existing wall switch - Great for home alarm systems or controlling lights & small appliances, ON-OFF Switch-LED TRIP Indicator **COLOR: WHITE**
SIZE: 5"W x 5"H X 1-3/8"D
- **VOLTAGE** 120 OR 277VAC 50/60HZ
- **MIN LOAD** 80 WATT 120V
- **MAX LOAD** 1000W 120V

Sensor Low Power Ultrasonic 25KHZ
- **ADJUSTMENT:** Sensitivity & Time out (0 TO 25 MINUTES)
- **Documentation & schematic included. ENERGY SAVINGS 30 TO 60%**

ORIGINAL PRICE $100.00
SPECIAL SALE PRICE
..... $12.95 EA.
5 FOR $60.00



MOTION SENSING AUTOMATIC SWITCH

2 x 16 SMART LCD DISPLAY GoldStar ELECTRON AMERICA INC.
GOLDSTAR MODEL #LC16208
•Character: 16 •Line: 2 •Power requirement:5vdc @ 3mA
Window size: 5/8" x 2-1/2"L - 2 goldstar drivers: #GM9120 - Display comes mounted on a 3-3/4" x 4-1/4" circuit board with 16 mini push button switches and 3 rectangular LED'S. (No schematics with this item) ***SALE $12.95***



Nidec
Nidec BETA V High Volume FAN # TA600DC
Model # A34263-58
■VOLTAGE: 12 VDC ■2.0 AMP ■200 cfm
■24 watt ■VOLTAGE RANGE 6-14VDC
■ BALL BEARING ■ Sound level: 55.8 dBA
■Aluminum housed - ■ 5 blade phenolic impeller. ■ UL & Csa Approved.
■Size: 6-3/4" Diam. x 2" thick
Brand new factory packed.
list price...$56.95
BRIGAR PRICE $15.95

PANELITE - LIGHTED PUSHBUTTON SWITCH
SIZE: 1-3/8"H x 0.85" DIA.
SOLDER/QUICK CONN. TERMINALS
SPDT - N/O, N/C
BRIGHT FULL SURFACE ILLUMINATION
Opp. force: 7 ONCE
complete with hardware - bulbs included
BRIGAR SALE - YOUR CHOICE ..... *$1.25 EA.*

PART #	COLOR	DESCRIPTION
LB-16WK12-FJ	Green	ON/OFF 3A 125 VAC 3A 250 VAC
LB-16WK12-GJ	BLUE	MOM. 0.4VA MAX 28V MAX
LB-16WK12-EJ	YELLOW	MOM. 0.4VA MAX 28V MAX

LED
LEDTRONICS, INC.
GREEN LED'S
PART# L120TG5B
GREEN DIFFUSED
SIZE: T1
DIAM: .119" - 3mm
1.7V @ 20 mA
BRIGAR PRICE....
100 PCS. @ 6¢ ea.
500 PCS. @ 5¢ ea.
1000 PCS. @ 4¢ ea.

POWER SUPPLY
200 WATT - AT COMPATABLE
MFG: 3Y TECHNOLOGY #PA-4201-1
INPUT: 120/240 VAC (Switchable)
OUTPUT: 5V @ 20 AMP
12V @ 8 AMP
- 5V @ 0.5 AMP
-12V @ 0.5 AMP
UL Approved - Fan Cooled
Size: 8-1/4"L x 6"D x 6"H
AT compatable connectors ..... $ 10.95

WESTERN DIGITAL **MODEL# WDA-L160**
3.5 160 MB IDE HARD DRIVE

Cyl.	R/W HEADS	Sectors Per Track	F ' Matted Mbytes
924	10	35	160

THE WDA-L160 designed for IBM or IBM compatables AT(286,386,and 486) systems. AT interface IDE Hard Drive.
BRAND NEW.... $85.95

MULTIMETER

MFG: PHASTRON
Analog meter movement 50 Micro Amp D.C. full scale. Large 4.5"diam - 3.5" viewing area. Zero adjustment knob. White face. Scales: in Green, Black, and Blue letters. Three AC & three DC Volt Scales. 0 - 2.5,5 and 10. One resistance scale from 0 to infinity. Includes mounting hardware. BRAND NEW - FACTORY BOXED. ***REDUCED PRICE $4.95***

ANALOG PANEL METER
PART # 40-013857

POWER PRODUCTS # HE381
Linear power supply module.
Size: 2-1/4"W x 4-3/4"L x 1-1/2"D
Input: 115vac 50/60hz 271 ma.
Output: 5vdc 5000ma.
Price... $24.95 ea.

PHOENIX CONTACT
Pheonix contact # CM62-PS-120AC/24
Linear Regulated compact **POWER SUPPLY INPUT: 120VAC**
OUTPUT: 24VDC 1AMP
fuse & overload protected. UL & CSA APPROVED. SLIDE MOUNTABLE.
Unit includes heat sink
SIZE: 3"W X 5-1/2"H X 2-1/2"D
NEW FACTORY BOXED. MANUALS INCLUDED. LIST PRICE .. $259.95
BRIGAR PRICE.. $ 59.95

MODULAR TELEPHONE CABLE RJ11
BLACK 10 FT. FLAT CABLE WITH 6P4C MOD Connectors on each end
Gold plate contacts. Fits standard telephone outlets.
SPECIAL SALE PRICE $1.50

PHILIPS
SIGNETICS # SC87C451CCA68
MICROCONTROLLER
ROMless/128 60 I/O 12MHz com. temp 68 PIN PLCC
List price... $24.95
BRIGAR SALE PRICE $3.95

GoldStar
ELECTRON AMERICA INC.
1 MEG 30 PIN SIMM MEMORY MODULE
GOLDSTAR #GMM781000NS70
NON PARITY - 70 ns
BRIGAR SALE PRICE $3.95

PORTABLE FLUORESCENT - MINI LIGHT
Plug in anywhere - No Wiring - as bright as
a 20-Watt Bulb.
■Energy efficient fluorescent bulb costs only pennies a day.
■Plugs into any standard outlet
■Convenient ON/OFF switch
■ portable -plugs into any standard outlet.
■Lasts up to 3 years with normal use.
■UL Listed. - 3.5watt - 120vac
■Size: 5-1/4"Long x 1-1/4"H x 1-3/4"deep
■Color: White Use at Home: kitchen, hallway, stairway, bedroom etc.
Use away: RV, Boat, Motel room, Camp
A LEVITON DIVISION

BRAND NEW - DISPLAY PACKED.
PART# 6508
PRICE....$4.95

SEALED BALL BEARING
MFG: NSK #6203DU

BORE: .668"
Diameter: 5.75" O.D.
.47" THICK
List Price... $7.00
BRIGAR PRICE ... $2.95

CDE CORNELL DUBILIER
EMI/RFI FILTER
CORNELL DUBILIER NF10869-208
RATED 2 X 10 AMP @ 250 VAC, 50/60HZ
PROVIDES FILTERING FOR BOTH SIDES OF LINE. QUICK CONNECT TERMINALS.
SIZE: 3-1/8" X 2-1/8" X 2"
WEIGHT: 1 LB **PRICE .... $4.00 EA.**

Computer Power Supply 225 WATT
MFG: PLESSEY # 90X9109
INPUT: 100-125V~ 4.6A 50/60HZ
200-240V~ 2.6A 50/60HZ
OUTPUT: +5V 27.25 AMP
+12V 7.0 AMP
-12V 0.39AMP
SIZE: 16"L x 6"W X 4-1/2"H
UL & CSA APPROVED - Weight 8 LB
FAN COOLED - ON/OFF POWER SWITCH.
SALE PRICE ... $ 9.95

AC TO DC WALL TRANSFORMER
MFG: AUDIOVOX PART# CNR405
INPUT: 120VAC 60Hz 11W
Output: 12 VDC 300mA
Polarity: Center Neg.
comes complete with 6' zip cord
2.5 mm Female receptacle.
UL & CSA APPR.
SALE PRICE ...
$2.25

MULTIMEDIA MICROPHONE
Omnidirectional microphone is ideal for voice and sound input into your computer multimedia applications.
6 ft. cord with 1/8" stereo jack. Includes stand with tape back for mounting, or mic can be attached to lapel.
BRIGAR SALE PRICE ... $2.95

Write in 52 on Reader Service Card.

THE ROSENTHAL UTILITIES Try **FREE** http://slonet.org/~doren/

FREE DISK CATALOG and discount coupon! Inexpensive, quality, IBM shareware and CD-ROMs. <ASP> vendor: **MOM 'N' POP'S SOFTWARE**, PO Box 15003-N, Springhill, FL 34609-0111. 352-688-9108. momnpop@gate.net

BRAND NEW Windows NT 4.0 not upgrade full install $150. **Mdivicino@erols.com** 860-267-5951, 860-267-4982.

BRAND NEW Windows NT 4.0 server 10 license package $275. **Mdivicino@erols.com** 860-267-5951, 860-267-4982.

MARKETING SOFTWARE outperform them all, get maximum returns. Want more information, call 1-800-228-1628 or connect to HTTP://members.tripod.com/~GD_Enterprises/index.html GD Enterprises, PO Box 292705, Davie, FL 33329.

SONY PLAYSTATION mod chips: These allow you to play international games (imports) also you can play gold/green CD recordable backups. Chip & full instructions $50 ea. qty discounts available. 1-800-663-8530.

IBM SHAREWARE, free catalog, $1 disk, 35¢ specials, huge selection, 100% virus free. PMA, Box 2424, Scottsdale, AZ 85252. 602-496-6547. Specify disk size.

20,000 + TECHNICAL REPAIRS for **TVs, VCRs, PROJECTION TVs, CAMCORDERs, AUDIO** on disk. COMPONENT/BOARD LEVEL REPAIRS. Installs on your hard drive. Easy look-up by model/chassis number. **ADD** your own tech repairs. **PRINT** out repairs. **FREE DEMO. HIGHER INTELLIGENCE SOFTWARE, 60 FARMINGTON LANE, MELVILLE, NY 11747. 1-800-215-5081.**

ATARI & Colecovsion games & magazines wanted! Send your list. Video Games, Box 9542, Pittsburgh, PA 15223.

COMPUTER EQUIPMENT WANTED

WANTED: FOR historical museum, pre-1980 microcomputers, magazines, and sales literature. Floyd, VA 24091-0341 (540-231-6478/540-763-2321).

HP CALCULATORS wanted: models 10, 70, 81, 97S, and calculator watch for private collection. Bob Morrow, 317-855-2348, rkmorrow@aol.com

Z88 PERIPHERALS, manuals wanted. Tel+Fax: 415-567-8504.

WANTED: TERMINALS + PRINTERS: DEC, Wyse, IBM, ADDS, Okidata, Data South, Epson, C.ITOH, etc. Call for quote on any surplus computer equipment. Call Jeremy, 603-673-8077.

TEST EQUIPMENT

MILLIONS IN scrap gold are about to hit the market in the form of old computer junk. I'm making a bundle recycling this material and you can join me. Call 24-hour message: 603-645-4776.

www.lehmanscientific.com check it out! Online inventory! New, used, surplus analytical balances, microscopes, DMMs, oscilloscopes, centrifuges, power supplies, chart recorders, Gaussmeters, unusual experimenter's items! **Lehman Scientific 1-800-784-8680.**

WANTED: RADIO service monitors, IFR, Motorola, Marconi, HP signal generators, spectrum analyzers, and late model HP equipment. 716-763-9104 or 716-661-9964. Fax: 716-763-0371. http://www.madbbs.com/amtronix

GENERATOR/OSCILLATOR SALE: HP 8640B/002/003 1024MHz $1,800; HP 8640B/001 512MHz $850; HP 8656A 990MHz (HP-IB) $1,950; HP 8601 $375; HP 652B $200; TEK FG 504 40MHz $375; FG 507 2MHz $425; HP 8616A $275. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

SPECIAL PURCHASE Sorensen lab power supply QRD 40-75 $50, 4 available; Fluke 8000 DMM $60. **Psitech Plus** 707-745-4804, Fax 707-747-5277 E-Mail: apeas@ix.netcom.com

EQUIPMENT MANUALS we have 1000's of service and operators manuals for all types of test and measurement equipment from 1950 to present. All test equipment manufacturers are represented. Call, write, or fax your want list. Please include mfg.'s manual P/N unit serial numbers if known. **Manuals Plus,** Box 549, TAD #601, Tooele, UT 84074. 801-882-7188, FAX 801-882-7195.

ACE COMPUTERS

Since 1983

8 East Camp McDonald Road, Prospect Heights, Illinois 60070 (847) 253-9498 FAX

(800) ACE-5936 www.acecomputers.com

Home Office Pro

- Intel 430TX Chipset w/512K Pipelined Burst Cache
- 32 Megs SDRAM
- 24X Speed CD-ROM Drive, Multimedia compatible
- 3.2 GB UDMA Hard Drive/1.44M Floppy Drive
- US Robotics 56KB Fax/Modem (**ADD $50 Rebate!**)
- Diamond Stealth 3D ViRGE Video PCI 2M EDO
- 15" SVGA Monitor w/0.28 Dot Pitch
- Sound Blaster 16 Plug & Play with 160W Speakers
- Microsoft Ergonomic Style Mouse/104 Keyboard
- Mini-Tower Case w/250W UL Pwr/2 Fans
- **Airmedia Wireless Internet Antenna**
- Microsoft Win 95 or Windows NT 4.0 (Add $99)

Add Office 97 Only $199 with System!

*P166MMX-$1599 *P233MMX - $1799
*AMD K6-200-$1649 *PII-233MMX-$1949
*P200MMX - $1699 *PII-266MMX-$2149
*AMD K6-233-$1849 *PII-300MMX-$2399

AGP Powerstation II

- Intel 440 LX Chipset w/ Ultra EIDE Controller
- Intel Pentium II Processor with 512K Cache
- 32 Megs High Speed SDRAM (Exp. to 384Mb)
- 24X Speed CD-ROM Drive, Multimedia compatible
- 3.2GB Ultra DMA Hard Drive/1.44M Floppy Drive
- US Robotics 56Kb Int. Fax/Modem (**$50 Rebate!!**)
- **AGP Video -ATI Xpert@ Play -4M RAM**
- Panasonic S70 - 17" -0.27 Dot Pitch Monitor
- Yamaha 3D Wavetable Sound w/Amplified Speakers
- **Airmedia Wireless Internet Antenna**
- Microsoft PS/2 Mouse/104 Keyboard
- MidTower ATX Case w/3 Fans
- Microsoft Win95 or Windows NT 4.0 (Add $99)

PII-233MMX-$2349
PII-266MMX-$2549
PII-300MMX-$2799
-(After $50 in Modem Rebates)-

Network Equipment

Network Interface Cards

Microdyne NE2000 - ISA Coax/AUI Network Card	$ 14.99
Microdyne Home Gaming Kit (2 Cards, Coax Cable)	$ 24.99
Microdyne NE2500 - ISA Twisted Pair Network Card	$ 29.99
Microdyne NE2500 - ISA Combo Network Card	$ 39.99
3Com Etherlink III - ISA Combo Network Card	$ 79.99
Microdyne NE2500 - ISA Combo 5 Pack	$119.99
Microdyne NE5500 - PCI Twisted Pair Network Card	$ 49.99
Microdyne NE5500 - PCI Twisted Pair 5 Pack	$179.99
SMC Etherpower - Twisted Pair Ethernet Card	$ 49.99
3COM Etherlink XL - PCI Twisted Pair Ethernet Card	$ 59.99
SMC Etherpower - PCI Combo Ethernet Card	$ 69.99
Microdyne NE5500 - PCI Combo Network Card	$ 69.99
Microdyne NE5500 - PCI Combo 5 Pack	$249.99
3COM Etherlink XL - PCI Combo Ethernet Card	$ 89.99
SMC Etherpower II - 10/100 PCI Ethernet Card	$ 69.99
3COM Etherlink XL - 10/100 PCI Ethernet Card	$ 79.99
Intel Etherexpress Pro - 10/100 PCI Ethernet Card	$ 79.99
Intel Etherexpress Pro - 10/100 PCI 5 Pack	$349.99

Network Concentrators (Hubs)

Magitronic 8 Port/16 Port Rackmountable Hub	$69/$119
SMC EtherEZ Hub 8 Port Desktop/16 Port Rackmount	$139/$379
3Com OfficeConnect 8 Port Hub	$ 149
3Com Superstack 12 Port Rackmountable Hub	$ 329
SMC Tigerstack 12 Port/24 Port Hubs with NMM	$ 479/$899

CALL ABOUT NETWORK EQUIPMENT NOT LISTED!

SVGA Monitors

VISIONMASTER liyama

liyama Visionmaster 350 - 15" 0.28 Dot Pitch, Digital, 1280 x 1024	$289
liyama Visionmaster 8817E 0.26 Dot, 1600 x 1280,Digital	$579
liyama Visionmaster 9017E, 0.25 AG - PC Editor's Choice 9/97	$649
liyama Visionmaster 8221, 21" Monitor, .27mm Dot Pitch	$1249
liyama Visionmaster 8721, 21" Monitor, 1800 x 1440 Resolution	$1499
liyama Visionmaster 9021E, 21" Diamondtron	$1399
liyama Visionmaster 9221E, 21" Diamondtron, 1800 x 1440 Resolution	$1599
Megaplus 14" Non-Interlaced 0.28 Dot Pitch	$179
Megaplus 15" Non-Interlaced 0.28 Dot Pitch	$229
Sony Multiscan 15sf Trinitron, Digital - Special Purchase!	$349
Megaplus 17" Non-Interlaced, 0.28 Dot Pitch, 1280 x 1024	$449
Panasonic S70, 0.27 Pitch, 3 Year warranty-1Year onsite!	$549
MAG Innovision DJ700 - 0.26 Dot Pitch,Digital, JAG Controls	$549
Sony Multiscan 17sf 0.25 Aperture, Digital	$699
NEC Multisync XV17+ 0.25 Dot Pitch, CromaClear, Digital	$589
MAG Innovision MX-21F, 0.28 FST	$1399
NEC Multisync P1150, 0.28 Dot Pitch	$1799
Sony SPD300 SFT, 0.25 AG, Trinitron Tube	$1699

December Special

Buy any 17" Monitor and get free Ground Shipping in Continental US!

Memory/Microprocessors

30 Pin SIMM Modules

1M x 9 SIMM/SIPP	$8/$10
4M x 9 SIMM	$29

72 Pin SIMM Modules

4M NonParity/EDO/Parity	$16/$16/$29
8M NonParity/EDO/Parity	$29/$27/$45
16M NonParity/EDO/Parity	$49/$45/$59
32M NonParity/EDO/Parity	$85/$79/$109
64M EDO/Parity	$259/$329

168 Pin DIMM Modules

16M SDRAM 10ns	$55
32M SDRAM 10ns	$89
64M SDRAM 10ns	$225

Microprocessor Chips

Pentium® II- 300	$749
Pentium® II- 266 /233 Mhz	$549/$449
Pentium® Pro 200 Mhz -512K/200-256K	$799/$479
Pentium® Pro 180 Mhz/150 Mhz	$299/$199
Pentium® 233 Mhz MMX/200 MMX	$329/$229
Pentium® 200 Mhz/166 Mhz MMX	$199/$139
Pentium® 166 Mhz/133Mhz	$129/$99
Pentium® 120Mhz/100 Mhz	$95/$89
AMD K6 - 233/200/166	$339/$189/$129
Pentium® II/Pentium® Pro/Pentium® Fans	$20/$15/$8

All Fans are Ball Bearing - High Quality with Heatsink!!

Enhanced IDE & SCSI2 Hard Drives

Enhanced IDE Drives

1.08 Gig Seagate, 9 ms access	$119.99
1.28 Gig Seagate, 12.5 ms access	$129.99
1.28 Gig Western Digital, 10 ms access	$149.99
1.61 Gig Western Digital, 10 ms access	$159.99
1.62 Gig Quantum Fireball Ultra DMA, 9 ms	$169.99
1.75 Gig Seagate, 12.5 ms access	$139.99
2.14 Gig Seagate, 12 ms access	$169.99
2.14 Gig Western Digital,10 ms access	$179.99
2.14 Gig Quantum Fireball Ultra DMA, 9 ms	$189.99
2.55 Gig Micropolis Mustang, 9 ms access	$179.99
3.1 Gig Western Digital, 11 ms access	$209.99
3.2 Gig Quantum Fireball Ultra DMA, 9 ms	**$209.99**
4.0 Gig Western Digital, 10 ms access	**$249.99**
4.0 Gig Micropolis Mustang, 9 ms access	$249.99
4.3 Gig Quantum Fireball Ultra DMA, 9 ms	$259.99
5.0 Gig Micropolis Mustang, 9 ms access	$299.99
5.1 Gig Western Digital, 10 ms Ultra DMA	$299.99
6.4 Gig Quantum Fireball, Ultra DMA, 9 ms	$339.99
6.4 Gig Seagate Medalist Pro,Ultra DMA, 9 ms	$339.99
6.4 Gig Western Digital, 10 ms Ultra DMA	**$329.99**
8.4 Gig Maxtor Diamondmax, Ultra DMA, 10 ms	$449.99
8.4 Gig Quantum Fireball, Ultra DMA, 9 ms	$499.99

SCSI2 Drives

2.1 GB Quantum Fireball Ultra SCSI, 9 ms	$ 249.99
2.1 GB Seagate Cayman Ultra Wide, 9 ms	$ 269.99
3.2 GB Quantum Fireball Ultra SCSI, 9 ms	$ 329.99
4.3 GB Quantum Fireball Ultra SCSI, 9 ms	$ 399.99
4.5 GB Micropolis Tomahawk Ultra/Ultra Wide 8 ms	$579/$599
4.5 GB Seagate Barracuda Ultra/Ultra Wide, 7.9 ms	$ 599.99
6.4 GB Quantum Fireball Ultra SCSI, 9 ms	**$ 489.99**
8.7 GB Micropolis Tomahawk Ultra/ Ultra Wide, 8 ms	$ 879.99
9.1 GB Micropolis Scorpio 5.25" FH SCSI2/Wide 9 ms	$ 599.99
9.1Gig IBM Deskstar Ultra Wide 7 ms	**$ 799.99**
9.1 Gig Seagate Barracuda Ultra/Ultra Wide	$1229.99

MOTHERBOARDS FOR PENTIUM® PROCESSORS bcm

BCM 575 AT-430TX,P75-233PCI w/512K,DIMM,MMX	**$129**
BCM 550 ATX-430TX,P75-233PCI w/512K,DIMM,MMX	**$129**
Tyan Tomcat , Single/Dual CPU, w/8 SIMMs,512K	$149/$159
Tyan Turbo-2 AT/ATX, Intel 430TX w/6 SIMM/2 DIMM 512K	$139
SuperMicro P55MMS98-Intel 430TX, 512K	$149
Quicktek, P75-200 w/Adaptec 2940UW SCSI2,512K Pipe.	$279
ASUS TX97/TX97E, AT-430TX,P75-233 PCI w/512K	$149

Motherboards for the Pentium® Pro Processor

BCM 600 - 150-200 MHz, Intel 440FX Chipset, PCI/ISA	**$199**
Supermicro ,AT or ATX 150-200, Intel 440FX, PCI/ISA	$219
Tyan Titan Pro - Single/Dual processor PCI/ISA, AT or ATX	$209/$279
Intel PR440FX - Dual Pro, UW SCSI,10/100 LAN, Audio, ATX	$499

Motherboards for the Pentium® II Processor

BCM 660 - , Intel 440FX Chipset, PCI/ISA, SIMMs, ATX	**$ 199**
BCM 630 - Intel 440LX Chipset, PCI/ISA/AGP/DIMMs,ATX	**$ 219**
Intel AL440LX - Intel 440LX, PCI/ISA/AGP/DIMMs,Audio,ATX	$ 229
Asus P2L97 - Intel 440LX, PCI/ISA/AGP, ATX	$ 229
Asus P2L97S - Intel 440LX, PCI/ISA/AGP/UW SCSI, ATX	$ 299
Supermicro P6DLS-440LX,Dual P2,PCI/AGP/DIMM/UW SCSI	$ 499
Supermicro P6SNE II - P-II with Standard AT Form Factor	$ 249
Supermicro P6SKS/SKS-P-II/P-Pro,ATX, UW SCSI/No SCSI	$349/$249
Tyan Tahoe II - Dual Processor Pentium II, ATX	$ 329

Closeout boards for the Pentium® Processor

Tyan Tomcat I/II - Intel 430HX, Single or Dual Processor	$99/$129
Tyan Titan III/Titan VX - Intel 430FX/VX, 256K Cache	$ 79

CD-ROM/Modems/Sound

CD ROM Drives

Mitsumi EIDE 8X, 145 ms	$64.99
Toshiba EIDE 12X,115 ms	$74.99
Toshiba EIDE 24X, 99 ms	$79.99
Toshiba EIDE 32X, 85 ms	$109.99
Panasonic SCSI2 8X, 145 ms	$79.99
Toshiba SCSI2 12X, 115 ms	$119.99
NEC SCSI2 16X, 105 ms	$129.99
Panasonic SCSI2 24X, 99 ms	$169.99
NEC SCSI2 24X, 95 ms	$169.99
HP CD-Writer EIDE CD/RW	$399.99
HP CD-Writer Parallel CD/RW	$499.99

Modems

Airmedia Wireless Modem	**$69.99**
USR Sportster 56K Int/Ext	$119/$139
USR 56K Voice Int/Ext	$139/$159
USR 56K Courier Int/Ext	$145/$175
($50 Rebate on USR 56K Applied Above!!)	

Sound Cards

Yamaha 32 Voice Wavetable	$39.99
Creative Sound Blaster 16 PNP	$49.99
Creative Sound Blaster 64 Value	$89.99
Creative Sound Blaster 64 Gold	$169.99

SVGA Cards and Accelerators

Diamond Stealth 3D, 2M/4M DRAM PCI	$69/$89
ATI 3D Xpression 2M/4M PCI	$79/$99
Diamond Monster 3D - 3DFX VooDoo Chipset Add-On	$179
Matrox Mystique 220 PCI with 2M/4M RAM	$119/$149
ATI Pro Turbo PCI + PC2TV w/ 4M/8M SGRAM	$149/$219
Matrox Millenium II PCI 4M/8M WRAM(1920x1440)	**$179/$249**
Diamond Stealth 3D-3000 PCI 2M/4M VRAM	$129/$179
ATI Xpert @ Work/Xpert @ Play AGP 4M (8M +$50)	**$179/$199**
Diamond Viper 330 Pro AGP with 4M RAM/8M RAM	**$179/$229**
#9 Revolution 3D Pro AGP with 4M WRAM/8M WRAM	$299/$429

INEXPENSIVE POWER INVERTER CONVERSION PROJECT

by Kenton Chun



Getting Started

With the cost of solar arrays coming down, many experimenters are wondering how they can get in on harvesting free energy from the sun. If you have investigated this topic, you probably realize that solar energy is far from free. After pricing an 80-watt solar panel at $400-$500, it is difficult to look at a 500-watt modified sinewave inverter costing yet another $500.00. Add a good quality deep cycle lead-acid battery and the total cost of a small photovoltaic system can set you back well over a $1,000.00!

This project suggests a low-cost alternative to purchasing an expensive new inverter and yet produces quality modified sinewave power for your household appliances. All but the most sensitive of electronic equipment may be run, including televisions and computers.

By retro-fitting an ordinary UPS (Uninterruptible Power Supply, typically sold for backing up computers) with a larger battery, and making some minor modifications, you can effectively turn it into a low-cost power inverter. It is inexpensive and it works.

It is important to realize up front that certain appliances do not lend themselves well to photovoltaic power. Capacitor-start inductive motors are an example. A capacitor-start motor may require more than twice the run power to get started under load. Refrigerators, washing machines, dishwashers, and air conditioners fall into this category. Other devices simply require too much energy to be solar-powered practically. Full house heaters, oven ranges, and water heaters fall into this category. This still leaves a surprising number of devices that consume significant amounts of power, most less than 500 watts. They include: stereo systems, radios, televisions, computers, and home lighting.

Small amounts of power consumption eventually add up to large amounts. A 100-watt light bulb left burning 24 hours a day will consume 2.4 kilowatts per day. In an average month, this adds up to 72 kilowatts. At the typical rate of 20 cents a kilowatt-hour, this one light bulb will cost monthly over $14.00 to burn day and night! No wonder we try to turn off lights when we aren't using them.

However, if you are an average tech-hound, you probably own quite a few things that never get turned off – maybe a fax machine, a personal computer, or a radio. Try this experiment and just add up all of the wall warts plugged in – the wall transformers that power your portable telephone(s), battery chargers, caller ID boxes, answering machines, and so on. I was surprised to find almost 60 watts worth of these alone in my home!

It is difficult to cut costs on a solar panel. While amorphous silicon construction has dropped prices significantly, the lower limit on cost is fairly constant across the board. It is difficult to find bargain basement prices on solar panels capable of producing the several amps of current necessary to charge an automobile battery. Small, cheap panels just will not be sufficient to replace the charge taken from the battery by even a tiny load.

If you are serious about employing alternative energy sources, it is likely you will end up paying a lot for a decent quality solar array. You will have to try to cut costs elsewhere.

During recent forays to hamfests and computer shows, it became apparent that a large number of used UPSs were hitting the tables at bargain prices. Nothing more was wrong with them except that the internal batteries had worn out, but the former owners were simply not interested in repairing them. This was not surprising considering the batteries inside the units were usually small 6 or 12-volt, 7 amp-hour, lead-acid gel-cell batteries made by Yuasa-Exide or Matsushita Electric, costing half as much as replacing the entire UPS! No wonder no one wanted to repair them.

The computer UPS is an example of technology where function follows form, instead of vice versa. The size and shape of the batteries inside these units are determined by ergonomics instead of physics. They are simply too small. After all, nobody wants to stash a car battery under their mahogany desk next to their personal computer. This is why the UPS ratings are so tiny.



FIGURE 1
REMOVING THE CASE.



FIGURE 2
UNSOLDERING THE ALARM TRANSDUCER.



FIGURE 3
DRILL THE HOLE FOR THE NEW POWER CABLES, AND INSTALL A GROMMET.

FIGURE 4
ATTACH THE NEW POWER CABLES OBSERVING THE CORRECT POLARITY.



FIGURE 5
INSTALLING AN ADDITIONAL COOLING FAN.

A 500 VA UPS is rated for only a few minutes at this output, not because the circuitry can't take it, but because the teeny gel-cell packed into the UPS box is only rated at 7 amp-hours. Under a 500-watt load, this battery is having over 40 amps sucked out of it. No wonder it only lasts five minutes! This probably also accounts for why so many of these units are going to the trash pile.

Lead-acid batteries dislike being discharged fast and deep – they often do not recover well from this kind of treatment. After only a few power outages, the battery is probably on its way out. This is where you – the experimenter – can take over.

Shopping for a Used UPS

When shopping for a used UPS, be prepared to test it and to open it up. Most "dead" UPSs will have enough charge capacity left in the battery to switch into invert mode when the plug is pulled from the wall. You can usually perform this test yourself at the computer show or the hamfest. If the UPS will hold any kind of a load at all, so much the better, although this is not necessary for a successful conversion.

It is a good thing when hunting for a used UPS to keep a little six-watt night light in your pocket to use as a test load – it is enough to test the inverter section of the UPS, and it is not so much as to bring a weak battery to its knees in two milliseconds.

Plug the unit in and turn it on. There should be an indicator light on somewhere. If not, check the fuse, but be suspicious. A blown fuse may be a simple fix or it may mean that the unit was severely overloaded. Carry around a two-amp slow blow fuse to test units, if necessary. If the switch light comes on, plug in your test night light and pull the plug.

If it lights, and the unit starts alarming and gives off a 60-cycle buzz – even for a few seconds or so – you probably have a winner. If the seller will allow you to pop the unit open, you can also verify that it is a 12-volt model. The vast majority of them are.

Most of the newer UPS units have standardized on 12 volts as the primary power supply. Some older units out there use six volts and I have also seen some that use 24 volts. There are efficiency advantages to using higher primary supply voltages, but for lowest cost and ease of conversion, try to stick with the 12-volt models. Our conversion project will use a Kensington Power Backer 520. It only cost us $40.00 at the local flea hamfest.

The Conversion Process

Make sure the unit is unplugged and powered off. Start by unscrewing the case screws. Usually the case is a shell type. You should not have to undo screws for the feet or the back of the unit, although individual units vary (Figure 1). Slip the shell off toward the back of the unit, being careful not to tear any cardboard spacers or short any power lugs.

If the unit has any battery power, turn it on and try to identify the location of the alarm on the main circuit board. It will usually be a small black cylindrical or square object with a hole in the middle, or small grille holes. Once you have identified the alarm transducer, turn the UPS off. Carefully unsolder one leg of this transducer, taking care not to break or burn any of the traces on the circuit board. Bend the transducer up and away from the circuit board (Figure 2). There may be other ways to silence the alarm, but we have found this to be the simplest and most reliable method.

Identify the batteries. They will probably occupy most of the space in the UPS. The configuration may vary, so look at them carefully. If there is only a single battery and the voltage is marked on the side of it, then all you need to do is to carefully label the battery leads positive and negative and then disconnect the battery.

In multiple battery configurations, note if there is a single short jumper going between the two batteries. If so, then they are connected in series. If the two batteries are six volts, then the unit is a 12-volt unit. If the batteries are 12 volts, then the unit is a 24-volt unit.

The two batteries may also be wired in parallel. If this is the case, then there will be jumpers on both sides of the batteries connecting them together positive to positive and negative to negative.

After you have correctly labeled the power leads, feel free to remove the batteries. Although you can leave them in the UPS without affecting the conversion, there is a risk of eventual acid leakage and damage to the unit. Please discard them in an environmentally-safe fashion.

In order to supply power to the inverter, we will have to drill a hole in the case. Carefully drill a 3/8" hole, preferably in a place that is not removable (like the shell). We drilled our hole in the back of the unit. Make sure there are no other components near the hole location and do not drive the drill into the circuit board or other sensitive locations inside the unit. Carefully remove any metal chips produced by the drilling process with a vacuum or a small brush. Install a rubber or vinyl grommet in the hole (Figure 3).

You must choose a power cable gauge depending on the power capacity of the UPS you are converting. To figure out the necessary size wire for your unit, divide the maximum power rating (in watts or VA) by the battery supply voltage (6,12,24), and then look up the wire size nearest to your final current draw in amps (Table 1). Our Kensington drew a maximum of about

45 amps (520 watts divided by 12 volts = 43.33 amps).

The table suggests an 8-gauge copper wire will be more than adequate to supply this amount of current. This is a fairly large wire, so what we did was to go to a flea market and purchase a "cheapie" 10' car jumper cable for about $8.00. By cutting it in half, we got two big power supply cables complete with heavy-duty battery clips!

Five feet will be plenty of cable to connect our inverter to the battery. Bear in mind that increasing the distance between the battery and the inverter will require heavier gauges of wire to cut resistance losses. Small losses in this power cable will amount to big losses in the overall efficiency of the power conversion. For example, increasing the distance from 5' to 50' from the battery to the inverter will require that we go from 8-gauge wire to #4/0 cable to keep the voltage drop inside two percent!

Try to keep the battery as near to the unit as possible. If you wish to place the project in a remote location i.e., the garage, laundry, or shed, etc., remember that it is far more efficient to run the AC output longer distances with less losses in smaller gauge wire than the DC power supply.

Feed the power wires through the grommet and tie a knot. This will be a strain relief in the event that the wires are accidently jerked. Solder spade lug mates to the power wires in the unit and attach them making sure to observe the correct polarity (Figure 4). The red clip should be positive and the black clip should be negative. Accidently reversing these may destroy the UPS. Finally, wrap the connections with electrical tape and tie-wrap the cable ends to something solid inside the unit to prevent them from shifting around.

Testing the Unit

Connect the battery clips to a good car battery, make sure the polarity is correct, and switch the unit on. Do not plug the unit into the wall. It should be in invert mode humming or buzzing. Connect a load, like your test night light. It should be on. If you have a multimeter that will measure AC and/or a frequency counter, you can make sure the unit is operating within nominal specs.

Increase the load to the inverter by adding a 100-watt trouble light or some desk lamps. The unit should carry the load without complaint.

If everything checks out okay, turn everything off, disconnect the battery, and close the unit up.

The 100% design load capacity of a consumer-grade UPS is sometimes hard to estimate. We have torture-tested good quality UPSs at near load capacity for weeks without any problems. However, if you plan on running your inverter continuously under high loads, we suggest you make the following additional modification.

Additional Cooling Modification

Expensive, high-end inverters tend to have aluminum cases with heatsink area all over the unit to allow the output devices to run as cool as possible. When your unit is open, look inside for the location of the output devices. These will usually be on a heatsink of some kind, possibly on the frame itself.

If the outer shell has ventilation holes, inspect them to make sure that they are placed in locations that will offer a good flow of air to the output devices. If they are not placed well, you may have to drill additional holes in the shell to create a better airflow to these devices.

In addition, you may want to bolt a high-quality muffin fan to the case to force air over the interior of the inverter. Monitor your inverter in a torture test. If the case gets warm to the touch, you should consider adding forced-air cooling. One clever trick is to plug a 115-volt muffin cooling fan into one of the inverter's own outlets. This way, the fan is only on when the inverter is running (Figure 5.)

Connect the solar panel either directly to the battery, or through any charge controller you may have. An ammeter is the single most useful measurement instrument for a photovoltaic installation. It must be comfortably rated at least twice what your solar panel is capable of charging the battery at.

The ammeter should be placed in series with the solar panel and the battery. If it is a direct-reading ammeter, make sure to put a fuse rated less than the meter's full-scale value in series with it to protect it in the event of a short circuit.

If the ammeter is a shunt measurement type, try to keep the shunt as large as possible to minimize the series resistance in your charging load. You will not need to use as heavy a wire for the charging circuit of your system.

If the solar panel has an 80-watt capacity, it will produce between 4 and 5 amps in full sunlight into a battery charging load. For a 20' run from the solar panel to your battery, you can use 10-gauge wire. At 40', you are back to 8-gauge wire again. Remember, it is important to try to keep the DC distances in the project as small as possible.

How Much Power Can I Draw?

If your unit has reasonable thermal dissipation, you can draw the inverter's full rated output until your battery runs out. When Hurricane Andrew hit in 1992, we ran our 27" Sony XBR for about six hours. It consumed 225 watts drawing almost 20 amps on an ordinary, partially-charged car battery. A deep cycle marine battery designed for this type of service will offer much better performance under the same circumstances.

The sustainability of the system is more difficult to predict and depends primarily on the rate at which you can recharge the battery off the solar panel. Using the figures above for the panel charging specs, and assuming a six-hour average charging period in a day at this rate, you will be able to replace about 30 amp-hours of battery power per sunny day. This means that breakeven will be around 360 watt-hours of consumption per day, equivalent to running a couple hundred watt load for a couple of hours a day.

We could, for example, run our 60-watt wall wart assortment for about six hours a day. On the longest days of the year, when we receive 12 hours or more of good charging sun, we may be able to run our wall wart assortment for an equal amount of time in the evening. You could also run a 15-watt light bulb continuously, or a combination of higher-powered loads on an intermittent basis.

Conclusion

Although it is not yet economically advantageous to cut utility power service and switch entirely to solar power, a thrifty experimenter can create a portable, environmentally-safe electrical power source with a high peak load capacity for less than one might think.

The principles outlined in this article are intended to provide some direction for those who have ideas, and an interest in developing the virtually untapped resource of solar energy. Happy Hunting! NV

Kenton Chun is an Information Systems Consultant living in Miami, FL. He has a Master's Degree in English and Technical Writing from the University of Miami. He has spent over 10 years working in the computer and electronics fields. His wife's name is Sandra and he has one son Carrington, who is three months old.

TABLE 1

Max. distance for 2% voltage drop for various wire gauges and currents.

Amps	Wire Size									
	#14	#12	#10	#8	#6	#4	#2	#1/0	#2/0	#4/0
1	45	70	115	180	290					
2	22.5	35	57.5	90	145	228				
4	10	17.5	27.5	45	72.5	114	200			
6	7.5	12	17.5	30	47.5	75	120	193		
8	5.5	8.5	11.5	22.5	35.5	57	90	145	190	
10	4.5	7	11.5	18	28.5	45.5	72.5	115	155	195
15	3	4.5	5.5	12	19	30	48	76.5	110	150
20	2	3.5	4.5	9	14.5	22.5	36	57.5	85	116
25	1.8	2.8	3.5	7	11.5	18	29	46	65	92
30	1.5	2.4	2.8	6	9.5	15	24	38.5	55	77
40			2.3	4.5	7	11.5	18	29	39	56
50				3.6	5.5	9	14.5	23	32	46
100					2.9	4.6	7.2	11.5	15	23
150							4.8	7.7	10	15
200							3.6	5.8	7.5	11

2539 W. 237th Street, Bldg. F, Torrance, CA 90505
Order desk only: USA: (800) 872-8878 CA: (800) 223-9977
L.A. & Technical Info: (310) 784-5488 Fax: (310) 784-7590
OEM INQUIRIES WELCOME

TIMELINE INC.

Over 11 years and 29,000 customers and still growing

Minimum Order: $20.00. Minimum shipping and handling charge $5.00. We accept cashiers checks, MC or VISA. No personal checks or COD's. CA residents add 8.25% sales tax. We are not responsible for typographical errors. All merchandise subject to prior sale. Phone orders welcome. Foreign orders require special handling. Prices subject to change without notice. 20% restocking fee for returned orders.

Liquid Crystal Displays

240x64 dot LCD with built-in controller.

AND 4021ST-EO. *Unit is EL back-lit.* **$59.00 or 2 for $109.00** *or*
OPTREX. DMF5005 *(non back-lit)* **$49.00 or 2 for $89.00**
20 character x 8 line
7¾L x 2½H

The built-in controller allows you to do text and graphics.

Alphanumeric—parallel interface

16x1	$7.00	20x2	$10.00	32x2	$8.00
16x1 (lg. char.)	$10.00	20x4	$15.00	40x1	$8.00
16x2	$7.00	20x4 (lg. char.)	$10.00	40x2	2 for $20.00
16x2 (lg. char.)	$10.00	24x2	$10.00	40x4	$20.00
16x4	$15.00	32x4	$10.00	4x2	$5.00

5V power required • Built-in C-MOS LCD driver & controller • Easy "microprocessor" interface • 98 ASCII character generator • ***Certain models are backlit, call for more info.***

Graphics and alphanumeric—serial interface

size	Mfr.	price	size	Mfr.	price
640x480 (backlit)	Epson	$25.00	480x128	Hitachi	$10.00
640x400 (backlit)	Panasonic	$20.00	256x128	Epson	$20.00
640x200	Toshiba	$15.00	240x128 (backlit)	Optrex	$20.00
480x128 (backlit)	ALPS	$10.00	240x64	Epson	$15.00
			160x128	Optrex	$15.00

6" VGA LCD 640X480, Sanyo LMDK55-22 **$25.00**

Monitors

9" COLOR SVGA MONITOR $249.00
Fully Enclosed – Tilt and swivel type.

Monitors

Non-Enclosed TTL

Comes with pinout. 12V at 1.4 Amp input • Horizontal frequency 15Khz. • Ability to do 40 and 80 column.

5 inch Amber $25.00 • 7 inch Amber $25.00
9 inch Amber or Green $25.00

5" COLOR MONITOR $39.00
2 for $69.00
• Flat Faceplate • 320 x 200 Dot Resolution • CGA & Hercules Compatible
• 12 VDC Operation • 15.75 KHz Horiz. Freq. • 60 Hz Vert. Sync. Freq.
• Open Frame Construction • Standard Interface Connector • Degaussing Coil included • *Mfr. Samtron*

Hacker Corner

Encased Spread Spectrum RF Modem $199.00

The ProxLink Radio Module is a small communication device which replaces cables between RS-232 devices with wireless RF (Radio Frequency) technology. Attaching a pair of ProxLinks to any two devices with three wire asynchronous RS-232 ports allows wireless data transmittal at rates up to 19.2 Kbaud (full duplex) over a range of 500 - 800 feet. Modules use 900 MZ spread spectrum radio for communication which does not require an FCC site license. A variety of configuration information (radio channel, baud rate, serial port configuration, etc.) can be programmed into module's non-volatile memory by host PC to provide compatibility and avoid overlapping systems. Configuration changes are supported by menu driven, on-board software. Commonly used Terminal Emulation software and transfer protocols can be used for configuring modules and transferring data between computers. ProxLinks require only 6-9 VDC (350 mA), RS-232 (9 pin sub - D) interface, and small (~ 4") whip antenna for operation. Unit size is 4.0" x 6.5" x 0.75". Installation schematics and application details available.

COLOR CCD CAMERA $149.00

• 12 VDC • 1/3-inch, CCD area image sensor • 514 (horizontal) x 491 (vertical) • 2:1 interlaced • 15.734 kHz (horizontal), 59.94 Hz (vertical) • 330 horizontal and 350 vertical lines • 10 lx • 1V, NTSC signal format • Lens: 1/3-inch, fixed focus (F:2.8 f:5.6) • Dimensions: (W) 67 (2.63) x (H) 34 (1.45) x (D) 112.6 (4.43)

US made Micronics 486 VLB ALL in ONE $39.00 or 2 for $69.00

motherboard, supports 3.4 or 5V CPU, at either 25 or 33 mhz basic clock. Can use AMD or Intel from 486SX25 thru 486DX4-100 to HOT new AMD 5X86-133 cpu. On board SVGA video. On board 1 meg video ram expandable to 2 meg with ATI Mach 2 chip set. On board 2 high speed serial ports, 1 printer port, floppy and IDE hard drive controller. On board 256K cache. Uses 72 pin simm memory. Landmark speed rating of 479 with AMD chip.

Board will not fit standard All in One case because of non standard location of riser board. VLB riser board is included with motherboard.

SONY Miniature Color LCD Display (LCX005BKB) $29.00

• 1.4 CM (0.55 inch) Diagonal Full Color Display • Built In Horizontal and Vertical Drivers • Delta Dot Pattern for High Picture Quality - 537 dots (H) x 222 dots (V) • Compatible with NTSC & PAL Format and Sync Inputs • 12 VDC Operation with -1 to +17 V RGB Signal and Driver Input Voltage • Excellent Display for Virtual Reality Projects, Viewfinders, and Miniature Test Equipment Displays • Pin Outs and Specification Included • Unit Requires Clock, Synchronization and Video

CELL SITE TRANSCEIVER $49.00 2 for $99.00

These transceivers were designed for operation in an AMPS (Advanced Mobile Phone Service) cell site. The 20 MHz bandwidth of the transceiver allows it to operate on all 666 channels allocated. The transmit channels are 870.030-889.980 MHz with the receive channels 45 MHz below those frequencies. A digital synthesizer is utilized to generate the selected frequency. Each unit contains two independent receivers to demodulate voice and data with a Receive Signal Strength Indicator (RSSI) circuit to select the one with the best signal strength. The transmitter provides a 1.5 watt modulated signal to drive an external power amplifier, channel selection is accomplished with a 10 bit binary input via a connector on the back panel. Other interface requirements for operation are 26 VDC (unregulated) and an 18.990 MHz reference frequency for the digital synthesizer. The units contain independent boards for receivers, exciter, synthesizer, tunable front end, and interface assembly (which includes power supplies and voltage-controlled oscillator). Service manual, schematics and circuit descriptions included.

Encased Black & White Composite CCD Camera with Adapter
IR viewing to 1000 nm 7 ½ L x 2 ⅞ W x 1 ⅞ H
Comes complete with CCD camera, mounting nut on bottom of casing, 12VDC power supply. Excellent low light capability, standard RCA NTSC video out. **$89.00**
Great for: entryway security/remote monitoring, video conferencing/desktop video conferencing **2 for $159.00**

Write in 179 on Reader Service Card.

How many shopping days til Christmas?

If you're looking for that perfect gift for the hard-to-please electronics enthusiast, why not surprise them with a gift subscription to *Nuts & Volts Magazine*!?!

Each monthly issue is packed with all kinds of "goodies" sure to please even the toughest of enthusiasts.

Order today!
Nuts & Volts Magazine
430 Princeland Court, Corona, CA 91719
800-783-4624 · 909-371-3052 FAX
http://www.nutsvolts.com



CATALOG 8 IS HERE!!

400 Pages of Hard-To-Find Electronic Parts.
Order now and receive a $5.00 Rebate on First Order.

$5.00 (U.S.)
$10.00 (All Others)
Mail Check To: 1502 Jones St. Omaha, NE 68102
Call In Orders: (800) 244-4567

MasterCard VISA American Express Discover

VISIT OUR WEB SITE: www.surplussales.com • E-MAIL: grinnell@surplussales.com

WHITE-STAR ELECTRONICS
TEL: 405-631-5153 FAX: 405-631-4788

CONVERTERS:	20	50	100+
Regal CR-83	45	39	35
* New, Panasonic TZPC 145	75	69	65
DQN-5 (2 or 3) (unmodified)	45	39	35
DRZ-3 PJ (unmodified) 70 Channel Plain	35	32	29
DRX-3 PJ (unmodified) 60 Channel Plain	32	30	27

Call for FREE catalog.
405-631-5153

REMOTE CONTROL HAND UNITS:	20	50	100+
Jerrold Replaces: 400/450/550	4.95	4.50	4.25
Scientific Atlanta: 075/175/475	4.95	4.50	4.25
8600: On screen display	7.50	7.00	6.50
Pioneer: BR 81, 82	4.95	4.50	4.25
Panasonic: Call for model #	7.50	7.00	6.50
Zenith: All	4.95	4.50	4.25
Tocom: 5503-VIP, 5503-A	7.00	6.50	6.25
Universal: 4 in 1 R/M	7.50	7.00	6.50

Call for Oak, Hamlin, Regal-83, Regency, Texscan, and all others.

Tamper-Bit tools: (10-lot)
Jerrold compatible bits:
1/4" Stacom Bit $8.00
Oval Round D $20.00
Torx Bit:
Tocom T-8 ..... $8.00
Zenith T-10,T-15 ..... $8.00
Pioneer T-20 ..... $8.00
Scientific Atlanta T-20 ..... $8.00
Pio 63XX Oval $20.00
Bit Driver Handle $4.00

We carry most remote hand units. If you don't find the one you're looking for, we can locate for you.

Specializing in large quantities.

HOURS: Monday thru Friday 9 am to 5 pm Central Time.

Call for FREE catalog • E-Mail: WSE405@AOL.COM

Write in 63 on Reader Service Card.

ELECTRONIC TEST EQUIPMENT BOUGHT & SOLD

Ailtech 360D11, Frequency Syn. .01-2GHz	$1,000
Argosystems AS210, Frequency Calibration System	$2,000
Bafco 911A, Frequency Response Analyzer (unused)	$400
Ball Efratom PC-10, Rubidium Standard	$800
Ballantine 1627A, Scope Calib., with/acc. heads	$1,000
Bird 4381, RF Power Analyst, Opt. 832	$300
Boonton 4200, Power Meter, w/Detector, 100KHz-18GHz	$600
Boonton 42BD, Microwattmeter .2MHz-7GHz	$300
Boonton 518-A4, Q Standard	$250
Boonton 82AD, Modulation Meter	$650
Boonton 92A, RF Millivoltmeter w/Probe	$300
Bruel & Kjaer 1612, Bandpass Filter	$250
Cushman CE24B, Frequency Selective Voltmeter	$800
Datron 1062, Digital Multimeter	$300
DDC SR-400, Syncro Resolver Simulator	$400
DR Thiedig MILLI-TO2, Ohmmeter, 1 Milliohm-2 Terraohms	$400
Eaton 380K11, Synthesizer, 1-2000MHz Opt. 01, 03, 183	$2,500
EIP 371, Source Locking Microwave Counter, .18GHz	$1,500
Fluke 3330B, DC Voltage, Current Calibrator	$400
Fluke 335A, DC Voltage Standard, 0-1100VDC	$600
Fluke 515A, Portable Calibrator	$1,000
Fluke 5200A, Programmable AC Voltage Standard HPIB	$1,200
Fluke 6080A/AN Frequency Syn., .5-1024MHz	$5,000
Fluke 9010A, Micro-System Troubleshooter Opt. 001	$450
Fluke A55, Thermal Converter	$200
General Microwave 478A, Peak Power Meter	$1,000
General Radio 1422-CB, Standard Cap.	$200
General Radio 1433G, Decade Resistor, 1.111111m.	$300
General Radio 1482Q, Standard Inductor, 2 Henry	$100
General Radio 1531, Strobetac	$200
General Radio 1538-P4, High Intensity Flash Capacitor	$100
General Radio 1650A, Impedance Bridge	$200
Gigatronics 600/6-12, Synthesized Source	$1,000
Goldstar OS-7040A, Scope, 40MHz, Dual Trace	$200
Gould 4500, Digital Storage Scope, 35MHz	$450
Guildline 9154C, Transvolt Standard Cell	$300
Hitachi V-212, Scope, 20MHz, Dual Trace	$200
HP 1124A, 100MHz Active Divider Probe, Unused	$100
HP 1630G, Logic Analyzer, 65 Ch. 100MHz	$800
HP 1741A, Scope, Storage, 100MHz	$450
HP 1742A, Scope, 100MHz Dual Trace, DMM	$400
HP 1744A, Scope, Storage, 100MHz, Dual Trace	$500
HP 214B, Pulse Generator	$1,000
HP 2804A, Quartz Thermometer, No Probe	$300
HP 3320A, Frequency Synthesizer	$250
HP 3320B, Frequency Synthesizer	$350
HP 334A, Distortion Meter	$300
HP 3406A, Broadband Sampling Voltmeter	$300
HP 3455A, Digital Multimeter	$300
HP 3456A, Digital Multimeter, 6.5 Digits	$800
HP 3580A, Spectrum Analyzer	$800
HP 3581C, Selective Level Meter	$600
HP 4270A, Automatic Capacitance Bridge	$400
HP 478A, Thermistor Mount, New	$200
HP 4800A, Vector Impedance Meter	$600
HP 4815A, Vector Inpedance Meter	$1,000
HP 5004A, Signature Analyzer	$100
HP 5334A, 100MHz Universal Counter, HPIB	$1,200
HP 5335A, Frequency Counter, 11 Digit, Opt. 010,040	$800
HP 5340A, Frequency Counter, 18GHz	$800
HP 5340A, Frequency Counter, 18GHz, LEDs	$1,000
HP 5342A, Frequency Counter, 18GHz, Opt. 01,02	$2,800
HP 5345A, Universal Counter	$400
HP 5385A, Frequency Counter, 10Hz-16Hz	$800
HP 54200A, Digital Storage Scope, Dual Trace, 200/MG/S	$1,000
HP 6112A, Power Supply, 0-40V, 0.5A	$200
HP 6920A, Meter Calibrator	$300
HP 8002A, Pulse Generator, .3HZ-10MHz	$250
HP 8015A, Pulse Generator, .1Hz-50MHz, 30V	$500
HP 8165A, Programmable Signal Source, .0001-50MHz	$1,800
HP 8443A, Tracking Generator	$300
HP 8445B, Spectrum Anyz., Automatic Pre-Selector	$300
HP 8553B, Spectrum Anyz., RF Plug-in, 1KC-110MHz	$200
HP 8554B/8552B, Spectrum Analyzer 141T, 1.2GHz	$1,500
HP 8555A/8552B, Spectrum Analyzer 141T, 18GHz	$1,600
HP 8556A, Plug-In, Spectrum Analyzer, 20Hz-300KHz	$300
HP 8557A/180TR, Spectrum Analyzer, .01-350MHz	$1,000
HP 8558B/180TR, Spectrum Analyzer, .1-1500MHz	$1,800
HP 8565A, Spectrum Analyzer, .01-22GHz	$3,500
HP 8569B, Spectrum Analyzer, .01-22GHz	$7,500
HP 8621B, RF Draw, with 86350A, 8-12.4GHz, 8620C	$400
HP 86222A, RF Plug-in, .01-2.4GHz	$1,000
HP 86222B/H69, RF Plug-in, .01-4GHz	$1,000
HP 86241A, RF Plug-in, 3.2-6.5GHz	$400
HP 86260A, RF Plug-in, 12.4-18GHz	$400
HP 86290A, RF Plug-in, 2-18GHz w/Scales	$1,200
HP 8640B/01, Signal Gen., .5-512MHz AM/FM	$1,000
HP 8640B/02/03, Signal Gen., .5-1024MHz	$1,800
HP 8660A/86601A/86632A, Freq. Syn.	$1,000
HP 8660C/86603A/86632B, Freq. Syn., 2.6GHz, AM/FM, HPIB	$2,500
HP 86601A, RF Plug-in, 110MHz	$250
HP 8683A, Signal Gen. 2.3-6.5GHz, Opt 1, 2	$1,500
HP 8821A, Medium Gain Bank Amp	$150
HP 8901A, Modulation Analyzer	$3,000
HP 8903A, Audio Analyzer	$2,700
Huntron HTR-1005-1S, Tracker Component Tester	$200
Keithley 192, Programmable DMM, 6.5 Digits, HPIB	$600
Keithley 614, Electrometer	$700
Kepco ATE-100-1M, Power Supply, 0-100V, 0-1A (new)	$200
Krohn-Hite 3202, Filter, LP, HP, BP, 20Hz-2MHz, Unused	$350
Leeds & North 1091, Capacitor Decade, .001uF-1uF	$150
Marconi TF2300A, Modulation Meter	$250
North Atl 540/10, Resolver Synchro Bridge	$600
PMI 1018B, Peak Power Meter	$350
PMI 1038, Network Anyz., 1MHz-26.5GHz, w/detectors	$600
Polarad 1105 E-L, Sig. Gen., 1020A Mod., .8-2.4GHz	$300
Polarad 1207, Signal Source 3.8-8.2GHz	$200
Polarad SPNH, Generator 20Hz 20KHz	$450
Racal Dana 1515, Delay Pulse Generator	$500
Racal Dana 1992, Frequency Counter, High Stab., HPIB	$500
Racal Dana 9082P, Signal Gen. 1.5-520MHz AM, FM	$800
Racal Dana 9303, True RMS RF Level Meter	$650
Racal Dana 9515, Universal Counter, HPIB, Opt. 41	$200
Sanders 5440C, Noise Figure Mtr., 10KHz-40GHz	$650
Sencore TF30, Super Cricket Transistor Tester	$200
Tek 11302, Scope, 500MHz w/(2) 11A71 Plug-ins	$1,400
Tek 1502/04, TDR with Chart Recorder	$1,000
Tek 1503/04, TDR, Option 03, 04	$1,200
Tek 178, Linear IC Test Fixture, For 577	$300
Tek 2246, Scope, 100MHz, 4 Ch. Cursors	$1,400
Tek 2336, Scope, 100MHz, Dual Trace	$800
Tek 2230, Storage Scope, 100MHz, Dual Trace	$2,200
Tek 2230, Scope, Digital Storage, 100MHz	$2,200
Tek 284, Pulse Generator	$350
Tek 318, Logic Analyzer, with Pods	$600
Tek 464, Scope/100MHz Dual Trace, Storage	$500
Tek 465M, Scope, 100MHz Dual Trace	$400
Tek 466, Scope, 100MHz Dual Trace, Storage	$600
Tek 468, Scope, 100MHz Digital Storage	$800
Tek 475, Scope 200MHz, Dual Trace	$600
Tek 475A, Scope 250MHz, Dual Trace	$650
Tek 485, Scope 350MHz, Dual Trace	$750
Tek 492, Spectrum Analyzer, Opt. 02	$5,000
Tek 496P, Programmable Spectrum Analyzer	$8,000
Tek 5003, Power Module	$300
Tek 624, XY Monitor	$200
Tek 7CTIN, Curve Tracer Plug-In	$350
Tek 7D20, Programmable Digitizer PI	$600
Tek 7L13, Spectrum Analyzer, 1KHz-1.8GHz	$1,200
Tek 7L13/7603, Spectrum Anyz., .1KHz-1.8GHz	$1,200
Tek 7L5, Spectrum Analyzer	$1,000
Tek 7S12/S6/S52/S53, TDR Sampler	$1,200
Tek AA5001/TM5003, Distortion Analyzer	$1,000
Tek AM503, Current Probe Amp	$400
Tek CG551AP/515P, Scope Calibrator	$1,000
Tek DC503, Universal Counter Timer TM500	$150
Tek DC504, Counter/Timer TM500	$100
Tek DC505A, Frequency Counter, DC-225MHz	$300
Tek MR501, XY Monitor Scope	$200
Tek P6046, Differential Probe Kit	$350
Tek P6452, Data Acquisition Probe	$25
Tek PG508, Pulse Generator, 50MHz	$300
Tek PS503A, Dual Tracking Power Supply, TM500	$200
Tek S-52, Pulse Generator Head	$500
Tek S-53, Trigger Recognizer	$500
Tek SC502, Scope, 15MHz, Dual Trace	$250
Tek SG502, Sig. Gen. 5Hz-50KHz TM500 Sys.	$200
Tek T202, Scope, LCD Handheld	$350
Tek TG501, Time Mark Generator	$400
Tek TM503, Mainframe 3 Slot, TM500	$100
Texscan SSG2000, Freq. Syn., 100KHz-2GHz, AM, FM	$1,800
Vu-Data 5110, Semiconductor Tester, In/out Circuit	$150
Wavetek 1045/14139, Power Meter 1MHz-18GHz Opt. 01, 05	$800
Wavetek 144, HF Sweep Gen. .0005Hz/10MHz	$200
Wavetek 180, Sweep Function Gen. .1Hz-2MHz	$300
Wavetek 185, Sweep Function Gen. .0001-5MHz	$400
Wavetek 1084, Signal Gen. Sweeper, 3.5-4.5GHz	$300
Wavetek 1910, XY Monitor, Dual Trace	$600
Wavetek 2002A, Signal Gen. Sweeper, 1-2500MHz	$1,000
Wavetek 3000, Signal Gen., 1-520MHz, AM, FM	$800
Wavetek 3001, Signal Gen., 1-520MHz, AM, FM	$800
Wavetek 452, Filter, Dual Hi/Lo, 1Hz-10KHz	$450
Wavetek 750, Phase Meter	$300
Wavetek 7530A, FFT Spectrum Analyzer 0-100KHz	$650
Wavetek 859, Programmable Pulse Gen.	$1,000
Wiltron 560A, Network Analyzer, HPIB	$850

PHELPS INSTRUMENTS
2631 Hillside Ave., Norco, CA 91760 • 909-279-7347

MasterCard VISA AMERICAN EXPRESS

Turn Your Multimedia PC into a Powerful Real-Time Audio Spectrum Analyzer

Features

- 20 kHz real-time bandwith
- Fast 32 bit executable
- Dual channel analysis
- High Resolution FFT
- Octave Analysis
- THD, THD+N, SNR measurements
- Signal Generation
- Digital Filtering
- Triggering, Decimation
- Transfer Functions, Coherence
- Dynamic Data Exchange (DDE)
- Time Series, Spectrum Phase, Spectrgram and 3-D Surface plots
- Real-Time Recording and Post-Processing modes



Applications

- Distortion Analysis
- Frequency Response Testing
- Vibration Measurements
- Acoustic Research

System Requirements

- 486 CPU or greater
- 8 MB RAM minimum
- Win. 95, NT, or Win. 3.1 + Win.32s
- Mouse and Math coprocessor
- 16 bit sound card

Priced from $299

(U.S. sales only – not for export/resale)

Professional Quality Sound Cards Available...Call

DOWNLOAD FREE 30 DAY TRIAL!

www.telebyte.com/pioneer

PHS Pioneer Hill Software
24460 Mason Rd. N.W.
Poulsbo, WA 98370

Spectra Plus 4.0
Affordable Signal Processing Software

Sales: (360) 697-3472 *Fax: (360) 697-7717* *e-mail: pioneer@telebyte.com*

Write in 140 on Reader Service Card.

Cable TV Outlet



Factory Direct!



We Carry A Complete Line Of Cable Television Equipment!

-Unbeatable Wholesale Pricing-
-Replacement Converters-
-Filters and Accessories-
-Full Satisfaction Guaranteed-

QB VIDEO

Open M-F 9a to 5p (CT)

1-800-249-3025

Visa, MC & C.O.D.'s Welcome

Write in 90 on Reader Service Card.

USER'S GUIDE TO AUDIO POWER AMPLIFIER ICs

Part 5

by Ray Marston

Ray Marston describes practical IC-based audio power amplifier circuit design techniques in this final episode of the series.

Parts 1 to 4 of this series have explained various audio power amplifier IC operating principles and presented a large selection of practical application circuits based on popular audio power amplifier ICs with maximum output power ratings in the range of 325mW tp 68W.

Between them, these various articles have covered many practical aspects of audio power amplifier IC usage. There are, however, still several important details of audio power amplifier IC usage that have not yet been covered, and included among them are the matters of loudspeaker selection, power amplifier sensitivity, power supply parameter selection, IC power dissipation, heatsink selection, and practical audio power amplifier design techniques.

All of these subjects are dealt with in this final part of the series.

LOUDSPEAKER SELECTION

The loudspeaker is the final and perhaps weakest link in the audio signal communication chain. In each channel of a hi-fi system, the speaker unit is normally connected (directly or via an isolating capacitor) between the amplifier's output and the ground (common) line.

The speaker unit may take the form of a single full-range loudspeaker, as shown in the basic 'single-ended power supply' amplifier circuit of Figure 1, but more often takes the form of two or more speakers that are driven via a passive crossover filter, as shown in the simple example in Figure 2.

In Figure 2, one speaker handles the bass frequencies and the other (called a tweeter) handles the treble tones; the diagram shows typical component values for a 6dB/octave filter that drives a pair of 8R0 speakers and has a crossover frequency of 5KHz.

Note that the unit is designed to give an input impedance equal to that of a single speaker (8R0 in this case), and thus appears to the amplifier as a single speaker load.

The most important basic parameter of a loudspeaker is (ignoring its frequency response and its power handling capacity) its input or coil impedance. Modern loudspeakers have standard impedances or 8R0, 6R0, or 16R (but sometimes 64R in very-low-power types) in most domestic or music-system applications, or 4R0 in low-voltage units such as in-car entertainment systems (which operate at a nominal 14.4V under actual running conditions).

Often, in in-car systems, two 4R0 speakers are wired in parallel to form a high-power 2R0 unit. To obtain the maximum possible output power from an audio system, it is necessary to correctly match the effective speaker load impedance to the operating characteristics of the audio power amplifier.

All audio power amplifier ICs have specific supply-voltage and load-current handling and power dissipation limits, and these greatly influence the maximum power that can be safely fed to speakers with particular values of load impedance. The following formulas define the relationships between speaker load impedance, voltage, current, and power:

$$(1)\ I=\sqrt{\frac{W}{R}} \qquad (2)\ E=\sqrt{RW}$$

$$(3)\ W=\frac{E^2}{R} \qquad (4)\ W=I^2R$$

where E = load voltage in rms volts, I = load current in rms amps, R = load impedance in ohms, and W = load power dissipation in rms watts. Thus: from (1) and (2) it can be deduced that an 8R0 load operating at a 10W power level consumes 1.12A at 8.94V; from (3) that an amplifier that produces an output of 10V rms generates 12.5W in an 8R0 load; and from (4) that an amplifier that can produce a maximum output of 1.2A can generate a maximum of 11.52W in an 8R0 speaker.

In practice, IC drive-current limits are usually specified in terms of I_{peak}, and their output voltage swing limits (which are typically about 10% less than their supply voltage values) are specified in V_{pk} terms in split-supply applications or in $V_{pk\text{-}pk}$ (V_{pp}) in single-ended-supply applications. The following formulas show the relationships between rms (rms), peak (pk), and peak-to-peak (pp) voltage or current values:

$$(5)\ I_{pk}=I_{rms}\sqrt{2} \qquad (6)\ I_{rms}=\frac{I_{pk}}{\sqrt{2}}$$

$$(7)\ V_{rms}=\frac{V_{pk}}{\sqrt{2}}=\frac{V_{pp}}{2\sqrt{2}} \qquad (8)\ V_{pk}=V_{rms}\sqrt{2}$$

$$(9)\ V_{pp}=2V_{rms}\sqrt{2}$$

Thus, from (6), (4), (2), and (9) it can be deduced that an IC that can supply an I_{peak} of 3.5A can supply a maximum I_{rms} of 2.47A and generate a maximum of 49W in an 8R0 speaker at a drive voltage of $19.8V_{rms}$ or $56V_{pp}$, thus requiring a typical supply voltage of at least 62V from a single-ended power unit or ±31V from a split-supply unit.

The same IC could generate a maximum of only 24.5W (at $9.9V_{rms}$) in a 4R0 speaker, but a pair of ICs could generate 98W in a 16R speaker (or a pair of series-wired 8R0 types) when connected in the bridge-drive mode (in which they effectively double the speaker's drive voltage).

Thus, the first step in designing an IC audio power amplifier system for a particular application is to select a suitable IC and speaker, using the basic data given above.

Figure 3, for example, lists the actual voltage and current values of five different speakers when they are operating at 10W power levels. At low operating voltages, low impedance (2R0 or 4R0) speakers must be used to obtain a good power output.



Figure 1. A power amplifier, operated from a single-ended supply, driving a single full-range loudspeaker.



Figure 2. A speaker unit consisting of two loudspeakers and a simple (6dB) cross-over filter unit.

At reasonable high voltages, 8R0 or 16R speakers can be used.

Note, when making calculations of the types described in this section, that if you do not have access to precise data concerning an IC's I_{peak} limit, the data can often be inferred from the manufacturer's application circuits, which are usually designed to show the product operating close to its performance limits.

Thus, the LM3886 circuit of last month's Figure 22, which can generate 68W in a 4R0 load, implies — using formulas (2) and (5) — that the IC can comfortably generate output currents of at least $4.12A_{rms}$ or $5.8A_{pk}$.

POWER AMPLIFIER SENSITIVITY

A power amplifier's 'sensitivity' value defines the magnitude of rms input signal voltage needed to produce a particular output power level from the amplifier. Commercial hi-fi units usually specify the sensitivity at both a standard 1W output level and at the full-rated output power level. The 'standard' (1W) sensitivities of commercial units vary between roughly 25mV and 200mV; a good compromise value is 100mV.

The power amplifier's output power level is proportional to the square of the input voltage, thus, if the amplifier has a basic 100mV sensitivity, it intrinsically gives an output of 4W at 200mV, 16W at 400mV, 36W at 600mV, and 40W at 632mV.

The basic formulas that link an amplifier's output power, standard sensitivity, and actual sensitivity are:

$$(10)\ W_{out}=\left(\frac{V_{input}}{V_{sens}}\right)^2$$

$$(11)\ V_{input}=V_{sens}\sqrt{W_{out}}$$

where V_{sens} and V_{input} are in millivolts and W_{out} is in watts.

The amplifier's sensitivity is determined by its voltage gain (A_V), speaker impedance (R), and output power level (W), using the formulas:

$$(12)\ A_V=\frac{V_{out}}{V_{input}}=\frac{\sqrt{RW}}{V_{sens}}$$

Speaker impedance	V_{rms}	I_{rms}	$V_{pk\text{-}pk}$	I_{pk}
16R	12.65V	0.79A	35.8V	1.12A
8R0	8.94V	1.12A	25.3V	1.58A
6R0	7.75V	1.29A	21.9V	1.82A
4R0	8.32V	1.58A	17.9V	2.23A
2R0	4.47V	2.24A	12.6V	3.16A

Figure 3. Voltage and current values of various speakers at 10W power levels.



Figure 4. Basic circuit and formula for setting the A_V (and hence sensitivity) value of a modern inverting 'op-amp' type of power amplifier (PA) circuit.

In practice, 4R0 and 8R0 speaker loads absorb 2.0V and 2.83V of drive respectively at 1W power levels. Thus, to give a standard sensitivity value of 100mV, the amplifier needs an A_V of x20 with a 4R0 load or x28.3 with an



Figure 5. Basic circuit and formula for setting the A_V (and hence sensitivity) value of a modern non-inverting 'op-amp' type of power amplifier (PA) circuit.

rents, which are usually relatively small.

Formula (14) defines the total power input into the IC, in terms of supply voltage and current (I_{DC}). Formula (15) defines the power amplifier IC's power conversion efficiency in terms of P_{OUT} (to the speaker load) versus P_{INPUT}. Finally, formula (16) defines the actual power dissipated across the IC as P_{INPUT} minus P_{OUT}.

Returning now to Figure 6, note that in an ideal class-AB power amplifier, the load's sinewave output voltage would be able to swing fully between the two supply rail levels (0V and V_{SUPPLY}) without clipping. Such an amplifier would — at maximum power output — operate with an efficiency of 78.5%.



Figure 6. Basic details of an audio power amplifier IC circuit operated from a single-ended supply (a), and its sinewave output waveform when driving maximum power into a speaker load (b).



Figure 7. Typical P_{IC} versus P_L curve of an LM384-based 6.5W amplifier driving an 8R0 load from a 26V supply.

quently rises to its permitted 'nominal+10%' upper limit, the IC power dissipation will rise to 9.4W at 10W output, and the IC will operate with an efficiency of only 51.5%. Good power supply design is thus vital.

From the above, it can be seen that the ideal power supply should be a low ripple type that, at the designed maximum audio power output level, produces a per-channel output current of I_{DC} (see formula (13)) and a voltage of $V_L+V_{D1}+V_{D2}$ if the supply is a single-ended type, or ± half of this value if it is a split type.

Note that — if the supply is an unregulated type — the supply voltage will (depending on the supply's actual regulation factor) typically rise by 15% under very-low-load conditions and by a further 10% if the AC power line voltage rises to its maximum permitted value.

This worst-case voltage must not exceed the IC's supply voltage limit. If the IC is operating close to its critical supply voltage or power dissipation levels, a regulated power supply should be used.

8R0 load. Most modern audio power amplifier ICs function like high-power op-amps that are used in either the inverting or non-inverting mode, and their A_V (and hence sensitivity) values can thus be set to any desired values by selecting their R1 and R2 feedback resistor values in the basic ways shown in Figures 4 and 5.

POWER SUPPLY REQUIREMENTS

An audio power amplifier IC's power supply is a critical part of the audio system and, if poorly specified or designed, can have a highly detrimental effect on the audio power amplifier IC's operating efficiency and power dissipation.

Figure 6 illustrates some important audio power amplifier IC characteristics that are relevant to power supply design. The diagram shows a basic amplifier that is powered from a single-ended supply, together with its maximum peak-to-peak sinewave output waveform superimposed on the supply's half-voltage line. The following formulas are relevant to this diagram and to the next few paragraphs of text:

$$(13)\quad I_{DC} = 0.45 \times I_{rms}$$

$$(14)\quad P_{INPUT} = V_{SUPPLY} \times I_{DC}$$

$$(15)\quad Efficiency = \frac{P_{OUT}}{P_{INPUT}}$$

$$(16)\quad P_{IC} = P_{INPUT} - P_{OUT}$$

Regarding these formulas — which all assume that the IC is a single (rather than a dual) type — formula (13) defines the IC's power supply current (I_{DC}) as a function of the IC's load (speaker) current, I_{rms} (see formula (1)), but ignores the effects of the IC's quiescent cur-

If this ideal amplifier is driving 10W into an 8R0 load at its maximum output level, V_{SUPPLY} will have a value of 25.28V (the load's V_L peak-to-peak voltage value), the IC will consume a supply current (I_{DC}) of 0.504A (= 0.45 times the load's 1.12A rms signal current), a total of 12.74W (= 25.28V x 0.504A) will be consumed from the power supply, and 2.74W of this will be developed across the IC and 10W across the load.

In a real-life class-AB power amplifier IC, significant voltage losses occur in the IC's output driver stages, and in Figure 6 these are represented by two 'dropout' voltages, V_{D1} and V_{D2}, and to compensate for these, the above 10W amplifier needs a minimum supply voltage of $V_L+V_{D1}+V_{D2}$.

Suppose that this combination calls for a minimum V_{SUPPLY} value of 30V. In this case, a total of 15.12W (= 30V x 0.504A) will be consumed from the supply at 10W output, and 5.12W of this is generated across the IC, which thus operates with an efficiency of only 66.1% (= P_{OUT}/P_{IN}). (Note that dropout voltage values are often given in manufacturer's data sheets, but if this information is not readily available it can — if the IC is fitted with an adequate heatsink — easily be ascertained from practical power amplifier tests with the aid of an oscilloscope.)

Suppose now that, in the above 10W amplifier circuit, the power supply is a badly designed unregulated type that — at the nominal AC power line voltage — gives an actual output of 35V at full load. In this case, a total of 17.64W (= 35V x 0.504A) will be consumed from the supply at 10W output, and 7.64W of this is developed across the IC, which thus operates with an efficiency of only 56.7% at full output.

If the AC power line voltage subse-



Figure 8. Graph showing the relationship between chip temperature and chip power dissipation limits.

IC POWER DISSIPATION

The previous few paragraphs outlined some basic principles concerning power dissipation in audio power amplifier ICs. A good understanding of this subject is important in practical applications, since IC power dissipation generates heat in the IC and must — if the IC is to function correctly — be kept under control (usually with the aid of a suitable heatsink). This section provides additional information on the subject, as follows.

If the sinewave input signal voltage to an IC audio power amplifier circuit is progressively increased from zero to maximum, the circuit's load (speaker) voltage and current both increase proportionately, and the load power thus increases in proportion to the square of the input voltage.

The power dissipation of the actual IC, however, varies in a rather different way, since any increase in input voltage causes an increase in the IC's supply current, but a decrease in the volt drop across the IC's power-driving output stages. Initially, the IC's power dissipation increases as the input voltage is increased, but eventually a point is reached where the power dissipation reaches a peak value, and any further increase in input voltage results in a *decrease* in the IC's power dissipation.

The IC's peak power dissipation point ($P_{IC(MAX)}$) occurs when V_L (the load's peak-to-peak signal voltage) equals 63.7% of V_S (the IC's supply voltage), at which point $P_{IC(MAX)}$ has, in theory, a value of:

$$(16)\quad P_{IC(MAX)} = \frac{(V_S)^2}{20R_L}$$

Note, however, that this widely quoted, but slightly simplified, theoretical figure assumes the use of an electronically perfect IC that (among other things) is perfectly linear and generates zero signal distortion. In practice, actual $P_{IC(MAX)}$ figures may be as much as 20% higher than given in formula (16), particularly if very low impedance (2R0 or 4R0) speaker loads are used.

Thus, in the well-designed 10W, 30V, 8R0 amplifier mentioned previously, the IC has a theoretical $P_{IC(MAX)}$ value of 5.62W but, in practice, has a probable value of about 6.2W.

If the IC's sinewave input signal voltage is increased beyond the $P_{IC(MAX)}$ point, a level is eventually reached where the load is operating at its designed maximum power level, and any further increase in input voltage generates a clipped (square shaped if severely clipped) output signal that has a greater power content than a simple sinewave; the IC's power dissipation decreases sharply under this condition.

As a consequence of the various factors described above, *all* analogue audio power amplifier ICs generate a P_{IC} versus P_L curve that follows the basic form shown in Figure 7, in which — as the P_L value is increased from zero to maximum — the P_{IC} value rises exponentially from zero to a peak value that occurs at the $P_{IC(MAX)}$ point, and then starts to fall again as the P_L value heads towards the signal-clipping point.

Note that the above $P_{IC(MAX)}$ figures apply to 'single' ICs. In dual (two-channel) ICs, or in single types that form one half of a bridge-type amplifier, the above $P_{IC(MAX)}$ figures must be doubled.

HEATSINK CALCULATIONS

The heart of any IC is its solid-state chip, and it is this that becomes heated when power is generated within the IC. By industry-wide convention, an IC chip's recommended safe maximum power handling capacity is normally specified at a chip temperature of 25°C, and — in commercial ICs that use a plastic package — the chip's recommended maximum allowable operating temperature is limited to 150°C, at which temperature its spare power handling capacity is deemed to be zero.

The chip's power handling capacity is inversely proportional to the chip temperature, and is 40% of maximum at 100°C. Most modern audio power amplifier IC chips incorporate thermal protection circuitry that automatically cuts off the chip's power feed at a chip temperature of 165°C, thus protecting the IC against catastrophic power-induced over-temperature damage.

Figure 8 presents the above data in graphic form, with the chip's power



Figure 9. Simple thermal resistance model of a power amplifier IC that has its case bonded to an infinite heatsink.

handling capacity presented as a percentage of the maximum figure attainable at the 25°C value. Thus, if the chip can handle a maximum of 10W at 25°C, its temperature must be kept below 100°C if it is to be used in an application where its maximum power dissipation ($P_{IC(MAX)}$) is expected to reach 4W.

This temperature control is normally exercised via an external heatsink, which helps the internally power-generated heat to flow away and be absorbed by the ambient conditions.

Heat flow is best modeled in terms of thermal resistance, where a 'thermal resistance' represents the thermal conductor's input-to-output temperature drop divided by the power dissipated by the conductor, in °C/W. The symbol used to represent thermal resistance is q (theta), and is usually followed by a subscript that denotes the direction of heat flow. Thus, the symbol q_{JC} denotes the thermal resistance that exists between the IC's junction (chip) and case.

Figure 9 shows a simple thermal resistance model of an audio power amplifier IC that has a power dissipation limit of 125W at a chip temperature of 25°C, has a q_{JC} value of 1°C/W, and has its case bonded to an infinite heatsink that is operating at an ambient temperature of T_A °C.

It is fairly obvious from this model that, at a chip power dissipation value of W, the chip's junction temperature (T_J) equals $T_A + (W.q_{JC})$. Thus, if T_A is 25°C, the T_J value works out at 35°C at 10W, 75°C at 50W, or 150°C at 125W, and if T_A is 45°C the T_J value works out at 55°C at 10W, 95°C at 50W, or 150°C at 105W, and so on.

In the real world, the point of union between the case and heatsink inevitably has a certain thermal resistance value, and this is given the symbol q_{CS} (case-to-sink) and has a typical value of 0.2°C/W if the union is a bolted type made via a good *modern* heat transfer compound.

Also, the heatsink is inevitably finite, and is represented by the symbol q_{SA} (sink-to-ambient), and has a value of X°C/W.

The *total* thermal resistance between the chip junction and the ambient temperature is represented by the symbol q_{JA} (junction-to-ambient) and is equal to the sum of these three thermal resistance values. Thus, $q_{JA} = q_{JC} + q_{CS} + q_{SA}$.

Figure 10 shows a thermal resistance model of a real-world version of the Figure 9 audio power amplifier IC, bolted to a finite heatsink that has a q_{SA} value of 2°C/W and is operating at an ambient temperature of 25°C.



Figure 10. Real-world thermal model of a power amplifier IC that has its case bolted to a finite heatsink.

The IC again has a power dissipation limit of 125W at a chip temperature of 25°C, and has a q_{JC} value of 1°C/W. The total thermal resistance, q_{JA}, between the chip junction and ambient thus equals 1°C/W + 0.2°C/W + 2°C/W, i.e., 3.2°C/W. Consequently, in this example, the IC's T_J value equals $T_A + (W.q_{JA})$, and works out at 57°C at 10W, or 121°C at 30W.

In practice, the two most valuable pieces of data that can be gleaned from a real-world thermal model of the Figure 10 type are, first, the maximum power dissipation limit ($P_{IC(MAX)}$) of an IC at a given q_{JA} value, and second, the *minimum* heatsink value (q_{SA}) needed to dissipate a known value of IC power, P_{IC}. The following two formulas, in which $T_{J(MAX)}$ has a value of 150°C in normal commercial ICs, define this data.

$$(17)\quad P_{IC(MAX)} = \frac{T_{J(MAX)} - T_A}{\theta_{JA}}$$

$$(18)\quad \theta_{SA} = \frac{T_{J(MAX)} - T_A}{P_{IC}} - (\theta_{JC} + \theta_{CS})$$

Thus, from (17) it can be seen that, when using the q_{JA} value of 3.2°C/W shown in Figure 10, the IC can dissipate a maximum of 39W, and — from (18) — that, for the IC to dissipate 50W, the heatsink needs a *maximum* q_{SA} value of 1.3°C/W.

HEATSINK PRACTICALITIES

When using formula (18) it is always wise to use a realistic (rather than optimistic) worst-case T_A figure, such as 30°C rather than 25°C.

The vital q_{JC} value used in the formula is usually given in the IC's data sheet.

It is important to note that formula (18) indicates the theoretical *absolute maximum* size of heatsink q_{SA} value that should be used in a particular application, and that in practice a heatsink with a somewhat lower q_{SA} value should actually be used.

In the case of the Figure 10 50W amplifier given above, for example, where the formula gives a maximum q_{SA} value of 1.3°C/W, a heatsink with an actual value of 1°C/W should be used. Note, however, that the physical size (and cost) of a heatsink is inversely proportional to its q_{SA} value, and a 1°C/W heatsink is thus physically larger and more expensive than a 1.3°C/W type.

Heatsinks are readily available in a wide range of q_{SA} values.

When selecting an actual heatsink size after completing the formula (18) calculations, some thought should be given to two conflicting theories in the subject. These can be called the 'real life audio' and the 'IC reliability' theories.

The first of these theories states that real life audio systems deal primarily with music or speech signals, and these — at full volume — have a mean power output that is typically less than one-third of the maximum continuous sinewave value used in the formula (18) calculation.

This theory concludes that — in hi-fi types of audio application — there is no practical advantage in using a heatsink that is physically larger than the minimum value indicated by formula (18).

The alternative 'IC reliability' theory is based on IC failure rate studies that show that failure rates are exponentially proportion to the IC's junction temperature, and under worst-case conditions increase by a factor of three for every 10°C rise in junction temperature.

When these failure rate studies are applied to the above-mentioned 50W audio amplifier, they show that — when the IC is operating under worst-case conditions at full (50W) sinewave power — the IC's failure rate is reduced by a factor of five by using a heatsink with a q_{SA} value of 1°C/W, rather than the 1.3°C/W value indicated by formula (14), and that under typical full-volume (16.6W average output power) music conditions, the failure rate is almost halved by using the 1°C/W heatsink.

BASIC AUDIO POWER AMPLIFIER DESIGN

To conclude this final episode of the 'Audio ICs' series, this final section shows how the information so-far presented in this episode can be used to design a complete and reliable basic audio power amplifier system.

The first step in creating such a design is to draw up a specification that includes per-channel details such as: (a) maximum power output; (b) output load impedance; (c) input impedance; (d) input sensitivity; and (e) a basic amplifier description, and to then select a specific IC for use in the design.

Suppose that this basic specification is as follows:

(a). Maximum power output = 30W.
(b). Load (speaker) impedance = 8R0.
(c). Input impedance = 47K.
(d). Input sensitivity (at 1W output) = 100mV.
(e). Amplifier type = non-inverting; powered from a split supply.

The procedure for designing such an amplifier is as follows:

Regarding specifications (a) and (b), formulas (2), (8), (1), and (5) in the LOUDSPEAKER SELECTION section of this article show that the power amplifier must supply the 8R0 load with a peak voltage of 21.9V and a peak current of 2.74A at the 30W power level. These values are well within the capabilities of the LM3875 IC (see Part 4 of this series).

This IC's data sheet shows that the IC's upper and lower dropout voltage each have values of 4V under the specified maximum load driving conditions, and the split (dual) power supply must thus generate an output of ±26V at (from formulas (1) and (13)) 0.87A under full load conditions.

The worst-case off-load voltage, assuming a 15% regulation factor in the power supply and a +10% voltage rise in the AC supply line, is thus ±32.5V, and is well within the operating limits of the LM3875.



Figure 11. Design example of a 30W non-inverting amplifier powered from a split (dual) supply (see text for design procedure).

Regarding specification (e), this calls for a basic amplifier design of the type shown in Figure 11 (which is based on the Figure 18 circuit shown last month).

In this design, specification (c) can be met by giving volume control RV1 a value of 47K. Specification (d) can, as described in the POWER AMPLIFIER SENSITIVITY section of this article, be met by giving the amplifier an A_V value of (ideally) x28.3, and in the Figure 11 circuit this is achieved by giving R3 a value of 27K.

The final step in the amplifier design exercise is that of selecting a suitable heatsink. From formula (16), it can be seen that in this circuit the IC's maximum power dissipation is (remembering that the IC is using a dual — rather than single-ended — supply) 16.9W.

The LM3875 IC has a q_{JA} value of 1°C/W, and the q_{CS} value is typically 0.2°C/W. Consequently, formula (18) shows that, at an ambient temperature of 30°C, the heatsink needs a maximum q_{SA} value of 5.9°C/W.

In practice, a heatsink with a somewhat lower q_{SA} value should be used. **NV**

If you'd like a reprint of the entire five-part series, contact Nuts & Volts at 909-371-8497 for details.

WESTERN TEST SYSTEMS

WE BUY AND SELL

Inquiries **303-438-9662** • Fax **303-438-9685**

Orders only **800-538-1493**

530 Compton St., Unit #C, Broomfield, Colorado 80020

OSCILLOSCOPES & ACCESSORIES

TO 100 MHz

TEK 7A18 75 MHz Dual Trace Amplifier $100.00
TEK 7A22 1 MHz High CMRR Differential Amplifier $300.00
TEK 7B53A 100 MHz Dual Time Base $175.00
TEK SC502 15 MHz Dual Trace Oscilloscope, TM500 series $375.00
TEK SC504 80 MHz Dual Trace Oscilloscope, TM500 series $450.00

ABOVE 100 MHz

TEK 475A 250 MHz Dual Trace Oscilloscope $900.00
TEK 7104 1 GHz Oscilloscope, ... $4,500.00
with 7A29, 7A29-04, 7B10, 7B15
TEK 7844 400 MHz Dual Beam Oscilloscope frame $750.00
TEK 7844 400 MHz Dual Beam Oscilloscope $1,250.00
with 7A24,7A26,7B80,7B85
TEK 7854 400 MHz Waveform Processing Oscilloscope frame $1,250.00
TEK 7904A 500 MHz System, with 7A24, 7A26, 7B92A $1,250.00
TEK 7904A 500 MHz System, with 7A24, 7A26, 7B80, 7B85 ..... $1,250.00
TEK 7A13 105 MHz Differential Comparator $225.00
TEK 7A19 600 MHz Single Trace Amplifier $150.00
TEK 7A24 400 MHz Dual Trace Amplifier $300.00
TEK 7A26 200 MHz Dual Trace Amplifier $175.00
TEK 7B15 1 GHz Delaying Time Base $450.00
TEK 7B80 400 MHz Delayed Time Base $175.00
TEK 7B85 400 MHz Delta Delaying Time Base $175.00
TEK 7B92A 500 MHz Dual Time Base $275.00

STORAGE

TEK 7633 100 MHz Storage Oscilloscope frame $650.00
TEK 7633 100 MHz Storage Oscilloscope $1,000.00
with (2) 7A26, (1) 7B92A

PROBES

HP 1122A Probe Power Supply $200.00
TEK 1101 Accessory Power Supply, for FET probes $250.00
TEK P6101A 34 MHz 1X Modular Probe, 2m length *NEW* $25.00
TEK P6201 900 MHz 1X/10X/100X FET Probe $450.00
TEK P6202A 500 MHz 10X FET Probe $300.00
TEK P6701-opt.02 O/E Converter, ... $675.00
450-1050 nm/0-1 mW: DC-700 MHz, ST conn.

CALIBRATION

TEK 067-0587-01 Signal Standardizer $300.00
Calibration Fixture, 7000 series
TEK CG5001-opt.01/TM5006 Programmable $6,000.00
Oscilloscope Calibrator, with power module
TEK CG551AP/TM506A Oscilloscope $2,500.00
Calibrator, with pulse head & power module
TEK SG503 Level Generator, 250 kHz-250 MHz, TM500 series $600.00

WAVEFORM GENERATORS

FUNCTION

HP 3310A 5 MHz Function Generator $250.00
HP 3310B 5 MHz Function Generator, ... $325.00
monocycle & var.phase trigger
HP 3312A 13 MHz Function Generator $750.00
KROHN-HITE 2000 30 MHz Function Generator $600.00
TEK DD501 Digital Delay & Burst Gen., for function & pulse gen's $275.00
TEK FG501 1 MHz Function Generator, TM500 series $225.00
TEK FGF503 3 MHz Function Generator, TM500 series $250.00
TEK RG501 Ramp Generator, TM500 series $225.00
WAVETEK 186 5 MHz Phaselock Function Generator $350.00

PULSE

BERKELEY NUCLEONICS 7085B Digital $900.00
Delay Generator, 0-100 mS, 1 nS res.,5 Hz-5 MHz
HP 214B-001 10 MHz Pulse Generator, ... $2,000.00
50 V/50 ohms, counted burst opt
HP 8005B 20 MHz Dual Output Pulse Generator $450.00
HP 8007B 100 MHz Pulse Generator $650.00
HP 8012B 50 MHz Pulse Generator, variable transition time $600.00
HP 8015A 50 MHz Dual Output Pulse Generator $700.00
HP 8015A-002,007 50 MHz Dual Output Pulse Gen., burst option $800.00
HP 8080A/91A/92A/93A 1 GHz Single Channel Pulse Generator $950.00
TEK PG502 250 MHz Pulse Generator, Tr<1nS, TM500 series $600.00
TEK PG505 100 kHz Pulse Generator, 80 V peak, TM500 series $275.00

PROGRAMMABLE

HP 8165A-002,003 Prog. Signal Source, ... $2,000.00
1 mHz-50 MHz, log sweep, rear out
TEK AWG5102 Arb.Waveform Gen.,20 MS/s, ... $1,400.00
12 bits,50ppm synthesis <1MHz
TEK AWG5105-opt.02 Arbitrary Waveform $1,900.00
Generator, dual channel option
TEK FG5010 Programmable 20 MHz $1,200.00
Function Generator, TM5000 series
WAVETEK 178 50 MHz Programmable Waveform Synthesizer $1,000.00
WAVETEK 288 20 MHz Synthesized Function Generator, GPIB $1,250.00

RF & MICROWAVE

SPECTRUM ANALYZERS

HP 3456A 6-1/2 Digit Voltmeter $850.00
HP 3478A 5-1/2 digit Multimeter, HPIB $700.00
KEITHLEY 181 6-1/2 digit Nanovoltmeter, ... $1,200.00
10 nV sensitivity, GPIB
KEITHLEY 195A/1950 5-1/2 digit Multimeter, AC/Current option $500.00
SOLARTRON 7081 8-1/2 digit Voltmeter $3,900.00

CALIBRATION

DATRON 4000A DC Voltage/Current Calibrator $2,500.00
DATRON 4200 AC Voltage/Current Calibrator $2,500.00
FLUKE 343A DC Voltage Calibrator, ... $950.00
0-1100 V, 7 decades, 20 ppm acc.
FLUKE 5100B-03,05 Calibrator, wideband AC & GPIB options $4,500.00
FLUKE 510A AC Reference Standard, 10 VRMS, 0-10 mA $450.00
FLUKE 515A Portable Calibrator, ... $1,000.00
DC/AC/Ohms, line & battery power
FLUKE 5220A Transconductance $3,750.00
Amplifier, DC-5 kHz, 0-20 A
FLUKE 731B DC Reference Standard $400.00
FLUKE 732A DC Voltage Standard $2,000.00
FLUKE A40-series Current Shunts $200.00
FLUKE A55-series AC Thermal Converters $300.00
VALHALLA 2500 AC-DC Current Calibrator, ... $700.00
2 uA-2 A, DC-10 kHz
VALHALLA 2703 AC Volt.Std., ... $2,250.00
0-120V/10 Hz-100 kHz;120-1200V/10 Hz-1 kHz

VOLTAGE SOURCES

HP 6115A Precision Dual Range Power $875.00
Supply, 50V 0.8A / 100V 0.4A

CURRENT METERS & SOURCES

HOLT HCS-1AF Primary Current Shunt Set, ... $750.00
0.02/0.2/0.5/2/5/20 Amp
HP 4140B Picoammeter / DC Voltage Source $4,000.00
HP 6177C DC Current Source, to 50V, 500mA $500.00
HP 6181C DC Current Source, to 100 V, 250 mA $500.00
HP 6186C DC Current Source, to 300V, 100mA $750.00
KEITHLEY 225 Current Source, 0.1 uA-100 mA, ... $500.00
10-100 V compliance
KEITHLEY 228 Programmable Voltage/Current Source $2,500.00
KEITHLEY 261 Picoampere Source $375.00
KEITHLEY 414A Picoammeter, 0.1 nA-10 mA $325.00
KEITHLEY 614 Electrometer $800.00
KEITHLEY 642 Electrometer $2,900.00
TEK CT-5 -opt.05 High Current Transformer $500.00
for P6021/A6302, to 1000A
VALHALLA 2301 Programmable Single $1,250.00
Phase Power Analyzer

IMPEDANCE & COMPONENT TEST

L.C.R.

BOONTON 62AD 1 MHz Inductance Meter, 2-2000 uH $550.00
ESI 2160 LCR Bridge, 20 Hz-150 kHz, GPIB $2,000.00
HP 4275A-001 5-1/2 digit LCR Meter, ... $6,000.00
10 kHz-10 MHz, 0-35 V int. bias

STANDARDS

E.S.I. RS925D 7-Decade Resistance Standard, ... $2,000.00
0.01 Ohms - 1.2 Megohms
E.S.I. SR1010 Resistance Transfer Standards, ... $700.00
1 Ohm-100 K/step
E.S.I. SR1050-10M Resistance Transfer $2,500.00
Standard, 10 Megohms/step
E.S.I. SR1050-1M Resistance Transfer $2,000.00
Standard, 1 Megohm/step
E.S.I. SR1-set Set of eight Standard Resistors, ... $900.00
1 Ohm - 10 Megohms
GR 1403-SERIES Standard Air Capacitors, 0.1% accuracy $150.00
GR 1404-A 1000 pF Reference Standard Capacitor $700.00
GR 1406 Standard Air Capacitors, GR900 connector, 0.1% acc. $375.00
GR 1412-BC Decade Capacitor, 50 pF - 1.11115 uF $350.00
GR 1432-U 4-Decade Resistor, ... $125.00
0-111.10 Ohms, 0.01 Ohm resolution
GR 1433-J 4-Decade Resistor, 0-1,110 Ohms, ... $350.00
1 Ohm resolution
GR 1433-N 5-Decade Resistor, 0-11,111 Ohms, ... $400.00
0.1 Ohm resolution
GR 1433-U 4-Decade Resistor, 0-111.0 Ohms, ... $350.00
0.01 Ohm resolution
GR 1433-X 6-Decade Resistor, to 111, ... $450.00
111.0 Ohms, 0.1 Ohm res.
GR 1434-G 7-Decade Resistor, 0-1,111,111.0 Ohms, ... $300.00
0.1 Ohm res.
GR 1440-set Set of nine Standard Resistors, ... $1,200.00
0.01 Ohm - 1 Megohm
GR 1482-series Standard Inductors $275.00
GR 1666 DC Resistance Bridge, 1 Micro-Ohm - 100 Kilohms $600.00
HP 16380A Standard Air Capacitor Set, 1-1000 pF $1,750.00
VALHALLA 2724A Programmable Resistance $1,675.00
Standard, 0-11 Gigaohms, GPIB

HI & LO RESISTANCE

HP 4328A Milliohmeter $1,300.00
VALHALLA 4150-ATC 4-1/2 digit Ohmmeter, ... $750.00
20 milliohms-2 kilohms, 4-wire

CURVE TRACERS

TEK 577D1/177 Storage Curve Tracer, with standard test fixture $2,250.00
TEK 577D2/177 Curve Tracer, with standard test fixture $1,850.00

T.D.R.

TEK 1503-opt.04 Time Domain Reflectometer, ... $1,400.00
0-50,000 feet,chart recorder

POWER SUPPLIES

SINGLE OUTPUT

HP 6200B Dual Range Supply, ... $200.00
0-20 V 0-1.5 A/ 0-40 V 0-750 mA CVCC
HP 6201B 0-20 V 0-1.5 A CV/CC Power Supply $175.00
HP 6206B Dual Range 0-60 V 0.5 A / 0-30 V 1 A CV/CL Supply $200.00
HP 6207B 0-160 V 0-200 mA CV/CC Power Supply $300.00
HP 6260B-027 0-10 V 0-100 A CV/CC $675.00
Power Supply; 208 VAC line
HP 6261B-027 0-20 V 0-50 A CV/CC $675.00
Power Supply; 208 VAC line
HP 6263B 0-20 V 0-10 A CV/CC Power Supply $400.00
HP 6267B 0-40 V 0-10 A CV/CC Power Supply $550.00
HP 6281A 0-7.5 V 0-5 A CV/CC Power Supply $175.00
HP 6284A 0-20 V 0-3 A CV/CC Power Supply $225.00
HP 6290A 0-40 V 0-3 A CV/CC Power Supply $300.00
HP 6299A 0-100 V 0-750 mA CV/CC Power Supply $225.00
HP 6384A 4.0-5.5 V at 8 A CV/CL Power Supply $175.00
SORENSEN DCR 20-25B 0-20 V 0-25 A CV/CC Power Supply $550.00
SORENSON DCR 300-1.5B 0-300 V $600.00
0-1.5 A CV/CC Power Supply
SORENSON DCR 300-8A 0-300 V 0-8 A CV/CC $950.00
Power Supply, 208/230 VAC line
SORENSON SRL 20-12 0-20 V 0-12 A CV/CC Power Supply $500.00
SORENSON SRL 60-8 0-60 V 0-8 A CV/CC Power Supply $750.00
TEK PS501-1 Power Supply, 0-20 V, 2 mV res., ... $175.00
400 mA, TM500 series

MULTIPLE OUTPUT

HP 6227B Dual 0-25 V 0-2 A CV/CC Power Supply $600.00
HP 6228B Dual 0-50 V 0-1 A CV/CC Power Supply $600.00
HP 6236B Triple Output Power Supply, +/-20 V 0.5 A, +6 V 2.5 A $550.00
HP 6237B Triple Output Power Supply, +/-20 V 0.5 A, +18 V 1 A $550.00
HP 6253A Dual Output 0-20 V 0-3 A CV/CC Power Supply $550.00
TEK PS5010 Programmable Triple Power Supply, TM5000 series $750.00
TEK PS503A Dual Power Supply, TM500 series $200.00

MISCELLANEOUS

ACME PS2L-500 Programmable Load, ... $400.00
0-75 V / 0-75 A / 500 Watts max.
HP 59501B HPIB Isolated DAC/Power Supply Programmer $175.00
TRANSISTOR DEVICES DAL-50-15-100 ..... $200.00
Programmable Load, 0-50 V, 0-15 A, 100 Watts max.

TIME & FREQUENCY

UNIVERSAL COUNTERS

HP 5315A 100 MHz/100 nS Universal Counter $500.00
HP 5315A-002,003 100 MHz/100 nS Univ. Counter, ... $750.00
battery power, 1 GHz C-ch
HP 5315B 100 MHz/ 100 nS Universal Counter $600.00
HP 5316A 100 MHz/100 nS Universal Counter, HPIB $700.00
HP 5316A-003,006 100 MHz/100 nS Counter, ... $1,000.00
1 GHz C-ch., offset/normalize
HP 5316B 100 MHz/ 100 nS Universal Counter, HPIB $1,000.00
HP 5334A 100 MHz Universal Counter, HPIB $875.00
HP 5334B-010,060 100 MHz Universal Counter, HPIB, OCXO $1,000.00
HP 5335A 200 MHz Universal / Statistical Counter $1,200.00
RACAL 1996 200 MHz/1 nS Universal $1,000.00
Counter, 1.3 GHz C-channel
RACAL-DANA 1992-04 100 MHz/1 nS Univ. $750.00
Counter, 1.3 GHz C-channel, OCXO
TEK DC5004 Programmable 100 MHz/100nS $250.00
Counter/Timer, TM5000 series
TEK DC5009 Programmable 135 MHz Univ. $500.00
Counter/Timer, TM5000 series
TEK DC503A 125 MHz/ 100 nS Universal Counter, TM500 series $275.00

FREQUENCY COUNTERS

EIP 575 18 GHz Source Locking Counter, GPIB $3,250.00
EIP 578-opt.02,05 26.5 GHz Source Locking $5,000.00
Counter; power meas., OCXO
FLUKE 7220A 1.3 GHz Communications Counter $500.00
HP 5340A-011 18 GHz Frequency Counter, HPIB $1,250.00
HP 5342A 18 GHz Frequency Counter $2,400.00
HP 5342A-001 18 GHz Frequency Counter, OCXO reference $2,500.00
HP 5342A-003 18 GHz Freq.Counter, ... $2,400.00
+22 dBm,-20 dBm dynamic range
HP 5342A-01,04,05 24 GHz Frequency Counter, OCXO, DAC $3,250.00
HP 5343A-006 26.5 GHz Frequency Counter; limiter option $4,500.00
HP 5345A/5355A/5356B $4,000.00
26.5 GHz CW/Pulse Frequency Counter

STANDARDS

HP 105A Quartz Oscillator, 0.1/ 1.0/ 5.0 MHz $750.00
HP 105B Quartz Oscillator, 0.1/ 1.0/ 5.0 MHz, battery power $1,500.00
HP 5087A-opt.033 Distribution Amplifier; 12 outputs at 10 MHz $1,750.00

AUDIO & BASEBAND

SELECTIVE LEVEL METERS

HP 3586C Selective Level Meter, 50 Hz-32.5 MHz, 50 & 75 ohms .. $1,500.00

DISTORTION ANALYZERS

HP 339A Distortion Analyzer, built-in low distortion osc. $1,800.00
HP 8903A-001 Audio Analyzer, 20 Hz-100 kHz; rear panel input $2,600.00

Write in 182 on Reader Service Card.

VISA

90 DAY WARRANTY PARTS AND LABOR • 10 DAY INSPECTION

TEST EQUIPMENT WANTED CALL OR FAX LIST • OPEN ACCOUNTS

MasterCard

HP 8903B-001,013,051 Audio Analyzer, 20 Hz-100 kHz; C-message, CCITT $4,250.00
TEK DA4084 Programmable Distortion Analyzer $1,000.00

RMS VOLTMETERS

FLUKE 8920A True RMS Voltmeter, 180 uV-700 V, 10 Hz-20 MHz $600.00
FLUKE 8922A True RMS Voltmeter, 180 uV-700 V, 2 Hz-11 MHz $600.00

OSCILLATORS

HP 204C Oscillator, 5 Hz-1.2 MHz, 5 VRMS $150.00
HP 204D Oscillator, 5 Hz-1.2 MHz, 5 VRMS, 80 dB step attenuator $200.00
HP 209A Sine/Square Wave Generator, 4 Hz-2 MHz, 5 VRMS max. $225.00
HP 652A Test Oscillator, 10 Hz-10 MHz $250.00
TEK SG502 Sine/Square Osc., 5 Hz-500 kHz, 70 dB step atten.,TM500 ..... $200.00

MISCELLANEOUS

HP 4437A Step Attenuator, 0-119.9 dB, DC-1 MHz, 600 ohms unbal. $175.00
HP 461A Amplifier, 20/40 dB, 1 kHz-150 MHz, 0.5 V/50 Ohms $125.00
KROHN-HITE 3103 High/Low Pass Filter, 10 Hz-3 MHz, 24 dB/octave $500.00
KROHN-HITE 3342R Dual HP/LP Filter, 0.001 Hz-99.9 kHz, 48 dB/octave $1,100.00
KROHN-HITE 3750 LP/HP/BP/BR Filter, 0.02 Hz-20 kHz, 6/12/18/24 dB/oct. $700.00
ROCKLAND 852 Dual Highpass/Lowpass Filter, 0.1 Hz-111 kHz $1,000.00
TEK AF501 Tunable Bandpass Filter / Amplifier, 3 Hz-35 kHz $300.00
TEK AM502 Differential Amplifier, 0.1 Hz-1 MHz, TM500 series $475.00

RF & MICROWAVE

SPECTRUM ANALYZERS

HP 11970A WR28 Harmonic Mixer, 26.5-40 GHz $1,100.00
HP 11970Q WR22 Harmonic Mixer, 33-50 GHz $1,400.00
HP 11971A WR28 Harmonic Mixer, 26.5-40.0 GHz, for 8569B $1,100.00
HP 11971K WR42 Harmonic Mixer, 18.0-26.5 GHz, for 8569B $1,100.00
HP 8406A Comb Generator, 1/10/100 MHz increments, to 5 GHz $450.00
HP 8444A-059 Tracking Generator, 0.5-1500 MHz, for 8554,8568,etc. $1,250.00
HP 8445B Preselector, 1.8-18.0 GHz, for HP 8555A $650.00
HP 8553B/8552B/8443/141 Spectrum Analyzer, 0.1-110 MHz, with tracking generator $2,500.00
HP 8565A-100 Spectrum Analyzer, 10 MHz-22 GHz, 100 Hz min.res.bw. $5,000.00
HP 8569B Spectrum Analyzer, 10 MHz-22 GHz, 100 Hz min.res.bw. $8,500.00
TEK 119-0098-00 WR42 Single Ended Mixer, 18.0-26.5 GHz, for Tek 491 ..... $200.00
TEK 119-0099-00 WR28 Single Ended Mixer, 26.5-40 GHz, for Tek 491 ..... $200.00
TEK TR503 Tracking Generator, 0.1-1800 MHz, for 492/4/5/6 ..... $1,375.00
TEK WM782V WR15 Harmonic Mixer, 50-75 GHz $2,000.00

NETWORK ANALYZERS

HP 11664C Detector Adapter, for 8755/6/7 ..... $200.00
HP 11666A Reflectometer Bridge, 0.04-18.0 GHz, for HP 8755/6/7 ..... $1,100.00
HP 8505A Network Analyzer, 0.5-1300 MHz $3,750.00
HP 8756A/(3)11664A-001 Scalar Network Analyzer, w/(3) det., APC7, 0.01-18 GHz $3,750.00

SIGNAL GENERATORS

FLUKE 6060A/AN Synthesized Signal Gen., 10 kHz-520 MHz, 10 Hz res,GPIB $2,000.00
FLUKE 6062A Signal Generator, 0.1-2100 MHz, 10 Hz resolution $5,500.00
FLUKE 6070A Synthesized Signal Generator, 0.2-520 MHz, 1 Hz res. $2,000.00
GIGATRONICS 600/10-18 Synthesized Source, 10-18 GHz, 1 MHz res., GPIB $2,600.00
GIGATRONICS 605/10-18 Synthesized Source, 10-18 GHz, 1 kHz res., GPIB $3,000.00
GIGATRONICS 840-01 Freq. Doubler, 26.5-40 GHz (WR28) out, 13-20 GHz in $2,000.00
GIGATRONICS 875/50 Levelled Multiplier, x4, 50.0-75.0 GHz output, -3 dBm $3,500.00
GIGATRONICS 875/86 Levelled Multiplier, 26.5-40.0 & 50.0-75.0 GHz outputs $5,000.00
GIGATRONICS 910/12-18,opt6,14,16 Synthesized Source/Sweeper, 12-18 GHz, 1 Hz res., OCXO $3,500.00
HP 11720A Pulse Modulator, 2-18 GHz, 80 dB on/off ratio $750.00
HP 85100V Frequency Mult., 10-15 GHz in / 50-75 GHz out >0 dBm $4,250.00
HP 8640B-001,002,003 Signal Gen., 0.5-1024 MHz, AM, FM, var. audio osc. $2,250.00
HP 8654A Signal Generator, 10-520 MHz, calibrated AM & uncal. FM $550.00
HP 8660C/86602B-002 Synth. Sig. Gen., 1-2600 MHz, FM / Phase mod. w/86635A $3,250.00

SWEEP GENERATORS

HP 8350B/83592A Programmable Sweep Generator, 0.01-20 GHz, +10 dBm $16,500.00
HP 8600A Digital Marker, for HP 8601A $400.00
HP 8601A Generator/Sweeper, 0.1-110 MHz, +20 dBm levelled $400.00
HP 8620C Sweep Oscillator Frame $550.00
HP 8620C-011 Sweep Oscillator Frame, HPIB programmable $675.00
HP 86222A-002 RF Plug-in, 10-2400 MHz, +13 dBm levelled, 70 dB atten. $1,600.00
HP 86230B RF Plug-in, 1.8-4.2 GHz, +10 dBm unlevelled $675.00
HP 86235A-001,002 RF Plug-in, 1.7-4.3 GHz, +14 dBm levelled, 70 dB atten. $1,000.00
HP 86240C RF Plug-in, 3.6-8.6 GHz, +16 dBm levelled $1,000.00
HP 86241A-001 RF Plug-in, 3.2-6.5 GHz, +8 dBm levelled $500.00
HP 86242D-004,008 RF Plug-In, 5.9-9.0 GHz, +10 dBm levelled $500.00
HP 86245A RF Plug-in, 5.9-12.4 GHz, +16 dBm levelled $1,100.00
HP 86250D RF Plug-in, 8.0-12.4 GHz, +10 dBm levelled $675.00
HP 86260A RF Plug-in, 12.0-18.0 GHz, +10 dBm unlevelled $800.00
HP 86260A-H04 RF Plug-in, 10.0-15.0 GHz, +10 dBm unlevelled $800.00
HP 86290A RF Plug-in, 2.0-18.0 GHz, +7 dBm levelled $1,750.00
HP 86290B RF Plug-in, 2.0-18.6 GHz, +10 dBm levelled $2,000.00
WAVETEK 962 Sweep Generator, 1.0-4.0 GHz, markers, +12 dBm unlvld. $1,500.00

POWER METERS

ANRITSU MP-81B/ML-83A Power Meter, 75-110 GHz (WR10), -20 to +20 dBm $2,500.00
ANRITSU MP-82B/ML-83A Power Meter, 90-140 GHz (WR8) pin flange, -20, +20 dBm $3,250.00
BOONTON 4200-01A,03/&-4A x2 Dual Channel Microwattmeter, w/(2) 1 MHz-7 GHz sensors $1,500.00
BOONTON 42B/41-4B Analog Power Meter, with 1 MHz-12 GHz sensor $375.00
BOONTON 42B/41-4E Analog Power Meter, with 1 MHz-18 GHz sensor $500.00
GENERAL MICROWAVE 476/4240A Power Meter & Sensor, 0.01-18 GHz, -35 to +10 dBm $300.00
HP 11683A Range Calibrator, for HP 435/6/7/8 ..... $700.00
HP 432A/8478B Power Meter, -25 to +10 dBm, 10 MHz-18 GHz $450.00
HP 435A/8481A Power Meter, 10 MHz-18 GHz, -30 to +20 dBm $1,000.00
HP 435A/8482A Power Meter, 0.1-4200 MHz, -30 to +20 dBm $1,000.00
HP 435A/8482H Power Meter, 0.1-4200 MHz, -10 to +34 dBm $1,150.00
HP 8477A Power Meter Calibrator, for HP 432 series $500.00
HP Q8486A Power Sensor, 33.0-50.0 GHz, WR22, for 435/6/7/8 ..... $1,500.00
HP R486A WR28 Thermistor Mount, 26.5-40 GHz, for 432 series $350.00

RF MILLIVOLTMETERS

BOONTON 9200A-01 RF Millivoltmeter, 10 kHz-1.2 GHz, GPIB $900.00
RACAL 9303 TRMS Level Meter, 10 kHz-2 GHz, -77 to +23 dBm, GPIB $875.00

AMPLIFIERS, MISCELLANEOUS

BOONTON 82AD-opt.01A Modulation Meter, AM, FM, 10-1200 MHz, GPIB $900.00
HP 465A Amplifier, 20/40 dB, 5 Hz-1 MHz, 1/2 Watt/50 Ohms $125.00
HP 8447A-001 Dual Amplifier, 0.1-400 MHz $450.00
HP 8447E Amplifier, 22 dB, 0.1-1300 MHz, +13 dBm output $750.00
HP 8901A Modulation Analyzer, 150 kHz-1300 MHz $3,750.00
HP 8901B-001 Modulation Analyzer, 150 kHz-1300 MHz, rear panel input $6,750.00
HP 8970A Noise Figure Meter $6,000.00
HUGHES 1177H01F000 TWT Amplifier, 2.0-4.0 GHz, 10 Watts output $1,500.00
HUGHES 1177H02F000 TWT Amplifier, 4.0-8.0 GHz, 10 Watts output $1,500.00
M.P.D. LAB2-1020-2A Amplifier, 34 dB, 1.0-2.0 GHz, 2 Watts $800.00
M.P.D. LAB2-714-3A Amplifier, 34 dB, 0.7-1.4 GHz, 3 Watts $800.00
MICROWAVE SEMI.CORP. MC5112 Noise Source, 25.5 dB ENR, 1.0-12.4 GHz, N(m), +28 VDC $325.00
ROHDE & SCHWARTZ ESH2 Test Receiver, 9 kHz-30 MHz $6,000.00

COAXIAL & WAVEGUIDE

AMERICAN NUCLEONICS AM-432 Cavity Backed Spiral Antenna,LHC, 2-18 GHz,TNC(f) *NEW* $95.00
FXR/MICROLAB S3-02N Triple Stub Tuner, 200-1000 MHz, 100 Watts max., N(m/f) $125.00
GR 874-LTL Constant Impedance Trombone Line, 0-44 cm, DC-2 GHz $400.00
GR 900-Q GR900 14mm Interseries Adapters $125.00
HP 11590A-001 Bias Network, 1.0-18.0 GHz, APC7 ..... $450.00
HP 11612A Bias Network, 45 MHz-26.5 GHz, APC3.5 ..... $550.00
HP 11691D Directional Coupler, 22 dB, 2-18 GHz $450.00
HP 11692D Dual Directional Coupler, 22 dB, 2-18 GHz $800.00
HP 11721A Freq. Doubler, 50-1300 MHz in/100-2600 MHz out $400.00
HP 11904B APC2.4(f) x K(f) Adapter, DC-40 GHz $225.00
HP 774D Dual Directional Coupler, 20 dB, 215-450 MHz $275.00
HP 777D Dual Directional Coupler, 20 dB, 1.9-4.1 GHz $275.00
HP 8470B Crystal Detector, 10 MHz-18 GHz, neg. pol., APC7 ..... $250.00
HP 8491A-030 30 dB Attenuator, DC-12.4 GHz, 2 Watts, N(m/f) $50.00
HP 8494G-002 Programmable Step Attenuator, 0-11 dB, DC-4 GHz, SMA $400.00
HP 8495G-002 Programmable Step Attenuator, 0-70 dB, DC-4 GHz, SMA $300.00
HP 8495H-002 Programmable Step Attenuator, 0-70 dB, DC-18 GHz, SMA $400.00
HP 8497K-004 Programmable Step Attenuator, 0-90 dB, DC-26.5 GHz $750.00
HP K422A WR42 Flat Broadband Detector, 18.0-26.5 GHz $350.00
HP K532A WR42 Frequency Meter, 18.0-26.5 GHz $500.00
HP K870A WR42 Slide Screw Tuner, 18.0-26.5 GHz $275.00
HP K914B WR42 Moving Load, 18.0-26.5 GHz $425.00
HP Q752D WR22 Directional Coupler, 20 dB, 33-50 GHz $650.00
HP R375A WR28 Variable Attenuator, 0-20 dB, 26.5-40 GHz $375.00
HP R422A WR28 Flat Broadband Detector, 26.5-40 GHz $400.00
HP R532A WR28 Frequency Meter, 26.5-40 GHz $500.00
HP R752A WR28 Directional Coupler, 3 dB, 26.5-40 GHz $450.00
HP R752D WR28 Directional Coupler, 20 dB, 26.5-40 GHz $450.00
HP R914B WR28 Moving Load, 26.5-40 GHz $300.00
HP V365A WR15 Isolator, 25 dB, 50-75 GHz $900.00
HP V752D WR15 Directional Coupler, 20 dB, 50-75 GHz $650.00
HP X870A WR90 Slide Screw Tuner $150.00
HUGHES 45111H-2000 WR28 Isolator, 25 dB, 26.5-40 GHz $450.00
HUGHES 45113H-1000 WR19 Isolator, 25 dB, 40-60 GHz $650.00
HUGHES 45712H-1000 WR22 Frequency Meter, 33-50 GHz $900.00
HUGHES 47316H-1111 WR10 Tuneable Detector, 75-110 GHz, positive polarity $750.00
HUGHES 47323H-1211 WR19 Flat Broadband Detector, negative, 40-60 GHz $650.00
HUGHES 47974H-1000 WR15 SPST PIN Switch, 250 MHz speed, 60-62 GHz response $375.00
INSULATED WIRE SPRR-175-78 Low Loss Coaxial Cable, 78 in., DC-18 GHz, SMA(m/ram) $45.00
KAY 442D Step Attenuator, 0-101 dB, 75 ohms, BNC $100.00
KRYTAR 1818 Directional Coupler, 16 dB, 2-18 GHz, SMA(f) $200.00
M/A-COM 3-19-300/10 WR19 Directional Coupler, 10 dB, 40-60 GHz $450.00
MIDWEST MICROWAVE 3537 DC Block, 0.1-12.4 GHz, SMA(m/f) *NEW* $40.00
MINI-CIRCUITS ZFDC-20-4 Directional Coupler, 19.5 dB, 1-1000 MHz, SMA(f) $25.00
NARDA 25171 Level Set Attenuator, 0-17 dB, 2-8 GHz, SMA(f) $100.00
NARDA 26298 20 dB Attenuator, 150 Watts, DC-1 GHz, N(f/f) $200.00
NARDA 3000-SERIES Directional Couplers $150.00
NARDA 3024 Bi-Directional Coupler, 20 dB, 4-8 GHz $300.00
NARDA 3090-SERIES Precision High Directivity Couplers $225.00
NARDA 368NM Coaxial High Power Load, 500 Watts, 2.0-12.4 GHz, N(m) $400.00
NARDA 369BNF High Power Termination, 175 Watts, 0.7-18 GHz, N(f) $325.00
NARDA 3753B Coaxial Phase Shifter, 0-55 deg./GHz, 3.5-12.4 GHz $1,250.00
NARDA 4000-SERIES SMA Miniature Directional Couplers $75.00
NARDA 4203-6 Directional Coupler, 6 dB, 2-18 GHz, SMA(f/f/f) $225.00
NARDA 4245-10 Directional Coupler, 10 dB, 4-12 GHz, SMA(f) $100.00
NARDA 4799 Level Set Attenuator, 0-15 dB, 4-18 GHz, SMA(f) $135.00
NARDA 5070-SERIES Precision Reflectometer Couplers $300.00
NARDA 765-20 20 dB Attenuator, 50 Watts, DC-5 GHz, N(m/f) $135.00
NARDA 766-10 10 dB Attenuator, 20 Watts, DC-4 GHz, N(m/f) $100.00
NARDA 768-20 20 dB Attenuator, 20 Watts, DC-11 GHz, N(m/f) $125.00
NARDA 792FF Variable Attenuator, 0-20 dB, 2.0-12.4 GHz $375.00
OMNI-SPECTRA 2085-6010-00 Crystal Detector, 1-18 GHz, negative polarity, SMA(m/f) $50.00
PAMTECH KYG1014 WR42 Junction Circulator, 18.0-26.5 GHz $250.00
SONOMA SCIENTIFIC 21A3 WR42 Circulator, 20 dB, 20.6-24.8 GHz $125.00
SPACEK LABS DQ-1 WR22 Flat Broadband Detector, 33-50 GHz $400.00
TRG B528 WR22 Direct Reading Phase Shifter, 0-360 deg.,33-50 GHz $1,250.00
TRG V551 WR15 Frequency Meter, 50-75 GHz $600.00
TRG W551 WR10 Frequency Meter, 75-110 GHz $750.00
WAVELINE 100080 WR28 Terminated Crossguide Coupler, 30 dB $250.00
WEINSCHEL 1515 Power Divider, 2-Way, DC-18 GHz, SMA(m/f/f) $125.00
WEINSCHEL 45-30-43 30 dB Attenuator, 250 Watts, DC-1.5 GHz, N(f/m) $250.00
WILTRON 4612K Programmable Step Attenuator, 0-70 dB, DC-40 GHz $800.00
WILTRON 60NF50 SWR Bridge, 5-2000 MHz, 40 dB directivity, N(f/f/f) $450.00

LOGIC

HP 10343B/10269C SCSI Bus Preprocessor, w/probe intfc., for 1630 series $300.00
HP 5005A Signature Multimeter $350.00
HP 8170A-002 Logic Pattern Generator, 2 MB/s, address driver option $1,200.00
TEK 1240D2/1D 10-channel 50 MHz D/A Module for 1240, without probes $50.00
TEK 30DM08 80286 Probe, for Tek Prism $50.00
TEK DP186P 80186 / 80188 Probe, for Tek 1230 ..... $50.00
TEK DP286P 80286 Probe, for Tek 1230 ..... $50.00
TEK DPHC11 68HC11 Probe, for Tek 1230 ..... $50.00
TEK P6454 100 MHz Clock Probe, for DAS $50.00

COMMUNICATIONS

HP 4972A LAN Protocol Analyzer $1,500.00
HP 59401A HPIB Bus Analyzer $700.00
TEK 1410R NTSC Gen., w/SPG2 sync. generator, TSG7 color bars $1,000.00
TEK 1411R PAL Gen.,w/SPG12 sync; TSG11 color bars;TSG13 linearity $1,000.00
TEK 1411R PAL Test Gen., w/SPG12,TSG11,TSG13,TSG15,TSG16 ..... $1,400.00
TEK 1411R PAL Test Gen., w/SPG12,TSG11,TSG12,TSG13,TSG15,TSG16 ..... $1,600.00
TEK 1411R-opt.04 PAL Test Gen.,w/ SPG12,TSG11,TSP11,TSG13,TSG15,TSG16 ..... $1,900.00
TEK 147A NTSC Test Signal Generator, with noise test signal $800.00
TEK 148 PAL Insertion Test Signal Generator $800.00
TEK 1750 NTSC Waveform / Vector Monitor $2,750.00
TEK 520A NTSC Vectorscope $750.00
TEK 521A PAL Vectorscope $750.00

MISCELLANEOUS

KEITHLEY 706/ 7055 x12 Scanner,w/(12) 7055 General Purpose Relay Scanner cards $1,000.00
P.A.R. 5205-94,95,96,98 Lock-In Amp, 20 Hz-20 kHz, int. osc., lin/log, GPIB $2,000.00
P.A.R. 5206 Two-Phase Lock-In Amplifier, 2 Hz-200 kHz $1,750.00
P.A.R. 5208-92,94,97,98 Two Phase Lock-In Amp., 5 Hz-20 kHz or 200 kHz, GPIB $2,500.00
TEK TM5006 5000-series 6-slot Programmable Power Module $600.00
TEK TM504 500-series 4-slot Power Module $175.00
TEK TM506 500-series 6-slot Power Module $250.00
TEK TM515 500-series 5-slot Traveller Power Module $275.00

TEST EQUIPMENT *cont.*

WANTED: LATE model TEST EQUIPMENT and test equipment MANUALS, HP, Tektronix, and others. Fax your for sale list to 410-750-1192 or mail to US Surplus, PO Box 37, Ellicott City, MD 21041, Attn: Ron Baublitz. Phone # 410-750-1083, E-Mail: ussurplu@clark.net

IFR1500 SERVICE monitor, excellent condition $5,900. Many more at: http://www.madbbs.com/amtronix 716-763-9104 or 716-661-9964.

WANTED: WESTERN electric test equipment. Tube-type only please. Freq. measuring sets, oscillators, amplifiers, parts, tubes, etc. 1-800-251-5454.

NEW HEWLETT-PACKARD 141T CRTs. $195 EACH. We have quantities available. These are double boxed, unopened with 1985 date code, guaranteed. Price is $195 each plus shipping. Contact Brian at Kentronix. 732-681-3229 or FAX 732-681-3312. Mailing: PO Box 2444, Farmingdale, NJ 07727 or E-Mail brian@kentronix.com

FEITEK HAS the test equipment you want at reasonable prices. We buy, sell, and trade HP, Tek, GR, etc. Call or fax Monday thru Friday, 9 to 5, 314-423-1770, or write us at Box 3423, St. Louis, MO 63143.

FEITEK PROVIDES repair, calibration and certification on many makes of test equipment. We also have a large selection of used equipment. Send large SASE envelope for list. VISA and MasterCard accepted. Feitek Inc., 2752 Walton Road, St. Louis, MO 63114, 314-423-1770.

QUALITY TEST EQUIPMENT: HP 3488A switch/control mainframe $850 (cards available). **HP 59306A** relay actuator (6-SPDT) $200. **HP 59307A** dual VHF switch (2-SP4T) $200. **HP 8161A/020** 100MHz HP-IB dual channel pulse generator $3,100. **HP 5334A** 100MHz counter (rise/fall time, HP-IB, etc.) $850. **HP 5335A/20,40** 200MHz counter (rise/fall time, statistics, HP-IB, etc.) $1,200. **Stanford Research SR 510** lock-in amplifier $1,400. **HP 339A** distortion analyzer $1,600. **Tek 222A** handheld battery-operated digital storage scope $1,250 (many accessories available). **HP 11869A** adapter (for 8350B) $350. **HP 8502A/H26** transmission/reflection test set $950. **HP 8748A/H26** S-parameter test set $1,550. **HP 436A/022, 8481A** RF power meter, sensor $1,775. Excellent condition! All with warranty. Pepper Systems, 214-353-0257 (FAX 214-902-9511).

28 ITEMS of test equipment, plus miscellaneous parts and equipment. 1. Astron RM35A power supply $30. 2. Bird #4431 wattmeter kit, with case and slugs $100. 3. Bird 82 500W dummy load $75. 4. Boonton 230A RF power amplifier 2 ea., one not operating $150/pair. 5. Boonton 250A RX meter $175. 6. Exact 124 multigenerator $15. 7. Fluke 8800 5.5 digit multimeter $45. 8. Fluke 8050A 4.5 digit multimeter $40. 9. Helper #801 RF millivoltmeter with probe $125. 10. HP 302A wave analyzer $125. 11. HP 310A wave analyzer $175. 12. HP 427A electronic multimeter $25. 13. HP 432A power meter with thermistor mount, inoperative. 14. HP 803A VHF bridge $15. 15. HP 3466A 4.5 digit multimeter, not operating $25. 16. HP 5302A 50 MHz, counter with display $25. 17. HP 34701A digital voltmeter with display $20. 18. HP 600 ohm attenuator 0-110 dB DC-1 MHz $10. 19. HP 4800A vector impedance meter $200. 20. Lambda 28V, 30A, power supply $40. 21. Logimetrics 921 signal generator 50 KHz-80 MHz $150. 22. Military ME30F/U, equivalent to HP 400 series AC voltmeter $35. 23. Millen 90651-A grid dip meter, with case and all coils, like new $40. 24. Military USM223 multimeter $5. 25. Modular devices 0-500V, 100mA power supply $15. 26. Simpson AC wattmeter 5KW and 10KW scales $40. 27. Simpson 604 multicorder, strip chart recording multimeter $40. 28. Squires-Sander BSSG-1 spectrum generator, not operating $10. Other items: Green #106 engraver, no fonts $125. Approx. 25,000 ft. #24/#26 wire in 4 colors $75. Sola constant voltage transformer, 120VA $3. Assorted variable voltage transformers (variac type). Assorted power supplies. Weller soldering stations W-TCP and WTCPN $5-10, 3.125" square, 12VDC, fans, have 22 $2 ea. also 2" and 4". Pick up only, all prices FIRM. Dan 714-444-2228 (Costa Mesa). After 11am.

SALE BOONTON 1120 audio analyzer $650, 2 available SCIENTIFIC ATLANTA 4651B DS3 transmitter, 4654A error analyzer, 4657A/B DS3 error analyzer 5 units available @ 150 ea., offers. **Psitech Plus** 707-745-4804, Fax 707-747-5277 E-Mail: apeas@ix.netcom.com

RAMSEY Wireless Video Headquarters

The Cube

World's Smallest TV Transmitter

Perfect video transmission from a transmitter you can hide under a quarter and only as thick as a stack of four pennies- that's a nickel in the picture! Transmits color or B&W up to 150' to any TV tuned to cable channel 59 with a solid 20 mW of power. Crystal controlled for no frequency drift with performance that equals law enforcement models that cost hundreds more! Deluxe model includes sound using a sensitive built-in mike that will hear a whisper 15 feet away! Units run on 9 volts and hook-up to most any CCD camera. Our cameras shown below have been tested to mate perfectly with The Cube and work great. Fully assembled.

C-2000 Video Transmitter Cube.....$89.95
C-3000 Video and Audio Transmitter Cube.....$149.95



CCD Video Cameras

If you're looking for a good quality CCD board camera, stop right here! Our cameras use top quality Japanese Class 'A' CCD arrays, not the off-spec arrays that are found on many other cameras. You see, the Japanese suppliers grade the CCDs at manufacture and some manufacturers end up with the off-grade chips due to either cost constraints or lack of buying 'clout'. These cameras have nice clean fields and excellent light sensitivity, you'll really see the difference, and if you want to see in the dark, these are super IR (Infra-Red) sensitive! Available with Wide-angle (80º) or super slim Pin-hole style lens. Both run on 9 VDC and produce standard 1 volt p-p video. Add one of our transmitter units for wireless transmission to any TV set, or add our Interface board (below) for Audio sound pick-up and direct wire connection to any Video monitor or TV video/audio input jacks. Fully assembled.

CCDWA-2 CCD Camera, wide-angle lens.....$99.95
CCDPH-2 CCD Camera, slim fit pin-hole lens.....$99.95

CCD Camera Interface Board



Here's a nifty little kit that eases hook-up of your CCD camera module to any video monitor, VCR or video input TV set. The board provides a voltage regulated and filtered source to power the camera (CCD Cameras require a stable source of power for best operation), sensitive electret condensor mike for great sound pick-up and RCA Phono jacks for both audio and video outputs. Runs on 11 - 20 VDC.

IB-1 Interface Board Kit.....$14.95

Budget TV Transmitter

Transmit audio and video to any TV set with this fully assembled transmitter. Although not tiny, it still offers some neat features. Takes standard 1 volt p-p video and audio and transmits on any UHF TV channel of your choice from 17 - 42. Has rugged metal case, includes AC adapter, whip antenna and even RCA phono plug patch cords! Can also run on 12 VDC.

VS-2 Video and Audio Sender, Fully Assembled.....$29.95

IR Illuminator for CCD Cameras

See in total darkness with one of our CCD video cameras and this IR illuminator! IR light can't be seen, illuminate the scene with IR and a CCD camera 'sees' just fine. The array of 24 extra high intensity LEDs are invisible to anybody - except for aliens and Casper! Runs on 12 VDC. Illuminates similar to that of a bright flashlight.

IR-1 IR Illuminator Kit.....$24.95

MicroEye CCD Camera & Transmitter Combo

We married together one of our quality CCD cameras, a sensitive electret microphone and a small TV transmitter to give you a super neat - and tiny - all in one, 'knows all, sees all, hears all' package! Small enough to fit into a cigarette pack and powerful enough to transmit up to 150' to any standard TV set. Tunable to operate on TV channels 4, 5, or 6 and runs on 9 to 20 VDC. The sensitive mike picks up normal voice within an average size room. Ideal for private detectives, investigators, hobbyists, babysitters, model rocketeers, RC airplanes and other uses limited only by your imagination. Camera module is fully wired and the transmitter unit is an easy to build kit that goes together in an evening. Includes all parts, handsome jet-black case and clear, concise instructions with ideas for use. And, don't forget, our CCD cameras are very sensitive to IR light - just add the IR-1 IR Illuminator kit for see-in-the-dark operation!

ME-2000 MicroEye TV Transmitter Combo $149.95

Wavecom Wireless Video and Audio Transmission System

Transmit extremely clean and sharp video and audio up to 300 feet. Wavecom transmits in the 2.4 GHz band using FM and circular polarization for state-of-the-art transmission. There is no fading, ghosting, humming, buzzing or picture rolling when using the Wavecom. System consists of two parts, a transmitter unit and a receiver unit. Switch selectable 4 channel operation allows use of multiple Wavecoms in the same geographic area. Connections are video and audio in and out using standard RCA phono jacks. Includes AC wall plug adapters, patch cords, coax cable jumper, TV antenna A/B switch and complete hook-up instructions. Fully assembled with one year warranty.

The Wavecom Sr. has all of the features above plus adds the capability of transmitting your TV/DSS/VCR remote control signals from the receiver unit back to the transmitter unit. This is great for controlling your DSS satellite receiver or VCR from any room in the house. We also offer the small internal transmitter module assembly for those who wish to make their own concealed video transmitter system. Module is about the size of a couple of matchboxes and includes microwave patch antenna.

WC-1 Wavecom Jr. Wireless System.....$189.95
WC-5 Wavecom Sr. with Remote Capability.....$239.95
WC-TX Transmitter Module Assembly.....$105.00

RAMSEY ELECTRONICS, INC.
793 Canning Parkway Victor, NY 14564

Call for our free catalogue or visit us on the web: www.ramseyelectronics.com

Toll-free Order Service: 1-800-446-2295
Sorry, no technical info or order status at this number

For Tech Info or Order Status, Call the Factory Direct
Phone (716) 924-4560
Fax (716) 924-4555

ORDERING INFO: Satisfaction Guaranteed. Examine for 10 days, if not pleased, return in original form for refund. Add $5.95 for shipping, handling and insurance. Orders under $20, add $3.00. NY residents add 7% sales tax. Sorry, no CODs. Foreign orders, add 20% for surface mail or use credit card and specify shipping method.

VISA MasterCard DISCOVER

Write in 101 on Reader Service Card.

QUALITY TEST EQUIPMENT: HP 8082A 250MHz pulse generator $995. **HP 8016A** ECL/TTL word generator $295. **HP 8161A/030** 100MHz programmable precision dual channel pulse generator $3,100. **HP 4274A** LCR meter (5-1/2 digit, 100Hz-100KHz, HP-IB) $3,900. **HP 339A** distortion analyzer $1,650. **HP 7595A** DraftMaster I (sizes A-E) $1,675. **HP 7475A** plotter $220. **HP 7090A** measuring plotter $1,500. **HP 5334A** 100MHz counter (rise/fall time, HP-IB, etc.) $850. **HP 5335A/20,40** 200MHz counter (rise/fall time, statistics, HP-IB, etc.) $1,200. **HP 5345A** 500MHz counter $400, with HP-IB $675. **HP 5370A** 100MHz time interval counter (oven time base) $1,200. **HP 3488A** switch/control mainframe $850 (cards available). **HP 59306A** relay actuator (6 SPDT, HP-IB and lighted pushbutton) $200. **HP 59307A** dual VHF switch (2-SP4T, HP-IB and lighted pushbutton) $200. **HP 59401A** HP-IB bus analyzer $250. We also can provide HP-IB programming services and custom ATE systems.) **Fluke 540B** transfer standard $750. **Tek 390AD** digitizer $475. **Tek P6201** 900MHz active probe $325. **Tek 520A** NTSC vectorscope $750. **Stanford Research SR 510** lock-in amplifier $1,400. Excellent condition! All with warranty. Pepper Systems, 214-353-0257 Fax 214-902-9511.

ELECTROMAGNETIC DETECTORS, including **Trifield® broadband meter** (analog) reads field strength of 10-1000 V/M at 100KHz-2.5GHz, also independently reads magnetic (3-axis) and electric fields, below 100KHz. (0.2-100 milliGauss, and .5-100 KV/M, at 60 Hz). Ideal general detection tool for both AC power and RF work $170 postpaid. **Atmospheric ion counter** (digital) reads both polarities 10-2,000,000 ions/cc. (Atmosphere is typically 300-5000 positive and 200-3000 negative. Depends on weather, etc.) **For the first time, under $4,000 for a true ion counter!** $580 postpaid. **DC Gaussmeter** (digital) includes compact Hall probe (.01-20,000 Gauss) **and** differential coil probe (.01 milliGauss - 20 Gauss). Complete $265 postpaid. All above have 1 year warranty and include 9-volt batteries. Made in USA by Alphalab Inc., 1280 South 300 West, Salt Lake City, UT 84101. Tel. 1-800-769-3754 or 801-487-9492. Free catalog.

HP 1744A oscilloscope $300; HP 432C power meter $175; HP 432A $75; HP 86632A $100; HP 86602A $100; HP 86601A $300; Tek TM504 $60; Tek FG504 $200; Tek 508A $200; Tek DC 503 $100; Tek 321 oscilloscope $100; HP 2225A printer HP-IB interface $75; Tek TM506 $60; JDR 2000 oscilloscope $150; Tek P6452, P6455 data acquisition $25; Simpson multimeter 461 $40. Call 714-827-7345

WANTED: HI-voltage power supplies and hi-pot testers. Jennings JHP-70A, Von's C-1, hi-potronics, Spellman. Also looking for VDF 2.8pF Jennings capacitors and hi-voltage calibration resistors for units. Youngson's, Inc., 6701 Melrose Ave., Louisville, KY 40216. 502-448-6228.

TEKTRONIX SCOPE sale, 453 454 $75; 465 465B $350; 475 $450. Sold as is. Ty Miller, South Coast Surplus 714-830-9170.

WANTED! TEST equipment. We pay top dollar for used scopes, generators, analyzers from HP, Tektronix, and others. Call Charles at Metric for immediate quotation. 1-800-432-3424.

AFFORDABLE HP power sensor repair! Most 8481As repaired for $230 or less. We also handle 478As and many others. Call or fax for more information. Willamette RF, Inc., 541-754-7226, FAX 541-753-4629.

MICRODYNE 1100, 1200, 1400 series receivers all bands, FM and PM demods, SDU, IF filters. Aydin, Schlumberger, monitor systems bit syncs. 805-934-2058.

SELL: BIRD 8141 250W RF load DC-2.5 GHz, $200; Bird 8322 in line attenuator, 30dB, 200W, DC-1GHz, $400; Boonton 260A q meter, $300; Bird 694 wattmeter, RF load 1KW 2-30MHz, $300; HP 7225B XY plotter A size single pen, HPIB, $150; A-Comm Electronics 303-290-8012.

Bearcat Intercepts Trunked Radio

COMMUNICATIONS ELECTRONICS INC.™

New...Bearcat Trunktracking radios

Get your Bearcat 235XLT for only $199.95 or Bearcat 895XLT for only $239.95

when you order our package deal. To get your **free fax-on-demand catalog**, call 313-663-8888 from the telephone handset on your fax machine and follow the recorded voice prompts. Get many free benefits such as extended warranty coverage on new Bearcat scanners when you use your Communications Electronics Platinum Plus Master Card® issued by MBNA. No annual fee. Call 1-800-523-7666 anyitme and mention offer Q3KI to request yours today.

Get your **Bearcat 895XLT for only $239.95** when you order package deal **#UNI8PD**. Our package deal includes mobile mounting bracket **#MB001** $14.95; Cigarette lighter power cord **#PS001** $14.95; external speaker **#EX711** $19.95 and mag-mount mobile antenna with 12 feet cable **#ANTMMBNC** $29.95; plus $29.00 shipping. Total package deal price is $348.75. Hurry offer expires 1/31/98.

Bearcat®895XLT-A Radio Scanner

Mfg. suggested list price $729.95/**Special $319.95**
300 Channels • 10 banks • Built-in CTCSS • S Meter
Size: 10-1/2" Wide x 7-1/2" Deep x 3-3/8" High
Frequency Coverage: 29.000-54.000 MHz., 108.000-174 MHz., 216.000-512.000 MHz., 806.000-823.995 MHz., 849.0125–868.995 MHz., 894.0125-956.000 MHz.

The Bearcat 895XLT is superb for intercepting trunked communications transmissions (see BC235XLT description) with features like TurboScan™ to search VHF channels at 100 steps per second. This base and mobile scanner is also ideal for intelligence professionals because it has a Signal Strength Meter, RS232C Port to allow computer-control of your scanner via optional hardware and 30 trunking channel indicator annunciators to show you real-time trunking activity for an entire trunking system. Other features include *Auto Store*– Automatically stores all active frequencies within the specified bank(s). *Auto Recording*– This feature lets you record channel activity from the scanner onto a tape recorder. *CTCSS Tone Board* (Continuous Tone Control Squelch System) which allows the squelch to be broken during scanning only when a correct CTCSS tone is received. For maximum scanning enjoyment, order the following optional accessories: **PS001** Cigarette lighter power cord for temporary operation from your vehicle's cigarette lighter $14.95; **PS002** DC power cord - enables permanent operation from your vehicle's fuse box $14.95; **MB001** Mobile mounting bracket $14.95; **EX711** External speaker with mounting bracket & 10 feet of cable with plug attached $19.95. The BC895XLT comes with AC adapter, telescopic antenna, owner's manual and one year limited Uniden warranty. Save $80.00...order the package deal above.

Bearcat®3000XLT-A Radio Scanner

Mfg. suggested list price $699.95/**Special $329.95**
FREE - Get an extra BP2500 battery pack, a $51.95 value when you order a Bearcat 3000XLT. Hurry...offer expires 1/31/98.
400 Channels • 20 banks • Twin Turbo Search/Scan
Frequency Transfer • VFO Control • Automatic Store
10 Priority Channels • Selectable Mode • Data Skip
Frequency step resolution 5, 12.5 & 25 KHz.
Size: 2-3/4" Wide x 1-1/2" Deep x 7-3/8" High
Frequency Coverage:
25.000-549.995 MHz., 760.000-823.995 MHz., 849.0125–868.995 MHz., 894.0125-1,300.000 MHz.

The Bearcat 3000XLT is the ideal handheld radio scanner for communications professionals. This handheld scanner scans at 100 channels per second and searches at a rate up to 300 steps per second. A selectable attenuator eliminates annoying intermodulation from adjacent frequencies in highly populated areas. Selectable AM, Wide FM and Narrow FM modes allow you to change the default receiving mode of the BC3000XLT. For maximum scanning pleasure, order the following optional accessories: **UA502** Cigarette lighter power cord for temporary operation from your vehicle's cigarette lighter $14.95; **LC3000** Deluxe swivel leather carrying case $49.95; **BP2500** rechargeable nickel-cadmium battery pack for up to five hours of dependable use $39.95; **ANTMMBNC** Magnetic mount scanner antenna with BNC jack and 12 feet of cable $29.95. **ANTSGBNC** Glass mount scanner antenna with BNC cable $29.95. The BC3000XLT comes with AC adapter, belt clip, flexible rubber antenna, earphone, owner's manual and one year limited Uniden warranty. Order today.

TrunkTracking Radio

Get your **Bearcat 235XLT for only $199.95** when you order package deal **#UNI2PD**. Our package deal includes deluxe swivel belt loop leather carrying case **#LC235** $49.95; Cigarette lighter power cord **#UA502** $14.95; and mag-mount mobile antenna with 12 feet cable **#ANTMMBNC** $29.95; plus $29.00 shipping. Total package deal price is $323.80. Hurry offer expires 1/31/98.

Bearcat®235XLT-A TrunkTracker

Mfg. suggested list price $429.95/**CEI price $269.95**
300 Channels • 10 banks • Trunk Scan and Scan Lists
Trunk Lockout • Trunk Delay• Extra battery & charger
10 Priority Channels • Programmed Service Search
Size: 2-1/2" Wide x 1-3/4" Deep x 6" High
Frequency Coverage:
29.000-54.000 MHz., 108-174 MHz., 406-512 MHz., 806-823.995 MHz., 849.0125–868.995 MHz., 894.0125-956.000 MHz.

The Bearcat TrunkTracker BC235XLT, is the world's first scanner capable of tracking a selected radio transmission as it moves across a trunked radio system. Now it's easy to monitor fleets and subfleets in analog trunked radio systems. The BC235XLT can also work as a conventional scanner. This 300-channel, programmable handheld scanner provides scanner users with uninterrupted monitoring capabilities of Type I, II, IIi and hybrid trunking systems. One of the biggest obstacles in the scanner industry has been the increasing use of trunking radio systems in business and public service agencies throughout the United States and Canada. This makes it nearly impossible to track a conversation as it moves within a trunk system from frequency to frequency. According to Ken Ascher, WB8LIT, Chairman & CEO of Communications Electronics, "The Bearcat 235XLT is a revolutionary breakthrough in scanner technology. Now it's easy to continuously monitor conversations even though the message is switching frequencies." The BC235XLT comes with AC adapter, CRX120 battery charger, two rechargeable long life ni-cad battery packs, belt clip, flexible rubber antenna, earphone, owner's manual and one year limited Uniden warranty. Not compatible with AGEIS, ASTRO, EDACS, ESAS and LTR systems. Call 1-800-USA-SCAN to order your scanner now.

VHF/GMRS/CB Radios

Have fun and use our CB, GMRS and commercial radios to keep in touch with friends. For even bigger savings, *Nuts & Volts Magazine* readers use the coupon on this page.

Cobra 148FGTL-A SSB CB with frequency counter	$179.95
Cobra 29WXST-A CB with sound tracker technology	$149.95
Cobra 25WXST-A CB with sound tracker technology	$129.95
Cobra 2010GTLWX-A SSB CB Base (†$25.00 shipping)	$299.95
Cobra HH45WX-A Handheld CB radio with weather	$89.95
Cobra FRS200-A Family Radio Service transceiver	$89.95
Maxon GMRS210+3-A GMRS transceiver/SPECIAL	$166.95
RELM RH256NB-A 25 watt VHF mobile transceiver	$284.95
RELM MPV32-A 5 watt VHF handheld transceiver	$299.95
Uniden GRANTXL-A SSB CB Mobile	$124.95
Uniden PRO538W-A CB & Weather	$54.95

Save up to $995.00

It pays to be a *Nuts & Volts* magazine reader. Order any scanner or transceiver from CEI. Send or fax this coupon with your order and save. Call 1-800-USA-SCAN to order.

VR204DAT8 8 channel digital audio logger	Save $750.00
HS100 RELM 100 channel handheld scanner	Save $15.00
HS200 RELM 200 channel scanner with CTCSS/DCS	Save $55.00
LC3000 Leather carrying case for BC3000XLT	Save $10.00
LC235 Leather carrying case for BC235XLT, SC150	Save $20.00
29WXST Cobra CB with sound tracker technology	Save $15.00
LCMP RELM swivel deluxe leather carrying case	Save $20.00
BCMP RELM rapid charge ni-cad battery charger	Save $10.00
SMMP RELM speaker/mic for WHS or MP radio	Save $10.00
BC007 RELM extra ni-cad battery pack	Save $10.00
BC002 Bearcat CTCSS tone board	Save $20.00
BC003 Bearcat switch assembly for BC002	Save $10.00
BC005 Bearcat CTCSS tone board	Save $20.00
EX711 Bearcat scanner external speaker	Save $10.00
ANTSGBNC glass mount antenna with BNC	Save $10.00
ANTMMBNC magnet mount antenna with BNC	Save $10.00

Offer valid only on prepaid orders mailed to Communications Electronics Inc., PO Box 1045, Ann Arbor MI 48106 USA. Offer valid December 1, 1997 to January 31, 1998. Limit one coupon per item. Coupon is not redeemable with any other coupon or any other offer. Mention offer number AN.

Bearcat Scanners

Monitor fire, police, weather, marine, medical, aircraft and other transmissions with your Bearcat scanner.

Bearcat 9000XLT-A base/mobile	$344.95
Bearcat 3000XLT-A handheld	$329.95
Bearcat 895XLT-A TrunkTracker base	$319.95
Bearcat 860XLT-A2 100 channel base	$149.95
Bearcat 760XLT-A base/mobile	$179.95
Bearcat 230XLT-A handheld/SPECIAL	$194.95
Bearcat 235XLT-A TrunkTracker scanner	$269.95
Bearcat 178XLT-A base with weather alert	$99.95
Sportcat 150-A handheld with 800 MHz.	$144.95
Bearcat 80XLT-A handheld with 800 MHz.	$129.95
Bearcat BCT7-A information mobile	$149.95
Bearcat BCT12-A information mobile	$169.95
Relm HS200-A handheld CTCSS/800 MHz.	$224.95
Relm HS100-A handheld 100 channel	$129.95

NEW! RELM®MPV32-A Transceiver

Mfg. suggested list price $515.00/**Special $299.95**

Looking for a great hand-held two-way transceiver? Two-way radio operators depend on the RELM MPV32 transceiver for direct two-way communications with their fire or police department, civil defense agency or ham radio repeater. The MPV32 is our most popular programmable frequency agile five watt, 32 or optional 64 channel handheld transceiver that has built-in CTCSS, which may be programmed for any 39 standard EIA tones. Frequency range 136.000 to 174.000 MHz. The full function, DTMF compatible keypad also allows for DTMF Encode/Decode and programmable ANI. Weighing only 15.5 oz., it features dealer programmable synthesized frequencies either simplex or half duplex in 2.5 KHz. increments. Other features include PC programming and cloning capabilities, scan list, priority channel, selectable scan delay, selectable 5 watt/1 watt power levels, liquid crystal display, time-out timer and much more. When you order the MPV32 from CEI, you'll get a complete package deal including antenna, 700 ma battery (add $20.00 to substitute a 1000 ma battery), battery charger, belt clip and user operating instructions. Other useful accessories are available. A heavy duty leather carrying case with swivel belt loop part **#LCMP** is $49.95; rapid charge battery charger, part **#BCMP** is $69.95; speaker/microphone, part **#SMMP** is $54.95; extra high capacity 1000 ma. ni-cad battery pack, part **#BPMP1** is $79.95; extra 700 ma. ni-cad battery pack, part **#BPMP7** is $59.95; 64 channel option, order **#64MP** is $79.95; cloning cable part **#CCMP** is $29.95; PC programming kit, part **#PCKIT030** is $224.95. A UHF version with a frequency range of 450-480 MHz. part **#MPU32** is $349.95. The radio technician maintaining your radio system should order dealer programming instructions part **#PIMPV** for $18.00 to activate this radio.

Buy with confidence

It's easy to order from us. **Mail orders to**: Communications Electronics Inc., P.O. Box 1045, Ann Arbor, Michigan 48106 USA. Add $17.00 per weather station or radio product for UPS ground shipping, handling and insurance to the continental USA unless otherwise stated. Add $12.00 shipping for all accessories and publications. Add $12.00 shipping per antenna. For Canada, Puerto Rico, Hawaii, Alaska, Guam, P.O. Box or APO/FPO delivery, shipping charges are two times continental US rates. Michigan residents add state sales tax. No COD's. Satisfaction guaranteed or return item in unused condition in original packaging within 61 days for refund, less shipping charges. 10% surcharge for net 10 billing to qualified accounts. All sales are subject to availability, acceptance and verification. Prices, terms and specifications are subject to change without notice. We welcome your Discover, Visa, American Express or MasterCard. Call anytime 1-800-USA-SCAN or 800-872-7226 to order toll-free. Call 313-996-8888 if outside Canada or the USA. FAX anytime, dial 313-663-8888. Dealer and international inquiries invited. Order from Communications Electronics Inc. today and save.

Price schedule effective December 1, 1997 AD #120197NV ©1997 Communications Electronics Inc.

For credit card orders call
1-800-USA-SCAN
Communications Electronics Inc.
Emergency Operations Center
PO Box 1045, Ann Arbor, Michigan 48106-1045 USA
For information call 313-996-8888 or FAX 313-663-8888

Order a FREE catalog via the internet!

www.rogerssystems.com

Roger's Systems Specialist

800-366-0579

"We Have Great Connections"

Computer - Communications
Network - Audio - Video

Place your order via the internet!

www.rogerssystems.com

Universal AC to DC Converter

- Eliminates Batteries
- Great for small radios,



#TM-310 **$5.00 each**
1.5v -12v DC/1000 ma
#TM-307 **$3.00** each
1.5v -12v DC/300 ma

Parallel Port

DB25 Female to 26 pin socket IDC



#CN-702 $.50 each
100/$.40

14" SCSI III Cables

34 Twisted Pairs with drain wire
Half Pitch Db 68 Male-to-Male

#CC-693-18
$5.00 each

Microphone

Stick-on monitor or clip on or stick onshirt 6 ft. cord; condenser mic.

#TM-MIC-2
$2.00 each

I-EEE 1284 Printer Cable

10' Bi-Directional
DB25 Male to Mini Centronic 36
A.K.A. type "A" - "C"

#CC-PR6-BIMIN

$.89 each

Multi-Modular Cable Tester

Tests continuity for each pair.
Includes unit for remote testing and carrying case.

RJ11/45 & BNC
#TM-147
$79.00

Great for networks!

RJ11/45
#TM-149
$69.00

BTC Extended Keyboard

104 keys with 5 pin DIN Plug
3 LED mode indicator
extra Windows 95 keys



#TM-KB-1
$16.00 each

Diskette Filing Case

Holds 100 diskettes • Double row filing with lock



#TM-DSC-3
$4.00 each

CD Jewel Case

Replacement for original case



#TM-CD1
$.40 each

Uni-Directional Dynamic Vocal Mic

Well suited for professional quality recording & PA
Durable 8 ft cord
Dynamic freq. response: 80-13,000 Hz

#TM-MIC $3.00 each
Call for quantity discounts!

4" Stereo Mini Phono Plug to 2 RCA Jacks

3.5 mm stereo mini phono plug to 2 RCA phono jacks



#AD-561
$.50 each

Miniature Mouse

2-Button, black
Great for small hands or laptop!

#TM-290-MINI
$4.00 each

Call for prices on:
PS/2 mouse
Touch Pads
Serial mouse

SVGA Shielded Cables



6 ft. HD 15 male to female

#CC-VGA-4
$3.00 each
4/$5.00

6 ft. HD 15 male to female
Dual coaxial shield
-helps with ghosting, line loss, and high resolution monitors

#CC-VGA-4C
$9.00 each

6 ft. HD 15 male to male
switch box cable

#CC-VGA-3
$3.00 each

6 ft. HD 15 male to male
switch box cable
Dual coaxial shield
-helps with ghosting, line loss, and high resolution monitors

#CC-VGA-3C
$9.00 each

6 ft. HD 15 male to 5 BNC

#CC-VGA5BNC
$12.00 each

Electronic/ Auto Switch Share one Monitor, Keyboard, and Mouse with multiple Computers

Features:

Supports S-VGA, VGA, Multisync Monitors
Simple Keystrokes or push buttons for PC Selections
No Software required
Daisy chainable
Auto scan and manual selections

Applications:

Access file servers via one console
Testing equipment
Demo, displays

Call for price on 2, 6, and 8 way switches

$290.00 each



DS-104-KMM

Surge Protection

15 AMP fused circuit breaker w/ reset feature, built-in light indicator, Metal case,
5' heavy duty cord,



#TM-199

$6.00 each

Battery Backup

w/ built in surge and noise suppression

TRIPP LITE POWER PROTECTION

Features:

RFI/EMI line noise filtering
protects against brownouts
up-front diagnostic LEDs and alarm
Microprocessor control of on-board functions

Protects against:

Active Data Loss
Hard Drive Data Loss
Computer and Monitor Damage

TM-225
$139.00 each

P.C. MultiMedia Speakers

Famous Maker Mini-Size amplified



#TM-172
$8.50 each set
10/$7.85 each

Major Brand! Stereo Digital Headphones

Black, foam pads
3.5 mm stereo plug
great for walkman & multi-media use

#TM-170
$3.00 each
20/$2.80

Universal Serial Bus Cables!

USB

6 foot USB Cable
Male to Male
#CC-USB-6
$5.00

also
Two USB Female on slot bracket to
#CC-USB-9
$7.00

New Price!

"TOUCHÉ" Touch Pad

-Plug and Play
-Lifetime Warranty

PS/2 6-pin
#TM-267
$18.00 each

DB9 Serial Plug
#TM-269
$18.00 each

PS/2 & SERIAL MOUSE 2- BUTTON

INTERACT

Includes
Serial to PS/2 Adapter
DB25 to DB9 adapter
Setup disk

#TM-290-2
$6.00 each

Modular Crimp Tool

Hardened Steel Frames - Black-Oxide Finish - Separate Cutting and Stripping

4&6 conductors telephone
#TE-CR6
$14.00 each

4,6,& 8 conductors telephone & network
#TE-CR2
$25.00 each

8 conductors network
#TE-CR8
$14.00 each

Power/Modem Protection

3 stage-EMI/RFI/Surge protection, FAX/modem protection, 5' cord, 6 outlet



#TM-200

$12.00 each

www.rogerssystems.com

Local 805-295-5577 Remember, We Have Great Connections...For You! FAX 805-295-8777

$10.00 minimum order required • Add $4.50 shipping for pre-paid orders
California residents add 8.25% tax • eMail Sales@RogersSystems.com
Call for quantity discounts • No out of state checks accepted • Most orders shipped same day

24895 Avenue Rockefeller, Valencia, CA 91355

American Express Cards · Discover · Novus · MasterCard · VISA

Write in 208 on Reader Service Card.

Flat Panel Display Solutions

VGA, TFT & STN LCD - LCD CONTROLLERS - TOUCH SCREENS

Earth has a broad line of VGA Flat Panel Display Solutions including ISA, P.C.I., NTSC, RS-232 & PC-104 Controllers. Monochrome & Color displays are available starting under $100. Sizes from 6.3" to 14" are available. LCD monitors are available with and without Touch Screens. Our global sourcing of new and surplus displays assure you the best value in LCD monitors for industrial, embedded systems, kiosk and point of sale applications.

LCD CONTROLLERS | **LCD DISPLAYS**





LCD TOUCH SCREENS | **LCD MONITORS**





Get our current catalog on the web at ***http://www.flat-panel.com***

EARTH
Computer Technologies

1110 Calle Cordillera - San Clemente, CA 92673
Ph: (714) 361-2333 - Fax: (714) 361-2121
Email: oemsales@flat-panel.com

Write in 27 on Reader Service Card.

MIDWEST ELECTRONICS

124 12TH AVE. SOUTH, MINNEAPOLIS, MN 55415
PHONE: (612) 339-9533 FAX: (612) 305-0964
WWW.MIDWEST-ELECTRONICS.COM
WE'RE ALWAYS HAVING A SALE — COMPARE OUR PRICES

COMPUTERS

BRAND NEW 200 MMX PENTIUM SYSTEMS

INTEL 200MMX CPU, 16MB RAM, TX MB W/512K CACHE, 1.2GB HARD DRIVE, 2MB (UPGR) PCI VIDEO, 1.44 FDD, 12X CD-ROM, 16 BIT STEREO SOUND, 80 WATT SPEAKERS, 33.6 DATA/FAX MODEM, KBD & MOUSE, WIN95 OSR-2, MINI-TOWER CASE **$949**

ZDS P-100, 100MHz PENTIUM PROCESSOR, 16MB RAM, 1.2GB HARD DRIVE, 4X CD-ROM, 16 BIT STEREO SOUND SYSTEM **$549**

ZDS P-75 ALL-IN-ONE INTEL 75MHz PENTIUM PROCESSOR, 8MB RAM, 600MB HARD DRIVE, 4X CD-ROM, BUILT-IN SOUND CARD & SPEAKERS, BUILT-IN 14" SVGA MONITOR **$549**

BARE BONES SYSTEM

75-200MHz MOTHERBOARD W/256K CACHE, CASE & PWR . SUPPLY, BUILT-IN IDE & I/O, 1MB (UPGR TO 2MB) PCI VIDEO, 1.44 FLOPPY **$199**

NEW MONITORS

14" 1024X768 SVGA .28DP **$189** 15" 1024X768 SVGA .28DP **$249**
17" 1280X1024 SVGA .28DP **$449**
11" VGA FLAT PANEL TOUCHSCREEN **$69**

USED MONITORS

14" 640X480 VGA *STARTING AT* **$89** 14" 1024X768 SVGA *STARTING AT* **$129**

VIDEO

1MB (UPGR TO 2MB) PCI VIDEO **$35** 2MB PCI VIDEO CARD **$55**

MODEMS

33.6 INT. DATA/FAX MODEM W/VOICE **$59**

MULTIMEDIA

8X IDE CD-ROM **$69**
16 BIT STEREO SOUND CARD **$29**

BRAND NEW ACER KEYBOARDS **$15** PS-2 MOUSE **$15**
SERIAL MOUSE **$10** 1.44 FLOPPY DISK DRIVE **$22**
PCMCIA 28.8 DATA/FAX MODEM W/10 BIT ETHERNET **$99**

CALL US OR CHECK OUR WEB PAGE FOR GREAT DEALS ON NEW AND USED PARTS & ACCESSORIES

Write in 145 on Reader Service Card.

If you would be interested in selling *Nuts & Volts* in your store or on your newsstand, we have a great deal for you!

For details, contact

Nuts & Volts Magazine
430 Princeland Court
Corona, CA 91719
Phone 909-371-8497
Fax 909-371-3052
E-Mail:
editor@nutsvolts.com

PIC'n Books

LEARN ABOUT PIC16/17 MICROCONTROLLERS

EASY PIC'n
Beginner

- Programming techniques
  - Instruction set
  - Addressing modes
  - Bit manipulation
  - Subroutines
  - Sequencing
  - Lookup tables
  - Interrupts
- Using a text editor - source code
- Using an assembler
- Timing and counting
- Interfacing - I/O conversion
- Lots of examples

$29.95

PIC'n Up The Pace
Intermediate

- Serial communication
  - PIC16 to peripheral chips
  - PIC16 to PIC16
- Serial EEPROMS
- LCD interface
- Scanning keypads
- D/A conversion
- Sensors - analog voltage output
- A/D conversion
- Math routines
- Decimal interface
- PIC16C84 EEPROM data memory
- Lots of circuits and code

$34.95

+ $4 s/h in US for one book, $6 both books
VISA, MC, AMEX, MO, Check
CA residents please add 7.25% CA sales tax
PIC is a trademark of Microchip Technology Inc.

SQUARE 1 ELECTRONICS

P.O. Box 501, Kelseyville, CA 95451
Voice (707) 279-8881 FAX (707) 279-8883
http://www.sq-1.com

MORE POWER!

68HC11, 80C51 & 80C166

AM Research supports over 30 of the most popular Embedded controllers with both ***hardware*** and ***software***.



- ☑ **More Microcontrollers**
- ☑ **Faster Hardware.**
- ☑ **Faster Software.**
- ☑ **More Productive.**
- ☑ **More Tools & Utilities.**
- ☑ **IIC Peripherials.**
- ☑ **Single Chip Capable.**
- ☑ **Outstanding Support.**
- ☑ **Custom designs.**

Call or email for a free full line brochure

Orders (800) 949-8051
Info (916) 652-7472
fax (916) 652-6642
www.amresearch.com

AM Research, Inc.
PO Box 43
Loomis, CA 95650

The Embedded Controller Experts

Write in 66 on Reader Service Card.

PRIME ELECTRONIC COMPONENTS, INC.

OUR WEB SITE IS BACK UP!

150 West Industry Court, Deer Park, NY 11729

CHECK OUT OUR WEB SITE @ www.primelec.com

OUR WEB SITE IS BACK UP!

516-254-0101 • FAX 516-242-8995 • 1-800-707-8160 (ORDERS ONLY)

EPROM & CPU/MPUs SOCKET PULLS
Math-Coproccessor & CPU

8087-1	$19.95	8748H	$6.50
80287XL	$19.95	8749	$5.95
80386DX-16	$4.95	8749H	$6.50
80387SX-16	$14.95	8751	$8.95
80387SX-20	$17.95	8751H	$9.95
80387SX-25	$19.95	8752	$13.95
80387DX-20	$17.95	8755	$6.95
80387DX-25	$24.95	MC68020RC20	$14.95
80486SX-25 (PGA)	$14.95	MC68020RC33E	$19.95
AM486DX-33 (PGA)	$17.95	MC68030RC25	$24.95
80486DX-50 (PGA)	$19.95	MC68030RC33	$29.95
8741	$3.95	MC68881RC20	$9.95
8742	$4.95	MC68882RC25	$14.95
8748	$4.95		

All parts, all socket pulls (must be Cleaned & Erased). *Note: Speed selection available at additional charge and all parts subject to availability.

EPROMS

2516	$0.65	27C256	$2.25
2716	$0.65	27512	$2.45
2732	$0.75	27C512	$2.65
2764	$0.95	27C010	$4.95
2764A	$0.95	27C100	$4.95
27C64	$1.25	27C1001	$6.50
27128	$1.45	27C1024	$3.95
27128A	$1.45	27C020	$5.95
27256	$1.90		

All DRAMS are clean socket pulls and have full leads.

4164-15	$0.18 Ea.	41256-15	$1.00 Ea.
4164-12	$0.25 Ea.	41256-12	$1.25 Ea.
		41256-10	$1.35 Ea.

NEW ALPS 2.88 MEG 3.5" FLOPPY DISK DRIVE FOR 755 SERIES THINKPAD LAPTOP
New 2.88 Meg 3.5" floppy disk drive mfr. by Alps for IBM Thinkpads 755 Series computers. This drive replaces the 1.44 Meg drive by transferring it into the original mounting bracket (5 min.) and it will be auto-detected when the computer is started. Supports 720K/1.44Meg/2.88Meg standards.
TP755/2.88 (IBM P/N 1619718) ..... $49.95 Ea.

NEW HAYES ACCURA 28.8 INTERNAL FAX/MODEM
28.8 Hayes Accura internal plug-n-play fax/modem. Card comes with Quarterdeck InternetSuite 2 and Webtalk. Requires 16 bit ISA slot. Windows 95 Plug-n-Play compatible. Five year manufacturer's warranty. Accura 28.8B Fax Modem ..... $49.95 Ea.

NEW INTEL A80487SX PGA MATH CO-PROCESSOR
New retail box Intel math co-processor comes complete with used guide, utility and diagnostic software. Great price and easy installation on upgradable systems. (Chip package 169 pin PGA.) A80487SX ..... $24.95 Ea.

NEC 6X CD-ROM DRIVE FOR VERSA 2400 SERIES
New fast 6X CD-ROM add-on or upgrade for NEC Versa 2400 laptop computer. Slides easily into VersaBay 2400 slot. One year manufacturer's limited warranty.
OP-260-65001 (Versa CD 6X Drive) ..... $69.95 Ea.

NEW COLORADO JUMBO 120 INTERNAL TAPE BACKUP DRIVE
New Colorado Jumbo 120 tape backup system has up to 120MB capacity using data compression. Installs in minutes connecting to most existing floppy controllers. Includes powerful, easy-to-use Colorado backup for DOS software program. Fits into 5-1/4" or 3-1/2" half height drive bays. QIC-40 compatible. Kit includes: drive, cable, mounting screws, and all documentation. Note: Tape not included.
Jumbo 120 Tape Backup ..... $29.95 Ea.

USED MICROSOFT PS/2 MOUSE
(New Style Contoured Type)
Used Microsoft PS/2 mouse, from older upgraded computer systems. All test with 30-day warranty.
Used MS PS/2 Mouse ..... $14.95 Ea.

WALL PLUG WALL ADAPTERS
Input: 117 Vac 50/60 Hz. Outputs Available.



Quantity Pricing Available

8Vdc 500Ma	$2.00 Ea.
9Vdc 200Ma	$1.50 Ea.
9Vdc 300Ma	$2.50 Ea.
9Vdc 450Ma	$3.50 Ea.
9Vac 500Ma	$2.95 Ea.
9.5Vac 750Ma	$3.50 Ea.
12Vdc 100Ma	$1.25 Ea.
12Vdc 200Ma	$1.50 Ea.
12Vdc 500Ma	$2.95 Ea.
12Vdc 600Ma	$3.95 Ea.
12Vdc 800Ma	$6.95 Ea.
12Vac 830Ma	$4.95 Ea.
14Vdc 700Ma	$5.95 Ea.
16Vdc 1.2Amp	$6.95 Ea.

NEW ADAPTEC AHA-1540CF ISA SCSI CONTROLLER CARD WITH EZ-SCSI V 2.0 SOFTWARE
Adaptec 1540CF SCSI-2 ISA card with external high density SCSI-2 port (up to 7 devices). On board BIOS set-up and diagnostics, jumperless configuration. Kit comes with card, cable for two devices, manual, and software. Originally packages for NCR Corp. Note: No floppy support on this model. Adaptec 1540CF KIT ..... $99.95 Ea.

NEW NISCAN/GS PLUS OCR/ 256 GRAY SCALE SCANNER
Brand New True 256 Gray Scale Hand Scanner.
Resolution: 25-400 DPI.
Scan Width: 4.2 In. Scan Length: 11 In.
Interface: 16 Bit high speed (ISA) card, 64K SRAM. System Requirements: 286/386/486 PC Compatible (16MHz).

Available 16-Bit Interface slot, Windows 3.1, 4 Meg RAM, 10 Meg of Available HD space (Min.), Mouse or Other pointing device.
Software Included: Picture Publisher LE 3.1, (Imaging Software), Perceive Personal 2.1, (OCR Software)
Niscan/GS Plus ..... $29.95 Ea.

NEW TANDY SUPER VGA 1 MEG DRAM
(16-Bit ISA Bus Type)
This board is your basic super VGA video board with 1 meg of DRAM type memory. (ISA BUS TYPE.) Core Logic Chip: WD90C31-ZS-00-02. Resolution/Color: 640x480/256C, 800x600/256C, 1024x768/256C, 1024x1024/16C. Note: Software drivers included with board. Windows 3.1, VESA, Autocad, etc.
Tandy SVGA 25-4055 ..... $19.95 Ea.

NEW 300W BABY SWITCHING POWER SUPPLY
UL & CSA RATED 110-220VAC
Input voltage: 110-220VAC 50Hz/60Hz UL & CSA. Output voltage: +12VDC @ 12 amp/-12VDC @ 0.5 amp; +5VDC @ 30 amp/-5VDC @ 0.5 amp.
Model # Hipro HP-300PPFS ..... $39.95 ea.

NEW INTEL N80287XLT MATH CO-PROCESSOR
New retail box Intel math co-processor comes complete with used guide, utility and diagnostic software. Great price on a hard-to-find part for 286 laptops. (Chip package 44 pin PLCC.)
N80287XLT ..... $19.95 Ea.

NEW CYRIX FASMATH COPROCESSOR CX-83D87-33-GP
New Cyrix FasMath coprocessors for 80386DX16-33 systems. This FPU unit is used in place of Intel's 80387DX16-33 part. Originally priced at $100.00, a steal $10.95. Case: 68 pin grid array.
Cyrix CX-83D87-33-GP ..... $10.95 Ea.

NEW SQUARE EQUIPMENT FANS

115 Vac 3.1" or 4.7"	$7.95 Ea.
12 Vdc 3.1" or 4.7"	$6.00 Ea.
12 Vdc 2-3/8"	$4.95 Ea.
12 Vdc 2-5/8"	$6.00 Ea.

NEW PANASONIC 360K 5-1/4" FLOPPY DRIVE
5-1/4" half height Panasonic M# JU-455. Black face plates only.
P/N: JU-455 ..... $9.95 Ea.

512K PCMCIA SRAM CARD
New 512K PCMCIA SRAM card made by Fujitsu. Will work in most laptop, PDA, or handheld computers with PCMCIA socket and socket management software. HP100/200, OmniGo, Zaurus, Etc.
Requires one lithium coin battery (BR2325/CR2325).
Note: Battery not included.
Fujitsu (512K SRAM PCMCIA) ..... $24.95 Ea.

NEW 28.8/V.34 PCMCIA MODEM/FAX MADE SIMPLE TECHNOLOGY
New 28.8/V.34 PCMCIA modem/FAX, cellular ready (MNP10-EC & TX-CEL Protocol) with Flash upgradeability to 33.6. Windows 95 Plug n' Play, Hot swap capabilities. Bitware Fax software included.
Note: Separate purchase of connecting cable from Simple Technology needed for cellular operation.
28.8 Communicator (Simple Tech.) ..... $74.95 Ea.

USED PULLED WORKING ASSORTED HARD DRIVES
Pulled from working equipment, tested and guaranteed for 30 days. IDE and SCSI, from 40 Megs to 500 Megs. Call for availability, model numbers, and current pricing.

NEW MITSUBISHI 1.2 MEG 5-1/4" FLOPPY DRIVE
5-1/4" Half Height Mitsumi. Model #MF504C-318MD. Tan face plate only.
Mitsubishi 1.2M FDrive ..... $24.95 Ea.

NEW 500MEG SCSI 3.5" SEAGATE
ST1480N ..... $74.95 Ea.

NEW 16-BIT 256K ISA VGA CARDS
Designed for the PC-XT/PC-AT & compatibles, this is a basic low cost VGA video card. 256K DRAM with chips & technology 82C451. Full backward compatibility with EGA, CGA, MDA, and Hercules modes. Card type: ISA 16-bit.
Model # VGA 300 (VGA Card) ..... $14.95 Ea.

FIRST AID 95 BY CYBERMEDIA
New retain boxed CD-ROM version for Windows 95 and 3.1. Fixes Windows problems automatically. System Req. IBM Compatible 386 or higher PC with Windows 95, 3.1, 3.11 / 4MEG RAM / 7MEG HD Space.
FirstAID 95 Ver. 2.0 ..... $14.95 Ea.

NEW TEAC 1.44 MEG 3.5" FLOPPY DISK DRIVE
New Standard 1.44 Meg 3.5" floppy disk drive. Manufactured by Teac, Model #FD-235HG. Face plate color: Beige. 34 pin interface connector with 4 pin power.
FD-235HG Teac 1.44M ..... $32.95 Ea.

3D HOME ARCHITECT
New retain boxed CD-ROM version for Windows 95 & 3.1. The complete software solution for easy home design. Easily create detailed floorplans, customize from over 400 furniture and fixture library items. View finished product in 2D and 3D. Over 150 sample plans included. System Req. 486 or higher Windows 95 or 3.1, 4MEG RAM / 8MEG HD SPACE / 2X CD-ROM / VGA or better.
3D Home Architect ..... $19.95 Ea.

NEW PCMCIA 10 MEG FLASH MEMORY CARD
Made by Sundisk. (Read/Write 5VDC.) Works with any laptop or PDA with PCMCIA ATA Spec. interface & software drivers. (**Software drives not included**) (Note: 10 meg is uncompressed capacity) Platform compatibility: HP 100LX/200LX IBM TP 350, 365, 500, 750, 755, and others, contact Sundisk for your specific model. Cards are Plug-Play Windows 95 compatible. Sundisk 408-562-0595 or www.sandisk.com
SDP5-10 SUNDISK ..... $124.95 Ea.

NEW INTEL PENTIUM 60/66 CPU HEATSINK 12VDC FAN COMBO
New Pentium 60/66 heatsink 12VDC fan combo for cooling the older, hotter, CPUs. Low profile type with seven inch wires. Can be used on other CPUs if you have the physical space..
Pentium 60/66 CPU Cooler ..... $4.95 Ea.

NEW TEAC COMBO 700 TAPE BACKUP AND FLOPPY DRIVE 1.44 3.5"
The Teac combo is a 3.5" floppy drive and QIC tape backup unit built into 5.25" half height frame. Great for systems with limited drive bays. Tape backup unit utilizes the PC's existing floppy controller. Capacity: 680MB compressed/340MB uncompressed. Tape Format: QIC-3010-MC. Data Trans. Rate: 0.5 & 1Mbps. Tape Media: 3M MC3000XL (400 ft.). Software Incl.: Arcada Backup for Windows 95, Windows 3.1 & DOS (1.44 Meg floppy). (Note: Back-up tape or cables not included with drive.)
FF-3101/700 Combo ..... $69.99 Ea.

Write in 168 on Reader Service Card.

GALVOS

Call Roger @
General Science & Engineering
716-338-7001

visit our web page
http://www.axsnet.com/~optics

NEW G120D
with feedback...$300 ea*

NEW G100
with feedback...$250 ea*

Galvo driver boards
$50 ea
P.S., set 20V@4A
$50/2

**Removed from new equipment*

MoTron

XC-2
DTMF To ASCII Transceiver
http://www.motron.com



The New **MoTron XC-2** is a versatile bi-directional DTMF to ASCII transceiver. DTMF digits are decoded from the audio line, converted to ASCII, and transmitted out through the serial port. ASCII data is received from the serial port, converted to DTMF digits and transmitted on the audio line. The **XC-2** uses the RS-232C serial communications protocol and includes a PTT output, which can be used to control a radio transmitter. The **XC-2** is user-configurable--select either 1200, 4800 or 9600 baud for the serial port and 5, 10, 15 or 20 cps DTMF transmission rate. Additional jumpers can be used to set DTMF "#" to generate an ASCII "CR", and to control an open-collector output with DTMF "*" (on) and "#" (off). Audio connection options allow combined audio signals, or separate audio input and output via standard 3.5mm jacks. A standard DE-9S is used for serial communications. The **XC-2** is a fully assembled and tested printed circuit board, requires +8 to +17 VDC @ 200ma, and is only 2-1/2" x 3-1/2". OEM and Quantity discounts are available.

XC-2 Bi-Directional DTMF to ASCII Transceiver PCB **$99.00** Plus Shipping

We accept American Express & Visa & MasterCard & Discover/Novus

Orders: (800) 338-9058 Info: (541) 687-2118 Fax: (541) 687-2492

Rave Review
Pop Comm
April '96

Professional 10 HOUR RECORDER

Factory Direct

"BUILT LIKE A BATTLESHIP"

- Heavy duty commercial recorder - NOT improvised from consumer models
- 12, 14, and 16 hour models also available
- BUILT-IN voice activation (add $30)
- Applications information included
- Dimensions: 11.5 x 7.0 x 2.75"

SPECIAL Nuts&Volts Price..

$159

..Includes UPS to 48 States

COD's OK. Calif. residents add tax. Sorry, no credit cards. Free catalog USA only; other countries $5.

Viking International 150 Executive Park Blvd. #4600 San Francisco, CA 94134
Phone: (415) 468-2066 · Fax: (415) 468-2067 · Web: www.vikingint.com "Since 1971"

Global Connections

Ties

Fuse Holders

P.O. BOX 8547, St. Joseph, MO, 64508, 1-800-626-0834, FAX (816) 364-2619

Consistantly low prices on your connection needs.

Call, FAX or Write for a catalog

3M Heat Shrink Tubing

Red/Black Zip Cord

Distributor for WBØW Gin Poles & Tower Accessories

FIRST
The Competition

Could Engineering be an Olympic Event?

The folks at FIRST (For Inspiration and Recognition of Science and Technology) have devised an exciting way to expose high school kids to engineering and technology. The program is the brainchild of Dean Kamen, a physicist, engineer, and entrepreneur from New Hampshire. His personal goal, and that of FIRST, is to show high school students how much fun engineering can be, encouraging them to pursue a career in technology.

Each year, Mr. Kamen and Professor Woodie Flowers of MIT, create a game in which student teams compete with a radio-controlled robot. The game in 1997 was called "Toroid Terror" and the goal was to place colored inner tubes on a rotating goal.

On the surface, maybe that sounds a little dull. But, when three robots are in play at once, all competing against the clock and cheered on by an excited crowd, you have the makings for a pretty wild time. Teams are encouraged to create stickers, buttons (for trading with other teams), tee shirts, hats, noisemakers, and whatever else contributes to team identity.

The students learn something about mechanical, electrical, electromechanical, pneumatic, and control systems as their volunteer sponsors build a competitive machine. Students and sponsors form cohesive teams very quickly.

The teams have only six weeks to construct a machine of their own design from a box of parts supplied by FIRST. There is a tremendous amount of design latitude afforded by the variety of parts, as long as weight and dimensional restrictions aren't violated.

The robot isn't as much a robot as it is a giant RC model. It even uses some RC components. FIRST provides two three-axis joysticks, eight rocker switches, and two potentiometers for the control station. Teams can use any or all of these controls, but the joysticks can't be altered. No machine can have a footprint larger than three by three feet, nor can it stand more than four feet high. Quite a design challenge when the goal is twice that high!

The fun doesn't end with tubes, gears, motors, switches, sheets, shafts, and wire. For the first time in 1997, the controller supplied by FIRST was programmable! The receive end of the control system has at its core, what amounts to a Parallax Stamp II. There are lots of synchronous serial peripherals that drive relays and RC speed controllers. Other peripherals read switch states and proportional inputs. FIRST supplies a default program which functions perfectly well for those who don't want to write their own code.

The example code, authored by Eric Rasmussen, was well annotated and easy to follow so most teams felt confident in writing custom functions for their controllers. Some were very creative with their programming. At least one team used position sensors on rotating members for feedback to the controller which held a preset position. Very creative!

Competitions

Regional competitions are held across the US beginning in March. All the teams learn a lot about strategy which prepares them for the finals at EPCOT Center in mid-April. Both events are open to the public. FIRST could not have picked a better place than EPCOT for the three-day event.

Disney and FIRST are about technology, fun, and the rewards of hard work. Students, teachers, technologists, and engineers learn from each other and have a great time doing it. All the teams show gracious sportsmanship, some even share tools, parts, and talent to get a competitor's machine battle-ready.

Awards

The Honeywell Leadership in Control Award goes to the team with the most unique control system. The team with the most robust design gets the Motorola Quality Award. Johnson and Johnson offers a Sportsmanship Award. Chrysler shows how much they value team efforts by presenting a Team Spirit Award. The Procter and Gamble Creativity Award is very broad, encompassing design and play criteria.

Other awards are: Best Play of the Day, Number One Seed, Outstanding Defense, Most Photogenic, Best Offensive Round, Featherweight in the Finals, and Rookie All-Star. A highly qualified body of judges determines which teams receive awards.

Of the 17 awards possible, the Chairman's Award is the most prestigious. This award has nothing to do with winning the game. It has to do with student involvement, teamwork, creativity, and the level of cooperation between school and sponsor.

The Founder's Award is presented by Dean Kamen to the person or organization which best promotes the goals of FIRST. The Autodesk Award goes to the team whose computer animation presents creative design solutions for The Competition. The Woodie Flowers Award goes to the individual who excels in teaching math, science, engineering, and creative design. All the teams have an opportunity to vote on which team will receive the Worcester Polytechnic Institute Design Innovation Scholarship.

The 1998 game won't be announced until January 10, so there's really no way to anticipate what kind of parts will be available or what the objective will be. That way, no team has a time advantage. Can your company or University sponsor a FIRST team? The hours can be long, but the rewards are great. It's worth every minute.

Want more information? Watch for a TV movie to be aired sometime this winter. Don't wait for the movie if you want to be a sponsor.

Visit the FIRST web site (www.usfirst.org).

Robot Wars 1997: Pretty Hate Machine

by Dan Danknick

"It was originally going to be called 'Grinder' or 'Mangler' before the aluminum parts came back from the anodizer with their purple coating," explains Christian Carlberg as he relaxes into his black leather sofa in an unassuming North Hollywood apartment. "Everyone kept saying 'It looks so pretty.' So, I settled on the name 'Pretty Hate Machine.'" And pretty it is, this 100-pound, eight-legged walking robot that competed at Robot Wars 1997 in San Francisco. But he is quick to add "I wanted something that looked mean." I wonder to myself if the 10" saw blades spinning at 14,000 RPM would qualify for that, as the 27-year-old movie special effects mechanic puts me to work helping to uncrate his robot.

As we pick Styrofoam packing material from its driveline (from a recent trip back to San Francisco, this time to become part of an ad for WebTV), Christian describes how it all started. "I made a lot of little Lego things to investigate walking and climbing mechanics. I thought about the design for 16 months. Construction was 700 hours of work over eight straight months." Schooled at Cornell and sporting a masters in mechanical engineering, Christian certainly has the background for a design of this complexity. Now sufficiently de-foamed, I groan as we lift the walker onto his coffee table for a better look at the design. At 30" wide by 54" long by 12" high, I realize: this is no small robot.

A single high torque wheelchair motor on each side moves the feet through a chain drive. Gliding in a set of spherical bearings, the legs attach through adjustable clamps (the purple parts) to a steel space frame, upon which the weapon system also rides. A pair of gel-cell batteries powers the motors, controlled smoothly through proportional H-bridges from a standard RC radio link.

Two bright green 21 cc gas engines pump 1.5 hp of destruction into independent arrays of saw blades, one fore and the other aft. The preferred attack mode is simple: walk the blades right into the target. "They originally had carbide tips on them, but the safety judges were afraid a tip might crack, fly off, and hurt someone." The jagged edge of tool steel that remains looks even more effective to me.

But with all this clever engineering, perhaps the most startling part is the feet. They're racquetballs. "I was the most disappointed with the feet; in some cases, the rubber sheared right off." Odd, considering they carried a 100-pound robot around to rain spinning death upon 50-pound foes.

To encourage the construction of walking entries, the Robot Wars organizers give a major concession to walkers, allowing them to compete in the next lower weight class. "The walkers weight advantage is a big plus," and he credits this incentive as one of the reasons he built a walker instead of a more common rolling entry. Well, that in addition to thinking the competition was "really cool."

If you're unfamiliar, Robot Wars plays yearly to sold-out crowds. Attended by all manner of engineers, artists, hobbyists, and the just plain curious, many guests go on to become entrants with their own designs. The goal of the competition is simple: disable the opposing robot, while inflicting maximum damage to the entertainment of the cheering crowd. In short, it's a bloodsport.

For fairness, the robots group by weight, from 25 pounds in the featherweights to 175 pounds in the heavyweights. Audience safety prohibits a few design elements: flames, chemicals, electrical discharges, radio jamming, expanding foam, and explosives. Many feel the kinetic energy mechanical weapons that remain make for a better show, as well as the fact they force the entrants to become more clever in their designs. In the words of event creator Marc Thorpe, "The cool tend to dominate."

Though PHM didn't glean a trophy this year, the audience cheer factor indicated it was a winner. What does he have planned for 1998? "I'm going to fix PHM at least. And I'm thinking about a 175-pound walker to compete in the middleweights." What would he build, given unlimited resources? "A 300-pound walking robot. Or a fully powered exoskeleton suit. Though nano-size insect robots might be cool, too." **NV**



Christian Carlberg can be reached on the Internet at christian@aceweb.net
For more information on the event, you can visit the Robot Wars website at http://www.robotwars.com/
A comprehensive analysis of the last two events is also available on competitor Andrew Lindsey's website at http://www.cybercomm.net/~alindsey/

Point Six, Inc. Data Acquisition Products based on Dallas Semiconductor 1-Wire™ Technology

Kelvin®

Dual Channel Temperature Monitor

The software has real-time and historical graphing as well as numerical display modes. The program runs under Windows® 95 , 3.1 and 3.11.

- Probes have digital outputs.
- No external power required.
- Connects to 9 pin RS232 port on the PC.
- Weight 1.0 lb. • One-year warranty

Item	Description	Price
DCTM01	Dual Channel Monitor	99.95

Eight Channel PC Interfaced Data Acquisition Card



T8AH

Data acquisition card with eight channels that can be individually configured as a **12 bit analog** input, a digital input, or a digital output. It has built in RS232 to 1-Wire™ converter and is supplied with the OneSix™ DDE Server.

- Built-in multi-drop controller.
- Unique device addressing.
- Analog inputs are 0-5V.
- 1-Wire™ drives 2000' net and 200 devices.
- No external power required.
- Connects to 9 pin RS232 port on the PC.
- Size 2.110W X 3.825L
- Weight 1.0 lb. • One-year warranty

Item	Description	Price
T8ADH	Analog And Digital Card	119.95
T8AH	Analog Only Card	99.95
T8DH	Digital Only Card	89.95

Eight Channel Data Acquisition Card



T8A

Data acquisition card with eight channels that can be individually accessed as a **12 bit analog** input, a digital input, or a digital output. It is supported by OneSix™ DDE Server.

- Built-in multi-drop controller.
- Unique device addressing.
- Analog inputs are 0-5V.
- Two 1-Wire™ Ports for net expansion.
- Requires Host Adapter or existing network.
- Size 2.110W X 3.375L
- Weight 1.0 lb. • One-year warranty

Item	Description	Price
T8AD	Analog and Digital Card	109.95
T8A	Analog Only Card	89.95
T8D	Digital Only Card	79.95

To Place An Order Contact Us At
Phone: 606-271-1744
FAX: 606-271-4695
E-Mail: sales@pointsix.com

MasterCard VISA

For application specific information contact Applications Engineering or visit our website at www.pointsix.com.

1-Wire™ Probes



STP010

Our probe designs are based on 1-Wire™ protocol devices all probes are multi-dropable and supported by OneSix™ DDE Server Software.

- Digital Data Output.
- Built-in multi-drop controllers.
- Unique device addressing.
- No external power required.
- Standard Temperature Range -30 to +182°F.
- Requires Host Adapter or existing network.
- Weight 1.0 lb. • One-year warranty

Item	Description	Price
STP010	Standard Temperature /W 10' Lead	14.95
STP025	Standard Temperature /W 25' Lead	16.95
ATP006	Acrylic Temperature 6" Waterproof	18.95
ATP010	Acrylic Temperature 10" Waterproof	19.95
FRP001	Fast Response Temperature /W 25' Lead	23.95
HTP001	High Temperature -30 to +225°F	24.95
PRP001	Pressure Probe 0-30 PSI	159.95
PHP001	pH Probe	159.95
CDP001	Conductivity Probe	159.95
HMP001	Humidity Probe	159.95
FCP001	1500g Force Probe	179.95

I/O Backplanes



T2SSM

T1SS

One and two position cascading backplanes accept industry standard miniature I/O modules to allow monitoring and control of high voltage/current applications. Both are supported by OneSix™ DDE Server.

- Built-in multi-drop controller.
- Unique device addressing.
- 4000VAC Isolation.
- Requires Host Adapter or existing network.
- Size (T1) 3.37W X 0.75L, (T2) 3.37W X 1.25L
- Weight 1.0 lb. • One-year warranty.

Item	Description	Price
T1SS	Digital I/O Card	29.95
T2SSM	Digital I/O Card	39.95
IAC5	AC Input Module	9.00
OAC5	AC Output Module	9.00
IDC5	DC Input Module	9.00
ODC5	DC Output Module	9.00

T8 Design Prototyping Card



The prototyping card connects to any T8ADH, T8AH, T8AD, or T8A to allow easy prototyping of I/O and analog conditioning circuits.

- On board power regulation.
- Size 3.375W X 3.375L
- Weight 1.0 lb.
- One-year warranty

Item	Description	Price
T8BDB	T8 Prototype Card	49.95

1-Wire™

1-Wire™ is a communication protocol developed by Dallas Semiconductor which allows 1-Wire™ devices to communicate on a two wire network with bi-directional data CRC checking.

OneSix™ DDE Server Software Driver

A software server driver for Windows® 95 , 3.1 and 3.11 that allows easy interface of 1-Wire™ devices and Point Six products to applications via DDE links. This eliminates the need for low level device communication programming.

- Searches network, adds and auto configures all new devices found.
- Copy and paste links to Office® products like Excel®, Word® and many other DDE capable applications.
- Works with HMI interface software such as Wonderware®, LabView®, and TestPoint®.
- Includes complete help.
- Includes an HA3 Host Adapter.
- Weight 0.5 lb. • One-year warranty

Item	Description	Price
ONESIX	DDE Server Software	69.95

PC Host Adapter

RS232 to 1-Wire™ protocol host adapter interface. Converts standard PC serial port to a 1-Wire™ network. All interface components are contained inside the DB9 shroud. The HA3 supports all Point Six Products.

- No external power required.
- Includes OneSix™ DDE Server Software.
- Connects to 9 pin RS232 port on the PC.
- 2000 ' Network and 200 1-Wire™ devices.
- Weight 0.5 lb. • One-year warranty.

Item	Description	Price
HA3	Host Adapter	69.95

Isolated PC Host Adapter

Isolated RS232 to 1-Wire™ protocol host adapter interface. Converts standard PC serial port to an Isolated 1-Wire™ network. Supports all Point Six Products.

- Includes OneSix™ DDE Server.
- 2000 ' Network and 200 1-Wire™ devices.
- 2000VAC Isolation from the 1-Wire™ Net.
- Connects to 9 pin RS232 port on the PC.
- Size 2.375W X 3.875L
- Weight 0.5 lb. • One-year warranty

Item	Description	Price
HA4	Host Adapter	139.95

Digital Thermometer



A simple easy way to access temperatures from a 1-Wire™ network. Supported by OneSix™ DDE Server.

- Built-in multi-drop controller.
- Unique device addressing.
- Temperature range -67 to +257°F.
- Can be powered for faster operation.
- 200 Devices per network.
- Requires Host Adapter or existing network.
- Weight 0.5 lb. • One-year warranty

Item	Description	Price
DS1820	Digital Thermometer Chip	3.49

Point Six, Inc. • 138 East Reynolds Road • Lexington KY • 40517 • 606-271-1744 • http://www.pointsix.com

TEST EQUIPMENT *cont.*

AM-FM SERVICE MONITORS bought & sold. IFR, Motorola, Wavetek, Marconi, Triplet, HP. **FOR QUOTE CALL TEST-TRONICS. Full calibration & repair, reasonable rates.** A division of Communications Signalling Inc. **1-888-423-2565, 805-251-2244, Fax 805-252-3100.**

ATLAS MISSILE E/F/H telemetry package flight certified. 2243.5MHz 10.6 watts PAM/FM/FM. 2 commutators, 20 VCOs. All tech data. 805-934-2058.

SENCORE CG-169 $90, CR-143 $110; CR-168 $180; RC-144 $10; TF-151 $60; TF-30 $70; EICO 369 $50, 715 $30; Nicolet Zeta 824A-CS $125; Narda 3042-20 $40; 3096 $50 new; 4031C $30; HP P281B-OPT 013 $50; P424A $30; P752A $50; P752C $50; P934A $40, 934A $40; 3300ID $40; 8447E $150; 8709 $75. G&G 210-674-8771.

HP 8640B option 3 signal generator $800. **Fluke 5200A** AC voltage calibrator $1,000. **Fluke 5205A** amplifier $800. Amadeus Surplus 810-465-1844 evenings.

OSCILLOSCOPES: TEKTRONIX, 5110, quadruple channel, 20 megahertz. Dual channel, 40 megahertz. $300. 360-262-9099 (Washington State).

6 MFD 3000VDC capacitors $10; HP 1980B scope w/2 plug-ins $300; HP 7035 XY recorder $50; HP 5325 counter $50; HP 400D VTVM $50; HP 180A scope $100. All plus shipping. SASE gets list. John Bartholomew, 519 Lower Terrace, Huntington, WV 25705. Phone 304-525-8793 E-Mail: PEHL52A@PRODIGY.COM

TEK-SALE: 1241 color logic analyzer $300; TM5006 frame $275; MI-5010 program. Multifunction interface $200 7A13 $135; 7A16A $40; 7A16P $75; 7A18 $50; 7A22 $100; 7A24 $125; 7A26 $53; 7B53A $64; 7B80 $70; 7B85 $75; 7B87 $125; 7B92A $125. 7D12 $100; 7D13 $100; 7D15 $250; DL-502 latch $50; DD-501 $85; DM-501 multimeter $100; 7S11 $150; PG-501 $125; SI-5010 $500; TM-503 frame $50; all with 30 day warranty; call **Psitech Plus** 707-745-4804 request bimonthly fax listings Fax 707-747-5277, E-Mail: apeas@ix.netcom.com

ALFA ELECTRONICS, INC.

- HIGH QUALITY TEST EQUIPMENT PROVIDER

1-800-526-2532 (526-ALFA)

15 Days Money Back Guarantee!

DMM

DMM-10 ($19.95): 3½ digit, DC/AC V, Ω, hFE, diode, signal output(+3V,-0.5Vsq.,50%duty)
DMM-17B ($39.95): 3½ digit,DC/ACV, contin., DC/ACA, Ω, Capacitance,hFE, diode, Freq
DMM-20 ($74.95): AC/DC (V, A), Freq, cont., Capac, Induct., Ω, hFE, diode, duty cycle
DMM-22 ($89.95): 4000counts, bar graph, Freq, AC/DC(V,A), Ω, Capacitance, diode, contin.
DMM-23T ($99.95): 4½ digit, high resol. (10uV, 10nA, 10mΩ), hFE, diode, contin., true rms
DMM-89S ($179.00): true rms, AC/DC (V,A), Ω, bar graph, freq, capac., dBm, logic, diode

DMM-113 ($24.95): Pocket Size, DC/ACV, Ω, diode, Continuity beeper
DMM-120 ($24.95): economy type, DCV,ACV, DCA, Ω,hFE, diode
DMM-122 ($59.95): DC/AC(V,A), Ω, hFE, diode, capacitance, freq, logic, continuity
DMM-123 ($44.95): DMM + capacitance, DC/AC(V,A), Ω, hFE, diode, continuity
DMM-124 ($69.95): Electrical+Temp,DC/ACV, , capacitance, freq, 3 phase, diode, contin.
DMM-125 ($54.95): Autorange + bar graph, DC/AC(V,A), Ω, diode, continuity beeper



LCR METER

CAP-15 *($49.95)*: 3½ digit, 0.1pF-20mF, 9 Ranges, 0.1pF resolution zero adjustment.
LCR-195 *($89.95)*: 1uH-200H (induct.), 0.1pF-200uF(Capac.), 0.01Ω-20M Ω(resistance)
LCR-814 *($189.95)*: 0.1uH-200H, 0.1pF-20mF, 0.1Ω-20MΩ, Q Factor, dissipation, zero adjust
LCR-131D *($229.95)*: autorange, 0.1uH-10kH, 0.1pF-10mF, 1mΩ-10MΩ, Q Factor, serial/parallel, 120Hz/1kHz testing mode

FREQ. COUNTER

FC-1200 *($129.95)*: 1.25GHz Handheld, 8 digits display, 10ppm accurary, sensitivity 5mV (130-350MHz), 30mV (440MHz), 22m (800MHz), batteries or 9V adapter.
FC-2500 *($179.95)*: 2.5GHz Handheld, 8 digits display, 4ppm accurary, sensitivity <50mV, batteries or 9V adapter.
FC-5270A *($149.95)* 1.2 Ghz bench type, 8 digit, 10 ppm, 35mV sensitivity, 10Vp-p max. input, power by 9V adapter.
FC-5700 *($329.95)* 1.3GHz bench type, 8 digit, 1 ppm accuracy, 20mV sensitivity, period 0.1us to 100ms. Ideal for test & repair of audio instrument.

FLUKE DMM

HandHeld		*Scope Meter*	
12	$ 84.95	92B	$1,399
70-II	$ 75.95	96B	$1,699
73-II	$ 97.95	99B	$1,999
75-II	$129.00	105B	$2,499
76-II	$175.00	863E	$469
77-II	$155.00	867E	$659
79/29-II	$175.00		
87	$287.00		

SPECIALTY

- Sound meter $169.95
- EMF Tester $69.95
- Conductivity $169.95
- Thermometer $69.95-$89.95
- Humid./Temp meter $169.95
- Press. meter $299.95
- Electr. scale $89.95
- Watt Meter $129.95
- High Voltgae Probe $59.95
- pH Meter $79.95
- Light Meter $80-$90
- Light Adapter $49.95
- Anemometer $179.95
- Anemometer adapter (And More) $89.95

OSCILLOSCOPE

Dual Trace, Component Test, 6" CRT, X-Y Operation, TV Sync, CH2 Output, Graticule Illum, 2 Probes(x1;x10)

- PS-200 20 MHz Dual Trace $339.95
- PS-205 20 MHz Dual w/ Delay Sweep $429.95
- PS-400 40 MHz Dual Trace $494.95
- PS-405 40 MHz Dual w/ Delay Sweep $569.95
- PS-605 60 MHz Dual w/ Delay Sweep $769.95
- PS-1000 100MHz Dual Trace $999.95

Digital Scope:
- DS-303 30MHz Digital, 20 Samples/sec $849.95
- DS-303P RS-232 interface, 30Mhz $1,049.95

Scope Probe:
HP-9060 (60MHz) $15, HP-9150 (150MHz) $22, HP-9250 (250MHz)$29, HP-9258 (250MHz,100:1)$39

AUDIO/RF/FUNCT. GENERATOR



RF Generator
- **SG-4160** ($124.95) 100kHz-150MHz sinewaves in 8 ranges, 100mV at 35MHz
- **SG-4162** ($229.95): Generate same signal as SG-4160, but with int. counter (150MHz).

Audio Generator
- **AG-2601** ($124.95)10Hz-1MHz, 0-8Vpp sine, 0-10Vpp squarewave
- **AG-2603** ($229.95): Same as AG-2601, but with additional counter and digital display.

Function Generator
- **FG-2100A**($169.95).2Hz-2MHz,5mV-20$V_{pp}$
- **FG-2102AD** ($229.95) same as FG-2100A, but with int. counter and TTL, CMOS output.
- **FG-2103** ($329.95) *Sweep* 0.5Hz-5MHz, linear/log, VCG, GCV, and int. counter

POWER SUPPLIES



Single Output DC Power Supplies
- Short Circuit and overload protected
- Constant current, constant voltage mode
- 0.02%+2mV line regulation; 0.02%+2mV load regulate

Analog Meters Display
PS-303 ($159.00) 30V/3A
PS-305 ($219.95) 30V/5A
PS-8110 ($289.95) 60V/5A
PS-8112 ($399.95) 60V/5A
PS-1610 ($289.00) 16V/10A
PS-8107 ($399.95) 30V/10A

Digital Voltage, Analog Current
PS-8200 ($179.95) 30V/3A
PS-8201 ($239.95) 30V/5A

Digital Volt & Current Display
PS-8300 ($199.95) 30V/3A
PS-8301 ($259.95) 30V/5A

Dual Tracking
- Short Circuit & overload protected
- Constant current & constant mode
- Independent or Tracking

Dual Tracking (Analog V & I Displays)
PS-303D ($314.95) 30V/3A/30V/3A
PS-305D ($399.95) 30V/5A/30V/5A
PS-8108 ($549.95) 60V/3A/60V/3A
PS-8109 ($699.95) 60V/5A/60V/5A

Triple Output
- One fixed 5VDC, 3 Amp output
- Parallel to double current output (PS-8102 & PS-8103 only)

Triple Output (Analog displays)
PS-8102 ($399.95) 30V/3A/30V/3A
PS-8103 ($489.95) 30V/5A/30V/5A
Digital Displays
PS-8202 ($499.95) 30V/3A/30V/3A
PS-8203 ($549.95) 30V/5A/30V/5A

INSTEK® Test & Measuring Instrument

ISO 9002 Cert. #934163 (2 Years Warranty)

OSCILLOSCOPE

OS-653 $699.95 30MHz Triggering | OS-622B $399.95 20 MHz Oscilloscope

- Dual CH / Delay sweep
- ALT trigger, trigger lock
- 1mV/div sen., delay line
- Zaxis input,CH1 output
- Hold off, TV syn.
- 2 probes (x1, x10)

- Dual CH/X-Y operation
- 1 mV/div sensitivity
- Z-axis input,CH1 output
- TV syn., trigger level lock
- 2 probes (x1, x10)

OS-305 ($209.95) - 5 MHz One Channel
OS-310 ($324.95) - 10 MHz One channel

DC POWER SUPPLIES

Triple Output

- 2 variable out 0-30V,0-3A
- One fixed 5V,3A output
- Auto track, serial, parallel
- Const. volt, current mode
- 4 analog or 2 digital display

PC-3030 ($499.95)
PC-3030D ($549.95)

Single Output

- Const voltage, current mod
- Voltage regulation <0.01%
- Current regulation <0.2%
- PS: 2 analog or 1 digital dis
- PR: 2 analog or 2 digital dis

Analog Meters Display
PS-1830 ($209.95) 18V/3A
PS-1850 ($219.95) 18V/5A
PS-3030 ($224.95) 30V/3A
PS-6010 ($209.95)60V/10A
PR-3060 ($314.95)30V/6A
PR-6030 ($314.95)60V/3A

Digital Meters Display
PS-1830D($219.95)18V/3A
PS-1850D($244.95)18V/5A
PS-3030D($254.95)30V/3A
PR-6030D($399.95)60V/3A

Programmable

- High stability, low drift
- One fixed 5V,3A output
- 100point program(PPS ser)
- 50point program(PPT ser.)
- Auto serial/parall.(PPT ser)
- Auto track (PPT series), IEEE-488.2 and SCPI compatible command set (optional)

PPS-1860G ($1,099.95)
PPS-3635G ($1,099.95)
PPS-6020G ($1,099.95)
PPT-1830G ($1,399.95)
PPT-3615G ($1,399.95)

FUNCTION GENERATOR

FG-8015G($189.95)Sweep
- 0.02Hz-2Mhz,no counter
- Sine/Squ/Tri/pulse/Ramp

FG-8016G ($239.95)
- 0.02Hz-2MHz w/ counter
- Pulse, function generator

FG-8017G($249.95)Sweep
- Sine/Tri/Squ/TTL/CMOS
- 0.02Hz-2Mhz, FM mod.

FG-8019 ($399.95) Sweep
- 0.02Hz-2MHz w/counter
- INT/EXT AM/FM mod

FG-8019 ($209.95)
- 0.02Hz-2MHz w/counter

FG-8050 ($499.95) Sweep
- 0.05Hz-5MHz w/counter
- INT/EXT AM/FM mod

FG-830 ($1,499.95) 30MHz Synthesized Function Gen.
- Output: sine, tri., square, sync out, arb. waveform
- 20mHz Freq. resolution
- Linear/log sweep
- Arbitrary modulation
- RS232; IEEE-488(option)

BENCHTOP DMM

DM-8034($179.95) 3½ dgt
- AC/DV(V,A),C,Ω,diode
- 1000V, 20A, 0.5% accu.

DM-8040($339.95) 3½ dgt
- ACV to 50kHz, true rms

DM-8055($649.95) 5½ dgt
- 0.006% basic accuracy
- 1uV,1mΩ,1nA resolution
- dBm,auto,REL, min/max

DM-8055G($889.95)GPIB
- Same funct. as DM-8055

Frequency Counters
FC-8131 ($469.95)1.3GHz
FC-8270 ($629.95)2.7GHz
UC-2010G ($294.95)

Programmable Electronic Load (PEL-300)

(Patent Nos 81011/81324)

* NEW * $1409.95

- Operating Rating: voltage 3-60V, current 6mA-60A, power 300W, temp 0-40C(operate)/-10-70C (store)
- Over voltage, over current, over power protection
- Operation mode: constant voltage, current, resistance
- Transient Gen. Frequency 1Hz-1kHz; duty 10-90%
- High Resolution: 20mV, 0.2mA, 0.3mΩ
- Self-Test and Software Calibration
- Meet UL CSA IEC Safety regulation

ALFA ELECTRONICS
P.O. BOX 8089
PRINCETON, NJ 08543

TEL: (800)526-ALFA(2532) / (609)897-1135
FAX: 609-897-0206
Email: alfa0168@aol.com

Call/Write/Fax/Email for **FREE CATALOG**
Visa, MC, AMEX, COD, PO Accepted. OEM Welcome.
1 Year Warranty (2 Years for Instek)

TEK 577/D2/177 curve tracer $850 in good condition. **CUSHMAN CE-24** selective level meter 1KHz-3.2MHz, -80 to 20dBm input $150. **TEK 2236** 100MHz oscilloscope with built-in DMM and frequency counter $790. 10 day money back guarantee. For more great deals on test equipment please call 650-244-9438 or visit our web site: http://www.odulo.com/corp/equiptek

SELL: HP 141T, 8552A, 8553B, SPEC. ANA., $1,300; HP 141T, 8552B, 8554B, $1,800. HP 141T, 8552B, 8555A, $2,000; HP 8690B, $200; PLUG-INS CALL FOR LOW COST PLUG-INS; HP 5340A, $1,200; EIP 371 source locking counter, $1,200; HP 8683B signal generator, $2,500; HP 432A, 8478A, power meter, $450; Bird 4430, Thruline wattmeter and six slugs, $500; Clarostat 240C decade power resistor, $200; Cabletron TDR 5000 time domain reflectometer, $800; HP 11729B carrier noise test set; HP 1725A 265MHz dual ch. scope, $500; HP 7475A six pen plotter, $250; HP 7550A, 8 pen graphics plotter, $400, Matrix 3000 color graphics recorder, $1,000; HP 5423A structural dynamics analyzer, $4,000; HP 3575A phase meter, $800, HP 3437A system voltmeter, $400; A-Comm Electronics 303-290-8012 Sales@A-comm.com

CALIBRATORS: FLUKE 335A $425; FLUKE 515A $575; FLUKE 5100B $2,750; FLUKE 5100B/03/05 $3,250. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

OPTICAL IMPULSE GENERATOR (UNUSED) TEK OIG-502 $3,500. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

FLUKE 6071A-1000MHz signal generator, complete but not working units $850/ea.; HP 853A/8559A 21GHz spectrum analyzer $4,200; Safco SMRTSAM cellular 500T analyzer (new) $475; HP 8901B $3,800; Marconi 2957 $3,200; Tektronix OF150 OTDR $450; Fluke 6060A $2,400; Marconi 2022A $1,800; HP 8657A $4,200. http://www.madbbs.com/amtronix 716-763-9104, fax 716-763-0371.

Write In 178 on Reader Service Card.

EQUIPMENT SALE Hewlett Packard 1122A probe supply $75; 36037A repeater $75; 37203A HP-IB extender $65; 59308 timing generator $50; 59501A power supply programmer (as new) $60; 59401A HP-IB bus analyzer $200. 435A power meter $150; 5420A w/10920A digital signal analyzer $300; late model 8170A $300; 8740A transmission test set $175; 8742A reflection test set $200; 1630G logic analyzer with acc. $500; **Psitech Plus** 707-745-4804 request twice-monthly fax listings Fax 707-747-5277. E-Mail: apeas@ix.netcom.com

---

INVENTORY REDUCTION SALE: PRICES SLASHED UP TO 50%! VIEW COMPLETE LIST AT OUR WEB SITE a-mall.com or CONTACT: AST GLOBAL ELECTRONICS, 24529 State Highway 408, Cambridge Springs, PA 16403. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

---

VIDEO SALE! Phillips PM5565 waveform monitor $350; Tek 1480C $475; Tek 1485C $525. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

---

SPECTRUM ANALYZERS. Frequency counters. Frequency standards. Meters. Scopes. Generators. Etc. **VISA & MASTERCARD.** For more information: **HTTP://TECH-SERVICES.COM** Performance tested. Calibrated. Warranteed. Gary N6ZD **408-385-0301.**

SELL: TRACOR 599K, VLF tracking receiver, $500, Wavetek SAM I-450 signal analyzer, $500; C-COR 4329E wide band solid state amplifier 20dB, 10Hz-70MHz 250MW output, $150; HP 4328A milliohmmeter, $800; HP 3400A, true RMS meter, $300; Rockland 1022F dual filter, $300; Tektronix 1410 NTSC gen. with SP-G2; TSG-2, TSG-3, $800, HP 8660A, 86634A, 86603A, $3,000; Fluke 893A diff voltmeter, $200; Kepco 188-030 power supply 0-1000V, 20mA, $150; Hickok DP170 ohm meter and frame, $150; HP 428B current meter and probe, $300; power designs 1556C 0-6KV power supply, $600; A-Comm Electronics 303-290-8012, http://www.A-COMM.COM

AUDIO TEST EQUIPMENT: HP 339A distortion analyzer $1,600. **HP 3580A** 5Hz-50KHz, 1Hz RBW, adaptive sweep, tracking generator: $790 (mech), $1,250 (LED). **Tek 7L5/L3** spectrum analyzer plug-in, 20Hz-5MHz, 10Hz RBW $1,400; with tracking generator $1,900. **Audio Precision System One + DSP** (SYS-222G) dual generator/analyzer with DSP, MEM, GPIB $8,200. Excellent condition, with warranty. Pepper Systems, 214-353-0257 Fax 214-902-9511.

Got A Battery Problem?

Get the *Ultimate* Battery Monitor

Fits 2" hole!

E-Meter™

Perfect for...
...Emergency vehicles.
...Power hungry mobiles.
...Back up power systems.
...Cell /repeater monitoring.

"Batteries don't die, they're murdered"

Proven in thousands of marine, military, RV, and industrial applications, the ***E-Meter*** gives you the battery information you need to build and run reliable DC systems. A multi-color bar graph shows battery status at a glance. Big LED's display ***volts***, ***amps***, ***amp-hours***, ***time*** or ***percent of capacity remaining***, and ***kilowatt-hours***. Tracks historical information including battery *charge efficiency*, number of *discharge cycles*, *deepest* and *average depth of discharge*. Optional RS232, temperature sensor, and low battery/genrun contact. Models up to 500V @1000A. 12-24V @ ≤ 500 A units are priced under $250 w/ sensor!

Call ext. 12 with any application or OEM questions!

Cruising Equipment

5245 Shilshole Ave. NW, Seattle, WA 98107
(206) 782-8100 Fax: (206) 782-4336
See us on the web: http://cruisingequip.com

Write in 147 on Reader Service Card.

CUNARD ASSOCIATES

R D 6 Box 104, BEDFORD, PA 15522
TEL / FAX 814 623 7000

THE POWER PRO

IF YOU NEED NEW BATTERIES FOR YOUR ELECTRONIC EQUIPMENT DON'T PITCH EM' ..... SEND THEM TO US FOR REBUILDING !

- *WE INSTALL NEW NI-CAD BATTERIES INTO YOUR ORIGINAL CASE.*
- *WE IMPROVE CAPACITY TO BETTER THAN ORIGINAL.*
- *WE FIX WHAT CAN'T BE FOUND. (OR AFFORDED)*
- *WE PROVIDE QUICK SERVICE. / EXTENDED LIFE FOR OLDER EQUIPMENT*
- *WE PROVIDE FREE QUOTES. / FREE RETURN IF QUOTE IS REFUSED.*
- *WE PROPERLY DISPOSE OF YOUR OLD CELLS BY RECYCLING.*
- *WE GIVE YOU A 12 MONTH WARRANTY.*
- *WE WILL BE HERE WHEN YOU NEED US / 10 YEARS IN BUSINESS.*
- *WE SAVE YOU **** MONEY **** !!!!!*

- *NO JOB IS TOO LARGE OR TOO SMALL ..... WE OFFER VOLUME DISCOUNTS TO LAW ENFORCEMENT / COMPANIES / FIRE DEPARTMENTS / UNIVERSITIES*

ALL MAKES & MODELS

FOR MORE INFORMATION ABOUT YOUR PARTICULAR NEEDS, WE CAN BE CONTACTED VIA PHONE OR FAX AT (814) 623-7000 OR VIA E-MAIL TO: ZAPPEM @ AOL.COM OR SEND YOUR PACKS FOR QUOTATION VIA UPS OR PRIORITY MAIL TO ADDRESS ABOVE.

GENERAL ELECTRIC		STANDARD		BENDIX KING	
MPD/PLS - MPR/MPS/MPX		CNB111/HWA110	$ 29.95	KR105/LAA125	$ 34.95
19A704850P(1200mAH)	$ 34.95	CNB120/HWA120	$ 34.95	KENWOOD	
19A704860P(1800mAH)	$ 39.95	CNB121/152/153	$ 39.95	PB2 / KNB3	$ 29.95
PL19D429763(777)G1/3	$ 37.95	UNIDEN		PB21/21H	$ 14.95
MAXON SA-1155	$ 39.95	APX650	$ 34.95	PB25/H/26	$ 24.95
MOTOROLA		APX1100/1200	$ 39.95	YAESU	
P200/HT600/MT1000		BP100/200/205	$ 19.95	FNB3/4//12/27	$ 32.95
NTN5521/4585/4824/5414	$ 37.95	ICOM		FNB11/14/16/26	$ 32.95
MIDLAND		BP2 / BP3 /BP22	$ 18.95	FNB17/25	$ 23.95
70-B32 / 70-B36	$ 39.95	BP5 / BP23 / 24	$ 24.95	COMPUTERS	
70-B10 / B16 / B19 / B21	$ 39.95	BP7 / CM7/ BP8	$ 34.95	SEND PACK FOR QUOTE	

BATTERY REBUILD SERVICE

MANY OTHERS AVAILABLE WRITE OR CALL

FREE CATALOG

ADD $ 4.50 SHIPPING & HANDLING PER ORDER

Write in 186 on Reader Service Card.

FOR THE BEST PRICES ON PROFESSIONAL TOOLS, CALL ELECTRO-TOOL

platt – Case – Deluxe Polypropylene. Chemical Resistant. Tools by CooperTools and others. 800T Case, complete with tools . . . **$419.95**
800T Case Only . . . **$121.80**



platt – Case – Cordura Exterior. Two exterior pockets & one literature pocket. 660ZT Case, complete with tools . . . **$223.00**
660ZT Case Only . . . **$59.45**
Optional Sperry meter #DM6510 as shown . . . **$65.00**

Weller WCC100- Electronically controlled station, temperature adjustable from 350°F-850°F, Zero voltage circuit-safe for sensitive components, 40 Watt pencil . . . **$97.90**

OptiVISOR – Superior magnification, Optical Glass Prismatic lenses (not plastic). Select any one of (6) magnifications . . . **$23.50**



GoldStar – 20 MHz Dual Trace Oscilloscope OS-9020A-Large 6" rectangular, high sensitivity: 1mV/div, high accuracy: ±3%, stable, low-drift design, 8 divisions of displayed dynamic range and accurate, distortion-free waveform measurements . . . **$380.00**

Electro Tool, Inc.

9103 Gillman, Livonia, MI 48150
Customer Service: (313) 422-1221
ORDERS ONLY: 1 (800) 772-3455
FAX: (313) 422-3432
"Tools American Made."

VISA MasterCard

Write in 108 on Reader Service Card.

GOOD DEALS: HP 3455A $250; HP 3581C $100; HP 8015A $150; HP 8556A $150; HP 86601A $100; Bruel Kjaer 4145, 4134 microphones $150, $200 each. Call Jeff for list, 508-533-5944.

METER SPECIALS: FLUKE 893A $45; FLUKE 8000 3-1/2 DIGITS $75; FLUKE 8050A 4-1/2 DIGITS $145; FLUKE 8502A OPT 02/03/09 6-1/2 DIGIT $450; HP 3455 5-1/2 OR 6-1/2 DIGIT $325. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

---

TEST EQUIPMENT for sale/wanted: RF, Microwave, video and fiber optic. Broadcast TV, satellite and related industries. Wavetek, Tektronix, Hewlett Packard and other manufacturers. Spectrum analyzers, signal level meters, sweep systems, TDRs, OTDRs, and much more. PTL Cable Service. Phone 561-747-3647 FAX 561-575-4635.

WANTED HP 86603-60043 attenuator assembly or 86601/86602/86603 RF head with a good attenuator assembly. Amadeus Surplus 810-465-1844 evenings.

TEST EQUIPMENT FOR SALE HTTP://WWW.A-COMM.COM

POWER SUPPLIES, ETC.: HP 6237B triple output: 0-18V, 1A; 0-20V, .5A dual tracking $375. **HP 6253A** 0-20V, 3A dual tracking $325. **HP 6255A** 0-40V, 1.5A dual tracking $325. **HP 6443B** 0-120V, 2.5A $350. **Tek PS 503A** triple output $175. **Xentek** extreme isolation transformers for clean power: 5 KVA, 2.5 KVA, etc., starting at $150. Excellent condition, warranty. Pepper Systems, 214-353-0257 Fax 214-902-9511.

Events

CALENDAR

The Events Calendar is a free service limited to electronic events such as computer shows, hamfests, flea markets, etc. If your organization is sponsoring an event and would like a free listing, contact us at least 60 days prior to the event. Include your flyer, estimated attendance, name of the person to contact, and phone number.

Complimentary issues are available upon request for distribution to your attendees. A street address for UPS is required.

While we strive for accuracy in our calendar, we can not be responsible for errors or cancellations. The information contained in this column is for the use of the readers of *Nuts & Volts* and may not be republished in any form without the written permission of T & L Publications, Inc.

All listing information should be sent to:
Nuts & Volts Magazine
Events Calendar
430 Princeland Court
Corona, CA 91719
Phone 909-371-8497
Fax 909-371-3052
E-mail events@nutsvolts.com

DECEMBER 1997

DECEMBER 6

AL - DOTHAN - Wiregrass ARC Hamfest. Mark Childre KE4OYU. 334-702-7406. Web: http://www.qsl.net/warc
AZ - MESA - Superstition ARC Hamfest. Gary Roberts AB7MX, 602-827-2195
CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
FL - OKEECHOBEE - ARC Hamfest. Al Berryman AD4RZ, 941-467-0516. E-Mail: ad4rz@juno.com
IL - JACKSONVILLE - Superfest. Jonathan Turner Jr. High School, 664 S. Lincoln Ave. 8am-2pm. Kaye Green KB9KHQ, 217-245-6778
LA - MINDEN - ARA Hamfest. Lowell A. "Dusty" Collins KB5WFE, 318-371-0636 dustyc@prysm.net
MI - LIVONIA - Super Computer Sale. Livonia Elks Lodge Hall. 31117 Plymouth Rd., 10am-3pm. Computers And You 313-283-1754
MN - GOLDEN VALLEY - Courage Handi Ham System Hamfest. Chris Peterson KG0PB, 612-520-0515
NC - GREENSBORO - Hamfest. Greensboro Coliseum Complex, 1921 W. Lee St. 910-851-1676
NH - SALEM - Computer Show. Rockingham Park Race Track. Northern Computer Shows 978-744-8440
NY - WHITE PLAINS - Computer Show. Westchester County Ctr. 9:30am-4pm. MarketPro 201-825-2229
OH - CLEVELAND - Computer Show. Cuyahoga Co. Fairgrounds. 10am-3pm. Peter Trapp Shows 603-272-5008. www.petertrapp.com

DECEMBER 6-7

CA - SACRAMENTO - Computer Show. Cal Expo. 10am-5pm. MarketPro 415-456-6730
NC - CHARLOTTE - Computer Show. Charlotte Merchandise Mart. 9:30am-4pm. MarketPro 201-825-2229

DECEMBER 7

CA - FULLERTON - Computer Show. Sequoia Conference Center. 1535 Deerpark Ave. Paul Martinez 619-295-1221
CA - LIVERMORE - Swapmeet. Las Positas College. Noel Anklam 510-447-3857
CA - SAN DIEGO - Computer Show. Scottish Rite Center. 10am-5pm. MarketPro 415-456-6730
MA - TAUNTON - Computer Show. Holiday Inn. Northern Computer Shows. 978-744-8440
MI - HAZEL PARK - ARC Swap & Shop. Hazel Park High School, 23400 Hughes St. 8am-2pm. Tom Austin N8TMQ. 810-293-7398
MI - SOUTHFIELD - Super Computer Sale. Southfield Pavilion, 26000 Evergreen. 10am-4pm. Computers And You 313-283-1754
NY - POUGHKEEPSIE - Computer Show. Mid-Hudson Civic Center. 9:30am-4pm. MarketPro 201-825-2229
OH - AKRON - Computer Show. Tadmor Shrine Temple. 10am-3pm. Peter Trapp Shows 603-272-5008. www.petertrapp.com

DECEMBER 12-13-14

MI - TAYLOR - Computer & Technology Show. Gibraltar Trade Center, 15525 Racho Rd. 313-287-2000

DECEMBER 13

CA - DALY CITY - Computer Show. Cow Palace, Gate #5, Geneva & Santos. Robert Austin Corp. 1-800-243-7041, Web: http://www.robertaustin.com
CA - FONTANA - Inland Empire ARC Amateur Radio & Electronics Swapmeet. A B Miller High School. Bill 909-822-4138 eves
CA - FRESNO - Computer Show. Fresno Fairgrounds. 10am-5pm. MarketPro 415-456-6730
FL - LAKE CITY - Hamfest & Computer Show. National Guard Armory. 8am-4pm. Colin Boutwell WA5RKR, 904-755-7969 1-800-752-7969. E-Mail: wa5rkr@isgroup.net
IN - INDIANAPOLIS - AGI Computer Fair. Indianapolis Events Center. 3655 E. Raymond St. 10am-4pm. 317-299-8827. E-Mail: agi@surf-ici.com Web: http://www.surf-ici.com/agi
ME - PORTLAND - Computer Show. Portland Expo. Northern Computer Shows. 978-744-8440
NY - SYRACUSE - Computer Show. NY State Fairgrounds. 10am-5pm. Peter Trapp Shows 603-272-5008 www.petertrapp.com
SC - UNION - Hamfest. Union National Guard Armory. 8am-3pm. Roger Gregory KD4YFB. 864-427-1462

DECEMBER 14

CA - LANCASTER - Computer Show. Antelope Valley Frgnds. 10am-5pm. MarketPro 415-456-6730
CA - SAN DIEGO - Computer Show. Scottish Rite Ctr. Paul Martinez 619-295-1221 Fax 619-295-7726
CA - SANTA ROSA - Computer Show. Sonoma Co. Fairgrounds. 10am-5pm. MarketPro 415-456-6730
IN - KOKOMO - AGI Computer Fair. Ramada Inn, 1709 E. Lincoln. 10am-3pm. 317-299-8827. E-Mail: agi@surf-ici.com Web: http://www.surf-ici.com/agi
NH - DURHAM - Computer Show. Whitemore Arena UNH. Northern Computer Shows. 978-744-8440
NY - HEMPSTEAD - Computer Show. Best Western. 9:30am-4pm. MarketPro 201-825-2229

DECEMBER 20

CA - OAKLAND - Computer Show. Oakland Convention Center, Broadway @ 10th St. 1-800-243-7041 Web: http://www.robertaustin.com
CA - SACRAMENTO - Computer Show. Scottish Rite Center. 10am-5pm. MarketPro 415-456-6730
CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
MI - FLINT - Super Computer Sale. IMA Arena, 3501 Lapeer Rd. 10am-3pm. Computers And You 313-283-1754
NH - SEABROOK - Computer Show. Seabrook Greyhound Park. Northern Computer Shows. 978-744-8440
NY - BUFFALO - Computer Show. Hamburg Fairgrounds. 9:30am-4pm. MarketPro 201-825-2229
PA - YORK - Computer Show. York Fairgrounds, Old Main Bldg. 10am-3pm. Peter Trapp Shows 603-272-5008 www.petertrapp.com

DECEMBER 20-21

CA - VENTURA - Computer Show. Ventura Fairgrounds. 10am-5pm. MarketPro 415-456-6730
GA - KENNESAW - Computer Show. Outlet Mall, I-75 @ Exit 117. Georgia Mountain Productions 706-838-4827
NY - STONY BROOK - Computer Show. SUNY Stony Brook. 9:30am-4pm. MarketPro 201-825-2229

DECEMBER 21

CA - RICHMOND - Computer Show. Memorial Auditorium. 10am-5pm. MarketPro 415-456-6730
CA - STOCKTON - Computer Show. Civic Auditorium. 10am-5pm. MarketPro 415-456-6730
MI - DEARBORN - Super Computer Sale. Dearborn Civic Center, 15801 Michigan Ave. 10am-4pm. Computers And You 313-283-1754
MI - FLINT - Computer Show. Holiday Inn, Gateway Centre, US 23 @ Hill Rd. Exit. Five Star Productions 810-890-0988
NY - ROCHESTER - Computer Show. The Dome Center. 9:30am-4pm. MarketPro 201-825-2229
PA- BETHLEHAM - Computer Show. Stabler Arena, Lehigh Univ. 10am-4pm. Peter Trapp Shows 603-272-5008. www.petertrapp.com

DECEMBER 26-27-28

MI - MT. CLEMENS - Computer & Technology Show. Gibraltar Trade Center, 237 N. River Rd. 810-465-6440

DECEMBER 26

MA - ROCKLAND - Computer Show. Sons of Italy Hall. Northern Computer Shows. 978-744-8440

DECEMBER 27

CA - BAKERSFIELD - Computer Show. Kern Co. Fairgrounds. 10am-5pm. MarketPro 415-456-6730
MI - TAYLOR - Super Computer Sale. Democratic Club Hall, 23400 Wick Rd. 10am-3pm. Computers And You 313-283-1754
NH - MANCHESTER - Computer Show. Center of NH Expo. Northern Computer Shows. 978-744-8440

DECEMBER 27-28

CA - SAN DIEGO - Computer Show. Scottish Rite Center. 10am-5pm. MarketPro 415-456-6730
CA - VALLEJO - Computer Show. Solano Co. Fairgrounds. 10am-5pm. MarketPro 415-456-6730
NJ - PARSIPPANY - Computer Show. Parsippany Hilton. 9:30am-4pm. MarketPro 201-825-2229
OH - AKRON - Computer Show. Summit Co. Frgnds, Tallmadge. Sat: 10am-4pm, Sun: 10am-3pm. Peter Trapp Shows 603-272-5008. www.petertrapp.com

DECEMBER 28

MI - MADISON HEIGHTS - Super Computer Sale. UFECW Hall, 876 Horace Brown Dr. 10am-4pm. Computers And You 313-283-1754
NH - WORCESTER - Computer Show. Worcester's Centrum Centre. Northern Computer Shows. 978-744-8440

JANUARY 1998

JANUARY 2-3-4

MN - ROCHESTER - Super Computer Sale. Mayo Civic Center. Blue Star Productions 612-788-1901. Web: http://www.supercomputersale.com

JANUARY 3-4

FL - FT. MYERS - ARC Hamfest. Colleen Sammons KQ4TR. 941-936-1431. E-Mail: csammons@juno.com

JANUARY 3

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
MI - LIVONIA - Super Computer Sale. Livonia Elks Lodge Hall, 31117 Plymouth Rd. 10am-3pm. Computers And You 313-283-1754
NH - NASHUA - Computer Show. Sheraton Tara Hotel. Northern Computer Shows. 978-744-8440
TN - MORRISTOWN - Lakeway ARC Hamfest. Perry Hensley N4PH, 423-828-4848

JANUARY 4

CA - LIVERMORE - Swapmeet. Las Positas College. Noel Anklam 510-447-3857
IN - SOUTH BEND - Hamfest and Computer Expo. The Century Center. Bob Denniston KA9WNR. 219-291-0252
MA - HYANNIS - Computer Show. Tara Hyannis Hotel. Northern Computer Shows. 978-744-8440
MI - SOUTHGATE - Super Computer Sale. Crystal Gardens, 16703 Fort St. 10am-4pm. Computers And You 313-283-1754

JANUARY 9-10-11

WI - LA CROSSE - Super Computer Sale. La Crosse Civic Center. Blue Star Productions 612-788-1901. Web: http://www.supercomputersale.com

JANUARY 10

AZ - GLENDALE - WestFest Hamfest. Glendale Community College, 6000 W. Olive. Mark Fellhauer KC7BXS, 602-931-1204. sparkfel@primenet.com
CA - FONTANA - Inland Empire ARC Amateur Radio & Electronics Swapmeet. A B Miller High School. Bill 909-822-4138 eves
CO - LOVELAND - ARC Superfest. Larimer County Fairgrounds. 700 Railroad Ave. 9am-3pm. 970-352-5304
IN - INDIANAPOLIS - AGI Computer Fair. Indianapolis Events Center. 3655 E. Raymond St. 10am-4pm. 317-299-8827. E-Mail: agi@surf-ici.com Web: http://www.surf-ici.com/agi
NE - KEARNEY - Midway ARC Hamfest. Jerry Ramsey W0PXD, 308-237-7539
NY - MARATHON - Skyline ARC Hamfest. Barbara Mudge KB2TIK, 607-849-6751

JANUARY 11

IN - NOBLESVILLE - AGI Computer Fair. Hamilton Co. Fairgrounds, 2003 E. Pleasant. 10am-3pm. 317-299-8827. E-Mail: agi@surf-ici.com Web: http://www.surf-ici.com/agi
WI - WAUKESHA - West Allis RAC Hamfest. Phil Gural W9NAW, 414-425-3649

JANUARY 16-17-18

MN - SHAKOPEE - Super Computer Sale. Canterbury Park. 1100 Canterbury Rd. Blue Star Productions 612-788-1901. Web: http://www.supercomputersale.com

JANUARY 17

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
LA - HAMMOND - S.E. LA ARC Hamfest. Jack Stang N5XVJ. 504-542-7605.
MO - ST. JOSEPH - Hamfest. Ramada Inn. 9am-4pm. Jean Pearson KC0GB, PO Box 8547, St. Joseph, MO 64508

JANUARY 18

FL - ST. PETERSBURG - Hamfest. Jean Endicott KC4KZU. 813-525-5178
NY - YONKERS - Flea Market. Lincoln High School. Kneeland Ave. 9am-3pm. Otto Supliski WB2SLQ, 914-969-1053
OH - NELSONVILLE - Sunday Creek AR Federation Hamfest. Russell Ellis N8MWK, 614-767-2226
VA - RICHMOND - Frostfest. The Showplace, 3000 Mechanicsville Tpke. 8:30am-3:30pm. 804-739-2269. E-Mail: frostfest@rats.net Web: http://www.frostfest.rats.net

JANUARY 23-24-25

KS - WICHITA - Super Computer Sale. Century 2 Conv. Ctr. 225 W. Douglas. Blue Star Productions 612-788-1901. Web: http://www.supercomputersale.com

JANUARY 24

MO - ST. CHARLES - St. Louis Repeater Hamfest. James E. Welby WB0ZJW. 6059 Sutherland, St. Louis, MO 63109-2247
TN - GALLATIN - Hamfest & Computer Show. Gallatin Civic Center. 8am-2pm. TN Valley Amateur Radio Network. Bill Ferrell N4SSB, 615-451-5992

JANUARY 25

CA - SANTA ANA - Swapmeet. ACP parking lot. Mary Russo 714-558-8813
IL - VILLA PARK - Wheaton Community Radio Amateurs Hamfest. Don Motz N9NYX, 630-665-7757. E-Mail: donlin@xnet.com
MD - ODENTON - Hamfest. Odenton Vol. Fire Dept. Hall, 1425 Annapolis Rd. Bill Ziegler KA6TYY. 410-987-2384. E-Mail: ka6tyy@juno.com
OH - DOVER - Hamfest. OH Nat'l Guard Armory, 2800 No. Wooster Ave. 8am-1pm. Howard Blind KD8KF. 330-364-5258

JANUARY 30-31-FEBRUARY 1

WI - MADISON - Super Computer Sale. Dane Co. Expo Center. 1881 Expo Hall E., Blue Star Productions. 612-788-1901. Web: http://www.supercomputersale.com

JANUARY 31

AL - GREENVILLE - RACES Hamfest. Bob W4MPQ. E-Mail: w4mpq@alaweb.com

FEBRUARY 1998

FEBRUARY 1

CA - LIVERMORE - Swapmeet. Las Positas College. Noel Anklam 510-447-3857

FEBRUARY 2

AZ - SUN CITY - Amateur radio equipment auction. St. Clement Social Hall, 15800 Del Webb Blvd. 7pm. George N7JSA, 602-933-0854. E-Mail: watgl@juno.com

FEBRUARY 6-7-8

Events CALENDAR

IL - PEORIA - Super Computer Sale. Peoria Civic Center. 201 S.W. Jefferson St. Blue Star Productions 612-788-1901. Web: http://www.supercomputersale.com

FEBRUARY 7

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
SC - NORTH CHARLESTON - ARS Hamfest. Jenny Myers WA4NGV, 803-747-2324. E-Mail: WA4USN@amsat.org

FEBRUARY 7-8

FL - MIAMI - Hamboree. Dade Co. Fair & Expo Center, SW 112th Ave. & Coral Way. Evelyn 305-642-4139. E-Mail: edg@elink.net Web: http:// hamboree.org
MO - ST. CHARLES - Computer Show & Sale. St. Charles Exposition Hall, St. Charles Center, I-70 & 5th St. Sat: 10am-4pm, Sun: 11am-3pm. Computer Central Shows 888-296-6066. E-Mail: computershow.chicago@mcimail.com
MS - JACKSON - State Convention. Ron Brown AB5WF, 601-956-1448, 601-982-0101. E-Mail: ab5wf@juno.com

FEBRUARY 8

OH - MANSFIELD - Mid*Winter hamfest. Richland Co. Fairgrounds. Pat Ackerman N8YOB, 419-589-7133 eves.
PA - LATROBE - Hamfest & computer show. American Legion, 1811 Ligonier St. 8am-3pm. Andrew Michalovicz KE3YU, 412-539-0468. Chris Weiss K3JDU, 412-537-6068

FEBRUARY 13-14-15

IN - INDIANAPOLIS - IN Convention RCA Dome. 100 S. Capital. Blue Star Productions 612-788-1901. Web: http://www.supercomputersale.com
FL - ORLANDO - Northern FL Section Convention. Tim Starr AE4NJ, 407-850-9258. E-Mail: AE4NJ@AOL.COM Web: http://www.oarc.org

FEBRUARY 14

CA - FONTANA - Inland Empire ARC Amateur Radio & Electronics Swapmeet. A B Miller High School. Bill 909-822-4138 eves
MA - MARLBOROUGH - Flea Market. Middle School. 10am-2pm. Ann Weldon 508-481-4988
MN - BLAINE - Ham and computer show. National Sports Center. 7:30am-3pm. Susan Baker N0JND, 612-537-1722

FEBRUARY 15

IL - ROCK ISLAND - Hamfest & Computer Show. QCCA Expo Center, 2621 4th Ave. Kent Williams K9UQI, 309-796-0718. E-Mail: k9uqi@arcsupport.com

FEBRUARY 20-21-22

KS - KANSAS CITY - Super Computer Sale. Overland Park Trade Ctr. 6800 W. 115th St. Blue Star Productions. 612-788-1901. Web: http://www.supercomputersale.com

FEBRUARY 21

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
NC - ELKIN - Briarpatch and Foothills ARCs Hamfest. Jimmy Holbrook KB4GKI, 910-957-3820. E-Mail: jholbro363@aol.com
OR - RICKREALL - Hamfair. Polk Co. Fairgrounds. 9am-3:30pm. Evan Burroughs N7IFJ, 503-585-5924

FEBRUARY 21-22

IN - INDIANAPOLIS - AGI Computer Fair. National Guard Armory, 3912 W. Minnesota. 10am-5pm. 317-299-8827. E-Mail: agi@surf-ici.com Web: http://www.surf-ici.com/agi
OH - CINCINNATI - Great Lakes Div. Convention. Cincinnati Gardens Exhibition Center, 2250 Seymour Ave. 8:30am-5pm. Bill Tittle KA8LAY, 513-661-1805. E-Mail: BOBGARFIELD@JUNO.COM

FEBRUARY 22

MI - DEARBORN - Swap 'n Shop. Civic Center. 8am-3pm. 313-261-5486. Web: www.larc.mi.org
OH - CUYAHOGA FALLS - Hamfest. Emidio's Party Ctr., 48 Bath Rd. 8am-2pm. Dan Adkinson KC8CFJ, 330-923-9045. hamfest@neo.lrun.com
PA - PITTSBURGH - South Hills ARC Hamfest. Steve Lane N3RNY, 412-341-1043. E-Mail: slane@sgi.net
WV - FAYETTEVILLE - Plateau ARA Hamfest. Richard M. Roy KB8SMC, 304-469-3292, 304-465-1911

FEBRUARY 27-28-29

CO - DENVER - Super Computer Sale. National Western Complex. 4655 Humboldt St. Blue Star Productions 612-788-1901. Web: http://www.supercomputersale.com

MARCH 1998

MARCH 1

CA - LIVERMORE - Swapmeet. Las Positas College. Noel Anklam 510-447-3857

MARCH 6-7-8

NE - NORFOLK - Nebraska State Convention. Fred Wiebelhaus N0VLX. 402-379-1929

MARCH 7-8

NC - CHARLOTTE - Mecklenburg ARS Hamfest. Tim Slay WO4G, 704-948-7373. http://www.w4bfb.org

MARCH 7

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
NJ - PARSIPPANY - Split Rock ARA Hamfest. Mark Turner KB2VKO, 973-347-3195. E-Mail: mlturner@bellatlantic.net Web: http://home.hsix.com/sara/hamfest.html

MARCH 8

IN - INDIANAPOLIS - Morgan Co. Repeater Assn. Hamfest. Brian Elliott N9JPX, 317-342-7236. E-Mail: belliott@surf-ici.com
NY - LINDENHURST - Hamfest. Walter Wenzel KA2RGI, 516-457-0218. E-Mail: Tom Carrubba: ka2d@li.net Web: http://www.li.net/~tom car/hamfest.htm
OH - CONNEAUT - ARC Hamfest. Clarence Baugher W8FAS, 440-593-3038
WI - WAUKESHA - SEWFARS ARC Hamfest. Mary J. Adams KB9IFF, 414-358-1003. E-Mail: mjadams@execpc.com

MARCH 13-14-15

NE - OMAHA - Super Computer Sale. Omaha Civic Auditorium. 1804 Capital Ave. Blue Star Productions 612-788-1901. Web: http://www.supercomputersale.com

MARCH 14

CA - FONTANA - Inland Empire ARC Amateur Radio & Electronics Swapmeet. A B Miller High School. Bill 909-822-4138 eves
FL - SEBRING - Highlands Co. ARC Hamfest. Dennis Koranda KF4JTM. 941-382-9560. E-Mail: kf40stra to.net Web: http://www.strato.net/~hamradio/
MO - KANSAS CITY - Ararat Shrine ARC Hamfest. Steve Dowdy WJ0I, 816-941-0620

MARCH 14-15

TX - MIDLAND - West TX State Conv. Beverley Harwood KC5BNT, 915-686-1841. E-Mail: sham rock@apex2000.net

MARCH 15

IL - STERLING - Hamfest. High School Field House, 1608 4th Ave. Lloyd Sherman KB9APW, 815-336-2434. E-Mail: lsherman@essexl.com
OH - MAUMEE - Toledo Mobile Radio Assn. Hamfest. Brenda Krukowski KB8IUP. 419-866-5928
WV - CHARLESTON - Hamfest & Computer Show. Jimmie Hewlett WD8MKS, 304-768-9788

MARCH 20-21-22

FL - FT. WALTON BEACH - Playground ARC Hamfest. Clyde Gowdy KE4FLC, 850-314-3337. E-Mail: parcfest@aol.com
WI - WEST ALLIS - Super Computer Sale. WI State Fairgrounds. 8100 W. Greenfield Ave. Blue Star Productions 612-788-1901. Web: http://www.supercomputersale.com

MARCH 21

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052

MARCH 22

NC - KINSTON - Down East Hamfest. Doug Burt W4OFO. 919-524-5724
NY - YONKERS - Westchester Emergency Comm. Assn. Hamfest. Thomas Raffaelli WB2NHC, 914-741-6606

MARCH 28

KY - ELIZABETHTOWN - Lincoln Trail ARC Hamfest. Harold Bennett AF4AC. 502-351-9599. E-Mail: hbennett@bbtel.com
OR - EUGENE - Hamfest. John Brambora KB7SXS. 541-747-2898

MARCH 28-29

MD - TIMONIUM - Maryland State Convention. William Dobson N3WD. 410-HAM-FEST. E-Mail: gbhc@concentric.net Web: http://www.concentric.net/~gbhc

MARCH 29

CA - SANTA ANA - Swapmeet. ACP parking lot. Mary Russo 714-558-8813
IL - TAYLORVILLE - Christian County Hamfest. David E. Nation, Sr. KA9JHW, 214-824-3707. E-Mail: ka9jhw@mindless.com

APRIL 1998

APRIL 4

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
NC - MORGANTON - Catawba Valley Hamfest and Computer Fair. Thomas Taylor KC4QPR. 704-433-6205. E-Mail: kc4qpr@vistatech.net
PA - FREDERICKSBURG - Appalachian AR Group Hamfest. Paul Felty WB3HEC. 717-566-2606
WA - VANCOUVER - Clark Co. Hamfest. Luther Brisky KC7KVL. 360-896-8909

APRIL 5

IA - DELOIT - Denison Repeater Assn. Hamfest. John Amdor KD6MXL. 712-748-8162. E-Mail: john mxl@netins.net Web: http://www.netins.net/showcase/johnmxl/deloit98. html
NC - RALEIGH - North Carolina State Convention. Wilbur Goss WD4RDT. 919-266-9335
WI - MADISON - Madison Area Repeater Assn. Hamfest. Jeremy Charles N9VHT. 608-245-8890

APRIL 10-11

MS - TUPELO - Tupelo, Booneville and Union Co. ARCs Hamfest. Jack Ellis KI5QV. 601-842-7255

APRIL 11

CA - FONTANA - Inland Empire ARC Amateur Radio & Electronics Swapmeet. A B Miller High School. Bill 909-822-4138 eves
OK - LAWTON - Lawton Ft. Sill ARC Hamfest. Bob Morford KA5YED, 405-355-6120, 405-353-8074

APRIL 18

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
MO - JOPLIN - ARC Hamfest. Andy Gabbert KA0TUD. 417-673-8371. E-Mail: agabbertka0tud@hotmail.com

APRIL 18-19

AL - BIRMINGHAM - Southeastern Div. Conv. Bill Levey WA4FAT, 205-97-0622. E-Mail: barc@bro.net Web: http://bro.net/barc

APRIL 19

MA - CAMBRIDGE - Flea Market. Kendall Square area. MIT. Nick Alternbernd KA1MQX, 617-253-3776

APRIL 24-25

AR - LITTLE ROCK - Hamfest. Jim Blackmon KB5IFV. 501-246-6736. E-Mail: 1rhamfest@usa.net Web: http://www.aristotle.net/~n5xay/lrh98.html

APRIL 25

IA - DES MOINES - RAA Hamfest. Ron Hobbs N0XWI. 515-255-4020
OR - KLAMATH FALLS - Keno ARC Hamfest. Tom Hamilton WD6EAW. 541-883-2736. E-Mail: wjonesjr@cdsnet.net Web: http://home.cdsnet.net/~wjonesjr/kenoarc.htm
PA - BLOOMSBURG - Columbia-Montour ARC Hamfest. Dave Schack WC3A. 717-752-6851

MAY 1998

MAY 2

AZ - SIERRA VISTA - Hamfest. Ronald Slominski KC7QXJ. 520-378-3018
CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052
KY - OWENSBORO - ARC Hamfest. George Stokes KD4CKT, 502-683-2169. E-Mail: w4nho@occ-uky.campus.mci.net

MAY 3

MD - HAGERSTOWN - Antietam Radio Assn. Hamfest. Donald Jones KB8WHW. 304-728-7769. E-Mail: kb8zqm@intrepid.net
NY - YONKERS - Flea Market. Lincoln High School. Kneeland Ave. 9am-3pm. Otto Supliski WB2SLQ. 914-969-1053
PA - WRIGHTSTOWN - Warminster ARC Hamfest. Tony Simek N3YNH, 215-674-5218
WV - RIPLEY - Jackson Co. ARC Hamfest. Gary Casto AG8RY, 304-372-2849

MAY 8-9

NH - ROCHESTER - HOSSTRADERS Hamfest. Joe Demaso K1RQG. 207-469-3492. E-Mail: k1rqg@aol.com

Continued on page 97

MICRO CIRCUITS, INC.

Manufacturer of Quality Printed Circuit Boards

- Single Sided
- Double Sided
- Multi Layered
- UL approved
- Photo Imageable solder mask
- Selective Plating (SMOBC)
- Fine Line Applications
- Carbon Ink/Conductive Ink
- Electrical Testing
- 100% Inspection
- Modem Transfer for Artwork (24 hours)

FAST PROTOTYPE TURN AROUND AVAILABLE

UP TO 10 PIECES PROTOTYPE

SQ INCHES	S/S	D/S
30	$250	$300
60	300	350
90	350	400
120	400	450

"We take pride in customer satisfaction"

630-628-5760 • Fax 630-628-5769 • Modem 630-628-7939

DIGITAL SATELLITE TV REVOLUTION!

KNOWLEDGE is POWER!

- A clear explanation of all aspects of digital satellite TV
- Communication fundamentals and standards
- Digital compression, MPEG-2, DVB, error correction
- Uplink, satellite and receive system operation
- Internet operation and satellite delivery of data
- Installing fixed and tracking dishes
- Retrofitting older systems and mobile systems
- Conventional and IF distribution systems
- Troubleshooting and repair ... and much more ...

CALL 800-483-2423

TO ORDER - Send $50 plus $4 s/h to:
Baylin Publications, 1905 Mariposa, Boulder, CO 80302
MASTER,VISA & AMEX /COD orders accepted

486 pages, 8-1/2" x 11"

JUST PUBLISHED!

Telephone: 303-449-4551 *FAX: 303-939-8720* *E-Mail: fbaylin@baylin.com*

FREE CATALOG – Satellite TV books, videos and software

Write in 132 on Reader Service Card.

SURPLUS TEST EQUIPMENT

HEWLETT PACKARD

11665B, Modulator (Unused) $450
11683A, Range Calibrator $600
11720A, Pulse Modulator, 2-18GHz $550
16510B, 80 Channel, 25MHz State & Timing Module $1000
1652B, Logic Analyzer w/Oscilloscope $4000
214A, Pulse Generator, 0.08V to 100V $200
3311A, Function Generator, .01Hz-1MHz $225
3312A, Function Generator, .1Hz-13MHz $700
3314A, Function Generator, .001Hz-19.99MHz $2800
3325A, Synthesizer/Function Generator $1800
334A, Distortion Analyzer $250
339A, Distortion Analyzer $1800
3455A, Digital Voltmeter $400
3456A, Digital Multimeter, 6.5 Digits $800
3478A, Digital Multimeter $700
3488A, Switch Control $1000
3551A, Transmission Test Set $950
35677A, S-Parameter Test Set $2700
3575A, Phase Gain Meter 1Hz-13MHz $1000
3581C, Selective Voltmeter $800
3582A, Spectrum Analyzer, .02Hz-25.5KHz $2500
3585A, Spectrum Analyzer, 20Hz-40MHz $7500
3586B, Selective Level Meter $750
3586C, Selective Level Meter $800
37204A, Multipoint HP-IB Extender $250
3779D, Multiplexer Analyzer $2500
3852A, Data Acquisition/Control Unit $2350
4191A, RF Impedance Analyzer $12,500
435A, Power Meter $150
435B, Power Meter $500
436A, Power Meter $1000
5314A/01/02, Universal Counter $225
5316B, Universal Counter $1000
5328B, Universal Counter $1000
5334A, 100MHz Universal Frequency Counter $1400
5334B, Universal Counter $1200
5335A, Frequency Counter, opt. 10/20 ..... $1200
5340A, Frequency Counter, 10Hz-18GHz $800
5354A, Frequency Converter $800
5355A, Frequency Converter $1000
5356A, Converter Head $950
5359A, Time Synthesizer $1000
54100A, Digitizing Oscilloscope $3000
54201A, Digitizing Oscilloscope, 300MHz $2500
54201D, Digitizing Oscilloscope $2650
6002A, Opt. 01, Power Supply, HP-IB, 0-50V/0-10A $700
6034A, DC Power Supply, 0-60V, 0-10A $1650
6038A, DC Power Supply, 0-60V, 0-10A $1800
6186C, DC Power Source, 0-300V, 0.100 MA $850
6227B, Dual Power Supply, 0-25V/0-2A $600
6291A, DC Power Supply, 0-40V, 0-5A $650
6469C, DC Power Supply, 0-36V, 0-300A $3000
6623A, Triple Output Power Supply $2800
7090A, Measuring Plotter $2000
8012B, Pulse Generator $750
8013B, Pulse Generator $750
8165A/002, Programmable Signal Source w/AM $2200
8182A, Data Analyzer $1500
8350A, Sweep Oscillator Mainframe $3000
8350B, Sweep Oscillator Mainframe $4000
83522A, Oscillator Plug-In, .01-2.4 GHz $5500
83540A/002, RF Plug-in, 2-8.4GHz $5000
83545A, Oscillator Plug-in, 5.9-12.4GHz $2500
8411A/018, Frequency Converter .11 to 18GHz $500
8444A, Tracking Generator w/Opt. 059 ..... $1200
853A/8558B, Spectrum Analyzer, 100KHz-1500MHz $3850
853A/8559A, Spectrum Analyzer, 10MHz-21GHz $4750
8563A, Spectrum Analyzer, 9KHz-50GHz (Mixers Included) $26,500
8566A/B, Spectrum Analyzer, 100Hz-22GHz $35,500
8569A, Spectrum Analyzer, .01-22GHz $6500
8569B, Spectrum Analyzer, .01-22GHz $7500
8620C/86222B, Sweep Oscillator, .01-2.4GHz $1800
8640B, Signal Generator, Opt. 002, .5-1024MHz $2100
8640B, Signal Generator, Opt. 1, 2 ..... $2200
8654A, Signal Generator, 10-520MHz $600
8656A, Signal Generator, 100KHz-990MHz $2500
86603A, RF Plug-in, 1-2600MHz $1500
8673B, Synth. Signal Gen., 2.0-26.5GHz $18,000
8672S, Synth. Signal Gen., .01-18GHz $13,000
8745A, S-Parameter Test Set $850
8746B, S-Parameter Test Set, 5-12.4GHz $700
8748A, S-Parameter Test Set w/Opt. 026 ..... $2500
8754A/H26, Network Analyzer, w//8748A Opt. 026 ..... $6000
8756A, Scalar Network Analyzer $1500
8770A, Arbitrary Waveform Synthesizer $3000
8901B, Modulation Analyzer $5000
8903B/001, Audio Analyzer $3000
8904A/001/003, Multifunction Synthesizer $2800

TEKTRONIX

1750, NTSC Monitor $1800
2230, 100MHz Digital Storage Oscilloscope $2500
2236, 100MHz Oscilloscope w/Counter/Timer/DMM $1550
2337, 100MHz Oscilloscope w/DMM $1650
2445, Four Channel 150MHz Oscilloscope $1800
466, 100MHz Storage Oscilloscope w/DM44 ..... $800
475, 200MHz Oscilloscope $650
475A, 250MHz Oscilloscope $800
485, Oscilloscope, 350MHz $900
494AP, Programmable Spectrum Analyzer, 10KHz-21GHz $16,000
520A, Vectorscope $400
577/D1, Curve Tracer w/Storage $1850
577/D2, Curve Tracer w/177 Fixture $1700
7A42, Four Channel Amplifier Plug-in $650
7D20, Programmable Digitizer $400
7L12, Spectrum Analyzer, 100KHz-1.8GHz $1500
7L14, Spectrum Analyzer, 1KHz-2.5GHz $2650
7L18, Spectrum Analyzer Plug-in, 1.5-18GHz Capable of 60GHz with Mixers $2500
7S12, TDR/Sampler $450
AA5001, Programmable Distortion Analyzer $1700
AM503, Current Probe Amplifier $400
CG5001, Programmable Calibration Generator $4000
FG507, 2MHz Function Generator $975
R2246, 4 Channel Oscilloscope, 150MHz $1650
RTD710, Digitizer $2500
SG5010, Programmable Oscillator $3000
SG503, Leveled Sinewave Generator $900
SG504, Leveled Sinewave Generator $2200
TM5003, Three Slot Power Mainframe $450
TM5006, Six Slot Power Mainframe $550
TR503, Tracking Generator for 492/4/5/6 ..... $850

MISCELLANEOUS

Acme Elect. PS2L1000, Electronic Load $850
Boonton 102F, AM/FM Signal Generator, DC-1040MHz $1850
Eaton 2052B, Amplifier, 100-512MHz $800
EIP 545A, Microwave Frequency Counter $1500
Fluke 5100B/03/05, Multifunction Calibrator $4000
Fluke 5100B/05, Multifunction Calibrator $3500
Fluke 5101B/03, Calibrator $4500
Fluke 5200A, AC Voltage Calibrator $2000
Fluke 5200A/5215A, AC Voltage Calibrator w/Power Amp $3850
Fluke 5440B, Precision DC Voltage Calibrator $4500
Fluke 6060B, Synthesized Signal Generator .01-1050MHz $3500
Fluke 6160B, Synthesizer, Opt. 09 ..... $1000
Fluke 845AB, Null Detector $600
Fluke 845AR, Voltmeter/Null Detector $350
Fluke 8520A, Digital Multimeter $700
Fluke R8840, Rackmount Digital Multimeter w/059 Option $750
Gen-Rad 1482B, Standard Inductor, 100UH $400
Gen-Rad 1482E, Standard Inductor, 1mH $350
Gen-Rad 1482L, Standard Inductor, 100mH $350
Gen-Rad 1482P, Standard Inductor, 1 Henry $400
Gen-Rad 1633A, Incremental Inductance Bridge $1700
Hughes, Amplifier 18-26.5GHz, 1 Watt $2500
IFR NAV750B $4500
Keithley 195A, System DMM w/Temp. $700
Kikusui PAD16-10L, Power Supply, 16V, 10A $300
Kikusui PLZ700W, Electronic Load $850
Krohn-Hite 3202/R3202, Tunable Filter/ Rack Version ..... $500/$350
Krohn-Hite 3342, Tunable Filter $1000
Phillips 5191, Prog. Synthesizer/Function Gen. 0.1MHz-2.147MHz $1750
Phillips PM5715/11, 50MHz Pulse Generator (New) $1300
Phillips 6652C, Prog. High Res. Counter/Timer, 8 Digit, 120MHz $1300
Solatron 1250, Frequency Response Analyzer $7000
Trans Devices DLR400 15 3500A, Dynamic Load $1500
Valhalla 2703, AC Voltage Standard $2350
Wavetek 166, Pulse Function Generator $1000
Wavetek 178, Automatic Synthesizer $1850
Wavetek 2002, Signal Generator, 1-2500MHz $1500
Wavetek 3000, Signal Generator, 1-520MHz $900
Wavetek 3000-200, Signal Generator $900
Wavetek 3001, Signal Generator 1-520MHz $1000
Wavetek 801, Pulse Generator, 5Hz-50MHz $800
Wavetek 802, Pulse Generator, 5Hz-50MHz w/Delay $600
Wavetek 8003, Precision Scalar Analyzer $5500
Wavetek 8541, Power Meter, 10MHz-40GHz (New) $1500
Wavetek 859, 50MHz Programmable Pulse Generator $850
Wavetek 907A, Signal Generator, 7-12.4GHz $850

OUR NEW INTERNET ADDRESS IS:
http://www.rssurplus.com

R & S Surplus
1050 E. CYPRESS STREET, COVINA, CA 91724

(626) 967-0846 • FAX (626) 967-1999

ANA Instruments

Phone: 1-800-944-0495
Fax: (540) 775-9638
E-Mail: anainstr@crosslink.net

Specials

HP 141T CRTs, New in Box $195.00
HP 8657A Signal Generator ...$4,800.00
100 KHz-1040 MHz
HP 8640B Signal Generator ...$2,100.00
Opt. 001, 002, 003
Gigatronics 600 .01-8 GHz.....$2,400.00
HP 86222A .01-2.4 GHz $1,200.00

Wanted

RF & Microwave Test and Measurement Equipment & Components

Electronic Test Equipment Bought and Sold
Visa and MasterCard Accepted

TEST EQUIPMENT *cont.*

DESOLDERING STATIONS: Hakko $225, Pace MP-1 $300, MBT101 $300, MBT200 $375, older Pace $200, Ungar 4924 $450, Weller DS1000 $300, Hart 200A $800. Soldering stations: Weller $50-$150, Hexacon $45. Jim 310-515-2058.

LOWEST PRICES! Check out Metric's "Bargain Basement" at http://www.metric sales.com Most items under $125!

SPECTRUM ANALYZERS: Avcom PSA35, Texscan VSM-58, also HP 339A, HP 334A, HP 3312A, HP 354A, Tek 2465A, all reasonably priced, sell or trade 407-423-1365.

SUCH A DEAL! On-line auction of popular test equipment. Check out Metric's "Auction" at http://www.metricsales.com There's nothing else like it!

HP 180A SCOPE (MIL SPEC AN/USM-281A) includes vertical plug-in 1801A (PL1186), horizontal plug-in 1821A (PL1187). Tested: $195. Manual reproduction: $15. Davilyn Corp. 1-800-235-6222.

SAM'S ELECTRONICS

TEL: 405-631-1856 FAX: 405-634-1526
MON-FRI 8AM TO 5PM CENTRAL

	10	50	100+
Regal CR-83 & RR-92 w/remote	$40	$37	$35
Featuring parental lock, ST/HRC/IRC programmable, last channel recall & 83 ch. capable.			
Zenith ST-300 w/remote ST/HRC/IRC switchable	$50	$47	$44
Last channel recall and 84 channel capable.			
Oak Micro 83 channel capable ST/HRC switchable	$45	$42	$39
Pioneer BC 4535 86 channel	$35	$32	$28
Oak Sigma 500 75 channel ST/HRC switchable	$25	$21	$19
DRZ-3 PJ 70 channel ST/HRC switchable	$25	$21	$18
DRX-3 PJ 60 channel ST/HRC switchable	$15	$15	$15
Panasonic TZPC 175 w/remote	$70	$62	$60
Zenith ST 1086	$47	$42	$38
SA 8529 83 channel ST/HRC programmable	$45	$40	$38
SA 80 channel ST/HRC switchable	$40	$35	$30

A Dozen Other Converters Available! All Converters Are Unmodified. Please Call.

SPECIAL PROJECTS



We design/build/modify/repair/consult on any device/system/process/project electronic/computer/mechanical/optical (eg: phone/auto/security/Radionic/lab/energy/HV/EM/RF/radar/ultrasonic/IR/UV/commo) for business and personal/invention needs. Describe & include nonrefundable $30 pre-engineering fee. Time & cost estimates 7-10 days. Confidentiality guaranteed.

OFF-THE-SHELF HARDWARE

Van Eck Systems★Data Card Reader/Writers★RF/EM/μWave/Radar/Ultrasonic/IR/Light/Sound Detectors/Xmitters/Jammers/Blasters ★ Security/Surveillance ★ EM Weaponry/Countermeasures ★ Neurophone/Rife/Resonant Crystal Radionics ★ Bug & Tap Detectors/Blasters ★ Lineman's Handsets★ Phone Color Boxes ★ Voice Disguisers ★ ESS Infinity Devices ★ DTMF Decoders ★ Child Finder ★ Panic Button ★ Slot Machine Masters ★ Subliminal Mixer/Amps (Ultrasonic/Infrasonic) ★ Alien Brainblasters ★ Electronic Dowsers ★ Shriek Modules ★ Ghost Detectors ★ Vortex Generator ★ Blackjack Devices ★ 6th Sense Communicator ★ Much, much, much more! *Buy our Catalog Today!!*

CELLULAR & CORDLESS PHREAKING $59

How cellphones operate and are modified. Vulnerabilities to hack attack and countermeasures. Comprehensive details on reprogramming NAMs, ESNs, etc (cloning), control data formats, computing encoded MINs, ESNs, SIDHs, operating systems, PROM programming, forcing ACK, test mode and resets, cable diagrams, scanning, tracking, scanner restorations, freq and channel allocations, roaming, ESN and SIDH tables, troubleshooting, parts/equipment sources, attendant stations, non-USA bands, health concerns, and the ECPA and critique. Step-by-step descriptions to keypad-reprogram 100+ popular cellphones. Plus complete section on phreaking cordless phones! Much more! 10 times more info than *any* competitor's manual!

Free Cellular Data Search: As a special service to C&CP buyers, we'll perform one FREE search of our massive cellphone database if requested within 30 days of your purchase. Search results not guaranteed. Request by mail (not fax); include a #10 SASE.

PAGER (BEEPER) MANUAL $29

Describes in detail how Pagers work, different types and uses, frequencies, advantages over and uses with cellphones, and tips and tricks. How Pagers are hacked and countermeasures. Includes plans for your own Personal Pocket Paging System (xmitter and receiver).

HACKING FAX MACHINES $29

Describes in detail how Faxes are hacked and countermeasures. Includes G3 Fax protocols, commo parameters, compression algorithms, Class 1 & Class 2 commands, Spy Fax Switcher, Fax Servers, FODs/FOCs, and Makeup/Terminating Codes. And insights into designing Fax interception devices and modifying existing Faxes into Stealth Faxes. *More!*

PBX HACKING $19

PBXs (Private Branch eXchanges) are hacked to the tune of about $8 Billion/yr! Exposes and details *all* issues relating to PBX hacking, including countermeasures. This is the *only* hacking manual ever *featured* in Forbes Magazine!

VOICE MAIL HACKING $29

Exposes how Voice Mail Box systems are used and the specific ways they are hacked. Includes ASPEN, MESSAGE CENTER, BIX, GENESIS, CENTAGRAM, RSVP, EZ, AUDIX, SYDNEY, PHONE MAIL, CINDY, SPERRY LINK, etc. A must for all users, hackers and security personnel!

10% Off Orders Over $100!!

TOP SECRET

NOW BIGGER AND BETTER!

CONSUMERTRONICS

P.O. Box 23097 ABQ, NM 87192-1097

ORDER TODAY! 505-237-2073

Fax: 505-292-4078

***Web Adventure*: www.tsc-global.com**

Established in 1971. Featured on CBS "60 Minutes," Forbes, New York Times.

Add $5 total S/H (US, Canada). Sold for educational purposes only.
Postal M.O. is fastest. VISA, MC OK. COD ($49-$999), add $7.

AUTOMATIC TELLER MACHINES $39

ATM crimes, abuses, vulnerabilities and defeats exposed! 100+ methods detailed, include: Physical, Reg. E, cipher, PIN compromise, card counterfeiting, magnetic stripe, false front, TEMPEST, Van Eck, tapping, spoofing, inside job, super-cool, vibration, pulse, high voltage - others. Case histories, law, countermeasures, detailed security checklist, labeled internal photos, figures. ATMs contain up to $250,000 in cash! *Add $19 for Placak Report!*

THE PLACAK REPORT $29

Describes the reading (using a simple method) and decryption of the magnetic flux-reversals on popular credit, debit, security and other card magnetic stripes. How to easily determine the decrypted PIN, PAN, bank number, routing codes, dates, number of daily uses and uses remaining (ex: cards that are decremented after each use).

BEYOND PHONE COLOR BOXES

Dozens of PCB's described - many circuits. Plus **Call Forwarding, Phreak History, Conferencing, Glossary, Diverters, Extenders, Loops, REMOBS, Bridging Heads & Cans, Optocom, 3rd Party** and many other non-box methods - more! *$29.*

HACKING THE INTERNET

The absolute latest tricks and methods being used on the Net to pirate software (warez) and the latest, coolest hacking websites. *Updated every two months*, so you know its fresh. Includes examples, countermeasures, password defeats, and lots of tips! *$24.*

HACKING ANSWERING MACHINES

All the known ways answering machines are hacked to listen to - even erase - messages, and to convert them into mini-VMBs. Plus countermeasures - **protect yourself from hackers, thieves!** *$19.*

BY AN ORDER OF THE MAGNITUDE

The most comprehensive, hard-hitting, hi-tech survival book ever written! Topics include electronic, computer, cryptography, chemistry, weaponry, commo, energy, concealment, revenge, alarm, disguise & ID change. Field-expedient use of technology in various threat and conflict environments. *More! $49.*

PHREAKING CALLER ID & ANI

Details on how they work and dozens of effective ways of defeating **Caller ID, ANI, *69, *57, Call Blocking,*67 etc.** Also describes **Caller ID, Orange, Beige, Cheese & CF Boxes, ESS, SS7, E-911,** various **Class services, CN/A, Non Pub DA, CAMA, DNR, 800-ECR, Diverters, LD Extenders, Centrex** - much more! *$19.*

CASINO HACKING

A Cheaters Guide to Gaming! *Includes*: The Rules of Cheating, Blackjack Cheats, Slots Cheats, Card Tricks, Inside Jobs, Surveillance, How to Set up Marks, Cheat Devices, *much more! Written by a true gaming professional!* Learn tricks that win big bucks! *$18.*

BEYOND VAN ECK PHREAKING

Eavesdropping on TV and computer video signals using an ordinary TV described in detail. Includes security industry reports. Range up to 1 KM. Plans include both the Consumertronics and the original Top Secret Van Eck designs! *$29.*

THE HACKER FILES

Compilation of 100s of the best eye-popping articles written by top hackers & phreakers. ASCII text. Covers every major topic in hackerdom! Comes on 3 HD PC Disks! *$39.*

STOPPING POWER METERS $29

As reported on "60 MINUTES"! **How devices can slow down (even stop) watt-hour meters - while loads draw full power!** Device plugs into one outlet and normal loads into other outlets. Describes meter creep, overload droop, etc. **Plans only!**

THE I.G. MANUAL: External magnetic ways (applied to meter) to slow down and stop power meters while drawing full loads. **Plans *$25.***

KW-HR METERS: How watt-hour meters work, calibration, error modes (many), ANSI Standards, etc. **Demand** and **Polyphase Meters.** Experimental results to slow and stop meters by others. *$25.*

Special! All 3 (above), *Only $59*!

COMPUTER PHREAKING $39

Describes in detail how computers penetrate each other, and how **VIRUSES, TROJAN HORSES, WORMS,** etc are implemented. Dozens of computer crime and abuse methods and countermeasures. Includes disk filled with hacker text files and utilities, and the legendary **FLUSHOT+** protection system (Ed. Choice, PC Magazine). Internet advice, password defeats, glossary - much more! **Manual + PC Disk!**

COOKIE TERMINATOR $19

Browser cookie files that are forced onto your hard drive by website providers contain personal data accessible to Internet predators, scammers, and snoops. *Protect your privacy!* CT details how to remove and stop these files from destroying your privacy, and how to keep them off your drive! *More!*

INTERNET TRACKING & TRACING $29

The Internet is infected with spammers, stalkers, scammers, and others who hide behind its anonymity. Learn step-by-step from master hackers how to trace them down in this comprehensive manual! *Invaluable!*

OTHER EXCITING TITLES!

CREDIT CARD SCAMS $29
Describes every known means of credit card fraud and scams. Includes countermeasures. Protect yourself!

RADIONICS MANUAL $29
Exciting electronic and electromagnetic therapeutic, diagnostic devices (mostly experimental). History, descriptions, plans, availability! Totally painless, can be used while asleep!

STEALTH TECHNOLOGY $24
Every known police radar and laser error - stealth method and material used to minimize reflections - strategies to fight speeding tickets - methods to detect and jam signals!

HIGH VOLTAGE DEVICES $29
Many HV device plans: Stun Gun, Taser, Prod, Cane, Flasher, Blaster, Zapper, Audio/RF/Radar Jammer, Jacob's Ladder, Plasma & Van de Graaff Gens., Fence Charger, Geiger Counter, Fish Stunner, Plant Stim., Kirlian, *much more!*

THE REBEL IS GONNA KICK YOUR ASS!!

IF YOU ORDER ANY CATALOG THIS YEAR, THIS MUST BE IT!

THE ALL-NEW TOP SECRET CATALOG FEATURES 200+ HI-TECH PRODUCTS! WILL *ROCK YOUR WORLD*!

MAIL $3, OR $1 WITH ORDER!

ORDER NOW!

S&N CELLULAR — The Electronics SuperStore

We offer a complete line of Cellular Programming Equipment

NO MORE FOOLIN' AROUND!!

STARTAC & EE3 ELITE
7 Way Kopy Kats w/cables
"Call For Best Prices"

NEC ESN Clip - Programs Model #'s 110, 120, 180, 181 ..... **$300**

NEC ESN Clip - Programs Model #'s P700, P701, P760, P761 ..... **$300**

GE, Ericsson ESN clip - Programs Model #'s **G.E.** CT700, CT550, CT750, CT800

Ericsson Model #'s AH210 AH220, AH235, AH237, AH238, AH300, AH310, AH320 **$300**

Call for Best Prices on Readers

NOW IN STOCK

C-TEK Cable - Turn OKI 900 or AT&T 3730 into a cellular monitor **$300**

GE Ericsson - Programmable phone, modified & complete **$600**

OKI 900 - Programmable phone, modified & complete **$500**
Chip installation only **$300**
Chip only - **$175**

DDI Reader/Scanner scans A&B systems, unlimited memory, continuous login, complete except for PC ..... **Call For Best Prices**

Please call your courteous service representatives for complete details at:

(954) 974-6161

S&N Cellular • 934 University Drive • Coral Springs, Florida 33071

AGREEMENT FOR PURCHASING OF CELLULAR PROGRAMMING SOFTWARE AND EQUIPMENT Purchaser agrees not to use said software and equipment for any illegal purposes. This includes line fraud, computer fraud, cellular service fraud, and any other fraudulent acts according to all federal and local laws, including rules of the FCC title #18, section 1029, and all Florida statutes. All software and equipment is sold only to qualified buyers. All software is sold for educational purposes ONLY!!!

PIC Emulator

PICE-6 from **$295**

- *Real-Time In-Circuit Emulator* (to 10 MHz)
- Supports PIC 16C62X, 16C6X, 16C7X, and 16C84
- Single step and run to Breakpoints
- Includes Assembler and Simulator
- 15 day money-back guarantee
- **Programmer** for PIC 16C5X, 16C6X, 16C7X, 16C84, and 17C4X in DIP packages, only ***$155***

Learn 8051 on PC!

With our 80C552 SBC connected to your PC's printer port, learn to write the 8051 program, debug and test it on PC.

- ***8051*** core processor (**80C552**) with 8 channel 10-bit ***A/D*** and ***PWM***
- 24 more I/Os and RS-232 port
- 32K ROM and 64K RAM
- Includes Assembler, Disassembler, Simulator, plus monitor and example programs, only **$225**

ROMY-16 EPROM EMULATOR

Emulates ROM or RAM in 8- and 16-bit systems for **$195** (2716-27256) or **$245** (2716-27010). Window/menu driven interface. 15 day money-back guarantee.

J&M Microtek, Inc.
83 Seaman Road, W Orange, NJ 07052
Tel:(973)325-1892 Fax:(973)736-4567

Write in 100 on Reader Service Card.

TEST EQUIPMENT *cont.*

HANDHELD LCR/DMM/frequency counter BelMerit DX460L, all standard DMM functions plus frequency to 20MHz, TTL and CMOS Logic, capacitance meter and inductance meter. Many other features. Comes with holster, battery, test leads and manual. **Three year factory warranty! Special price-$95.** Leeds & Northrup 4360 Precision Shunt, 0.1W, 15A, excellent condition $600. Power designs 2K20 power supply 0-2000VDC 20mA, VG condition $225. General Radio 1862C megohmmeter 500KΩ-2TΩ $300. 60 day guarantee. **Lehman Scientific 1-800-784-8680 Visa/MC. www.lehmanscientific.com Online catalog!**

WANTED: USED TEST EQUIPMENT. CONTACT: AST GLOBAL ELECTRONICS, 24529 State Highway 408, Cambridge Springs, PA 16403. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

TEXSCAN VSM-2C portable spectrum analyzer, 4-1,000MHz, 12VDC operation, very clean, $475. Precision 505-988-5233, E-Mail: jbau@dsrt.com

POCKET TESTBENCH - Handheld, inexpensive, RS232 virtual instrument. Digital, analog, serial protocol displays. High-speed counting. Sinewave, squarewave, PWM, binary outputs. Oricom Technologies, 303-444-9776, www.sni.net/~oricom

ATTENTION WHOLESALERS

AUTHORIZED DISTRIBUTOR FOR ALL NOVAVISION PRODUCTS

***NOVAVISION**

MODEL NV-5600
MODEL NV-5700
MODEL NV-5800
MODEL NV-6600

CALL

***CENTURION**

MODEL CT-3000

CALL

***MILLENNIUM**

MODEL MIL-3
MODEL MIL-3V

CALL

REFURBISHED CONVERTERS

CALL FOR THIS MONTH'S SPECIALS

CALL TODAY FOR YOUR FREE WHOLESALE ACCOUNT REGISTRATION NUMBER

CALL TOLL-FREE 1-800-366-6018 **R.B.USA**

*ALL CONVERTERS ARE ORIGINAL FACTORY NEW & GUARANTEED NO DESCRAMBLER SALES! AUTHORIZED WHOLESALERS ONLY! ANYONE IMPLYING THEFT OF SERVICE WILL BE DENIED SALE. FOR CUSTOMER SERVICE CALL 954-796-8742 KIM-11

Write in 139 on Reader Service Card.

RF Data Modules

Transmitters

- Only 30 x 10 x 5mm
- ERP 0.25mW into 50Ω
- 3V(F), 5V(F) or 6-12V(A)
- Up to 20k bps data transfer
- 418 or 433.9Mhz FM
- Simple to integrate -
- simply add antenna, data, power
- Range up to 200m
- Analog or digital data i/p
- SAW controlled - stability

TXM-4XX-A..... $24.50
TXM-4XX-F..... $25.80

Receivers

- Only 21 x 47 x 5mm
- 13mA; 130uA on power save (100:1)
- Carrier detect o/p
- Simple to integrate
- Up to 20k bps
- 418 or 433.9MHz FM Superhet
- SAW controlled - stability
- Analog or digital o/p
- Wide supply range 4,5-9V (A/F ver.)
- Fast enable time <3ms

SILRX-4XX-A..... $39.38
SILRX-4XX-F..... $41.92

Transceivers

- Only 23 x 33 x 11mm
- Up to 40,000bps of balanced code
- 19200 baud with ASCII
- Up to 170m range.
- 5v operation
- 0.25mW into 1/4 wave antenna
- 418 or 433MHz FM
- Fast 1ms enable for power saving
- Direct interface to 5V CMOS logic
- Auto TX/RX changeover

BIM-4XX-F..... $87.36

RS232 Transceivers

- 4,800 to 38,400 bps half duplex
- 3-wire RS232 interface
- Microcontroller with user EEPROM
- RS232 interface protected to ±15kV
- Auto TX/RX changeover
- 418 and 433Mhz versions
- Range 120-200m
- 0.25mW, 1mW & 10mW verions
- Reset switch and status LED's
- 7.5-15V dc via DB9 connector 20mA

BIM-4XX-RS232 .... $139.30

Synthesized Transceivers

70 x 55 x 18.5mm

- 64 channels, 25kHz width
- 464.075-464.850MHz
- Integral loop antenna
- External antenna option
- 5V operation
- 600m range -internal ant.
- TTL logic level I/O
- 5kbps data rate
- 10µA in standby mode
- 10mW RF o/p power

TXR-464-DTR100 ..... $313.50

ABACOM TECHNOLOGIES

Volume Discounts
Free Catalog Available

67 Hamptonbrook Dr • Weston • ON • M9P 1A2 • Canada

Tel: 416-242-3120
Fax: 416-242-2697
FaxBack: 416-242-3082

MISC. EQUIPMENT SALE! Dranetz 626 analyzer w/PA6001; PA6024B; PA6024A $1,400; HP 141T w/8552B/8555A 18 GHz $1,950; HP 1630D logic analyzer w/PODS $850. AST GLOBAL ELECTRONICS: Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

WANTED! TEST equipment. We pay top dollar for used scopes, generators, analyzers from HP, Tektronix, and others. Call Charles at Metric for immediate quotation. 1-800-432-3424.

GENERAL RADIO 1061 frequency synthesizer, latest color to 999MHz $200 free shipping. **Psitech Plus** 707-745-4804, Fax 707-747-5277.

POOR MAN'S Spectrum Analyzer/Monitor Receiver Kit. 2 to 1,700 MHz. Basic kit only $78. Now available with switched resolution filters, tracking generator and direct digital frequency readout. Works with ANY scope or IBM compatible computer. Send stamped envelope for details. Science Workshop, Box 310B, Bethpage, NY 11714. http://www.science-workshop.com

HP IIID DUPLEX LASER PRINTERS

- They Are Net workable
- They Print Both Sides of the Paper
- They Have Twin Paper Trays
- They use Standard 95A Cartridges
- They are Used but well maintained
- They have a 30 day warranty



$450.00 EA.

ANOTHER GREAT BUY FROM

ELECTRO MAVIN

800-421-2442 or FAX 310-632-3557

E-Mail john@mavin.com or visit our Web Page for more great buys http://www.cdc-online.com/mavsales.htm

** shipping wt. is 100 lbs from the Los Angeles area

90 DAY WARRANTY & 10 DAY INSPECTION
WE BUY AND SELL

HEWLETT PACKARD

11730D, Power Sensor Cable, 50 Ft (new) $75
16095A, Probe Fixture (used on 4192A) $175
1740A, 100 MHz Scope $375
1741A, 100 MHz Storage Scope $400
180TR, Rack Mount Display $200
214B, 10 MHz Pulse Generator, 100V/50 ohms $1400
3310A, 5 MHz Function Generator $200
3310B, 5 MHz Function Generator $225
3311A, Function Generator, .01 Hz-1 MHz $175
3312A, Function Generator, 0.1 Hz-13 MHz $650
332A, Distortion Analyzer $150
3400A, RMS Voltmeter, 10Hz-10MHz $175
3403C, Digital RMS Voltmeter, 2 Hz-100 MHz $325
3421A-201/44462A, Data Aquisition Control Unit $375
3455A, 6.5 Digit Multimeter $350
3465A, 4.5 Digit Multimeter $175
3497A-001, Data Acq/Cont Unit w/5.5 Dig Voltmeter $500
355C, Step Attenuator, DC-1 GHz $175
3575A, Gain/Phase Meter, 1 Hz-13 MHz $700
432A/478A, Power Meter, 10 MHz-10 GHz $225
432A/8478B, Power Meter, 10 MHz-18 GHz $325
4342A -01, Q-Meter, 10 KHz-32 MHz $1200
435A, Power Meter $200
436A, Power Meter $1450
4437A, Step Attenuator, DC-1 GHz, 600 ohm $175
44711A, 24 Chan FET Multiplexer $200
467A, Power Amp./Supply, DC-1 MHz, 10 Watt peak $150
491C, Amplifier, 2 GHz-4GHz, 1 Watt, 30dB Gain $675
5300A w/5302A, 50 MHz Counter $100
5300A w/5303A, 500 MHz Counter $200
5314A, 100 MHz Counter $175
5316A, 100 MHz Counter w/HPIB $450
5328A, 100 MHz Counter $175
5328A-021-030, 512 MHz Counter w/DVM $400
5335A-040, 200 MHz Counter $700
536A, Frequency Meter, 0.96-4.2 GHz $100
537A, Frequency Meter, 3.7-12.4 GHz $150
5508A, Measurement Display (for 5528A Laser Sys) .. $900
59306A, Relay Actuator $125
59313A, A/D Converter $100
59501B, Isolated DAC/Power Supply Programmer $125
6002A-01, Pwr Sup, 200 W, 0-50V @ 0-10A, GPIB $675
6110A, (Har), Pwr Sup, 0-3KV @ 6mA (cables incl) $300
6112A, Precision Pwr. Sup., 0-40V @ 0.5A $275
6181B, Constant Current Source, 100V, 250 mA $300
6200B, Pwr. Sup., 0-40V @ 0.75A or 0-20V @ 1.5A $200
6201B, Pwr. Sup., 0-20V @ 1.5A $150
6214C, Pwr. Sup., 0-10V @ 1A $100
6227B, Dual Pwr Sup, 0-25V @ 2A $475
6228B, Dual Pwr Sup, 0-50V @ 1A $475
6253A, Dual Pwr. Sup., 0-20V @ 3A $450
6261B-026, Pwr Sup, 0-20V @ 50A, 115 VAC input $575
6267B, Pwr Sup, 0-40V @ 10A $475
6271B, Pwr Sup, 0-60V @ 3A $350
6284A, Pwr Sup, 0-20V @ 3A $225
6289A, Pwr Sup, 0-40V @ 1.5A $225
6294A, Pwr Sup, 0-60V @ 1A $225
6384A, (Har), Pwr. Sup., 4-5.5V @ 8A $75
6434B, Pwr Sup, 0-40V @ 25A $650
6515A, (Har), Pwr Sup, 0-1.6KV @ 5mA (cables incl) . $275
6824A, Pwr. Sup./Amplifier $275
+/- 50V, +/-1A, 20 dB gain, DC-10 KHz
6827A, Pwr Sup/Amplifier $500
+/-100V, +/-0.5A, 80dB gain, DC-15 KHz
75000 series B, VXI data aquisition system $1000
7550A, 8-Pen Vector Plotter $175
7595B, DraftMaster SX Plotter, sizes A through E $1750
779D, Directional Coupler, 1.7-12.4 GHz $200
8007B, Pulse Generator, 100 MHz $450
8011A, Pulse Generator, 20 MHz $125
8084A, Word Generator, 300 MHz $275
8406A, Comb Generator, 1/10/100 MHz to 5 GHz $375
8444A-059, Tracking Generator, 0.5-1500 MHz $600
8445B-2-3, Tracking Preselector, 1.8-18 GHz $400
8503A, S-Parameter Test Set, 500 KHz-1.3 GHz $700
8505A, RF Network Analyzer, 500 KHz-1.3 GHz $2100
853A/8558B, Spectrum Analyzer, 0.1-1500 MHz $3500
8620C-011, Sweep Oscillator Mainframe, GPIB $400
86250D, RF Plug-in, 8.0-12.4 GHz $375
86290B, RF Plug-in, 2.0-18.6 GHz $1400
8640B, Signal Generator, 0.5-512 MHz $1200
8656A, Synth Signal Generator, 0.1-990 MHz, HPIB . $2200
86601A, RF Plug-In, .01-110 MHz $225
86602A, RF Plug-In, 1-1300 MHz $500
86631B, Aux Section (AM) $100
E1401A, 13-slot C-size VXI High Pwr Mainframe $1200
R382A, Precision Variable Attenuator, 26.5-40.0 GHz $1500
X486A, Thermistor Mount, 8.0-12.4 GHz $50
X752D, Directional Coupler, 20dB, 8.0-12.4 GHz $50

TEKTRONIX

067-0885-00, Microwave Comb Generator $600
2215, 60 MHz O'Scope $500
2337, 100 MHz O'Scope $900
465, 100 MHz Dual Trace Oscilloscope $425
465B, 100 MHz Dual Trace Oscilloscope $475
475, 200 MHz Dual Trace Oscilloscope $650
577D1/177, Storage Curve Tracer w/std test fixture .. $1700
7104, 1 GHz O'Scope Mainframe $1700
7104, 1 GHz O'Scope w/7A29, 7A26, 7B10, 7B15 ..... $2750
7603, 100 MHz O'Scope w/7A26, 7B53A $300
7844, 400 MHz Dual Beam Oscilloscope $900
w/7A24, 7A26, 7B80, 7B85
7A13, 105 MHz Differential Comparitor $150
7A18, 75 MHz Dual Trace Amplifier $50
7A22, 1 MHz High CMRR Differential Amplifier $200
7A26, 200 MHz Dual Trace Amplifier $75
7B50A, 150 MHz Time Base $75
7B53A, 100 MHz Dual Time Base $75
7B70, 200 MHz Time Base $75
7B71, 200 MHz Delaying Time Base $75
7B80, 400 MHz Delaying Time Base $100
7B85, 400 MHz Delta Delaying Time Base $100
7B92A, 500 MHz Dual Time Base $150
7CT1N, Curve Tracer Plug-In $300
7D11, Digital Delay $50
7L13/7603, 1 KHz-1.8 GHz Spectrum Analyzer $1650
7S14, 1 GHz Dual Trace Delayed Sweep Sampler $550
AM503, Current Probe Amplifier $350
DC5009, 135 MHz Universal Timer/Counter $375
DC503A, 125 MHz Counter $150
DM501, 4.5 Digit Multimeter $150
FG501A, 2 MHz Function Generator $175
FG504, 40MHz Function Generator $500
P6015, High Voltage Probe, 40 KV, 1000X, 75 MHz .. $250
P6201, Active FET Probe, DC-900 MHz, 1X/10X/100X $350
P6460, Data Aquisition Probe (for 1240/1241 Analyzer) $275
PG502, 250 MHz Pulse Generator, TM500 series $400
PS5010, Prog Tripple Pwr Sup, TM5000 series $600
PS503A, Tripple Pwr Sup, (2) 0-20@1A, 5V@1A $150
S-3A, Sampling Head, DC-1 GHz $225
S-53, Trigger Recognizer Head (new) $300
SC503, 10 MHz Storage O'Scope, TM500 Series $325
TG501, Time Mark Generator $400
TM5006, 6-slot Programmable Power Module $450
TM503, 3-slot Power Module $100
TM506, 6-slot Power Module $100

MISCELLANEOUS

Ando AQ-1135E, Optical Power Meter, 400-1600 nM .. $900
w/AQ-1986 Sensor, AQ-4120 Light Source, case & manual
Cal. Inst. 101TC-850T, AC Power Source $700
0-120VAC, 45Hz-5KHz, 100 Watt
Clarostat 240C, Power Decade Resistor $100
Doric 130A, Capacitance Meter $75
Dorn-Margolin ELT6.1, Emergency Locator Transmitter $150
Dranetz 606-3/101-103, Line Disturbance Alalyzer $525
EIP 548A-1-2-8-9, Microwave Counter $2800
10 Hz-26.5 GHz, DAC out, GPIB, rear input, power meter
Fluke 1910A, 125 MHz Counter $125
Fluke 5100B-03-05, Meter Calibrator $3400
Fluke 6070A-130, Synthesized Signal Generator $1850
200 KHz-520 MHz, GPIB & High Stability Time Base
Fluke 8050A-01, 4-1/2 Digit Multimeter w/battery opt . $200
Fluke 845AB, High Imp Null Detector $500
Fluke 8505A-02-03-05-09, 6.5 Digit Multimeter w/GPIB $600
Fluke 8860, 4.5 Digit Multimeter $275
Fluke 8920A, RMS Voltmeter, 10 Hz-20 MHz $475
Fluke 8922A, RMS Voltmeter, 2 Hz-11 MHz $475
GenRad 1432C, 3-Decade Resistor, 0-11,100 ohms $75
GenRad 1454-AH 4-Decade Voltage Divider $200
GenRad 219M, Decade Capacitor, 1.11 uF $75
Giga-Tronics 900/2-8, Synthesized Sweep/Sig. Gen. .. $1500
2 - 8 GHz, opt 026 GPIB
Heise 710A, Digital Pressure Gauge, 0 to 10 PSI, .1% . $300
Heise 710A, Digital Pressure Gauge, 0 to 30 PSI, .1% . $300
Heise 710B, Digital Pressure Gauge, 0 to 100 PSI, .05% $575
Heise 711B, Digital Pressure Gauge, 0 to 30 PSI, .05% $575
Hickok 539B, Vacuum Tube Tester $225
Keithley 181, 6.5 Digit Nanovoltmeter, GPIB $900
Krohn-Hite 6620, Precision Phasemeter $650
Krohn-Hite 7500, Power Amplifier, DC-100 KHz/75 W $650
Lambda LQ-532, Pwr. Sup., 0-40V @ 5A, Dig Display . $250
Laser Precision TD-9920, OTDR w/case & manual $950
Narda 3293-2, Directional Coupler, 1-12.4 GHz (N type) $150
Narda 4203-16, Directional Coupler, 2-18 GHz (SMA) $100
Narda 8616, RF Radiation Monitor w/probes $600
Phoenix 5500, Tele-Communications Analyzer $450
Phoenix 5500-300-1, CCITT V3.5 Interface Plug-in $300
Phoenix 5500-624-1, T1 Interface Plug-in $350
Scientech 36-0-401, Laser Calorimeter Head $400
Simco SS-2X, Electrostatic Locator w/probe $100
SysDon 101, 10 MHz Pulse Generator $75
Valhalla 4440, 4-1/2 Digit Voltmeter/Counter $125
Wavetek 154, Prog. Waveform Gen., .001 Hz-10MHz .. $250
Wavetek 175, Arbitrary Waveform Gen, GPIB $600
5 mega-samples per second, 8 bit resolution/1024 points
Wavetek 182A, 4MHz Function Generator $175
Wavetek 186, 5 MHz Phase Lock Generator $250
York FK11, Fiber Optic Cable Cleaver $150

WANTED

Send us a list of your extra catalogs and manuals

TEST EQUIPMENT PLUS
(520) 575-6967, FAX (520) 575-6936
3331 W. Bright Terrace, Tucson, AZ 85741

MasterCard VISA

Scope4pc $449

4 Channel Digital Storage Oscilloscope

- Connect to PC or Laptop (LPT port)
- 4 Channels, 20 MSPS per channel
- 5 mv/div to 10 v/div
- Uses standard X1 or X10 probes
- Win95 (or Win3.1) software with automatic measurements, calipers, color and label traces.
- Designed and made in USA



CED Inc. Voice/Fax (561) 417-4304
Email ced@flinet.com
Test drive software and view specs. at
www.flinet.com/~ced/

WHOLESALE CABLE

COMPLETE LINE OF CABLE PRODUCTS

☑ Quality merchandise by brand name manufacturers
☑ Satisfaction guaranteed ☑ Free gift on first order
☑ Technical support
☑ 2 year warranty on new converters
☑ COD shipping & overnight shipping by request
☑ Experience where it counts ☑ Volume pricing

Tell us the best price you were offered, where you got it from, and let us try to beat it.

PLAIN CONVERTERS: ZENITH, OAK, PANASONIC, PIONEER, EAGLE, HAMLIN, STARGATE, PLUS MORE.

REMOTE CONTROLS: ALL MAJOR BRANDS, INCLUDING 2-4 FUNCTION UNIVERSAL REMOTES



WHOLESALE CABLE M-F 11am-6pm EST **(800) 909-4333**
(718) 262-0900 · FAX (718) 657-4015 · (718) 297-9221

No NY sales. Federal and local laws provide criminal and civil penalties for unauthorized use. Check with your cable providers for permission to use equipment. Must be paying for all services you receive. Order by model number only. Some equipment refurbished as new.

WANTED: WATKINS Johnson frequency counter DRO-309A or DRO-333. For parts or working. Walter Iacobelli, 2147 Harman St., Queens, NY 11385. Tel. 718-456-1988.

LOWEST POSSIBLE PRICES. Untested, repairable test equipment as received directly from the government at cost +10%. **VISA & MASTERCARD.** For more information: **http://tech-services.com/cost+10.htm** Gary N6ZD. **408-385-0301**.

SELL: GR 1615A capacitance bridge with 1311A OSC. and 1232A detector tuned amp, $500; GR low pass filters $60 ea., 874-1000. 874-F-185, 874-F500; HP 1630D logic ana., $700; HP 1631D logic ana. 50MHz scope, $1,500; HP 606B; $300, Tracor 599K tracking receiver $500, Solar Electronics 6550-1 audio power sweep gen., $250; A-Comm Electronics HTTP://WWW.A-COMM.COM 303-290-8012.

TEKTRONIX TL12 spectrum analyzer with 7603 main frame included. Calibrated and guaranteed $1,000. 816-224-6005.

WATTMETERS URM-120, 2-1000 MHz, 10-1000W, three couplers, meter, case, manual, 10 lbs. $140. Add shipping. Tartan Electronics, Box 36841, Tucson, AZ 85740-6841, 520-577-1022.

WANTED! TEST equipment. We pay top dollar for used scopes, generators, analyzers from HP, Tektronix, and others. Call Charles at Metric for immediate quotation. 1-800-432-3424.

HP 3581C selective voltmeter, complete, cosmetically ok, needs some work, $149; HP 427A volt/multimeter, $75; Tek AM502 differential amp $149. Multimeters; Fluke 8025A $75; Fluke 8010M $120; Ballantine AN/USM-326A 550MHz counter, $200; Fluke 540B $275; Tek 1503TDR all options, $600. Technologies West 541-267-6064.

TRACKING GENERATOR HP 8443 (UNUSED W/CABLES) $650; HP 8443 $350. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

PORTABLE SCOPES: Tek 222A (10MHz) digital storage/readout, handheld battery-operated $1,250 (many accessories available). **Tek 475A** (250MHz) $650. **Tek 475A/DM44** (250MHz, multimeter) $725. **Tek 466** (100MHz, storage) $600. All with bright CRTs; excellent condition, warranty. Pepper Systems, 214-353-0257.

HUGE TEST EQUIPMENT SALE! PRICES SLASHED UP TO 50%! VIEW COMPLETE LIST AT OUR WEB SITE: a-mall.com or CONTACT: AST GLOBAL ELECTRONICS, 24529 State Highway 408, Cambridge Springs, PA 16403. Voice: 1-888-216-7159, Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

TEST EQUIP. GenRad 1863 megohmmeter $525. 1424A decade capacitor $450; 1316 oscillator $750. 978-251-3855.

MAGTROL 200 in./oz. Dynamometer $150. Harowe 2 piece direct mount brushless resolver $35. 818-761-8594.

WAVETEK 3007 signal gen., 1KHz -530MHz, with modulation meter, $900; Wavetek 3002-673, sig. gen. AM FM, 1KHz-530MHz, $850; HP 5335A counter, $1,200; HP 4815A, Vector Z meter, $1,500; HP 8444A, tracking generator, $500; EMCO 3102, log spiral ant.; EMCO 3101, log spiral ant.; Data Pulse 110B pulse gen., $200; FW Bell 350 Gaussmeter; $400; AR AT3000, E field generator, GR1863 megohmmeter, $500; HP 334A distortion ana., $500, HP 7550A, A-Comm Electronics 303-290-8012. E-Mail: SALES@A-comm.com

OSCILLOSCOPE SALE: TEK 335 (35MHz) $275; 464 (100MHz STORAGE) $375; 465 (100MHz) $375; 465B (100MHz) $450; 466 (100MHz STORAGE) $475; 475 (200MHz) $475; 475A (250MHz) $650; 7704A (250MHz MAINFRAME) $175; 2213 (100MHz) $375; 2215 (60MHz) $325; 2215A $350; 2335 (100MHz) $750; 2335 (100MHz) NEW IN BOX COMPLETE $1,150; 2445 (150MHz 4 CHANNEL) $1,850; TEK 2465 (300MHz) $2,450. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

POWER SUPPLY SALE: HP 6112A 40V 5A $175; HP 6253A DUAL 20V 3A $325; HP 6271B 60V 3A $375; HP 6434B 40V 25A $475; HP 6260B 10V 100A $400; HP 6264B 20V 20A $350; HP 6265B 40V 3A $300; HP 6266A 40V 6A $350; HP 6282A 10V 10A $325; HP 6403B 7.5V 3A $225. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

RF EQUIPMENT: HP 8761B coaxial switch (18GHz, SMA) $65. **HP 5342A/001** counter (18GHz, oven option) $1,950. **HP 11869A** adapter for 8350B $350. **HP 436A, 8481A** power meter, sensor $1,650. **HP 8555A, 8552B, 141T** (.01-18GHz spectrum analyzer) $1,600. **HP 8502A/H26** transmission/reflection test set $950. Excellent condition, with warranty. Pepper Systems, 214-353-0257.

The FBASIC TICkit™



- Max EEprom: 65535 bytes
- Signed 32bit Math
- 300% faster than Stamp I
- I²C Peripheral Buss
- Interactive Debugging
- EEprom Arrays and Structure
- 44780 LCD Module Routines
- 9600 Baud Serial Routines
- 16 Multi-purpose I/O Lines

Run FBASIC programs without the delays and difficulty of assembly coding. Simple to use, easy to learn, complete small projects quickly with the FBASIC TICkit.™ Suitable for both beginners and experienced engineers.
Starting as low $49.

The New TICkit-62

"Stamp" users – look at the new features of the TICkit-62

96 bytes RAM
Improved RS232 simulation with handshake
Background PWM
All previous TICkit features

QUESTIONS?
Call us at (303) 440-5590 or visit our home page at:
www.csn.net/versatech

Ask us about the I²C X-Tender Peripheral!

VersaTech Electronics
P.O. Box 18476, Boulder, CO 80308

TO ORDER CALL: Phone: (303) 440-5590, fax: (303) 440-9467, bbs: (303) 440-7828, e.mail: versatech@csn.net

BOATERS SEE BIG IMPROVEMENTS IN RADARS

by Gordon West

The term RADAR stands for RAdio Detection And Ranging.

The brand new Raytheon radar has an impressive LCD high-contrast screen.



Slotted waveguide antennas offer increased resolution to a cluster of small targets.

The first radar was developed in the mid-20s by the British. The British were bouncing very high frequency waves into the ionosphere and then measuring the time delay of the echo. Since the velocity of radio waves is approximately 300 million meters per second (the same as the speed of light), the British could determine the height of the ionosphere by timing the echo.

A radio wave will travel one nautical mile every 6.2 microseconds. When they measured a layer of the ionosphere up 100 miles, the time delay was 1,240 microseconds. This works out to be 620 microseconds up, and 620 microseconds back, for a total of 1,240 microseconds of up-and-back journey.

In the 30s, the British developed a shore-based radar that was able to detect aircraft in flight. They found signals in the VHF and UHF spectrum suitable for this purpose with up to 60 miles detection range possible. Although crude — massive and lacking the high degree of accuracy desired — this early VHF/UHF radar system was the foundation of early warning that later made a decisive contribution in winning the Battle of Britain in 1940.

In the 40s, British scientists Boot and Randall at Birmingham University successfully operated the first resonant cavity magnatron which generated high-powered microwave signals near 10,000 MHz which had such a short wavelength, that aiming them and concentrating them into a tight beam was easily possible with a relatively small parabolic reflector antenna.

After the war, early microwave radar equipment began to show up in war surplus stores, and were quickly scooped up by commercial boaters who wanted to be able to see what was happening out there ahead of them in the fog. The early radar A-SCOPES would show an oscilloscope-type readout with a horizontal line representing zero time delay to time delays up to 20 miles. The rotatable antenna was usually left in the forward position, and the mariner would peer at the scope and look for telltale "blips" that indicated something ahead that was reflecting the radar wave back a few microseconds later.

While this type of one-direction radar worked okay for boaters, it wasn't until the planned position indicator came along that radar really became a hit out on the water.

Some of the very first planned position indicating radars were from Decca, and two of the first inexpensive marine radars on the market were the Decca 101 and Decca 202. These radars offered up to 20-mile omnidirectional coverage at X-band frequencies 9415 MHz - 9475 MHz, 3.2 cm wavelength.

The antenna was an end-fed slotted waveguide array, four feet in length, and revolving at 24 revolutions per minute. This relatively small four-foot antenna offered a tight two-degree horizontal beam width (at -3 dB points half power), with side lobes down at least 23 dB. The vertical beam width was a comfortable 27 degrees which would allow the radar to work quite nicely on a small boat that might be pitching or rolling in moderate seas.

Transmitter power output was 3 KW peak power, with .1 microsecond nominal pulse length with a pulse repetition rate of 1,000 pulses per second.

The six-inch cathode ray tube for the earlier radars was similar to the construction of oscilloscope tubes — a phosphorous screen which would show a black background, and a relatively bright



What radar sees and what the chart looks like.

The marine 10 GHz radar antenna also contains the transmit and receive modules, too.

The radar transponder to improve target size on the screen.



Some X band antennas use slotted waveguides. Others use a printed circuit board (front right).



The very small Raytheon radar antenna contains the rotating arm, plus the transmitter and receiver, yet only weighs 13 pounds.

orange indication of echoes, as well as the orange straight-line sweep indicating the position of the antenna.

When echoes were received, they would be classified as "targets," going back to the early days of early warning radar in Britain. We still use the term "targets" today.

The phosphorous scope where the boat showed up in the center was called a planned position indicator. It indicated both target bearing, as well as target distance. And you could judge the size of the target by the intensity of the phosphorous target indication on the scope. If it was a big fat blob, chances are you were looking at a big steel-hulled vessel a few miles away. If it was a little tiny dot, it could be something as small as a little sailboat or power boat, or a small channel marker.

But the big phosphor scope in older radars required massive power supplies and major amounts of current for all the tubes inside the display unit. Tubes finally made way for transistors, and the transmitter receiver section of the radars were now small enough to eliminate waveguide and now go up into the actual turning antenna unit.

The modern pleasure boat marine radar of today still operates on those same X-band 9500 MHz frequencies. Power output is between 2,000 and 4,000 watts like the older sets, and the pulse length and pulse repetition rate (sometimes called pulse repetition frequency) is still about the same, but with more automatic variables depending on whether you are on a short-range or a long-range scale.

But now everything is relatively "battery friendly," with a 24-mile radar only requiring six amps of DC current at 12 volts, and an antenna T/R unit that weighs less than 50 pounds. The display unit has now switched from a phosphor scope over to a rectangular cathode ray tube using raster scan technology, and echo strength can be displayed either as bigger blob monochrome targets, or even color-coded targets with color CRTs available.

The switch from the old phosphor screen over to raster scan went almost unnoticed except for some old-time radar experts that liked the slow decay qualities of the old phosphor screen. The new raster scan displays needed small and powerful computer circuits to quantify the level of brightness of the displayed echoes. Four levels of display intensity were good, but eight were better. Small targets would show up as one tiny pixel, and a large target could consume as many as eight pixels in their relationship to the returned echo.

The capability of a CRT to define small targets with high resolution is dependent on their horizontal and vertical pixel capabilities. A 15-inch cathode ray tube radar display could provide as many as 480 horizontal and 640 vertical pixels, for a total of 307,200 pixels which is considered quite detailed and approaching the capabilities of what we originally had with an older phosphor screen which was not bound by pixel counts.

Most small boat radars feature either a green or orange target display, along with range rings and the heading mark plus cursor, all indicated over a black background. The raster scan display had a much better "look" when it came to nice sharp definitions over the older phosphor display, yet the older phosphor displays could still show some extremely small targets that the bigger raster scan display might consider as false echoes, and ignore.

About five years ago, a company called Apelco introduced a small boat marine radar with a liquid crystal display. It was an amazing performer, yet many radar "experts" felt that the LCD display could never have near the resolution as a CRT. And there were several years that a few pleasure boat marine radar manufacturers dabbled in LCD radar displays, only to find the review of their products mixed by boaters who had tried them in the sunlight, liked them at first, and then found that the display ultimately began to turn black as the sunlight heated up the LCD plate.

But one thing for sure — the LCD did a lot better job in the sunlight than the green or amber cathode ray tube. The CRT display had no place in the sun at all.

As LCD technology continued to produce improved plates that were much more tolerant to high temperatures, pixel counts on the LCD display plates for radars began to grow. You can now find a small six-inch diagonal screen using LCD technology to resolve 240 horizontal by 320 vertical pixels. The eight-inch LCD can show 480 horizontal by 640 vertical dots, for a total of 307,200 pixels, and the screen is almost identical in resolution to a larger cathode ray tube display for radar imaging.

Marine electronics giant Furuno (South San Francisco, CA; 415-873-9393) now has an eight-inch LCD display with a VGA-quality screen with 640 x 480 pixel count that rivals some of their present CRT radar displays. The Furuno display is totally waterproof and may be viewed in the direct



Radar line-of-sight.



"Picture in Picture" close-up box is common with raster scan LCD displays.

sunlight without turning dark. Furuno has also introduced an open-array antenna with this LCD display where other manufacturers were only offering a smaller antenna inside a radome.

The Furuno 41-inch rotating antenna has 4 KW of power driving it, and a 48 nautical mile range that allows you to see distant headlands, and plenty of power for the small commercial lobster boat to see his floating traps up to one-half mile away out on flat water.

Most pleasure boat radars operate between 2,000 watts and 4,000 watts output, so mariners are advised never to stand directly in line with the rotating antenna. Approximately five feet away is the recommended close-in safe distance. If the radar is well above their heads, all the better.

Radar range is line-of-sight to the horizon and objects beyond the ocean horizon. The calculations 1.22h allows you to calculate the radar horizon; h = the height of the radar antenna above the water. But you can do this in your head by simply taking the height of the radar antenna and figuring the square root for a distance to the horizon.

If the antenna is up 36 feet, it will see about six miles to the distant waves at the edge of the radar horizon. If a land mass is 500 feet tall, the square root of 500 is about 22 miles. Add 22 miles to the six miles of range you have to the horizon, and you have a total effective range to that distant land mass of just under 30 miles. If the radar you are using has a 24-mile range, you should begin to see the land show up at the maximum of its range.

But if you're running radar to stay away from other small boats, you could get as close as two or three miles to that other boat before it would show up on the screen. And when you run radar and look for breakwaters, the irregular rocks will many times scatter the signal, so you won't see the complete line of rocks on your radar scope until you are about three miles away.

On calm days, a properly running pleasure boat marine radar should be able to pick up big birds sitting on the water. I have even seen turtles floating in the water at about 1/8th of a mile away on radar in flat seas. But when the seas get rough, wave return will cause "popcorn" on the screen, and any small echoes will now blend in with all of the interference, and you won't know what is wave return from something really out there.

Radar reflectors will dramatically help return as much radar energy as possible as an echo because of the 90-degree corners. Small boats should always fly a radar reflector to intensify their signal on another radar scope.

The United States Coast Guard runs radar transponders on certain harbor approach buoys and bridges. These are known as RACONs, and they show up as an intensified target with Morse Code dots and dashes emanating out from the target for positive ID. Mariners would look on their marine charts and identify the Morse Code seen on the screen with a specific RACON listed with that same Morse Code identifier. But the radar must be in the full sensitivity mode with all interference filters turned off in order to get this special radar echo.

Another type of radar transponders found out on the water are called search and rescue transponders (SART). When these transponders sense radar X-band reception, they intensify their own target echo with the transmitted signal along with a series of dots emanating out from the SART activation. The SART is intended for man-overboard or sinking situations where rescue boats are trying to home in on faint targets seen on the radar scope. The telltale sign of SART reception would be the six dots seen going away from the actual radar target on the screen.

And brand new for the boating community is the active radar intensifier transponder called RTE (radar target enhancer). This European device is manufactured by McMurdo (Portsmouth, Hampshire, United Kingdom; 44(0)1705 775044). It operates between 9300 and 9500 MHz X-band radar frequencies, and has a typical conversion gain of 58 dB with a radiated power output of .8 watts typical. This device electronically amplifies the radar echo, thus imitating a much larger vessel. When compared to a passive radar reflector, this radar transponder may sometimes lead to reception range of up to 10 miles, whereas the reflector might only be seen up to five miles.

The device consists of an antenna unit that goes atop a sailboat or power boat antenna or mast, and an indicator unit which sounds off when radar activity is detected within 10 miles or more. Or less. You know when this unit detects radar because it automatically swings onto the transponder mode.

Many major harbors in the United States are also served by the radar vessel traffic system. Shore-based radars will monitor the shipping activity around a busy port, and will announce ship movements over the VHF marine channels, usually Channels 12 or 14. If the vessel traffic system detects an impending collision, it will closely watch their radar screens while guiding commercial shipping onto a safer course. Recreational vessels are encouraged to tune into the vessel traffic system frequencies, too.

Although mariners don't have the sophisticated transponders that private pilots now have, it appears that marine radar and marine radar systems are getting more sophisticated for the water. It's long overdue, and radar is certainly one way to find out what's happening all around you when the fog sets in, and visibility drops to zero zero. **NV**

Metric
Equipment Sales, Inc.

800-432-3424
Fax: 650-341-8874
www.metricsales.com

RENT • BUY • SELL
Yes, we will buy your surplus equipment!

Scopes, Meters, Analyzers, Power Supplies, Signal Generators, Counters, Recorders and more

Hewlett-Packard, Tektronix, Fluke, Dranetz, TTC, Anritsu, Wavetek, Keithley, and more

Test & Measurement Instruments

Over 7000 Models • 6-Month Warranty
Save 30-90% • 5-Day Free Trial

Write in 54 on Reader Service Card.

HF SSB RECEIVER



R-1051B RECEIVER, covers 2-29.9999 Mhz AM-CW-LSB-USB-ISB using six decade band tuning + vernier; 500 Khz IF. Meters and controls for LSB & USB Levels; also BFO, 600 ohm audio & 50 ohm input impedance. Solid-state except for 3 tubes. Requires 115 VAC 50-400 Hz; 7x17.4x18.9, 85 lbs sh.
USED-CHECKED ..... ~~$650~~ **$350**

MANUAL for R-1051B, partial repro ..... **$45** **SHOCKMOUNT, NEW** **$22**
R-1051G, later IC-version of above, **CHECKED** ..... ~~$795~~ **$625**

RECHARGE BATTERY PACK

LEAD-ACID BATTERY PACK with CHARGER, two BB-490 military batteries each rated 24 VDC (2x12 VDC) 1.8 A-Hrs @ 0.35 amps; 1990 dates. AMS-H6 charger fits on BB-490; shows "charging" or "ready" on LED's. MPS-CH2 charger power supply output 10 VDC 1.8 A from 115 V 60 Hz input. BB-490 used in PRC-104-117, etc radios; 4.3x5x2.5. **Kit 9 lbs. sh. NEW** **$12.95**

ENERGY STORAGE

NON-PCB CAPACITORS; 10x4.5x3.5, 10 lbs sh; 32 MF 4500 VDC, used, ... ~~$36.00~~ **$30.00**
88 MF 1200 VDC, used ..... **$17.50** **224 MF 1500 VDC** **$27.00**
9 MF 4 KV case ground; 8.3x3.5x2, 7 lbs sh ..... **Used $10.00**
27 MF 700 VAC, 9.3"Hx4.3"Wx2.7"D, 8 lbs. Captron, NEW **$7.50**

Prices F.O.B. Lima, O. • VISA, MASTERCARD Accepted.
Allow for Shipping • Write for latest Catalog
Address Dept. NV • Phone 419/227-6573 • Fax 419/227-1313
E-Mail: fairadio@wcoil.com H-Page: http//alpha..wcoil.com/~fairadio/

FAIR RADIO SALES
1016 E. EUREKA • Box 1105 • LIMA, OHIO • 45802

Write in 92 on Reader Service Card.

COMPUTER CIRCULATION CENTER, Inc.

dba: Alltech Electronics

2618 Temple Heights Drive.
Oceanside, CA 92056
Phone Order Hours 9AM - 5:30PM Mon- Fri

Phone Orders
760/724-2404
www.allelec.com

3 Southern California Locations!
World Wide Web http://www.allelec.com
1401 El Camino Real. Oceanside - 760/721-0093
1300 E. Edinger. Santa Ana - 714/543-5011
2018 W. Lomita BLVD. Lomita - 310/539-2260
We buy surplus & unwanted computer inventory as well as scrap electronics related inventory.

Mac/Powerbook Accessories

Macintosh IIfx MOTHERBOARD, CASE, & POWER SUPPLY. NO RAM or Floppy Drive	$119.00
External Video Adapter Cable (Not for 100, 140 or 170)	$12.00
Kensington ADB 10-Keypad (good with any MAC)	$19.00
Asante Micro SCSI/EN Ethernet for Power Books	$49.00
Powerbook 100-180Series Replacement AC Adapter (Apple Brand)	$24.00
Apple Plaintalk or Standard Microphone (Power Macs Req. Plaintalk)	$9.00
Level 2 256K Cache (for PPC 6100, 7100, 8100)	$19.00

Computer Parts
Accessories
Surplus Electronics
Qty. Discounts Available
Govern. & Educ POs accepted
Apple II / Mac / IBM

DEC ColorWriter 520ic
Refurbished Printer
Parallel Version

$129.00

digital

Seagate TapeStor 800 & 3200 Tape Backups

Up to 400 MB Uncompressed /
800 MB Compressed (2:1)
$49.00 Internal 3.5" Version
$69.00 With one Tape Cartridge
Add $3.95 for 5.25" Adapter
Seagate TapeStor 3200 TR-3 .....$69.00
These are refurbished in-house and carry a 90 Day Warranty

MONTHLY SPECIAL



Contains One Cold Cathode Fluorescent Tube, (5.5 inches)
Requires 1,500 VAC DC Inverter board to light. Backlit area is 5.25 x 8.5 inches.
Repair your laptop & save!
Great for experimenters!

LCD Backlight $19.00

External Drive Cases

$19 to $45.00



All SCSI Cases have 2 50 Pin Centronics connectors and 30 Watt P/S. **Open Face** has RCA's for CD Audio

1 HH 5.25" **SCSI** (Open Face)	$35.00
1 HH 5.25" or 3.5" **SCSI** (Closed Face)	$29.00
2 CD's or SyQuest Side by Side	$45.00
2HH or a Full Height SCSI Case	$45.00

System

486 DX2/ 66
W/NEW Monitor

SlimLine Case
Includes *NEW* SVGA Monitor
w/16megs of RAM
120meg Hard Drive
1.44 Floppy Drive
NEW Keyboard, Mouse & Monitor
System unit is refurbished.

$339

Chips & ROMs

Intel P75 (pulls)	**$55.00**
Intel P90 (pulls)	**$69.00**
Intel 486 SX -25	**$4.95**
Intel 486 SX-33	**$7.00**
Intel DX-25	**$7.00**
Intel DX-33	**$12.00**
Intel 486 DX/2 -50	**$20.00**
Intel 486 DX/2-66	**$35.00**
AMD 486SX/2-66	**$14.00**
80287-8	**$19.00**
80387DX-33	$19.00
82450	$2.00
8250	$1.00

RAM Chips

4Meg x 9-80	$27.00
1x32-70	$19.00
2x32-70	$39.00
4x32-70	$79.00
1 meg x9-10	$4.00
1 meg x9-80	$6.00
256k SIMMS (80or 70ns)	**$2.00**

20/40 Meg 1.3 Inch IDE Hard Disks

Mini IDE Hard Disk!



20 Meg $7.95
40 Meg $14.95

Cable Adapter $4.95

These have the same connector as a 2.5" IDE but are the size of a small box of matches.
See our web site for more details.

Power Supplies

Mini Tower 145 Watts.	$12.00
Mini/Mid Tower 200W	$19.00
XT Power Supply 150W	**$15.00**
Remote wired w/Side Switch AT Power Supply. 200W	**$19.00**

Monitors

10" Open Frame VGA

10" Open Frame VGA Color Monitor....$149.00
Open frame composite 9". B&W Monitor assembly. Build your own monitor.....**$19.00**
9" B&W Security Monitor. "Box" type with 75 Ω input.....**$59.00**
9" Composite "Box" type cabinet. Green screen. Good for **security monitor.** Input for 75Ω (standard) or High impedance**$35.00**
Color Composite Monitor. Not suitable for 80 column text but can be used for computer games, Nintendo, as a video monitor. Some have sound input also. Please Specify.....**$69.00**

EPROMs

2716 or 2732	$0.75
2764/27128/27256	$1.50
27512, 271000,	$2.00
27040	$3.00

SCSI CD ROM

2x External NEC	$59.00
2x Internal NEC	$35.00
4x External Toshiba	$85.00
4x Internal Toshiba	$59.00
Apple CD (2x) 300i Int.	$45.00

PC Cards & Accessories

9 Pin Serial Mouse	**$5.95**
PS2 HP/Logitech Mouse	**$9.00**
MicroSoft InPort Bus MouseCard & Mouse	**$12.95**
CGA/EGA Video Card	$19.00
VLB I/O Card	$12.95
VGA VLB Card 1 Meg.	$19.95
VGA VLB Card 1 Meg upgradable to 2meg.	$25.00
AT MFM HD Only Controller	**$9.95**
AT 2 Meg Mem. Exp Card w/2 Meg	**$19.00**
RAM Sack III AT/386 up to 8 Meg card (0K)	**$19.95**
AT Floppy, Serial & Par Controller	$9.95
Super I/O IDE, Floppy, 2 Serial, 1 Parallel	$14.95
AT MFM HD & Floppy Control	$14.95
Full Length CGA w/RCA out	$14.95
101 XT/AT Keyboard(Refurb.)	$9.00
101 AT Keyboard (NEW)	**$14.95**
Slot Expanders (3,4 or 5 Slot, for slim type PC cases) Installs in single slot and rises vertically	$9.95
XT Motherboard	$9.95
AT Motherboard w/1024K	$29.95
50Watt DC/AC Power Inverter	**$19.00**
Flip Phone Accessory Kit	**$19.00**

There is a $25 Minimum order for Mail Orders.
All prices and availability are subject to change without notice.

HTTP://WWW.ALLELEC.COM

VISIT OUR WEB PAGE DAILY FOR SPECIALS & MORE INFO. ON THESE ITEMS

CA Residents please add 7.25% Sales tax. • Minimum shipping & handling charges $8.50. • Warranty: Used/Refurbished products have a 90 day warranty • ALL Returns must have an RMA #, call before shipping back to us. • No Returns without an invoice. Shipping & Handling charges are non-refundable • 20% Restocking charge, applies to products purchased in error & incompatibility problems. School & University Purchase Orders accepted, others on AOC only. • Prices and availability subject to change at anytime without any notification whatsoever.

Javanco

The Electronics "Five & Dime"!

40,000 FT² OF REAL BARGAINS

- computer parts
- misc software
- TV/VCR service parts
- ICs
- sockets
- tubes
- transistors
- diodes
- LEDs
- telephone parts & acc.
- resistors
- capacitors
- switches & relays
- connectors
- tie-wraps
- batteries
- fuses
- crystals
- oscillators
- fans, meters
- speakers
- wire & cables
- obsolete parts
- equipment racks
- knobs & hardware
- circuit boards
- subassemblies
- neat "junque"

We have one of the largest selections of common and "hard to find" integrated circuits available. Check out our huge inventory of new and used computer equipment. We offer quick turn-around order processing. Call us first for the best selection and lowest price!

Call or write for a catalog

Orders only: 1-800-JAVANCO (528-2626)
(615) 244-4444
BBS: (615) 244-4445 Fax: (615) 244-4446
http://www.javanco.com

VISA MasterCard Discover

501 12th Avenue South - Nashville, TN 37203
Hours: 8:30a-5:30p CST M-F 9a-1p CST Sat

Write in 217 on Reader Service Card.

TEST EQUIPMENT *cont.*

HP 6940B multiprogrammer with 59500A interface, timer, scanner, and A/D cards, manuals, $300; 3722A noise generator, $150; 5314A counter, $75. **Leeds and Northrup:** 7553 (K-3) potentiometer, 8687-1 potentiometer, 4395 voltage divider, $60 each. **General Radio:** 1551B sound level meter with 1262B power supply, $150; 1219A pulse amplifier, $35; **Krohn-Hite** filter, $100. **General Microwave** 451 power meter, $35. **Gould** K100D, as-is, $50. Kent, 515-232-7528.

Are you missing any issues of Nuts & Volts?

Back issues are available for only $5.00 each!

Call our orderline at 800-783-4624 and use your Visa or MasterCard. Price includes First class postage.

NERDY PROFESSOR seeks equipment and will pay reasonable amount. Please E-Mail: kovacs@cis.stanford.edu if you have for sale: HP 9100A, 9815A, 9825A, 67 or 97 calculators, HP 5062 cesium beam clock, HP 43805 shielded cabinet x-ray system, HP 41201A oximeter, HP 970A handheld multimeter, Tektronix model 31 calculator, HP quartz thermometer probes or readout units.

CURVE TRACER SALE; TEK 577/D2 (LESS 177 PLUG) $450; TEK 577 D2/178 $900. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

TEKTRONIX PLUG-INS: AM 502, 7A22 high-sensitivity differential amplifiers $350, $290. **AM 503 & A6302** current probe & amplifier $850. **FG 504** 40MHz function generator $675. **TR 503** tracking generator $850. **5D10** waveform digitizer with readout $295. **7CT1N** curve tracer $350. **7D20** digital storage $650. **7S12, S-6, S-52** time domain reflectometer $1,350. **7S14** 1GHz sampler $575. Excellent condition! Mainframes and many other plug-ins available too. All with warranty. Pepper Systems, 214-353-0257.

CARL'S ELECTRONICS

OVER 200 ELECTRNONIC PLANS AND KITS, INCLUDING THE LATEST INFO ON CABLE AND SATELLITE DESCRAMBLING.

SURVEILLANCE
LASER WEAPONS
AND MUCH MORE

HTTP://WWW.ELECTRONICKITS.COM
PHONE(978)840-8834
FAX(978)-840-6172

CALL FOR A FREE CATALOG

24DOT7, Inc.

www.24dot7.net

Co-location
Web-hosting
Virtual Stores
Internet Malls
Secure Server for
Credit Card
Transactions

Put your
Company on
the
INTERNET

FAST and EASY with 1 Call
Full T-1 access

800-941-7715

Discount Computer Systems - SHOP US LAST !

Intel Pentium P166MMX MZH Multimedia System

Systems include:

Mid TW. CASE, MB W/VX CHIPS 512 CACHE, 16MB EDO RAM, 1.7 GB HARD DRIVE, 12X CD ROM, 1MB 64 BIT PCI VIDEO CARD, 3.5" 1.44MB FD, 16 BIT 3D SOUND CARD, 33.6 FAX MODEM WITH VOICE, WIN 95 MOUSE, WIN 95 104 KEYBOARD, 80 WATT SPEAKERS, WIN 95 REL. 2, 14" SVGA MONITOR INCLUDED

$1185

Intel Pentium P200MMX MZH Multimedia System

Systems include:

Mid TW. CASE, MB W/VX CHIPS 512 CACHE, 32MB EDO RAM, 2.5 GB HARD DRIVE, 16X CD ROM, 2MB 64 BIT PCI VIDEO CARD, 3.5" 1.44MB FD, 16 BIT 3D SOUND CARD, 33.6 FAX MODEM WITH VOICE, WIN 95 MOUSE, WIN 95 104 KEYBOARD, 80 WATT SPEAKERS, WIN 95 REL. 2, 14" SVGA MONITOR INCLUDED

$1499

Intel Pentium P233MMX MZH Multimedia System

Systems include:

Mid TW. CASE, MB W/VX CHIPS 512 CACHE, 32MB EDO RAM, 3.5 GB HARD DRIVE, 16X CD ROM, 2MB 64 BIT PCI VIDEO CARD, 3.5" 1.44MB FD, 16 BIT 3D SOUND CARD, 33.6 FAX MODEM WITH VOICE, WIN 95 MOUSE, WIN 95 104 KEYBOARD, 80 WATT SPEAKERS, WIN 95 REL. 2, 14" SVGA MONITOR INCLUDED

$1775

Also: 266 MZH System Available at Similar Savings! See AD MART

800-804-6552 All Software Loaded & Tested

VISA MasterCard

Write in 138 on Reader Service Card.

TEKTRONIX 492 50KHz-21GHz SPECTRUM ANALYZERS with options 1,2,3. Calibrated. $6,850. **EIP 931.01-20GHz SWEEPER** $6,500. **WATKINS-JOHNSON WJ-1250A .01-18GHz FREQUENCY SYNTHESIZER** with programmable sweep $5,450. **BALLANTINE 6127A OSCILLOSCOPE CALIBRATOR $875. FLUKE 515A PORTABLE METER CALIBRATOR $895. ESI 242B RESISTANCE CALIBRATOR $1,650. ESI 242D $3,450. 90-DAY WARRANTY. VISA-MasterCard/AMEX accepted. 760-439-1345 or 1-800-TO-BUY-TE.** Webpage: http://www.angelfire.com/biz/telist/index.html

FREQUENCY COUNTER SALE: HP 5328A/021 $350; HP 5328A/20/30 $350; HP 5328A/10/31/41 (1.3 GHz) $450. AST GLOBAL ELECTRONICS. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

TEKTRONIX PLUG-IN SALE: HUNDREDS OF 7000 AND 5000 SERIES PLUG-INS UP TO 50% OFF. VIEW COMPLETE LIST AT OUR WEB SITE: a-mall.com or CONTACT: AST GLOBAL ELECTRONICS. 24529 State Highway 408, Cambridge Springs, PA 16403. Voice: 1-888-216-7159; Fax: 814-398-1176; E-Mail: astmrktg@toolcity.net

SECURITY

REMOTE ZOOM lens, 15-150mm, F2.8, Canon V10X15RDC, C-mount, like new, $160. 310-454-4203.

PROFESSIONAL ALARM control panels and all equipment. For a free catalog: voice or fax: 908-840-1390.

PAGER OWNER! Use your pager as a security monitor to monitor your burglar alarm and telephone answering machine using Pageout automatic paging system $99.99. Other systems available. Call 410-483-6211. http://www.worldprofit.com/maateez.htm

VIDEO QUAD SPECIALS-American Dynamic Quad Multiplexers AD-1472-4 Cam B/W Quad reg. $410, NOW $240; AD-1473-Real Time Quad reg. $525, NOW $325; AD-1475A-8-Cam Real-Time 2-page Quad $375; AD-1476-Hi-Res 8-Cam W/ZoomR $800, $450; AD-1484-16Cam B/W multiplexerR $1,250, $550. **ALSO AVAILABLE: DIGI-QUADS+ COLOR (QUADS+ MULTIPLEXERS.)** Quan. lim. B-Stocks. **PRO-VID SYS. 781-933-0827.** Don't buy junk.

SATELLITE EQUIPMENT

FREE BIG dish catalog. Low prices! Systems, upgrades, parts, and "4DTV." Skyvision, 1016 Frontier Dr., Fergus Falls, MN 56537. www.skyvision.com **Call 1-800-543-3025.**

USED SATELLITE EQUIPMENT. You name it, we have it. LNAs, downconverters, drives, receivers. Working condition guaranteed. Call 765-385-2305.

BEST PRICING on 18" satellite TV systems for home and RV. DSS, DISH Network programming, multi-room viewing options, accessories. www.skyvision.com **Call 1-800-543-3025.**

SATELLITE EQUIPMENT available: Receivers $35 and up; 20-25 LNB $35; C-KU feed horns $65. Call 757-599-4408.

Save Big On Pre-Owned And New Equipment — Best Buys!!

Your Best Source For Bruel & Kjaer. We Buy And Sell!!!

Equipment From Such OEMs As:
Tektronix · Hewlett-Packard
Fluke · GenRad · Keithley · Hitachi

All equipment warranted and calibrated with CERTS upon request.

We Accept MasterCard and Visa

Excalibur Engineering, Inc.

3198-C Airport Loop Dr.
Costa Mesa, CA 92626
714-540-0169 FAX 714-540-5417
E-Mail: excalengineering@worldnet.com

Write in 177 on Reader Service Card.

EZ-EP DEVICE PROGRAMMER - $169.95

Check Web!! -- *www.m2l.com*

Fast - Programs 27C010 in 23 seconds

Portable - Connects to PC Parallel Port

Versatile - Programs 2716-080 plus EE and flash (28F, 29C) to 32 pins

Inexpensive - Best for less than $200

- Correct implementation of manufacturer algorithms for fast, reliable programming.
- Easy to use menu based software has binary editor, read, verify, copy, etc. Free updates via bbs or web.
- Full over current detection on all power supplies protects against bad chips and reverse insertion.
- Broad support for additional devices using adapters listed below.

Available Adapters

EP-PIC (16C5x,61,62x,71,84)	$49.95
EP-PIC64 (16C62-5,72-4)	$39.95
EP-PIC12 (12C50x)	$39.95
EP-PIC17 (17C4x)	$49.95
EP-51 (8751,C51)	$39.95
EP-11E (68HC11 E/A)	$59.95
EP-11D (68HC711D3)	$39.95
EP-16 (16bit EPROMS)	$49.95
EP-Z8 (Z86E02,3,4,6,7,8)	$39.95
EP-SEE2 (93x,24x,25x,85x)	$39.95
EP-750 (87C750,1,2)	$59.95
EP-PEEL (ICT22v10,18v8)	$59.95
EP-1051 (89C1051,2051)	$39.95
EP-PLCC (PLCC EPROMs)	$49.95
EP-SOIC (SOIC EPROMs)	$49.95
EP-TSOP (TSOP EPROMs)	$59.95

Many Other Adapters Available



M²L Electronics
310/837-7818
Fax/BBS: 310/841-6050
3526 Jasmine #4;
Los Angeles, CA 90034
CA orders please add 8.25% sales tax.
http://www.m2l.com

Write in 99 on Reader Service Card.

Digital Storage Oscilloscopes

From $189?

ATC modules connect to your PC printer port and transform it into a full-function DSO, spectrum analyzer, logger, & DVM. Units DC to 25MHz



Captured Waveforms Pico Tech ADC-200 in Windows

O-Scope II in DOS

ATC proudly announces the addition of Pico Technology Ltd. products to our product line. Pico is based in Britain and offers a variety of data logging and virtual instrument modules.

O-Scope Ip (ST 50KHz).....$189
O-Scope II (DT 500KHz).....$349
ADC-100 (DT 12bit 50KHz)..... $449
ADC-200/20 (DT 10MHz).....
ADC-200/50 (DT 25MHz)..... CALL
Loggers 1-22 ch. (8-16 bit) from $99
Shipping UPS $7.50 grnd, $11.50 (2 day)

800-980-9806
Allison Technology Corporation
8343 Carvel, Houston, TX 77036
Fax: 713-777-4746 Technical: 713-777-0401
BBS: 713-777-4753 **email: atc@accesscomm.net**
http://www.atcweb.com

DSS SURPLUS WANTED. Receivers, remotes, old & new access cards, antennas, feeds. Message/fax 561-483-8516. E-Mail: cable@flinet.com

SUBSCRIBE TO the North Star Gazer satellite related newsletter! Published monthly, we offer industry news, technical tips, full reports on the happenings in the satellite TV underground, & more! $48 per year. North Star, PO Box 1023, Lapeer, MI 48446. 810-664-4022 FAX: 810-664-0351

DSS TEST CARD information. Call toll free, 1-888-416-7296.

GET SOUND for VCII and VCII Plus without codes. Free detail. Send SASE to: Nassirian, Box 382-V, Rio Linda, CA 95673.

BEST PRICES for DSS components and accessories. New dual LNBFs $59.95, 3X4 multiswitch $49.95, diplexers $5.95. http://www.flash.net/~dmsi DMS Toll Free: 1-888-591-4416 Fax: 770-591-0249

MICRO VIDEO CAMERAS



MB-750U
Video Camera

$99.95

Inset shown with optional, PMC-1 Power & Video connection Cable.





MB-705UX
C-Mount Camera with Lens Included; 8 or 12mm Lens your choice!

$119.95

Inset shown with optional, PMC-1 Power & Video connection Cable.



MB-750P
Pinhole Camera

$129.95

Inset shown with optional, PMC-1 Power & Video connection Cable.





LIPSTICK CAMERA

LP-850i Video camera. Supplied with a PCM-1 Video/Power cable. The RCA female connection is for standard video connection to a Monitor or VCR, Video signal -75 ohms at 1 volt peak to peak NTSC. The power is supplied to the camera by a 2.1mm barrel connector, 12 VDC center positive. Insure your power supply can deliver well regulated DC voltage. We suggest our part number PS-01.

$249.95

New Catalog Available for All Models.

A-5060
Color 4" & 6" TFT-LCD TV / Monitor. Portable and Handy to take along anywhere. Employs, AC/DC adaptor, Earphone jack, A/V Input, and Diversity jack. External Antenna jack. Video Mute, Bar search function and Remote control.
A5040 *$349.95*
A5060 *$605.95*

1-800-752-3571

Visit Polaris Ind. Web Site at: http://www.polarisusa.com

Polaris Industries 470 Armour Drive NE • Atlanta GA 30324 • *Tech Info: 404-872-0722* • FAX 404-872-1038

Prices, availability and specifications are subject to change without notice. Shipping and Handling are not included with price.

Write in 188 on Reader Service Card.

by Thomas Henry

Build Your Own MIDI-to-Synthesizer Interface

Flip through any music or recording magazine and you'll find constant reference to the fact that we're in the midst of an analog synthesizer revival. Indeed, more and more musicians are dusting off their favorite instruments of yesteryear and hauling them into the studio or onto the stage again.

The claim is that these old analog synthesizers have a richer and warmer sound than their modern digital counterparts. The only trouble, though, is that analog units are voltage-controlled, whereas virtually all modern recording and performing equipment is MIDI based.

MIDI is a standard protocol that permits the interconnection of a broad range of musical devices, and then lets them communicate with each other via a digital bit stream.

Well, don't give up on your analog synthesizer just yet, for here's the MTS-100! The MTS-100 is an inexpensive monophonic MIDI-to-Synthesizer interface which lets you add digital control. With it, it's a snap to connect a modern music keyboard or a personal computer running sequencer software to your dinosaur.

The MIDI messages coming down the pike are converted to standard control voltage, gate and trigger formats, perfect for taming most older equipment. And just check out these features:

- MIDI IN and THRU jacks
- 1V/octave control voltage output
- Pitch bend (pitch wheel) control voltage output
- Independent gate and trigger outputs for full retriggerability
- Omni on or off switch and indicator
- Channel switch and indicator
- Recognizes a variety of MIDI Channel Mode messages
- Octave transpose switch extends response with short keyboards
- Fits behind an industry standard 1U rack panel (1-3/4" by 19")

But if you really want to know what the MTS-100 can do, then check out its Implementation Chart in Figure 1. By custom, each piece of MIDI gear is supposed to be provided with just such a chart. It's really nothing more than a standardized way to explain what MIDI features are available, what messages are recognized, etc. Take a moment to review it. After you get a feel for what to expect, then read on to see how the MTS-100 works.

CIRCUIT DESCRIPTION

Since the MTS-100 is really little else than a glorified digital-to-analog converter (DAC), it's convenient to split the schematic into two main parts. In broad terms, Figure 2 depicts the digital side of things, while Figure 3 shows the analog portion.

Refer to Figure 2 now. If you're getting a sense of deja vu, there's a reason! You might recall my ADV-MIDI project which appeared in the Oct. '97 issue of *Nuts & Volts Magazine*.

The purpose of that circuit was to convert incoming MIDI messages to triggers suitable for firing analog drum sets. As it turns out, quite a bit of the input circuitry can be copied over directly. So, we can really buzz through the explanation now. The basics will be described here, but if you need more details or want to refresh your knowledge of MIDI, refer back to the article just mentioned.

A source of MIDI messages (coming from a music keyboard, sequencer, personal computer, etc.) is applied to jack J5. Optocoupler IC1 isolates and translates the electrical signal as required by the MIDI specification. A suitable replica of the bit stream is generated at output pin 6 of IC1.

One path conducts this bit stream directly to input port line PA7 of the MC68705P3 microprocessor. (For brevity, this chip will be referred to as the 68705 from now on.) The bits roll in to the microprocessor one at a time and are properly reassembled into a complete byte under control of the firmware residing within the chip.

Function		Transmitted	Recognized	Remarks
Basic	Default	***	1	
Channel	Channel	***	1-16	note 1
	Default	***	Mode 4	
Mode	Messages	X	Modes 2 or 4	note 2
	Altered	***	Modes 2 or 4	note 3
Note		X	O	
Number	True Voice	***	0-127	note 4
Velocity	Note ON	X	X	
	Note OFF	X	X	
Aftertouch	Key	X	X	
	Channel	X	X	
Pitch Bend		X	O	
Controllers		X	O	note 5
Program		X	X	
Change	True #	***	***	
System Exclusive		X	X	
System	SPP	X	X	
Common	Song Select	X	X	
	Tune Request	X	X	
System	Clock	X	X	
Realtime	Commands	X	X	
Aux	Local ON/OFF	X	***	
	All Notes Off	X	O	note 6
	Active Sensing	X	X	
	Reset	X	O	note 7

Notes:
1. At power-up or during reset, switch S2 can set the MTS-100 to receive on any channel (1-16).
2. The MTS-100 can be set to Omni Off or Omni On either by front panel switch S1, or by an appropriate Channel Mode Message.
3. The MTS-100 is a monophonic device, but is compatible with any MIDI keyboard even if polyphonic. In this case, it simply responds to the most recent Note On message.
4. The MTS-100 can convert all 128 MIDI notes. If using a short keyboard, switch S3 can transpose notes up or down by one octave to extend the output range.
5. The following Channel Mode messages are recognized: Reset All Controllers, All Notes Off, Omni Off, and Omni On. Reset All Controllers sets the pitch bend output to its midposition value.
6. Sending the Omni Off or Omni On commands also turns all notes off, as required by the MIDI 1.0 spec.
7. The current channel can be changed during the Reset sequence, if desired.

Mode 1: Omni On, Poly Mode 2: Omni On, Mono O: Yes
Mode 3: Omni Off, Poly Mode 4: Omni Off, Mono X: No

Figure 1 — The MTS-100 Implementation Chart



Figure 2 — MTS-100 Schematic 1 of 2



Figure 3 — MTS-100 Schematic 2 of 2

Note: All of the grounds in this figure are "analog grounds," except where noted. All of the grounds in *Fig. 2* are "digital grounds." Digital ground and analog ground must connect at one point only.

Pin 6 of IC1 also feeds MIDI THRU jacks J6 and J7 by means of the buffers configured around IC2c and IC2d. Again, this is a standard arrangement described in the MIDI specification. The MIDI THRU jacks can be used to daisy chain other equipment to the MTS-100.

Since the MIDI messages are asynchronous in nature (i.e., can occur at any time), microprocessor interrupts are used to dictate when data is to be read in. Once a message is rolling in, it is important that the 68705 not be further interrupted. Thus, IC2b is used to pass or block external interrupts to pin 2 of the 68705, as required.

Switch S1 and LED D5 work in tandem to let the user turn Omni mode on or off from the front panel. Port line PC2 of the 68705 is normally high. Tapping pushbutton S1 once causes this line to momentarily drop low. The microprocessor senses the change and toggles the condition of the Omni status, as well as LED D5.

Obviously when the LED is shining, Omni mode is on, and when it is dark Omni mode is off. By the way, you can also turn Omni on or off by sending the standard MIDI Channel Mode message. The LED will still respond as just described.

S2 and D4 also work as a team, in this case to set or test the current channel. At power-up or during reset, the channel defaults to 1. But you can change it to any legal value (1-16) in the following way.

First, with power to the MTS-100 off, press and hold pushbutton S2. Now turn the power on. LED D4 will begin flashing, about once per second. Simply release the pushbutton after witnessing the desired number of blinks, representing the channel. For example, to set the MTS-100 to channel 5, hold S2 closed then turn the power on. After five blinks, release S2.

Once you're up and running, you can also use pushbutton S2 to check what the current channel is, in case you've forgotten it in the meanwhile. Simply tap the switch once. The LED will flash the number of times representing the current channel number. This is a very simple, yet effective method to set or test the channel. And best of all, it uses very little front panel real estate!

Switch S3, which connects to the 68705 port lines PC0 and PC1, can be used to transpose the currently played note up or down by one octave. This is handy if you are driving the MTS-100 with a smaller keyboard which spans less than the 128 notes of the standard MIDI scheme.

If the lowest note on your keyboard is number 36, for instance, then by flipping S3 to the minus position, the internal firmware automatically subtracts 12 (a one octave difference) and spits out the number 24 to the

DAC.

In a similar way, putting S3 to the plus position will add 12. In effect, your short keyboard has now gained an octave on both the low and high ends. By the way, the firmware takes care of any potential goofiness should you attempt to transpose a note out of range. In this case, it's simply left as is and passed on to the DAC unchanged.

The envelope generators in an analog synthesizer require a source of keyboard gate and trigger signals. A gate should normally be at 0V, but swing to +5V and stay there whenever a note is to be sounded. On the other hand, a trigger is a 0V to +5V pulse, several milliseconds wide. It is generated at the outset of a note, and can also be retriggered under certain other conditions.

For example, suppose you have pressed a key on a music keyboard for the first time. A trigger is created. Now imagine that you keep that key depressed and play another one in addition to it. The current note number is updated to the new value of course, but more importantly, another trigger is fired off as well.

What this means is that the MTS-100, like all good quality synths from the past, lets you use the musical technique known as a "trill." You can twiddle an extra note in addition to the currently held one and the envelope generator in the synthesizer will be automatically retriggered.

By the way, the description just given implies that the MTS-100 follows what is known in music circles as the "last note rule." This means that if you press more than one key, the unit will always respond to the most recent one. And of course, there's no such thing as "simultaneous" in MIDI, so one of the notes will always be the most recent!

The gate signal is created by port line PB0 of the 68705. During quiescence, this line is high, which keeps transistor Q2 turned on. This implies that the tip of jack J2 is at 0V as expected. (Also notice that LED D3 is off). But when the line goes low in response to a note number coming in, D3 shines and J2 goes to +5V.

The trigger signal is only slightly more complicated to create. When it's time for a trigger, port line PB1 swings low long enough for LED D2 to be plainly visible. At the same time, C8 and R30 differentiate the pulse, and Q1 squares it up nice and neat. What comes out of J1 is a good looking rectangular waveform, about five milliseconds wide.



Figure 4 — Foil Side of the MTS-100 Printed Circuit Board



Figure 5 — The MTS-100 Circuit Board Parts Placement Guide

There are 15 jumpers. Each is represented as a solid line connecting two points.

And that pretty much wraps up the digital side of things in the MTS-100. Before leaving Figure 2, however, notice that port lines PA0 through PA6, and PB4 and PB5 haven't been accounted for yet. They'll resurface as we investigate how the analog portion of the MTS-100 works. So let's move on.

Turn your attention to Figure 3 now. When a note number is received by the 68705 from the MIDI input, it is transferred to IC4 via port lines PA0 through PA6. Notice that one of the bit inputs of the DAC (pin 5) is tied to ground and not used. This is because the MIDI spec dictates that note numbers should run from 0 to 127, which only requires seven bits to represent.

The DAC needs a stable current reference for operation. So, resistor string R6, R28, and R29 first create a tapped voltage. R28 is actually a trimmer potentiometer. This will let you tweak the MTS-100 for a precise 1V/octave response. (Virtually all of the better analog synths follow this standard). Electrolytic capacitor C18 stabilizes things a bit. But more importantly, the follower composed of op-amp IC6b buffers the tapped voltage and provides a good, low-impedance output source.

The voltage at the output of IC6b is converted to a current by R14, which then feeds the positive reference input of the DAC at pin 14. Incidentally, R15 is of the same value and is used to balance the negative reference input at pin 15 of IC4.

The output of the DAC is a current; it flows from pin 4. This needs to be converted to a voltage before proceeding and that is the purpose of R25 and IC6a. As mentioned earlier, the voltage will follow a 1V/octave response.

Now comes the interesting part. You will probably be interfacing a music keyboard to the MTS-100 for much of your work. Most modern keyboards have a pitch wheel on them. By bobbling this wheel, you can bend the pitch of the currently played note up or down. We definitely want the MTS-100 to take advantage of this neat feature. But won't that require an additional DAC? Nope, not if we use a multiplexing scheme!

Here's the basic concept. The DAC will share its time between two separate sample-and-hold (S/H) circuits. At one instant, it stores the control voltage in the first S/H, and in the next instant it stores the pitch bend voltage in the second. Then the process starts over again. Since the multiplexing is happening at such a rapid rate (about 100 microseconds per cycle), the S/H capacitors never have a chance to drop or lose their stored charges. The net effect? The DAC appears to have two separate outputs. Let's look into the details.

The output voltage of the DAC is found at pin 3 of IC6a, the op-amp follower. This signal splits in two now, going to analog switches IC5a and IC5b. When switch IC5a is closed, the DAC voltage is applied to the S/H configured around C9 and IC6c. The buffered voltage is then presented to jack J3, the control voltage output. On the other hand, if IC5b is closed then the DAC's output is instead routed to C10 and IC6d. The buffered pitch bend voltage is available at jack J4.

In case you're wondering, the firmware within the 68705 makes certain that only one of these analog switches is closed at any given moment. Another thing to note is that the CMOS switches need to operate off of a +15V power supply. This is because the voltage from the DAC ranges on up to +10.58V (note number 127). So transistors Q3 and Q4,

Figure 6 — Front Panel



Figure 7 — Front Panel Drilling Guide

along with their associated resistors, translate the TTL control signals from the 68705 to a suitable +15V level.

To wrap things up, notice that there have been numerous capacitors not mentioned in the circuit description so far. Most of these are decoupling, bypass, or compensation caps. In general, these caps are used to stabilize the operation of the various chips. Even though they don't seem to do anything very glamorous, all of them are essential for proper performance.

Well, you're probably sick of circuit descriptions, so let's move on now and see how to actually construct the MTS-100!



Figure 8
The MTS-100 can easily interface a MIDI instrument — such as a music keyboard or a computer running sequencer software — with most any analog synthesizer.

BUILD IT!

Besides the hardware just described, it also takes firmware to put the MTS-100 through its paces. If you'd like to try a complete homebrew approach, then first obtain a blank 68705 chip. Jameco Electronics (1355 Shoreway Road, Belmont, CA 94002) is a good source for the part, and has them for under $15.00.

Next, you'll need to get your hands on the program for the firmware. Even though the object code is quite short (about 700 bytes), it's still too long to appear in this article. However, the complete annotated assembler source code is available free of charge for download on the World Wide Web. See the Parts List for details.

Next, you'll need to assemble the code and burn it into your chip. There are dozens of excellent freeware and shareware cross-assemblers available on the Internet; try your favorite search engine and see! As for programming the microprocessor, get your hands on a 68705 Motorola manual. You'll find complete directions for programming the internal EPROM.

But if the thought of hassling around with software doesn't appeal to you, then you might want to consider purchasing the kit of parts which includes a programmed 68705. Refer to the Parts List for ordering information.

All of the other components in the MTS-100 are available from a variety of sources. A quick check of the ads in this magazine or the catalogs of some of the better mail order houses will fill in the gaps almost immediately.

After gathering the parts together, ponder what method of construction you will employ. Most of the project is non-critical, but keep in mind that the S/H circuits, as well as the crystal oscillator, demand neatness. (Stray capacitance and the like can wreak havoc.) So, if you decide to handwire it, be sure you keep everything nice and tidy.

The best approach by far, however, is to use a printed circuit board. This is much more fun to put together, looks pretty, and will probably minimize any potential wiring errors. Many hobbyists are becoming old hands at etching their own boards nowadays using a laser printer and iron-on transfer material. If you'd like to give it whirl, refer to Figure 4 which shows the 1:1 positive artwork for the foil side. Conveniently, it all fits on a 4" by 6" board, which is a standard copper clad size.

See Figure 5 for the parts placement guide. Loading the board is pretty straightforward as long as you obey the usual rules. For example, be sure to observe the orientations of all of the polarized components. Diode D1 is marked with a standard schematic symbol. A plus sign indicates the positive lead of electrolytic capacitors C14-C18. The emitter, base, and collector leads of Q1-Q4 are called out with their initial letters.

Finally, don't forget to install the 15 jumpers. These are indicated as straight lines connecting pairs of points on the diagram.

After loading the printed circuit board, you can then proceed to the final wiring of the front panel. A rack-mounted unit is perhaps best, since most pro equipment comes that way nowadays.

The MTS-100 fits nicely behind a standard 1U rack panel (1-3/4" by 19"). Figure 6 shows a sample design, while Figure 7 gives the related drilling guide. The circuit board mounts behind the panel on standoffs or little angles, using #4 hardware to secure things.

To connect the circuit board to the panel, notice that all of the relevant pads are labeled on the parts placement guide in Figure 5. Even so, here are a few additional tips. For best results, twisted triples should be used to connect up jacks J5-J7. The schematic in Figure 2 shows the pin arrangement of these jacks, as seen from the solder lug side. Notice that G, the ground wire of the triple going to the MIDI input, does not connect to J5. Clip if off, and let it float.

The purpose of this wire is simply to provide a degree of shielding for the other two wires in the triple. It is left unconnected at the panel side to avoid ground loop problems.

On the other hand, G does connect to MIDI THRU jacks J6 and J7. Solder the respective ground wire of each triple directly to pin 2 of each of these.

Switches S1-S3 are daisy chained, with a final lead running back to one of the digital ground pads on the printed circuit board. The ground lugs of jacks J1-J4 are also daisy chained, with their final run going to one of the analog ground pads. (You'll see why there are separate digital and analog grounds in just a moment.) Finally, the anodes of LEDs D2-D5 are daisy chained back to one of the +5V pads.

The remaining connections to the switches, LEDs, and jacks are trivial, and easily identified from the designations on the parts placement guide.

At this point, you should have only five more pads to hook up: digital ground, +5V, -15V, analog ground, and +15V. They connect to your power supplies. Notice that these are standard synthesizer voltages, so you may be able to tap them from an existing supply. Plan on drawing about 120mA from the +5V supply, 10mA from the -15V side, and 15mA from the +15V side.

Connect up these last five lines. Now here is an easily overlooked, but vital point to remember. In any hybrid analog/digital circuit, it is essential that digital ground and analog ground connect at one point only! This helps to minimize interference and other gremlins. So, complete the hook-up by joining digital ground to analog ground right at the output of the power supplies.

For emphasis, this is the only place where the two grounds connect (not at the circuit board and not at the front panel). If you've followed these directions carefully, then you should be all set. Give your handiwork a once over and, if it looks good, then proceed!

MAKING MUSIC WITH THE MTS-100

Before you can make music with your new system, you need to calibrate the voltage response of the MTS-100. Here's a quick way to do it. The firmware has been programmed so that at power up, the current note defaults to number 60 (middle C). This corresponds to a control voltage of +5V. So simply turn on the power supply, and monitor the CV output at jack J3 with a digital voltmeter. Adjust trimmer potentiometer R28 until you obtain a reading of +5V.

By the way, most electronic components need a "break in" period, so you might want to tweak this up several hours later after the parts have aged a little.

That's it; you're all set to go! So, dig out your analog synthesizer and connect it up to an audio amplifier. Next, patch in the MTS-100 using 1/4" phone plug cables. Depending on the modules in your synthesizer, there may be several ways to do this. Then decide how you will drive the MTS-100; a music keyboard is the easiest for your initial testing. Naturally, you will need to use some standard MIDI cables for this. Figure 8 shows the details of a simple set-up, just to get you started.

Commence your testing by pressing the Omni button; confirm that the Omni LED lights up. Now start playing some notes on your keyboard. The Gate and Trigger LEDs should flash, letting you know that keys are being detected. Next, turn up the amplifier and play a few scales.

Now rotate the pitch wheel on your keyboard. Confirm that the VCO sweeps up or down appropriately. Your VCO input should have a pot on it, so dial in the amount sweeping action you like best. For example, you might want to attenuate the pitch bend so that a complete rotation covers only an octave.

Now shut off the MTS-100 and turn it on again, as you set it for a new channel. This was described earlier in the article. Follow this by pressing the Channel button one more time to confirm that the LED properly indicates the number you just chose.

Lastly, hook up your personal computer to the MTS-100. Of course, you'll need a MIDI port on the PC to do this. But remember that I described a do-it-yourself Sound Blaster 16 to MIDI interface in the April '97 issue of *Nuts & Volts Magazine*. This puts a MIDI port within reach of most everyone.

While running some sequencer software, experiment by sending various MIDI control messages. You should be able to turn Omni on and off, reset the pitch bend to its mid position value, turn off stuck notes, and do a complete system reset. Refer to the Implementation Chart in Figure 1 for details. If you've passed these tests, then you're all set to resuscitate that old dinosaur. You will now have the best of two worlds: the fat sound of an analog synthesizer, all under MIDI control! **NV**

Acknowledgments: *I am extremely grateful to John Simonton of PAiA Electronics, whose pioneering work in computers and synthesizers made this design all that much easier to accomplish. I also wish to thank Bernie Hutchins, publisher of the legendary ELECTRONOTES newsletter, for putting up with way too many questions, and patiently helping me track down circuit goblins.*

PARTS LIST

All resistors are 1/4-watt, 5% values.

R1 - R6	220 ohms
R7 - R10	470 ohms
R11, R12	1K
R13	1.2K
R14, R15	1.8K
R16 - R22	4.7K
R23 - R27	10K
R28	10K trimmer potentiometer
R29	22K
R30	100K
R31	220K

All capacitors are 16V.

C1	22 pF dipped silver mica
C2 - C7	0.01 mfd disc
C8 - C10	0.047 mfd mylar
C11 - C13	0.1 mfd disc
C14	1 mfd electrolytic
C15 - C17	10 mfd electrolytic
C18	100 mfd electrolytic

Semiconductors

D1	1N914 or 1N4148 diode
D2 - D5	Red LED
Q1 - Q4	2N3904 NPN transistor
IC1	6N138 optocoupler
IC2	74LS00 quad NAND gate
IC3	MC68705P3 MPU (programmed)
IC4	DAC0800 D-to-A converter
IC5	4016 quad SPST switch
IC6	4136 quad op-amp

Other components

X1	4 MHz crystal
S1, S2	SPST pushbutton switch
S3	SPDT (on-off-on) toggle switch
J1 - J4	1/4" phone jack
J5 - J7	Five-pin DIN jack (180 degrees)

Miscellaneous: printed circuit board, LED holders, IC sockets, front panel, wire, solder, etc.

ORDERING INFORMATION

A kit of parts for the MTS-100 is available from the source below. Included with the kit is an etched, drilled, and tinned printed circuit board, programmed microprocessor, all resistors, capacitors, semiconductors, crystal, switches, jacks, LED holders, sockets, and Assembly Guide. Does not include front panel, wire, or solder.

- MTS-100 Kit (#K210)-$69.95

US and Canadian orders add $5.00 shipping and handling. E-Mail or write for shipping information to other countries.

Prices shown in USA dollars. Remit US funds only. Money orders and checks only. MN residents add 6.5% sales tax. Prices and terms subject to change without notice.

Order from: **Midwest Analog Products**
P.O. Box 2101
N. Mankato, MN 56003

The complete source code for the MTS-100 firmware may be downloaded free of charge from the WWW homepage of Midwest Analog Products.

WWW: http://prairie.lakes.com/~map
E-Mail: map@prairie.lakes.com

MILITARY SURPLUS ELECTRONICS

PRECIOUS METALS CD now available. Find **gold, silver, platinum** content of over 500,000 components in the **Federal Supply System**. $95. For sample/order call **334-889-4637**.

AUDIO – VIDEO – LASERS

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.

AUDIO & video equipment sale! Quality pro & consumer pieces. Amplifiers, mixers, MIDI, tubes, switchers, TBCs, projectors & lenses. Buying old broadcast or studio gear. Locating & Brokering services available. Call Tom for detailed list. Tel 609-222-0636 Fax 609-222-0638 NJ.

DPSS LASERS: Brand new items in stock. I have high quality temperature stabilized 5mW, 20mW, and 100mW DPSS micro-green laser heads and power supplies. Starting at under $1,000 these units will sell fast. I also carry complete sets of NLO optics to build your own DPSS green or blue laser. Detailed set of instructions with illustrations shows you how to make the cavity and get results. Brand new high power laser diodes from 785NM to 1020NM from .5 watt to 15 watts CW or pulsed (pricing ranges from $200 up to $1,500 per diode). I will beat anyone's advertised price. 100 watt CW/pulsed hard seal water cooled CO2 laser head ($2,300 OBO). Other laser related items not listed. Please call for a free catalog. Contact Spectrum Technologies @ 407-658-4785 or E-Mail: mikes@server.netpass.com

ARGON LASERS. Large selection of used American 60X air cooled argon lasers. Prices start at $300. Power supplies and other accessories available. Call for price list. 805-230-2166.

BROADCAST VIDEO equipment wanted: all types, new or old. Please call, Jon with info. 317-539-2859.

VIDEO PATCH PANEL, 2 pcs. available, made by ADC @ $150 ea. Call Roger at GS&E, 716-338-7001. VISA-MC available.

13" COLOR COMPOSITE MONITORS, used but in great condition @ $60 ea. Call Roger @ GS&E, 716-338-7001. VISA-MC available.

DUAL GALVO KIT $139 programmable! Displays text and graphic designs. Draws square corners. Includes galvos, PID servo amp, mirrors, computer interface and software. **FREE CATALOG** of kits and surplus goodies. 510-582-6602, SVS_KITS@MSN.COM fax 510-582-6603.

AMPEX AVR-3 QUAD VTR IN EXCELLENT CONDITION. INCLUDES stereo audio. All onboard test and display monitors operational and included. Includes pre-recorded and new tape. (20 total) plus documentation and one set of spare heads. Machine refurbished to like-new condition. (Had very low mileage to begin with.) 5K firm. Fax 415-821-7500 or Tel 415-821-3359. F.O.B. San Francisco.

C02 25W Powerlase laser w/power supply/controller $800. 760-632-9775.

(2) JVC CR-850U 3/4 inch editing recorders, need repair, $600 total. (2) Sony VP-5000 players, (1) manual, (1) RX-353 auto search control, $250 total. Microtime 2100 video processor, $200. Epson E1020 crystal image LCD projector, $200, Kent, 515-232-7528.

SONY PLAYSTATION mod chips: These allow you to play international games (imports) also you can play gold/green CD recordable backups. Chip & full instructions $50 ea. qty discounts available. 1-800-663-8530.

SYNC-A-LINK UNIVERSAL VIDEO SYNC GENERATOR restores all horizontal & vertical sync lines, DC level, compensates for inverted video, color phase, from standard or distorted analogue video-type formats. Comes complete with operations manual & 90-day warranty. $160. 918-479-6451 or write to Sync-A-link Communications, PO Box 4, Locust Grove, OK 74352.

Try a classified ad in Nuts & Volts. They're inexpensive and they work! Details on page 112.

Virtual Reality Vest $39.50

Whether you are shooting the enemy in your favorite computer game, jamming to the rhythm of the latest punk rock sensation, or watching Jason carve up yet another nice neighbor, you will add a whole new dimension to the experience with this vest. Feel the action in your favorite video game, experience "body base" from your stereo, or add a new jolt to the violent machine gun and car crash video craze. This backpack style vest produces vibrations and sound in conjunction with loud or base tones from the audio source. Originally designed for Super Nintendo, Sega Genesis I & II, as well as others, the units also include instructions and connectors for portable music players, computer sound cards, TV and VCR units, and table top stereo receivers and CD players. AC powered, the unit includes vest, power amplifier, mini cord, game adapter, mini stereo adapter, and wall transformer...Oh, and all the trademark names used in this ad are the property of their respective owners! Mail order customers please add an additional $4.00 per unit to shipping charges for this item.

WAVETEK TEMPERATURE PROBE

Wavetek TP114K temperature probe with hypodermic tip. Type K immersion style thermocouple probe. Compatible with the Wavetek DM23XT, DM28XT, HD110, TC253, MH101K. Boxed. $15.00

PHOTON II MICROLIGHT

The popular photon microlight has been improved. These super-bright (better than 8 candellas!) LED lights are visible over a mile away. The LED is secured in a tough ABS case and offers a squeeze button for quick use, and a constant on slide switch for prolonged lighting needs. The lithium batteries last a very long time (10 year shelf life!) and are included. The light won't burn out because it is an LED! Specify your choice of five incredible bright colors. Great for home or office use, popular with fire and rescue professionals, pyrotechnicians, stage performers, and dimly lit restaurant patrons. PHOTON II microlights include a keyring and come in ruby red ($13.50), amber yellow ($13.50), sapphire blue ($17.50), diamond white ($17.50), and emerald green ($17.50). Includes two replaceable 2016 lithium batteries.

GIANT ARROW KIT $23.95

It flashes, it chases, it lights up in pretty colors! This giant arrow features 81 yellow and green LEDs, an on/off switch, and a potentiometer to adjust the speed of the arrow action. Comes complete with these and all other parts, a clearly marked circuit board, and an assembly instruction sheet with schematic diagram and trouble-shooting tips. Operates on 12VDC, so you can run it on your car battery, a wall pack, or any other appropriate power source you select.

surf the internet?

catch a wave to Gateway's home page

www.gatewayelex.com

Bone Conduction / Direct Sound Telephone Teleset $24.95

Attaches to your modular telephone and lets you switch from an ordinary handset to your hands-free TELESET. Nugget style ear plug serves as mic and receiver, and is a lightweight alternative to conventional boomsets. Offers the hands-free convenience of a speaker phone without the tunnel quality sound or lack of privacy. Great for home or office use. (Cannot be used on Trim-line style telephones.)

127 THERMOCOUPLES PELTIER JUNCTIONS

The peltier junction is a solid-state thermovoltaic device. Current applied to the device will produce heat on one side of the device and a cold surface on the other side. Water placed on the surface will freeze or boil depending on polarity of applied voltage. Ideal for applications from 3-12 VDC --

grab a battery and let your imagination run wild!

DOCUMENTATION INCLUDED!!!

Small Peltier Junction $20.00 (approximately 1.17"x1.17"x.12")

Large Peltier Junction $29.50 (approximately 1.56"x1.56"x.15")

Over 200 different circuits can be created with this fun and educational kit.

Radio and Electronics Superlab $43.50

Create an 8-key 16-note organ, electronic sound effects, a CB radio converter, 40 computer circuits, 30 electronic games, a lie detector, a human reflex tester, and more. A great introduction to the broad electronics hobby. Includes instructions, circuit and schematic diagrams. Appropriate for ages 10 and up. Batteries not included.

THE FINE PAINT : PRICES SUBJECT TO CHANGE WITHOUT NOTICE • GATEWAY IS NOT RESPONSIBLE FOR PRINTING ERRORS • MASTERCARD, VISA AND DISCOVER ACCEPTED • YES, WE'LL TAKE YOUR CHECK -- SORRY, NO C.O.D.s • $10 MERCHANDISE MINIMUM ON MAIL ORDERS • SUPPLY OF SOME ITEMS IS LIMITED • PRICES DO NOT INCLUDE SHIPPING • UPS GROUND SHIPPING/HANDLING WITHIN THE CONTINENTAL U.S. (ITEMS REQUIRING ADDITIONAL AMOUNTS ARE NOTED)...$4.25 FOR THE FIRST ITEM, $0.50 FOR EACH ADDITIONAL ITEM. RESTOCKING CHARGE MAY BE ASSESSED ON RETURNED ITEMS. HAVE YOU EVER SEEN A BOAT SUP?

TWISTER TWISTER $4.95

Originally designed for promotional displays, this unit features a 7.5" twisted clear plastic rod, a 3v motor, and an attached cardboard 5-3/4" sleeve battery holder (will hold 2 D-cell batteries, not included.) The motor measures 2" x 1-3/4" dia with a 5/8" long 1/8" dia. shaft, has mounting tabs and rotates at about 40 rpm. You can use it as an attention getter, mounting a small sign on top of the lucite rod, or come up with your own creative use. Great for long term use, because the current draw is so small!

10 pc. Tuning Tool Set $9.95

An assortment of square and slot style plastic adjustment tools, assures a style perfect for almost any application. 4-1/2" long with knurled handles for easy grup turning. An inexpensive addition to every tool box.

BASIC STAMP BOOK $32.95

Covering both the hardware and software sides of the Parallax BASIC Stamp I and II microprocessor operation and design, this is the first book we've found on this popular topic. The book is over 250 pages covering everything from hardware to programming instructions, including several application projects that are quite useful! Diagrams, illustrations, programming code, and examples make this book easy to read and understand. Appendices on reserved words, firmware, and Hayes modem commands are also helpful. Novice or expert, this is a must-have for your microcontroller library!

Are your batteries feeling tired and worn-out?

Call Dr. Nicad, The Nicad Battery Conditioner! With this kit, you can build a rapid charger that eliminates memory effect and brings many batteries to full charge in less than an hour! Charge NICad or NiMH packs from 2 to 10 cells (easily expanded) and current capacities up to 10 AH. Runs on 12-15 VDC. Features a switch-mode regulator that controls constant current charge while being monitored by a negative delta-V system that cuts of the fast charge at the exact point of full charge so your batteries don't get cooked! Dr. Nicad Kit $49.95

Optional Matching Case $14.95

gateway ELECTRONICS, INC

8123 PAGE BLVD • ST. LOUIS, MO 63130
(314)427-6116

9222 CHESAPEAKE DR. • SAN DIEGO, CA 92123
(619)279-6802

2525 FEDERAL BLVD. • DENVER, CO 80211
(303)458-5444

MAIL ORDERS CALL TOLL-FREE 1-800-669-5810

FAX ORDERS (314)427-3147

Passive Infra-red Talking Motion Detector !!! $27.50

"Stay out of that refrigerator !", "Watch your step!", "Do your homework", "Don't touch that remote!" ... The possibilities are mind-boggling with this talking motion detector. You speak into it to record your message (upto 12 seconds long), turn the unit on, and instantly your voice (or your mother-in-laws) reminds anyone in the vicinity that you were expecting them. Message can be changed with the flip of a switch. Uses 4 AA batteries (not included), or an external power source (built-in jack). May be used independently (80 db output) or with an amplified speaker to blast your message throughout the house. Approx 4"x 3-1/2"x 1-1/2".

TONY TALLI'S ORIGINAL
TELEVIEW DISTRIBUTORS

WHERE OUR VALUED CUSTOMERS' BUSINESS IS HONESTLY APPRECIATED

SERVING YOUR CABLE NEEDS SINCE 1984

1·800·847·3773

Vega One **ORDERS ALSO ACCEPTED**

Not affiliated with NCCA.

1·800·525·0428 P.M. SALES

Orders called in by 1:00 pm shipped same day. $15 shipping.
NO NEVADA SALES • Hours: M-F 9-4 PST

FREE 1 YEAR SUBSCRIPTION TO NUTS & VOLTS WITH $500.00 MIN. ORDER

FREE Golf Hat with $150 purchase.

FREE T-Shirt with $500 purchase.

Call for this month's Nuts & Volts Specials

MasterCard VISA

YES! WE HAVE COUPONS!

GIVE TELEVIEW TONY A CALL TODAY!

1-702-253-1852 • FAX 1-702-253-1854

P.O. BOX 71465 • LAS VEGAS, NV 89170-1465

Greenleaf
ELECTRONICS

For all your cable needs

Call us first!

SIX-MONTH GUARANTEE
(30-DAY MONEY BACK)

Phone 630-616-8050
or
Fax 630-616-8094

For orders only: 1-800-742-2567

HOURS: MON.-FRI. 8-6 CST • SAT. 10-2 CST

Greenleaf Electronics • P.O. Box 538 • Bensenville, IL 60106

JR COMMUNICATIONS

CELL: 917-915-0455 PAGER: 917-333-4410

F R E E



F R E E

F R E E



FREE COPY CATS
FREE SHIPPING
FREE CABLES

MAKE YOUR OWN PROGRAMMING UNIT/TEST CHIP. PLANS AND ALL SOURCES WHERE TO GET PARTS TO MAKE YOUR OWN UNIT.
CALL FOR ALL YOUR SOURCE NEEDS. IF YOU NEED IT, WE HAVE IT...
CALL FOR POCKET PRO 2 MINIATURE COPY CAT SOURCE NEEDS.
CALL FOR PRO 62 DATA ANALYZER SOURCE NEEDS.
CALL FOR ALL YOUR CABLE TV SOURCE NEEDS. (NEW J-UNIVERSAL)
CALL FOR OKI 900 AND AT&T 3730 5-NAM CHIP SOURCE NEEDS.
CALL FOR GE ERICSSON TEST CLIP SOURCE NEEDS.
CALL FOR MOTOROLA KEYPAD PROGRAMMING CHIP SOURCE NEEDS.
CALL FOR MOTOROLA STARTAC TEST CLIP SOURCE NEEDS.
CALL FOR MOTOROLA ELITE TEST CLIP SOURCE NEEDS.
CALL FOR MOTOROLA REGULAR FLIP TEST CLIP SOURCE NEEDS.
CALL WITH ANY QUESTIONS YOU HAVE ON WHAT SOURCE YOU ARE LOOKING FOR. IF YOU DON'T SEE IT, JUST CALL, CALL, CALL...
WE CARRY THE *POCKET PRO 2*, BEST AND SMALLEST 4-WAY MINIATURE COPY CAT WITH AN ILLUMINATED SCREEN.
WE HAVE THE *NEW POCKET PRO 62 AND POCKET PRO 64* DATA ANALYZERS... PLEASE CALL NUMBER ABOVE AND ASK FOR JUAN...

AGREEMENT FOR PURCHASING CELLULAR AND CABLE TV PROGRAMMING SOFTWARE AND EQUIPMENT: Purchaser agrees not to use said software and equipment for any illegal purposes. Please check with the Federal and State laws applicable in your locality.

ALL EQUIPMENT SOLD FOR EDUCATIONAL AND REPAIR PURPOSES ONLY!

Celebrating our 14th Year Of Service !!

MOTION DETECTOR KIT

Compact and portable. Adds safety to your home or office. Learn the basics of motion detector technology. Uses a pyroelectric infrared sensor. Simple and fun to build. Battery operated. Complete with all parts, PC board, case, schematic, and extensive training manual.

STOCK#		1-9	10-24	25+
SS50K	Detector Kit	19.99	18.99	17.09

RS-232 MINI TESTER

Used to monitor the 7 most commonly used data lines to see if equipment has failed. 7 two color LEDs check status of TD, RD, RTS, CTS, DSR, CD & DTR.

STOCK#	1-9	10-24	25+
MT100	9.99	9.49	8.54

11 PIECE COMPUTER TOOL KIT

11 piece kit: 3/16" & 1/4" nut driver, 3 prong retriever, Tweezer, 3/16", 1/4", #1 & #2 phillips reversable screwdriver, T-10 & T-15 reversable screwdriver 14-16 pin IC inserter, IC extractor, 1/8" flat screwdriver, #0 phillips screwdriver, Black vinyl zippered Case

STOCK#		1-9	10-24	25+
TK1100	Tool Kit	17.99	17.09	15.38

DIGITAL MULTIMETER

- 3 1/2 digit LCD
- Low battery display
- Floating decimal point
- Frequency counter
- AC & DC curr. (600V)
- Transistor tester
- Resistance test
- Low ohm cont. beeper
- Recessed input jacks reduces shock hazard
- Over range indicator (OL & -OL)
- Diode test function allows testing of semiconductor junctions
- Capacitance test sockets
- 3.5" W x 7.5" L x 1.4" D

STOCK#	1-9	10-24	25+
M1700	49.99	47.49	42.74

D-SUBMINIATURE - SOLDER CUP

- Steel shell
- 1 amp contact curr.
- 10 meg Ω res.

STOCK#	VALUE	1-24	25-99	100+
CODB9P	9 Pin Plug	.29	.28	.26
CODB9S	9 Pin Socket	.37	.35	.32
CODB15P	15 Pin Plug	.39	.37	.33
CODB15S	15 Pin Socket	.45	.43	.39
CODB15PHD	(High Density)	.59	.56	.50
CODB25P	25 Pin Plug	.45	.43	.39
CODB25S	25 Pin Socket	.55	.52	.47
CODB37P	37 Pin Plug	.79	.75	.68
CODB37S	37 Pin Socket	.89	.85	.77
CODB50P	50 Pin Plug	1.19	1.13	1.02
CODB50S	50 Pin Socket	1.29	1.23	1.11

LEAF SWITCH

- 4 amp
- N.O.

STOCK#	1-24	25-99	100+
SB1059	.29	.28	.25

What Do We Have ?

- I.C.'s
- Oscillators
- Crystals
- Diodes
- Tools
- Laser Diodes
- Vises
- Resistors
- Capacitors
- Connectors
- Trimpots
- Kits
- Vises
- LED's
- Transistors
- And more!

GADGETEER'S GOLDINE

This exciting collection of electronic projects features experiments ranging from magnetic levitation and lasers to high-tech surveillance and digital communications.

- By Gordon McComb

STOCK#	1-9	10-24	25+
TB3360	21.99	20.89	18.80

- Order Line — (800) 824-3432 • International — (412) 495-1230 • Fax Orders — (412) 495-7882
- Technical Support — (412) 495-1231 • No Minimum Order — (Orders under $20 subject to $ 5 charge)
- UPS 3 day, Blue, Red, & Fed. Ex. Shipping Available (Call for charges) • PA Res. Add 7 % Sales Tax
- Open Mon-Fri 9:00 AM - 5:00 PM (EST) • Corporate Accounts / Quantity Discounts Available
- We accept M/C, VISA with no surcharge • Call For FREE Catalog ($2.00 Outside U.S.)
- We Carry A Complete Line Of Electronic Components • Email - unielect@aol.com

FREE SHIPPING!!
on pre-paid orders

Unicorn Electronics
1142 State Route 18
Aliquippa, PA 15001

Write in 176 on Reader Service Card.

Nuts & Volts

SELL NUTS & VOLTS IN YOUR STORE AND EARN $$$
Contact us for details. 909-371-8497
E-Mail distributors@nutsvolts.com

Nuts & Volts

Network Service Tool Set

Popular installation and service tools for networks, modems and telephones. All hand tools are professional heavy duty type.

Use the compact tester on 10BASE-T (UTP & STP), thin Ethernet (BNC), 8-position Token Ring, AT&T 258A and EIA/TIA 568A/B. Automatically scans cables for continuity, wiring sequence and polarization. Tests STP cable ground. Testing installed cables is easy with Remote Terminator and gender changers (UTP and BNC). 9V battery included.

- Coax Stripping Tool, RG-58 & RG-59
- BNC Crimping Tool, RG-58 & RG-59
- Modular Cutting/Stripping/Crimping Tool (4, 6 & 8-Position)
- Multi-Network Cable Tester
- AC Receptacle Tester
- Cable Cutter

Order No. 55625 $197.00

PC Service Tool Set

Contains all tools needed to troubleshoot & service IBM-compatible PCs. Set includes:

- AMI Diagnostic Software
- POST Card
- Logic Probe
- Digital Multi-Meter
- AC Receptacle Tester
- Serial Adapter
- Serial & Parallel Loopback Connectors
- DIP IC Puller
- PLCC IC Puller
- Grounding Wrist Strap
- Key Top Puller

Order No. 55000 $198.00

PC Diagnostic Tool Set

- AMI Diagnostic Software
- POST Card

Order No. 55555 $89.00

Network Installation Tool Set

- Network Tool Set 55625 without the Multi-Network Cable Tester.

Order No. 55600 $99.00

Call for your FREE Catalog

Graymark®

P.O. Box 2015 Tustin, CA 92781
http://www.labvolt.com

CALL TODAY!
800-854-7393

VISA MasterCard AMERICAN EXPRESS Cards DISCOVER NOVUS

Write in 216 on Reader Service Card.

AUDIO – VIDEO – LASERS *cont.*

VIDEO PRINTERS - Prints a 3x5 near photo grade picture from any composite video signal, new $200 ea., used $140 ea. Call Roger at GS&E, 716-338-7001. VISA-MC available.

CABLE TV

CATV REPAIR, most models, great prices, warranty included. Please call 573-363-0402.

CABLE TV SURPLUS WANTED: We buy & sell trunk stations, cable converter boxes, line extenders, passives, power supplies. Message/fax 561-483-8516. E-Mail: cable@flinet.com

NEW! VIDEO cassette storage cases now available $1.25 each, plus shipping and COD, 100 piece minimum order black grain finish with interior hubs, call Ken Erny Electronics 24 hour order and information hot line 516-389-3536.

ATTN: CABLE CONVERTER RETAILERS. E-Mail or fax your monthly stock needs. All major brands available. Lowest prices. New/field pulls available. Bulk orders only. Message/Fax 561-483-8516. E-Mail: cable@flinet.com

DEALERS WANTED! CABLE TV EQUIPMENT & ACCESSORIES! ALL MAJOR MAKES & MODELS. Real dealers pricing. **1-800-820-1727.**

AMATEUR ROBOTICS

by Karl Lunt

Last month, I started my design of a fire-fighting robot. I had selected the New Micros' NMIX-0332 single-board computer (SBC) as my robot brain, and set out to design my robot software in C. Unfortunately, things haven't worked out, and I've had to shift gears. I'm still using the New Micros' board, but now I'm writing my robot code in Forth.

I gave it my best shot, though. The Software Development System (SDS) compiler, described last month, is excellent and, even though I was using a "demo" version, it included all the tools I would have needed for my project. It even has a nifty utility for splitting a large object file into two halves, suitable for burning into the upper and lower EPROMs common to 16-bit microcontroller (MCU) systems.

But after several days of effort, and a couple of calls to the technical desk at New Micros, I threw in the towel. I simply could not write even a simple assembly language program, burn it into the two EPROMs, and have the MCU execute my program on power-up. I've always agreed with the old maxim that it's a poor craftsman who blames his tools, but the New Micros "documentation" for this board truly sucks.

The most glaring example of this is page 26 from the NMIX-0332 Hardware Manual; except for the heading of "Programming Examples," the page is TOTALLY BLANK! This same hardware manual includes page 17, titled "Memory Map," which contains one paragraph describing where the 68332's 1K of internal RAM appears on power-up, but instead of a memory map, the page carries a table of miscellaneous jumpers.

Even this paragraph bothers me, since the 68332 has 2K of internal RAM, normally used by the Time Processor Unit (TPU), and that memory comes out of reset disabled. I invite any reader who was able to get a custom C or assembly program to execute on this board to contact me; I'd like to find out what I missed.

So there I sat one Saturday evening, having wasted far more time than I should have on getting a small program, any program, to run on my new board. Reluctantly, I reinstalled the original EPROMs in their sockets, strapped the NMIX board so it booted up in Max-FORTH, and hit the switch. Even if I couldn't get C to run, I could at least dabble a bit in Forth.

What a difference a language makes! In just four hours of hacking, I had most of the low-level timing routines written and tested. This, despite having never used the 68332's powerful TPU — the microcoded engine at the heart of the MCU's timing system. Forth has always been my language of choice, and the New Micros' 32-bit version of this power tool makes designing software so easy, it's fun.

Yes, I got more done in Forth because New Micros did the painful integration work up front, and I only had to use the finished tool. But the language itself plays a large part in the productivity boost; Forth is simply a strong, tight language for software development.

The bottom line: You are going to get a few lessons in developing Forth software. Those of you who have never seen the language before would do well to pick up one of the classic Forth texts — Leo Brodie's wonderful *Starting Forth* — published some years ago by Prentice-Hall. The book has been out of print for a few years now, but finding it is well worth the hunt.

Be sure you get the second edition, as the original work dealt with an old dialect of the language seldom in use any more. Even the second edition is behind the times, but his marvelous explanations of the core words still apply, and the book is both entertaining and educational.

Rather than bog down this article with a full explanation of Forth's inner workings, I'll settle for many examples with lots of comments. After all, this is an article about robotics, not about Forth. I will have to hit a few high points, though, so bear with me.

Forth is a stack-based language, similar to the Hewlett-Packard calculators. Whenever you want to perform an operation in Forth, you first push onto a data stack all the arguments that function (called a word) will need, then you invoke the word. When the word you've selected executes, it pulls its arguments from the stack, processes them, pushes any results back onto the stack, then exits.

A quick example should help. The Forth word for addition is + (pronounced "plus"). The Forth word for displaying an argument on the screen, similar to Basic's PRINT, is a period (pronounced "dot"). Thus, to display the sum of 7 and 82, you would enter the command:

```
7 82 + .
```

The Forth processor, called the interpreter, pushes 7 onto the stack, pushes 82 onto the stack, then invokes the word +. + adds the two arguments together and leaves the sum, 89, on the stack. The interpreter then invokes the word ., which pulls an argument off the stack (89, in this case) and displays it on the screen.

But the interpreter only processes your keystrokes; if you don't type, it doesn't execute anything. This is great for dabbling with the underlying hardware, since you can change I/O registers and memory contents, then watch what happens.

However, when you finally get around to writing a finished program, you need to compile your program so it will run later. For that, you need the Forth compiler, named : (pronounced "colon").

The colon compiler lets you create a new Forth word that performs whatever operation you want. Once defined, this word becomes an extension of the Forth system, as much an element of the language as any of the original words. Given the above example, we can create a word that displays the sum of the two original numbers by entering:

```
: SUM
7 82 + .
;
```

This isn't too useful in and of itself, but it illustrates a point. We have created a Forth word, called SUM, that does just what our first, interactive example does, only this word is compiled. We can execute it at any time by simply typing:

```
SUM
```

There, in a nutshell, is the essence of the Forth language; a stack-based, extensible, compiler-interpreter development system. These simple core elements, used properly, will (I hope) get my robot running by March. But it's a long road, and the first step to take involves the 68332's TPU. I hope the code I've developed for controlling this subsystem will also help you appreciate Forth's power in developing programs.

The 68332 TPU

My old favorite, the 68hc11, has a timing subsystem that eases the pain of developing precise timing elements. I've clocked pulses, generated frequencies, driven pulse-width modulation (PWM) electronics, and blinked more LEDs than I can recall, all using this wonderful little I/O subsystem. But as powerful as the 68hc11's timers are, they pale in comparison to the 68332's TPU.

The TPU contains a separate microprocessor dedicated to servicing timing instructions from the host 68332 core. Communications between the two processors occurs through a set of I/O registers and a bank of dual-ported RAM. Based on instructions provided by the 68332, the TPU can perform complex timing functions on any of 16 timing channels. Each channel has its own I/O pin, which your program can use to drive electronics or read signals. The TPU can provide functions such as PWM, servo step-pulse generation, input capture, output compare, period measurement with missing-pulse detection, position-synchronized pulse generation, and others.

It also supports a wide range of interrupts, allowing the CPU to get updates on timing activities, if necessary. And all of these functions take place with zero CPU impact, other than interrupts. Your code simply loads up a function, triggers its execution, and leaves the TPU to do the rest.

The TPU is so complex that Motorola has printed a separate book on its use. You can order a copy of the TPU Reference Manual (TPURM/AD) by calling your nearest Motorola office, or hitting the Motorola web site: www.mcu.motsps.com — I just received Rev. 3 of the manual, along with other books such as the *MC68332 User's Manual* (MC68332UM/AD), the *CPU32 Reference Manual* (CPU32RM/AD), the *System Integration Module Reference Manual* (SIMRM/AD), and the *Queued Serial Module Reference Manual* (QSMRM/AD). I expect to need all of these manuals at some point in the development, so I went ahead and got them early.

I also picked up a super collection of application notes for the TPU. This two-inch stack of documentation contains details on using many of the different TPU functions. For example, application note TPUPN00/D, titled "Using the TPU Function Library and TPU Emulation Mode," covers the basics of the TPU and the use of its underlying microcode engine.

The document includes information on setting up your own functions in the TPU's microcode, and even includes instructions on using TPUASM, Motorola's FREEWARE TPU assembler. You can find both the TPUASM assembler and the source code for the examples in this application note on the Motorola FREEWARE web site at: www.mcu.motsps.com:80/freeweb/

Other application notes in this collection cover topics such as designing an asynchronous serial port (UART) using a pair of TPU channels, using the TPU frequency measurement function,

and generating sophisticated PWM signal sequences. If you want to get the full value out of the 68332's TPU, this set of notes ranks as "must-have."

But before I could get started using the TPU, I first had to decide what timing functions my robot would require. I already know I'm going to have to generate stepper motor signals, but since I'm using Bill Bailey's terrific little stepper motor driver boards, I don't need the complicated four-wire step signals.

Instead, I can get by with just a direction line and a step-pulse line for each of two motors. The direction lines will be simple digital outputs, but the two step-pulse signals will be timer output lines controlled by the TPU.

Navigation will be a key element in the robot's design, and that means my program must be able to count pulses generated by an outside source, such as wheel encoders. Therefore, I'll also need some form of pulse-counting ability on at least two inputs.

I'll also need to generate one or more 40 KHz 50% duty-cycle squarewaves, for use with an IR object detection system. The TPU will save me a chip or two here, since I can set up a simple PWM output with the proper time period and duty-cycle, then let the microcode engine do the work. Finally, I expect to need at least one PWM signal for driving a hobby R/C servo motor. I'll attach a mechanism to this servo for controlling whatever fire-extinguishing system I design.

As of now, that's all I can foresee needing. Granted, these requirements won't begin to strain the TPU's capabilities, but they make an excellent starting point for exploring the power of this subsystem.

I first had to apply power to the board and hook up the PC. You can find some of the neatest little wall-wart power supplies in mail-order catalogs these days, and a first-rate multiple-output power supply for small SBCs shouldn't set you back more than $5.00. I'm using an old AT&T wall-wart that generates +5, +12, and -12 VDC, which I picked up ages ago at a surplus store. I cut the 15-pin connector off the end of the cable, then installed three two-pin connectors, one on each voltage and ground combination.

Now I can simply plug whatever voltage I need into the board and I'm ready to go. If you follow a similar course, be sure to label each connector so you don't accidentally plug -12 VDC into the +5 VDC input on your board; that'll hurt!

I connected the serial cable, supplied by New Micros, to my PC's serial port, then fired up an old copy of Crosstalk. Just about any communications program will work; I use Crosstalk because I can customize scripts for several different boards.

One feature you will need on your comm program is the ability to pace lines of text during an ASCII download. You will be sending source lines to the Forth compiler over the serial port, and each line must wait until the compiler signals that it is done with the previous line. I set Crosstalk to wait for an echo on each character and an echo on each line.

After finishing the set-up (9600 baud, 8N1), I was ready to hit the switch. My NMIX-0332 board responded with the Forth prompt. I started by tackling the 40 KHz signal generation, since that seemed the most straightforward. In the 68hc11, this type of function would be done with the timer output-compare function and some interrupt service request (ISR) code. Oddly enough, this knowledge of "how it's done" tripped me up, and I spent about an hour trying to use the TPU's output-compare function for this simple task. Finally, a talk with Kevin Ross, president of the Seattle Robotics Society, put me on the right track and I turned to the PWM function.

All TPU functions are set up using the same basic format. You must first decide which of the 16 available TPU channels you will assign to a task. Next, your software sets up that channel by writing the necessary information to various I/O registers and parameter RAM locations related to that channel.

Finally, your software enables the channel, allowing it to begin processing its assigned function. In general, a channel set-up uses the following sequence:

1. Write the function code you want to use to the proper TPU channel function select register (FSR).



Simplified 68332 Block Diagram

2. Write any necessary parameters to the area of TPU RAM assigned to that channel.

3. Write the appropriate host service request (HSR) to the section of the HSR registers assigned to that channel.

4. Write a priority value to the section of the channel priority registers (CPR) assigned to that channel.

At this point, the TPU should be executing your function. While all of this looks complicated, it actually reduces to a mere six lines of Forth code. Refer to the accompanying listing of 40khz.txt for details.

My example starts with some Forth housekeeping chores. HEX tells Forth to use hexadecimal as the default radix. FORGET TASK causes Forth to erase all known words back to and including the word TASK, if it exists. Finally, the third line defines an empty word named TASK, which I use to mark the beginning of my work space.

I then define a word called TPU-INIT, that does whatever low-level set-up is needed on the TPU. In this case, the only task I need to do is define the TPU's clock rate. I chose a value of $00c0; writing this value to address $fffe00 (TPUMCR) sets the TPU's clock prescaler to divide-by-4. This means that each TPU clock cycle is 250 nsec, given the standard 68332 system clock of 16 MHz.

Writing a 16-bit value to a memory location requires two stack values and the store word, H! (pronounced "H-store"). Notice that the order of the values is important; the value to write always appears first, then the address to modify, followed by the word that actually performs the store operation.

Next up, I define the word 40KHZ, which actually configures a TPU channel to generate a fixed 40 KHz signal. In this example, I've chosen TPU channel 0 for my 40 KHz output. The first line of code in the definition writes the PWM function ($09) to the proper section of the appropriate channel function select register (CFSR3).

There are four channel function select registers in the TPU, and each register supports four TPU channels. The section of a CFSR assigned to any one TPU channel spans four bits, leaving room for 16 available TPU functions, $00 through $0f. As you can see here, the value $09 selects the PWM timer function. You can also see that the low four bits of address $fffe12 are used by the TPU logic to hold the function assigned to TPU channel 0.

The TPU design uses a section of dual-ported RAM as a parameter area. Both the host CPU (68332) and the TPU can read/write addresses in this RAM. During TPU function set-up, your software writes any required parameters to the area of this RAM dedicated to the selected TPU channel. If necessary, your software can later examine addresses within this RAM to determine the state of a selected TPU channel.

Each TPU channel is assigned a block of eight words in TPU RAM for holding parameters. For channels 0 through 13, only the first six words in these blocks are really RAM; the last two words aren't actually implemented.

The second line of code in my little program writes the value $0091 to parameter 0 for channel 0. This value tells the TPU to use timer 1 (the TPU internal clock source) as the time base and to pull the output line for TPU channel high at the start of each PWM cycle. I don't need to write anything to parameter 1, since that is reserved as an output location for the TPU PWM function.

My next line of code writes the value $0032 to parameter 2, which gives the number of TPU clock cycles to hold the output pin in its assigned state. Recall that TPU-INIT set the TPU clock to 250 nsecs per period. Thus, this parameter means that the output pin will remain high for $32 (or 50) 250 nsec clocks, or 12.5 usecs.

The fourth line of code in this function writes the value $0064 to parameter 3. This gives the number of TPU clock cycles in the entire PWM

period, again measured in 250 nsec clocks. This works out to 100 clocks, or 25 usecs. The net result of parameters 3 and 4 is to create a pulse stream of 40 KHz frequency with a 50% duty-cycle.

The fifth line of code issues a command, known as a host service request (HSR), to the TPU. An HSR takes up two bits, and the HSR field for TPU channel 0 is the low two bits of address $fffe1a, the second of two HSRs (HSRR1). By writing the value %10 to this field, my code instructs the TPU to initialize TPU channel 0, using the values I've previously written to the parameter areas of RAM.

We are nearly done. The only remaining tasks are to enable the TPU processing of channel 0 and to assign a priority for that processing. Both of these tasks are handled by the last line of my little program, which writes the value $0003 to address $fffe1e, the second channel priority register (CPR1).

The priority value for any channel fits in two bits, and by using a value of %11 for TPU channel 0's priority, I'm assigning it high priority. Writing a value other than %00 to this field tells the TPU that the parameters are stable and that it can begin performing the assigned function.

The final phase of this program takes place in the word MAIN. Executing MAIN invokes the TPU-INIT word to set up the TPU, then invokes the 40KHZ word to set up and start TPU channel 0. MAIN then ends, returning control to the Forth interpreter. However, since the TPU has started the PWM function on channel 0, the desired 40 KHz signal appears on channel 0's output pin without any support from the 68332.

This first program fits the bill as a learning tool; by simply typing MAIN at the Forth prompt, I can generate a 40 KHz signal on timer pin 0. But the program needs some work before it can be used as part of robot firmware.

The biggest problem is that this code clobbers any values previously stored in several of the TPU I/O registers. To be truly useful, this and routines like it should leave previous values intact, changing only those fields assigned to functions of interest.

The second program, stepper.txt, carries the concepts of the previous example farther. This code begins with the customary removal of TASK, then sets the Forth dictionary pointer to a special RAM address, which will later be used by the New Micros start-up sequence; more on this in a later article. This file also includes the TPU-INIT word, just like the previous example.

The next word, HOR! (pronounced "H-O-R-store"), lets my software modify only selected bits within a 16-bit memory address. The technique uses some of the simpler Forth stack-manipulation words, and provides a good example of how to define and set up words that need several arguments. Using the comments in the definition, try to work out for yourself how the word does what it does; you can check later lines in the program for examples on using HOR!.

The next word, INIT-STEPPERS, sets up TPU channel 1 to generate a PWM pulse stream. As with the previous example, the code must modify several memory addresses. Those addresses in the range $fffexx are TPU registers, shared by other TPU channels. Thus, my code invokes HOR! so only the bits associated with channel 1 are modified.

Addresses in the range $ffffxx belong in the TPU parameter RAM and are dedicated solely to a specific channel. Therefore, my code can modify the entire word without trashing parameters belonging to another channel. The second half of

```
 HEX
FORGET TASK
: TASK ;
: TPU-INIT
  00C0 FFFE00 H! ( USE 250 NS RATE FOR TCR1 (PSCK=1)
;

(
( 40KHZ     ( - )
( Use the TPU to generate a 40 KHz output on TP0.
(
( This requires that the TPU be initialized to use a
( /4 prescaler (PSCK = 1)
(
: 40KHZ
  0009 FFFE12 H! ( CHNL 0 FUNCTION SELECT = PWM
  0091 FFFF00 H! ( TCR1, FORCE OUTPUT HIGH, TIMER CH 0
  0032 FFFF04 H! ( PWMHI = 12.5 USECS
  0064 FFFF06 H! ( PWMPER = 25.0 USECS
  0002 FFFE1A H! ( HSR FOR CHNL 0 = %10 (INIT)
  0003 FFFE1E H! ( PRIORITY FOR CHNL 0 = HIGH
;

: MAIN
  TPU-INIT
  40KHZ
  CR CR ." Done!" CR
;

Program for generating 40 KHz pulses using the TPU
 FORGET TASK
HEX
0 8000 !
8100 DP !
: TASK ;

0 CONSTANT RMTR
1 CONSTANT LMTR
: INIT-TPU
  00C0 FFFE00 H! ( USE 250 NS RATE FOR TCR1 (PSCK=1)
;
: HOR!  ( data addr mask - )
  OVER H@       ( get current word in addr
  AND           ( clear bits based on AND-mask
  ROT           ( get data on TOS
  OR          ( now add new bits
  SWAP H!       ( and write new value to addr
;

: INIT-STEPPERS
  0090 FFFE12 FF0F HOR! ( CHNL 1 FUNCTION SELECT = PWM
  0092 FFFF10 H!     ( TCR1, OUTPUT LOW, TIMER CH 1
  0000 FFFF14 H!     ( PWMHI = 0 USECS
  1F40 FFFF16 H!     ( PWMPER = 2.0 MSECS
  0008 FFFE1A FFF3 HOR! ( HSR FOR CHNL 1 = INIT
  0004 FFFE1E FFF3 HOR! ( PRIORITY FOR CHNL 1 = MEDIUM
  0900 FFFE12 F0FF HOR! ( CHNL 2 FUNCTION SELECT = PWM
  0092 FFFF20 H!     ( TCR1, OUTPUT LOW, TIMER CH 2
  0000 FFFF24 H!     ( PWMHI = 0 USECS
  7FFF FFFF26 H!     ( PWMPER = 8.19 MSECS = 122 HZ
  0020 FFFE1A FFCF HOR! ( HSR FOR CHNL 2 = INIT
  0010 FFFE1E FFCF HOR! ( PRIORITY FOR CHNL 2 = MEDIUM
;

: INIT-PULSE-COUNTER
  A000 FFFE12 0FFF HOR! ( CHNL 3 FUNCTION = TRANS CNTR
  000D FFFF30 H!     ( DETECT FALLING EDGES
  000E FFFF32 H!     ( NO LINKS, INCR DUMMY LOC
  2000 FFFF34 H!     ( NUMBER OF PULSES TO COUNT
  0000 FFFE16 FF3F HOR! ( NO LINK, SNGL MODE, HOST SEQ
  0040 FFFE1A FF3F HOR! ( HSR FOR CHNL 3 = INIT
  0080 FFFE1E FF3F HOR! ( PRIORITY FOR CHNL 3 = MEDIUM
;

: SET-STEPPER-RATE   ( MTR PERIOD - )
  SWAP
  RMTR = IF       ( DOING RIGHT MOTOR?
    FFFF16 H!     ( USE TOS AS PERIOD
  ELSE
    FFFF26 H!     ( USE TOS AS PERIOD
  THEN
;

: START-STEPPERS
  0091 FFFF10 H!     ( TCR1, FORCE OUTPUT HI, CH 1
  0190 FFFF14 H!     ( PWMHI = 100 USECS
  0004 FFFE1A FFF3 HOR! ( HSR FOR CHNL 1 = UPDATE
  0004 FFFE1E FFF3 HOR! ( PRIORITY FOR CHNL 1 = MEDIUM
  0091 FFFF20 H!     ( TCR1, FORCE OUTPUT HI, CH 2
  0190 FFFF24 H!     ( PWMHI = 100 USECS
  0010 FFFE1A FFCF HOR! ( HSR FOR CHNL 2 = UPDATE
  0010 FFFE1E FFCF HOR! ( PRIORITY FOR CHNL 2 = MEDIUM
;

: STOP-STEPPERS
  0092 FFFF10 H!     ( TCR1, FORCE OUTPUT LOW, CH 1
  0000 FFFF14 H!     ( PWMHI = 0 USECS
  0004 FFFE1A FFF3 HOR! ( HSR FOR CHNL 1 = UPDATE
  0004 FFFE1E FFF3 HOR! ( PRIORITY FOR CHNL 1 = MEDIUM
  0092 FFFF20 H!     ( TCR1, FORCE OUTPUT LOW, CH 2
  0000 FFFF24 H!     ( PWMHI = 0 USECS
  0010 FFFE1A FFCF HOR! ( HSR FOR CHNL 2 = UPDATE
  0010 FFFE1E FFCF HOR! ( PRIORITY FOR CHNL 2 = MEDIUM
;

: MAIN
  INIT-TPU
  INIT-STEPPERS
  INIT-PULSE-COUNTER
  CR ." Press a key..."
  KEY DROP
  RMTR 2000 SET-STEPPER-RATE
  LMTR 2000 SET-STEPPER-RATE
  START-STEPPERS
  CR CR ." Counting..."
  BEGIN
   FFFF34 H@       ( GET NUMBER OF PULSES TO COUNT
   FFFF36 H@       ( GET PULSES COUNTED SO FAR
   =           ( DONE WHEN THESE MATCH
  UNTIL
  STOP-STEPPERS
  ." done!" CR
;
```

Program for Generating Stepper Pulses and Counting Pulses

the INIT-STEPPERS word sets up TPU channel 2 to generate another PWM pulse stream; you can see how this block of code mimics the first half.

The word INIT-PULSE-COUNTER sets up TPU channel 3 as a pulse counter, to count the number of pulses applied to the I/O pin associated with that channel. I won't go into the details of this set-up, but instead refer you to the TPU manual. With this example and the manual, you shouldn't have any trouble figuring out how the transition or pulse counter function works.

START-STEPPERS and STOP-STEPPERS perform obvious functions. Note how these routines first modify selected areas in the parameter RAM and TPU registers, then execute a host service request called UPDATE. This HSR tells the TPU that the parameter RAM and I/O registers for this channel have been modified and a new function or new parameters are available. For START-STEPPERS, the new parameters assign a pulse width value and tell the TPU to generate active-high pulses.

For STOP-STEPPERS, the new parameters call for a pulse width of 0 nsecs and an active-low output. This latter combination essentially shuts off all pulse activity, stopping the motors.

The whole design comes together in the word MAIN. This code sets up the TPU, then sets up the three TPU channels using the words defined earlier. Next, the program sets the stepping rate for both motors and starts the motors running. The code then enters a loop that checks the values of two parameters in the RAM assigned to channel 3, which I'm using as a pulse-counter.

The TPU updates the value in address $ffff36 with the number of pulses counted since the last update or initialization, and the INIT-PULSE-COUNTER word loaded the desired pulse count in $ffff34.

When these two addresses hold the same value, the pulse counter has detected the desired number of pulses. At this point, the BEGIN-UNTIL loop terminates, MAIN prints out a useful message, and control returns to the Forth interpreter. For testing purposes, I connected a jumper between the output of channel 2 and the input of channel 3. Thus, channel 3 is used to count the number of pulses issued by channel 2.

In conclusion ...

This article has provided a brief look at both the Forth language as implemented by New Micros and the powerful Time Processing Unit built into the Motorola 68332. Hopefully, you will find my examples clear enough at least to get started with this high-octane microcontroller.

Be sure to hit the Motorola web site for more information on the 68332 chip. Also contact Motorola directly for the literature you will need to start out with this chip.

And now, I have to get back to my robot design. See you next month ... **NV**

As always, you can reach me at:
Karl Lunt
116 173rd St. S.W., Bothell, WA 98012
E-Mail: karllunt@seanet.com
Web: http://www.seanet.com/~karllunt

CABLE TV *cont.*

TOCOM RAW UNMODIFIED **5503s** COMPLETE UNTOUCHED. **$6 EACH**. 10 LOT MIN. **CALL 706-398-2100.**

CABLE TV converters and accessories, best performance, best prices, introducing new Panasonic 5 with volume control. Dealers only. Call for lot prices. NTS 1-888-355-6687.

NEW! CABLE converter electronic service equipment and supplies for most cable converter boxes. Highest service, lowest prices. Call Ken Erny Electronics. 24 hr. order and information hot line 516-389-3536.

CALL ALEN for all your cable needs or computer software, PICs, GALs read if you've lost your masters. Programming service available. For info call 909-941-4858 or E-Mail to alencable@aol.com or visit us at our web on-site http://members.aol.com/alencable

UNMODIFIED JERROLD Pioneer, SA and Panasonic Model 175 multivision. We carry all other cable products. Please call between 7-9 pm EST. 617-389-5155.

CABLE CONVERTERS. The best quality equipment w/warranty + money back guarantee. We have low overhead, so we sell for less. PRECISION ELECTRONICS, Houston, TX. 1-888-691-4610.

SECRET CABLE DESCRAMBLER anyone can build in **7 easy steps** under $12 using **Radio Shack parts**. Plans $6, bonus with order! GES Video, Box 72-V, Perryopolis, PA 15473.

CABLE PARTS! Computer parts. Call for great prices or visit us on the Web: HTTP://WWW.CB-Electronics.com or call 1-800-436-8630.

DEALERS NEEDED for new cable products. Call us for all your special needs. Design & programming services also available. 602-309-0367.

CABLE CONVERTERS. We should have the equipment you need. Warranty. PRECISION ELECTRONICS, Houston, TX. 1-888-691-4610.

CABLE FIELD pulls, unmodified. DP5, DPV5, DP7, DPV7, BB7, CFT, 8580, 8590, 8600, Pioneer 5535NP, Zenith ST-1600, Zenith DD-3, Tocom 5503 VIP, Panasonic 145. All equipment genuine unmodified. Catalog, credit cards, COD. 1-888-443-9185.

CABLE CONVERTERS. Highest quality equipment. Money back guarantee. PRECISION ELECTRONICS, Houston, TX. 1-888-691-4610.

TOCOM RAW UNMODIFIED **5503s** COMPLETE UNTOUCHED. **$6 EACH**. 10 LOT MIN. **CALL 706-398-2100.**

WANTED: RAW & unmodified cable converters. Please call 214-500-7162.

FOR SALE: Genuine unmodified Tocom 5503 VIP, SA 8600s; Panasonic volume control converters, Pioneer addressable from $65; NSC 550MHz ch. 4 for $25; new Zenith volume control 99 ch. from $55; DPV-5 or DPV-7, Zenith 1600s series as-is from $25 or guaranteed from $65; SA 8600 remotes from $3.50; Jerrold remotes model 400 & 450 from $1.50. Prices negotiable based on quantities. Other brands available. Call Mon-Fri 11am-6pm EST. 1-800-909-4333, FAX: 718-657-4015.

JERROLD UNMODIFIED CONVERTERS FOR SALE. CALL FOR BEST PRICES. **NO DESCRAMBLER SALES**. CALL BRLD ELECTRONICS 1-800-322-6316.

CABLE TV converters and accessories, best performance, best prices, introducing new Panasonic 5 with volume control. Dealers only. Call for lot prices. NTS 1-888-355-6687.

BATTERIES

REPLACEMENT BATTERIES
ALL NEW • MADE IN U.S.A.

KENWOOD

PB1	12v @ 1100 mAh	$50.00
KNB-3	7.2v @ 1200 mAh	30.00
KNB-4	7.2v @ 2200 mAh	69.00
PB6	7.2v @ 760 mAh	35.00
PB7	7.2v @ 1500 mAh	49.00
PB8	12v @ 850 mAh	49.00
PB-13	7.2v @ 750 mAh	37.00
PB-14	12v @ 800 mAh	49.00
PB-18	7.2v @ 1500 mAh	47.00

ICOM

7S	13.2v @ 1400 mAh	$53.00
8S	9.6v @ 1400 mAh	51.00
BP7	13.2v @ 600 mAh	53.00
BP8	8.4v @ 1400 mAh	50.00

SA/SAT

BP82, BP83A		
BP84	7.2v@1200 mAh 3"	$39.00
BP85B	12v 600 mAh 3"	69.00

YAESU

FNB-2	10.8v 600 mAh	$19.00
FNB-4	12v 750 mAh	39.00
FNB-4A	12v 1000 mAh	55.00
FNB-17	7.2v 600 mAh	30.00
FNB-10S	7.2v 1200 mah	39.00
FNB-12S	12v 600 mAh	40.00
FNB-25	7.2v 600 mAh	35.00
FNB-26	7.2v 1200 mAh	44.00
FNB-26S	7.2v 1500 mAh	49.00
FNB-27S	12v 800 mAh	49.00

ALINCO

EPB-10N	7.2v @ 700 mAh	$36.00
EPB-12N	12v @ 700 mAh	47.00
DJ-F1T		
EPB-16N	7.2v @ 750 mAh	$37.00
EPB-16N	12v @ 600 mAh	47.00
DJ-180, DJ580		
EPB-20N	7.2v @ 800 mAh	$34.00
EPB-20NX	7.2v @1600 mAh	44.00
EPB-22N	12v @ 800 mAh	49.00

CAMCORDER

Panasonic PB 80/88 ORIG PAN		$39.00
Sony NP77H	2400 mAh	39.00
Sony NP55	1200 mAh	29.00
Sony NP22	500 mAh	29.00
Canon 8mm	2000 mAh	36.00
Panasonic Palm	2400 mAh	39.00
JVC GR Type C	1500 mAh	36.00
Sharp BT 21/22	2000 mah	45.00
RCA/Hitachi 8mm	2400 mAh	39.00

ALL BRANDS AVAILABLE

SALE!
ALL 7.2 VOLT @ 1500 mAh*
BATTERY PACKS
$39.00
*EXCEPT FNB-35(S)(S)

MasterChargers®

MasterCharger I DELTA V, RAPID CHARGER
ALL VOLTAGE 4.8v - 13.2v 1/2-2 HOURS

MasterCharger IIa TAPER CHARGER
ALL VOLTAGE 4.8v - 13.2v 0 HOURS

DUAL CHARGERS
- MasterCharger I+I
- MasterCharger I+IIa
- MasterCharger IIa+IIa*

*AUTOMATICALLY CHARGES TWO BATTERIES AT THE SAME TIME

All MasterChargers (Single and Dual) Feature:
- Interchangeable Cups
- Fully Automatic Operation
- Built in Overcharging Protection
- User Friendly
- More Than 50 Cups Available
- Optional DC Charger

NEW!

KENWOOD TH22AT/79A

PB32	6v @ 600 mAh	
PB33	6v @ 1200 mAh	
PB34	9.6v @ 600 mAh	

YAESU FT-11/51R

FNB-31	4.8v @ 600 mAh	
FNB-33(S)	4.8v @ 1500 mAh	
FNB-35SS	7.2v @ 1500 mAh	
FNB-38	9.6v @ 600 mAh	

ICOM-W21AT/2GX

BP-157	7.2v @ 900 mAh	
BP-157(S)	7.2v @1500 mAh	
BP-132	12v @ 850 mAh	

available with and without microphone

MOTOROLA

GP-300	7.5v @ 1200 mAh	

MasterCard DISCOVER NOVUS VISA

BATTERY-TECH, INC. 800 SOUTH BROADWAY, HICKSVILLE, NY 11801
800-442-4275 • FAX 516-496-9523
SEND FOR FREE CATALOG • DEALER INQUIRIES WELCOME IN NEW YORK STATE CALL: 516-496-9520

Write in 192 on Reader Service Card.

UNBELIEVABLE PRICES. We carry a full line of cable tools and equipment for all your cable needs. Also a wide variety of electronic parts & accessories, tools, diagrams, converters, step-by-step instructions, no raw parts. **Full technical support**. 11am-7:30pm EST. **1-800-562-8442.**

EXPLOSIVE CABLE TV GRAB! BRINKER ZAPPER/SNOOPER STOPPER combo module all in one! Buy wholesale factory-direct, no middleman. Let others get fined + zapped instead. Protect your cable box now! 100% COMPATIBLE. We supply over 80 advertisers weekly! Your order shipped fast, within hours! Why pay $39 when you can buy direct! LIFETIME GUARANTEE! We accept VISA/MC/AMEX/COD/MO/CHECKS. ONLY $10 (SPECIAL: 3/$20 plus FREE DESCRAMBLER PLANS!). SUPER ZAPPER MODULES ONLY $16! (3/$33)! NOTCH FILTERS (2-22, 95-99): BUILT $22, PLANS $5; CABLE TV CONVERTER BOX SOURCES (125+) $7, CATV LIGHTNING SUPPRESSOR $8. FREE SHIPPING, ALWAYS! Call us anytime 1-888-430-7576 ext. 3135. BRINKER ENGINEERING LABS. (RIP-OFF ALERT: Advertisers now selling empty cans as cable protection. BEWARE!)

ATTENTION: YOU'VE tried the rest, now go with the best. **UNICORN ELECTRONICS** where our valued customers **ALWAYS** come first. **CABLE CONVERTERS AND ACCESSORIES.** We will beat all competitors prices **GUARANTEED**. All **UNITS** in **STOCK FOR IMMEDIATE SHIPMENT. FREE** batteries and coax cable. **FREE** bullet protection with every unit purchased. **FREE** shipping with a $500 purchase or more. **NO** COD charges. **ALL** products come with a 1 year warranty and a 30 day money back guarantee. Please give us a call TOLL FREE 1-888-738-8181 9am to 6:30pm EST. **VISA, M/CARD, DISCOVER, COD. UNICORN** Electronics does not advocate unauthorized use or theft of cable services.

CABLE ONE, one stop for all your cable needs. Overnight delivery **guaranteed!** Low prices. 11am-7:30pm **EST 1-800-562-8442.ZENITH RAW** UNMODIFIED **ST16XXs** COMPLETE UNTOUCHED. **$60 EACH.** 10 LOT MIN. **CALL 706-398-2100.**

CABLE CONVERTERS. We have the best quality equipment to fill your cable needs & the lowest prices around. Guaranteed w/warr. PRECISION ELECTRONICS, Houston, TX. 1-888-691-4610.

TOCOM RAW UNMODIFIED **5503s** COMPLETE UNTOUCHED. **$6 EACH**. 10 LOT MIN. **CALL 706-398-2100.**

QB VIDEO. We handle converters, remotes, and accessories. Wholesale/quantity discounts. Same day shipping. **1-800-249-3025.**

HOW TO MAKE UP TO

$250 AN HOUR!

IN THE FASCINATING FIELD OF

COUNTER-SURVEILLANCE!

ELECTRONIC EAVESDROPPING IS UNBELIEVABLY WIDESPREAD!

Individuals skilled in electronically "sweeping" homes and offices are reaping a bonanza!

NO EXPERIENCE NECESSARY!

Would YOU like to learn how others (*without prior experience*) have entered this exciting, immensely interesting and *extremely* profitable field?

BIG PROFITS IN ELECTRONIC SECURITY!

Call Toll-Free NOW for your FREE CATALOG and Complete Details

800 732-5000

Top Quality Recondi... Electronic Test Equipme...

Hewlett-Packard • Tektronix • Fluke • Wiltron

BOUGHT & SOLD
Test Equipment Wanted

Looking for Test Equipment Manuals?
Contact: Manuals Plus (801)882-7188 • Fax (801)882-7195

Corporate Offices
P.O. Box 1762
San Mateo, CA 94401

Seattle, WA 206-251-6653
285 S.W. 41st St.
Renton, WA 98055

415-579-1711 • Fax 415-579-5777
http://www.bellelect.com

BELL Electronics

Write in 137 on Reader Service Card.

PARTS - PARTS - PARTS

65.8 Mhz Saw Filters	100 pcs. - $2.40@	300 pcs. - $2.00@	600 pcs. - $1.75@
16 & 18 Pin IC Sockets	500 pcs. - $.09@	1,000 pcs. - $.07@	5,000 pcs. - $.05@
18VAC, 300mA, Wall Transformers *(Perfect for Stealth Units)*	50 pcs. - $3.00@	100 pcs. - $2.50@	250 pcs. - $2.00@
4 Mhz Resonators, 3 pins 4 & 8 Mhz Crystals, 2 pins	100 pcs. - $.45@	500 pcs. - $.40@	1,000 pcs. - $.35@
24 Mhz Crystals, 2 pins	100 pcs. - $.55@	500 pcs. - $.50@	1,000 pcs. - $.44@
Micro-Chip Pic-16C54RC	100 pcs. - $2.10@	250 pcs. - $1.95@	500 pcs. - $1.85@
Micro-Chip Pic-16C56RC	100 pcs. - $2.30@	250 pcs. - $2.25@	500 pcs. - $2.15@
TDA-8340 I.C.	100 pcs. - $2.00@	500 pcs. - $1.75@	1,000 pcs. - $1.68@
TSA-6060 I.C.	100 pcs. - $3.48@	500 pcs. - $2.75@	1,000 pcs. - $2.45@

Call for Larger Quantity Quotes

Phone: (515) 847-3888
Fax: (515) 847-3889
BBS: (515) 847-3890

CAPITAL ELECTRONICS INC.
303 Sherman Street
Ackley, Iowa 50601

E-Mail: sales@capital-elec.com
Web: http://www.capital-elec.com

WE ACCEPT VISA MasterCard

Write in 98 on Reader Service Card.

TIMELESS PRODUCTS

The Best Prices and Service • In Business over 15 years!

Phone 218-346-6660 Fax 218-346-6664

CABLE TV CONVERTERS

WILL NOT DECODE



TP1550PC

• LARGEST IN-STOCK DISTRIBUTOR OF TIMELESS AND PANASONIC CONVERTERS •

• REFURBISHED CONVERTERS ALSO AVAILABLE •

• QUALITY REPAIR DEPARTMENT FOR ALL YOUR TUNER REPAIRS •



TZPC175DG2
TZPC1453G2
TZPC1003

• REMOTES AVAILABLE FOR MOST CABLE BOXES •

DEALERS ONLY • GREAT QUANTITY PRICES • NO DECODER SALES

Write in 171 on Reader Service Card.

100% Satisfaction & Every day Low Price Leader

ALL Motherboards w/CPU:
486 DX66 MHZ w/256 $99
K5 AMD P90 MHz $139
586 DX 133 MHZ PCI 256K $139
ANY OTHER PL CALL

16MB Mem EDO $62

Orders & PRICE
T* 800 -899-6430
F* 209-521-5000
Free Tech Support
800 899 6430

16x Sp Bundle
$149
16x Speed CD
16 Bit Sound Card
CD Titles
Amplified Speakers

All Pentium
686 & 586 Mother Boards
Memory & Drives
at Super Low Price

Buy with Confidence
Risk Free
ys Money
ck
MPLETE SYSTEMS *
Printer Memory. *

PRE-CHRISTMAS SALE
EVERYTHING AT DISCOUNT PRICES
CALL FOR CURRENT PRICES

Floppy Drives :
1.44 MITSU $20
1.44 TEAC $23
1.2/1.44 COMBO $65

Member of Better Business Bureau

Monitors:
14" MONO.VGA $89
14" .28 108 NI, LOW-R $169
15" .28 1024x768 NI,LOW
17" .28 1280x1024 NI,LOW

16X Speed CD $79
20X Speed CD $8[illegible]
24X Speed CD
36X Speed C[illegible]
All Kinds Drive[illegible]
Speakers ar[illegible]
$229
$CALL

Keyboards:
101 KEYBOARD
KEYTRONI[illegible]
FOR[illegible]

[illegible]/Fax Modem
Voice M /Fax /Mod $59
US ROBOTIC 33.6 Int $95
33.6 PCMCIA $109
55.6k $119
ISDN $call

[illegible] Memory
low $$$
Life time Warranty

SVG[illegible]
PCI 1M[illegible]50
PCI / VE[illegible]GA 2MB $35
PCI / VESA VGA 4MB $69
DIAMOND PCI VGA 2MB $69
DIAMOND PCI VGA 2MB $129
ANY OTHER VGA CARDS PL CALL

Cases with P.SUPLIES
MINI TOWER PREMIUM $32
DESK TOP CASE PREMIUM $45
MED TOWER CASE PREMIUM $55
FULL TOWER CASE PREMIUM $75

ONE YEAR WARRANTY ON PARTS LIFE TIME Labor Warranty

Resellers Dealers Welcome

Terms:
No minimum Charge
No Hidden Charge
Prices change w/o Notice
15% Restock fee for Non Defective
Orders of $950 or more ground shipping free.
Except Case,Monitor,Keybord & F. Drives

Credit Cards Ok
Govt P.O. • C.O.D.

Controller Cards:
SUPER IDE-I/O $12
ADAPTEC 2940U $185
ADAPTEC 2940UW $205
ANY OTHER PL CALL

IBM 686DX P200+
Faster than pentium
200Mhz
$199

"Triton" Intel Mother Boards
Pentium 133 Mhz w/CPU $219
Pentium 166 Mhz w/CPU $249
Pentium 200MMX Mhz w/cpu $395
Pentium MMX/PRO/II $call

Bisme Computer, Inc., 906 N. Carpenter Rd. #A, Modesto, CA 95351

Write in 215 on Reader Service Card.

CABLE EQUIPMENT. We have converters. Much to choose from. Satisfaction guaranteed. PRECISION ELECTRONICS, Houston, TX. 1-888-691-4610.

ZENITH RAW UNMODIFIED **ST16XXs** COMPLETE UNTOUCHED. **$60 EACH.** 10 LOT MIN. **CALL 706-398-2100.**

NOTCH FILTERS 110, 108.5, 106.5, 97.5 75dB deep notch. $19.95 ea., 1-5 qty. $15.95 ea., 6-10 qty. $11.95 ea., 11-20 qty. $9.95 ea., 21 or more qty. Call 24 hr. order and information hot line 516-389-3536.

WE PROGRAM 16Cs, 68HCs, 16V8, 22V10, 2764 EEPROMs for your electronic needs. 30 days money back guarantee. KCS 1-800-879-8820.

PLANS: DESCRAMBLE CABLE FOR UNDER $12. PLUS TWO FREE BONUSES. TOLL FREE 1-888-588-3715.

GENUINE UNMODIFIED Jerrold DPBB 7312. 1-800-804-8655 FAX 410-483-9230 E-Mail: CLEWIS7298@AOL.COM

FREE CABLE DESCRAMBLER PLANS! For details write: Sierra Publishing, 909 E. Yorba Linda Blvd., Suite H-181, Dept. NVX, Placentia, CA 92870.

GENUINE UNMODIFIED 2R/V5 and S/A 8580 converters. BBPD 7. $wanted$ cash for unmodified CFTs, DBB & PV7 converters. 512-854-8989.

CONVERTER BOX sales-unmodified SA Zenith, Jerrold. Repair, parts & accessories. Call 573-363-0402 8am-4pm CST or leave a message.

CABLE TV parts, converters and info. Call Jake for flyer 1-800-879-9657.

TOCOM RAW UNMODIFIED **5503s** COMPLETE UNTOUCHED. **$6 EACH.** 10 LOT MIN. **CALL 706-398-2100.**

ZENITH RAW UNMODIFIED **ST16XXs** COMPLETE UNTOUCHED. **$60 EACH.** 10 LOT MIN. **CALL 706-398-2100.**

HAMLIN, PIONEER, ZENITH, AS and other manufacturer converters, various models including 6600, 6000 and 5000, 90s, 80s 29s, 28s 25s, and 100s, 5130, 5135, 4135 and 9310s, ST-1000 288 and 165 MP, 1086 and 1600, plus other models, **LARGE QUANTITIES, CALL for PRICING. 1-800-380-9530.**

T & L SERVICE. Sales and repair all major cable converter. Genuine Unmodified Jerr-DPV7, DPBB7, CFT2000 & 2200, SA8600, PIO-63XX, Zenith. 1-888-823-6047.

PICS, GALS READ if you've lost your masters. Programming service available. Call for info. Network Sales, 616-683-0500.

CABLE CONVERTERS, remotes, etc., free flyer. Jake 1-800-879-9657.

PC BOARDS REPAIRED. Prices start at $5. Minimum 25 of one type. Network Sales, 616-683-0500.

TOCOM RAW UNMODIFIED **5503s** COMPLETE UNTOUCHED. **$6 EACH.** 10 LOT MIN. **CALL 706-398-2100.**

CABLE CONVERTERS. Highest quality equipment. Money back guarantee. PRECISION ELECTRONICS, Houston, TX. 1-888-691-4610.

ZENITH RAW UNMODIFIED **ST16XXs** COMPLETE UNTOUCHED. **$60 EACH.** 10 LOT MIN. **CALL 706-398-2100.**

ELECTRONIX EXPRESS

WELLER SOLDERING STATION – *MODEL WLC 100*
- Variable power control (5 to 40 watts)
- Replaceable heating element
- Quality light-weight pencil iron

$36.95

DUAL-TRACE OSCILLOSCOPE
Goldstar 9020
20MHZ $339.00

SCOPE PROBE
60 MHZ
SWITCHABLE X1, X10 $12.95

BK PRECISION FUNCTION GEN.
5 MHZ, DIGITAL DISPLAY
MODEL 4011 $230.00

ALLIGATOR LEADS $2.10
SET OF 10

DIGITAL MULTIMETER
WITH CAP/FREQUENCY/ TRANSISTOR TESTER
Model DM645 $34.95

SWITCHES
8 POS DIP ..... 60¢ ea.
Mini Toggle SPDT ..... 50¢ ea. ON-ON

SOLDERLESS BREADBOARD
830 tie points. MB102PLT model features 3 binding posts and aluminum backplate.

Part No.	1-9	10+
MB102	5.95	5.00
MB102PLT	8.95	8.00



SOLDERING IRON 3-WIRE $5.25
HIGH PERFORMANCE
#060501

SOLDERING IRON STAND
W/SPONGE
#060842 $3.50

1 LB. 60/40 Solder Roll .031" $5.95

DESOLDER PUMP W/TIP $3.50
#060820

HELPING HAND WITH MAGNIFIER $3.50
#060836

RESISTOR KIT
1/4W 5% film. 5 pieces each of 73 values. 365 pieces total.
$3.95

15 TURN POT
69¢ ea.
Bourns 3006P series. All standard values available.

7 SEG. DISPLAY
60¢ ea.
MAN72 C.A Red 0.3"
MAN74 C.C Red 0.3"

PAD-234 DIGITAL/ ANALOG TRAINER
Complete portable workstation. Variable and fixed power supplies, function generator, digital I/O, rugged design, high impact case.

Assembled $145.00 Kit $95.00

HIGH QUALITY TOOLS
With Cushion Grips and Return Spring

Needle Nose Pliers $2.95 #060210



Wire Stripper $1.50 #060220



Diagonal Cutter $2.95 #060200



POWER SUPPLIES
0–30 VDC, 0–3 Amp. Built-in current limiting, overload protected, constant voltage and current operation.

01PSGP4303A	Analog Display	$169.00
01PSGP4303D	Digital Display	206.00

LM555 10 Min.	22¢ ea.
LM741 10 Min.	27¢ ea.
74LS00 10 Min.	18¢ ea.
7805 Regulator 10 Min.	30¢ ea.
2N3904 10 Min.	6¢ ea.
PN2222 10 Min.	6¢ ea.
Red LED T 1¾ 10 Min.	6¢ ea.
Green LED T 1¾ 10 Min.	7¢ ea.
Yellow LED T 1¾ 10 Min.	8¢ ea.
Photo Cell 10 Min.	65¢ ea.
100K Pot., 1" Shaft PC Mt. 10 Min.	15¢ ea.
CD22402	8.95 ea.

FREE CATALOG
MORE Low-Priced Items In Our FREE *192-Page Catalog*

TERMS: Min. $20 + shipping. School Purchase Orders, VISA/ MC, Money Order, Prepaid. NO PERSONAL CHECKS, NO COD. NJ Residents: Add 6% Sales Tax.

In NJ: 732-381-8020
FAX: 732-381-1572
365 Blair Road • Avenel, NJ 07001-2293
800-972-2225
http://www.elexp.com
Email: electron@elexp.com

Write in 59 on Reader Service Card.

TELEPHONE – FAX

PANASONIC, SOUTHWESTERN Bell, BBS Telecom, telephones, jacks, and systems. Free catalog: voice or fax: 908-840-1390.

EXTENSION PHONE LOCKOUTS. Prevent trashed downloads and FAX blasting. Easily installed with screwdriver. 99 cents each plus $6.50 per order. Docs included. SYNERGETICS SURPLUS, Box 809, Thatcher, AZ 85552. 520-428-4073. VISA/MC. synergetics@tina-ja.com

CELLULAR EXTENSIONS $60 plus shipping. Motorola loader phones $200. Loader phone kits $100. Quality used phones programmed on your number $150 (includes phone and programming). Call or E-Mail Stuart for details. 228-831-8708 ccomco@aol. com

BUY • SELL • CONSIGN

WANTED
- Electronic Test Equipment
- Electronics Inventory
- Scientific Equipment
- Mfg. Shop Equip.
- Data/Telco
- Memory

DEXIS

9749 Hamilton Road
Eden Prairie, MN 55344

We Sell Nationwide!
Call our Fax-On-Demand System, or our Internet site for current availability.
Visit our 25,000 sq. ft.showroom warehouse
M-F 9 to 6; Sat 9 to 5

PHONE: (612) 944-7670
INTERNET: WWW.GO2DEXIS.COM
FAX: (612)942-9712 • FAX-ON-DEMAND: 1-800-547-4636 X 300

Write In 175 on Reader Service Card.

OKI 900 programmable phone, modified & complete, $200. John 708-785-7439.

BEEPER, TWO-WAY radio repairs, modifications, duplications, all models, test equipment. Call TJ 718-341-1849, Fax 718-978-4616.

ESN READER, no scanner needed, only a PC needed and my S/W. Call 770-887-1475. $1,750. Handheld units that read pins $2,500.

ESN READER for $20? Yes, but here's the catch: it must be a pre-1933 US $20 gold piece rated MS-64 or better. Cash price: $725. This is an interface with software that goes between your scanner and your computer. For more info, please call 512-259-2940. 10am-6pm Central time.

BLUE BOOK PHONE REPAIR. 1000 models answering machines, cordless, wired, $25. KEN's, 2825 Lake, Kalamazoo, MI 49001 616-345-4609.

PHONELINE SIMULATOR. Authentic dial tone, busy signals, 20Hz ringing. Test/demonstrate phones, modems, faxes, voice mail, etc. "Ring-It" kit includes PCB, all components, microprocessor, documentation, $149. Custom enclosure $34.95. Fully assembled $325. Shipping $6.50. Checks, credit cards. Digital Products Company, 134 Windstar Circle, Folsom, CA 95630. 916-985-7219, Fax 916-985-8460, E-Mail: digprod@aol.com Web site: www.digitalproductsco.com

NEW NOKIA 2190 cellular phones all digital. 1-800-804-8655 FAX 410-483-9230 E-Mail: CLEWIS7298@AOL.COM

CELLULAR PHONE EXTENSIONS. Two cellular phones on one number, no extra monthly charges. 601-843-1044.

COMPONENTS

ELECTRONIC COMPONENTS and kits. Catalog $1. Dan's Small Parts and Kits, Box 3634, Missoula, MT 59806. Web: http://www.fix.net/dans.html

WE BUY & refine circuit cards for precious metal content. Electronic Recycling, 601-794-2570.

AMAZING! 35¢ ALL TOGGLE SWITCHES. Brand new. Rated 6A/125V. Hardware included. 1/4" PANEL HOLE: SPDT on-on, SPDT on-off-on, SPDT (mom)-off-on, DPDT on-on, DPDT on-off-on, DPDT (mom)-off-on. 3/16" PANEL HOLE: SPDT on-on, DPDT on-on. $20 minimum order. Add $5 freight. Gateway Products Corporation, PO Box 936397, Margate, FL 33093, 954-974-6864, Fax: 954-974-6818, VISA/MC. Free catalog.

WE BUY gold plated parts, transistors, hybrids, ICs, diodes, circuit boards, patch panels, military pins, tantalum capacitors, relays, old test equipment and all types of electronic material. **GOLD'N WEST SURPLUS** in Corona. Ph: 909-340-1501, FAX: 909-340-1504. ASK FOR MARK.

Your Lowest Price for Cable Converters and Accessories... JUST GOT LOWER!

Q-TRONICS

Take a Bite Out of Your Cable Bill!

Your One-Stop Wholesale Source for New and Refurbished Cable Converters

Guaranteed compatability for every major brand, Stock always on hand.

PRICES SO LOW WE CAN'T PUBLISH THEM.

Our 5-unit price is usually lower than everybody else's 10-unit price.

Unmatched reputation for customer service.

Most orders shipped same day.

No NY Sales.

1.888.228.8269

TORNADO COMMUNICATIONS

- SPECIALIZING IN ALL CONVERTERS
- WHOLESALE DEALERS ONLY
  PLEASE CALL MON-FRI
  8:00AM THRU 6:00PM EST
- EXCELLENT PRICES
- CALL (800) 685-2497 Ext. 78

- ALL EQUIPMENT IN STOCK AND READY TO SHIP

Since 1947

C and H SALES COMPANY

2176 E. Colorado Blvd., Pasadena, CA 91107

WE BUY AND SELL!

ORDER VIA TOLL FREE NUMBER BELOW OR FAX US AT (818) 796-4875

☑ *Master Charge* ☑ *Visa* ☑ *American Express* ☑ *Discover*

±15 VDC BECKMAN POWER SUPPLY

BECKMAN, #MPS-60. Input 120 VAC 60 Hz @ 1 amp. Dual adjustable outputs 0 to ±15 VDC @ 0-2 amps. Resolution 10 mV and 100 mA. Accuracy ±20 mV and 100mA. Has digital display for voltage and current. Dim.: 12" wide x 4-1/4" high x 13-1/4" deep. Weight 16 lbs. New, with manual.

Stock #PS9410 **$195.00**

RETRO-REFLECTIVE PRISM /IR FILTER

Very high quality retro-reflecting prism. This prism returns an incoming light beam back to the source. Beam divergence is 10° or less. A light ray is returned to its source irrespective of reception angle up to approx. 30°. In addition, this prism has the apex of the reflecting surfaces flattened and polished. An infrared filter is bonded to this flat surface. With this modification the prism can be used as a retro-reflecting objective lens. These units are ideal for use as IR receiving or transceiving elements. Two could be used with co-axially mounted emitter/receiver pairs to form an infrared transceiver, etc. Also can be used for any retro-reflection, range finding applications or experiments. Front surface has anti-reflection coating. New, in perfect condition. Dimensions: 2.610" max. O.D. Filter is 18mm dia. x 2mm thick. Overall depth of prism and filter is 1.412". NOTE: We have production quantities of these units available.

Stock #OL9600 **$69.50**

Without truncated apex or attached infrared filter.

Stock #OL9601 **$79.50**

3600 RPM DC MOTOR WITH ENCODER



ELECTRO-CRAFT #M1140 or equiv. 30 volts nom. input voltage. Permanent magnet, reversible servo motor. Has Hewlett Packard optical encoder. Ball bearings. No load speed at 30 VDC input is 4600 rpm. No load current 0.75 amp at 60 oz-in load rpm is 3600, current is approx. 6.6 amps. Torque constant is 9.1 oz-in per amp. Rotor inertia 0.0007 oz-in-sec². Terminal resistance 0.89 ohm. Optical encoder has 1024 counts per revolution, two channel quadrature output. Outputs are TTL compatible. Dual shafts: front shaft is 3/8" dia x 3/4" long. Rear shaft is 1/4" dia. x 7/16" long. Dimensions: 4" dia. x 5-1/2" long (excluding shafts.)

Stock #DCME9601 **$45.00**

HEWLETT PACKARD TEST EQUIPMENT

#4328A. Milliohmmeter. (No Probes)	$275.00
#141T. Spectrum Analyzer Mainframe.	$500.00
#8552A. Spectrum Analyzer IF Plug-in, Linear or 10 dB Div. Log	$400.00
#8555A. Spectrum Analyzer RF Plug-in	$500.00
#432B. Power Meter.	$150.00
#204C. Oscillator	$125.00
#333A. Distortion Analyzer	$695.00
#3330B. Automatic Synthesizer	$650.00
#8614B. Signal Generator. 0.8-2.4. GC	$695.00
#216A. Pulse Generator	$295.00
#8445B. Automatic Preselector	$495.00
#8057. Noise Generator	$295.00

See our catalog for more models in stock.

CALL OR WRITE FOR OUR FREE 120 PAGE CATALOG FILLED WITH GOODIES—ELECTRONIC, OPTICAL, MECHANICAL, AND MUCH MORE! ALSO, PLEASE VISIT OUR RETAIL STORE WHEN YOU'RE IN PASADENA.

TOLL FREE: 1-800-325-9465

Write in 136 on Reader Service Card.

Miniature Transmitters and Receivers

Small, Attractive, High End Quality, 2 Channel Transmitter
59,049 Settable Codes, 150'–300' Range, 1–1/4"x2"x7/16", Assembled

		Qty 1	5	10
RF300T	150' Transmitter	24.95	19.95	15.95
RF300XT	300' Range Transmitter	29.95	24.95	19.95

Small, High End Quality, Receiver for the RF300 Transmitters
1–1/4"x3–3/4"x9/16", 8–24 vdc CMOS Input / Outputs, PCB

RF300R	Receiver, assembled	24.95	20.95	16.95
RF300RK	Receiver, Parts Kit	19.95	15.95	12.95

Small, Economical, Transmitter and Receiver Set
Set Code, 60' Range, 1–7/8"x2–3/8"x7/16" (T), 2"x2–3/4"x9/16" (R)

RF60	Transmitter and Receiver	24.95	19.95	14.95

Add $ 4 shipping for first item + $ 1 for each additional item. Ca. residents add 8.25% tax
Visa, Mastercard, Money Orders Personal Checks and Cash C.O.D.s

Visitect Inc. (510) 651–1425 Fax (510) 651–8454
P.O. Box 14156 Fremont, CA. 94539

Write in 214 on Reader Service Card.

RESISTOR SPECIAL - 10,000 resistors 50 each of 200 values (our selection of values) 1/4 watt 1-5% metal film $95 (less than 1¢ each). Or, you select the values and the quantity of each. Minimum of each value 50 pieces. Minimum order $50. 5% 1¢ each 1-2% 2¢ each. Shipping and tax included. Money order or cashier's check. Personal checks wait 10 days. Each value clearly marked for ID. Over 400 values available from a stock of millions. You won't believe the time, money, and inconvenience you'll save. We haven't received one complaint in five years! Murphy's Surplus, 401 N. Johnson Ave., El Cajon, CA 92020.

RF TRANSISTORS, tubes, electrolytics. 2SC2879, 2SC2290, 2SC1969, 2SC2166, MRF454, 2SC1307. 2SC2029, 2SB754, 2SC2312, TA7222AP, 4CX250B, 572B, 12D6Q, 6JS6C, 3-500 graphite, trimmers, resistors. Westgate 1-800-213-4563.

MILLIONS IN scrap gold are about to hit the market in the form of old computer junk. I'm making a bundle recycling this material and you can join me. Call 24-hour message: 603-645-4776.



WANTED: EXCESS ELECTRONIC INVENTORIES, ICs, MEMORY, EPROMs, PALs, LEDs, CIRCUIT BOARDS, DIODES, AND TRANSISTORS. CALL ACTIVE MICRO, 562-494-4851 OR FAX 562-494-4913.

WANT TO Buy: ICs, military & aircraft relays, diodes, transistors, Cannon, TRW, Amp, Burndy, Deutsch, Bendix connectors, electronic test equipment & most components. Hoffy Electronic Ent., 818-718-1165, FAX 818-341-5506.

MICROCONTROLLERS

SOLDERLESS STAMP PROTOTYPING. Stamp designs are a snap with the ASP-1. Breadboard connects to PC and 9V battery. Supports Stamp I and II. Details at http://www.al-williams.com/awc/stamp.htm or call/fax 281-334-4341.

http://www.dontronics.com is Don-Tronics Home Page. Hardware: Atmel and PIC microcontroller prototype and development boards, programmers, SimmStick™. **Software:** BASIC Stamp II Windows 95 Front End, AVRBasic for the AT90S1200, BascomLT for the AT89C2051, multi-media "Pacman-like" tutorial for the PIC16F84, and lots more.

ANTIQUE ELECTRONICS

WANTED: FOR historical museum, pre-1980 microcomputers, magazines, and sales literature. Floyd, VA 24091-0341 (540-231-6478/540-763-2321).

WESTERN ELECTRIC WANTED: 1927-1960S. Amplifiers, speakers, tubes, etc. Free offer. 1-800-251-5454.

TELEPHONE LISTENING DEVICE WITH 12 HR. RECORDER



FCC Approved

Record telephone conversations in your office or home. Starts automatically when phone is answered, records both sides of phone conversation. Recorder stops when phone is hung up. $99.95 + $7 shipping. For telehone listening device separately $19.95 + $2 ship.

For comprehensive 50 page catalog of Micro Video, VHF transmitters,Surveillance, and Counter-surveillance and much more! Send $3.00

Call 407-725-1000

USI CORP

P.O. Box N2052 Melbourne,FL 32902

COD'S OK

Write in 97 on Reader Service Card.

Honey, I shrunk the COMPUTER!



PicStics are like BASIC Stamps® on steroids. They have more speed, more parallel I/O, more code and data space, and more neat features like a real-time clock, 12-bit ADC, and 12-bit DAC.

As low as $29

Call for a catalog or visit our Web site today.

www.micromint.com

MICRO MINT

4 Park St. • Vernon, CT 06066

(800) 635-3355
(860) 871-6170

BASIC Stamp is a registered trademark of Parallax, Inc.

Write in 58 on Reader Service Card.

More Radio Direction Finding

Open Channel

by Joseph J. Carr
K4IPV

Last month, we looked at the more basic forms of radio direction finding systems. Those RDFs were based on either loop or loopstick antennas. This month, we are going to look at some additional types of antenna and receiver systems used for RDF activity.

Sense Antenna Circuit

Last month, I discussed the type of radio direction finding (RDF) system in which a loop or loopstick bidirectional antenna is made unidirectional by adding a "sense antenna" to the circuit. Unfortunately, later I realized that I forgot to tell you how to make the circuit (sorry). Figure 1 shows a method for summing together the sense and loop signals. The two terminals of the loop are connected to the primary of an RF transformer. This primary (L1A) is center-tapped and the center-tap is grounded. The secondary of the transformer (L1B) is resonated by a variable capacitor, C1. The dots on the transformer coils indicate the 90-degree phase points.

The top of L1B is connected to the sense circuit, and to the receiver antenna input. The phasing control is a potentiometer (R1). The value of this pot is usually 10 Kohm to 100 Kohm, with 25 Kohm being a commonly seen value. Switch S1 is used to take the sense antenna out of the circuit. The reason for this switch is that the nulls of the loop or loopstick are typically a lot deeper than the null on the cardioid pattern.

The null is first located with the switch open. When the switch is closed, you can tell by the receiver S-meter whether or not the correct null was used. If not, then reverse the direction of the antenna and try again.

Adcock Antennas

The Adcock antenna has been around since 1919 when it was patented by F. Adcock. Figure 2 shows the basic Adcock RDF array. This antenna consists of two center-fed non-resonant (but identical) vertical radiators. Each side of each element is at least 0.1λ long, but need not be resonant (which means the antenna can be used over a wide band). The elements are spaced from 0.1λ to 0.75λ, although the example shown here is spaced 0.125λ.

The Adcock antenna is vertically polarized, so it will respond to the vertically polarized wave very much like loop or phased array antennas of similar size. The horizontally polarized wave, however, affects all elements the same, so the currents are essentially cancelled, resulting in no pattern. This characteristic makes the Adcock antenna suitable for high-frequency shortwave RDFing.

The pattern for an Adcock antenna is shown in Figure 3. This pattern was generated using Nec-Win Basic. The example antenna is a 10 MHz (30-meter band) Adcock that uses 1.455-meter elements (total 2.91 meters on each side), spaced four meters apart. The pattern is a traditional "figure-8" with deep nulls at 0 degrees and 180 degrees. The antenna can be rotated to find a null in the same manner as a loop.



Figure 1.
Sense circuit for a loop/sense antenna RDF.

Watson-Watt Adcock Array

Figure 4 shows the Watson-Watt Adcock RDF array. It consists of two Adcock arrays arranged orthogonally to each other. It is common practice to arrange one Adcock in the east-west direction and the other in the north-south direction. These are fed to identical receivers that are controlled by a common local oscillator (LO). The outputs of the receivers are balanced, and are used to drive the vertical and horizontal plates of a cathode ray oscilloscope (CRO).

Figure 5 shows the patterns achieved by signals of various phases arriving at the Watson-Watt array. The patterns of Figure 5A and Figure 5B are made from signals 180 degrees out of phase, while the signal of Figure 5C is a 90-degree phase difference.

Doppler RDF Antennas

Figure 6 shows the basic concept of a Doppler RDF antenna. The Doppler effect was discovered in the nineteenth century. A practical example of the Doppler effect is seen when an ambulance wailing siren is approaching you, and then passes you and heads out away from you. The wailing pitch will rise as the sound source approaches, and then falls as the sound source recedes in the opposite direction.

In a radio system, when the antenna and signal source move with respect to each other, a Doppler shift is generated. This shift is proportional to the relative speed difference. The Doppler RDF antenna of Figure 6 uses a rotating antenna. The signal approaches from a single direction, so there will be a predictable Doppler shift at any point on the circular path of the antenna. The magnitude of the phase shift is:

$$S = \frac{R \omega F_c}{c}$$

Where:
S is the Doppler shift in hertz (Hz)
R is the radius of rotation in meters
ω is the angular velocity of the antenna in radians per second (rad/s)
F_c is the carrier frequency of the incoming signal in hertz (Hz)
c is the velocity of light (3×10^8 m/s)

In theory, this antenna works nicely, but in practice there are problems. One of the big problems is getting a large enough Doppler shift to easily measure. Unfortunately, the rotational speed required of the antenna is very high ... too high for practical use. However, the effect can be simulated using a number of antennas arranged in a circle that are sequentially scanned. The result is a piecewise approximation of the effect seen when the antenna is rotated at high speed.



Figure 2.
Adcock array RDF antenna.



Figure 3. Adcock pattern.

Wullenweber Array

One of the problems associated with small RDF antennas is that they have such a small aperture that relatively large distortions of their pattern result from even small anomalies. Follow that? What it means is that the pattern is all messed up by small defects. If you build a Wide Aperture Direction Finder (WADF), however, you can average the signals from a large number of antenna elements distributed over a large circumference circle. The Wullenweber array (Figure 7) is such an antenna. It consists of a circle of vertical elements. In the HF band, the circle can be 500 to 2,000 feet in diameter.

A goniometer rotor spins inside the ring to produce an output that will indicate the direction of arrival of the signal as a function of the position of the goniometer. The theoretical resolution of the Wullenweber array is on the order of 0.1 degrees, although practical resolutions of about 2.8 degrees is commonly seen.

Time Difference of Arrival (TDOA) Array

If you erect two antennas with a distance, d, apart, then arriving signals can be detected by examining the time-of-arrival difference. Figure 8A shows an example signal. If the advancing wavefront is parallel to the line between the antennas, then it will arrive at both antennas at the same time. The TDOA is zero in that case. But if the signal arrives at an angle (as in Figure 8A), it will arrive at one antenna first. From the difference between the time of arrival at the two antennas, we can discern the direction of arrival.

There is an ambiguity in the basic TDOA array in that the combined output will be the same for conjugate angles, i.e., at the same angle from opposite directions. This problem can be resolved by the system shown in Figure 8B.

The signals from ANT1 and ANT2 are designated V1 and V2, respectively. These signals are detected by receivers (RCVR1 and RCVR2), and are then threshold detected in order to prevent signal-to-noise problems from interfering with the operation. The outputs of the threshold detectors are used to trigger a sawtooth generator that controls the horizontal sweep on an oscilloscope.

The two signals are then delayed, and one is inverted. The reason for inverting one signal is to allow the operator to distinguish them on the CRT screen. The reason why this is necessary is the ambiguity. If the antennas in Figure 8A are arrayed east-to-west, then the line perpendicular to the line between them is north-to-south.

If we designate north as zero degrees, then the signal shown arrives at an angle of 330 degrees. That means it will arrive at ANT1 before it arrives at ANT2. A signal arriving from a bearing of 30 degrees will produce the same output signal, even though it arrives at ANT2 before ANT1. All signals of bearing $0 \le x < 180$ degrees will arrive at ANT2 first, while all signals $180 \le x < 360$ degrees will arrive at ANT1 first. Yet both will produce the same blip on the oscilloscope screen.

The solution to discerning which of the two conjugate angles is intended is to invert the ANT1 signal. When this is done, the ANT1 signal falls below the baseline on the CRT screen, while the ANT2 signal is above the baseline. By noting the time difference between the pulses, and their relative position, we can determine the bearing of the arriving signal.

Switched Pattern RDF Antennas

Suppose we have a unidirectional pattern such as the cardioid shown in Figure 9. If we can rapidly switch the pattern back and forth between two directions that are 180 degrees apart, then we can-



Figure 5. Patterns for different signals on the Watson-Watt array.



Figure 6. Doppler antenna.



Figure 4. Watson-Watt Adcock array.



Figure 7. Wullenweber RDF array.

not only discern direction, but tell whether an off-axis signal is left or right. This feature is especially useful for mobile and portable direction finding.



In Figure 9 we have three different positions for a signal source. When the signal source is at point A, it will affect the pattern to the left more than the pattern to the right, so the meter will read "LEFT." If the signal source is at point B, on the other hand, the signal affects both pattern positions equally, so the meter reads zero. Finally, if the signal arrives from point C, it affects the right hand pattern more than the left hand pattern, so the meter reads "RIGHT."

Figure 10 shows how such a system can be constructed. This system has been used by amateur radio operators using "rubber ducky" VHF antennas and a single receiver, where it is commonly called the "Double-Ducky Direction Finder" (DDDF). The antennas are spaced from 0.25λ to 1λ apart over a good ground plane (such as the roof of a car or truck). If no ground plane exists, then a sheet metal ground plane should be provided.

In Figure 10, we see the antennas are fed from a common transmission to the receiver. In order to keep them electrically the same distance apart, a pair of identical half wavelength sections of transmission line are used to couple to the antennas.



Figure 9.
Switched pattern RDF system.

Switching is accomplished by using a bipolar squarewave and pin diodes. The bipolar squarewave (see inset to Figure 10) has a positive peak voltage and a negative peak voltage on opposite halves of the cycle. The pin diodes (D1 and D2) are connected in opposite polarity to each other. Diode D1 will conduct on negative excursions of the squarewave, while D2 conducts on positive excursions. The antenna connected to the conducting diode is the one that is connected to the receiver, while the other one is parasitic. The active antenna therefore switches back and forth between ANT-1 and ANT-2.

This antenna is coupled to the receiver through a small value capacitor (C1) so that the squarewave does not enter the receiver. This allows us to use the transmission line for both the RF signal and the switching signal. An RF choke (RFC3) is used to keep RF from the antenna from entering the squarewave generator.

The DDDF antenna produces a phase modulation of the incoming signal that has the same frequency as the squarewave. This signal can be heard in the receiver output. When the signal's direction of arrival is perpendicular to the line between the two antennas, the phase difference is zero, so the audio tone disappears.

The pattern of the DDDF antenna is bidirectional, so there is the same ambiguity problem as exists with loop antennas. The ambiguity can be resolved by either of two methods. First, a reflector can be placed λ/4 behind the antennas. This is attractive, but it tends to distort the antenna pattern a little bit. The other method is to rotate the antenna through 90 degrees (or walk an L-shaped path).



Figure 8.
A) Time difference of arrival (TDOA) RDF array.
B) block diagram of typical TDOA circuit.



Figure 10.
Double-ducky RDF system based on the switched pattern system.

Conclusion

Radio direction finding can be very useful for locating RF noise sources, illegal stations, and other RF sources. It can also be used to locate yourself if you can get bearings on at least two stations. The lines of bearing will cross at a location approximately where you are standing ... try it, you'll like it. **NV**

Connections ...
I can be reached at P.O. Box 1099, Falls Church, VA 22041, or via E-Mail at carrjj@aol.com Your comments and questions are appreciated.

ANTIQUE ELECTRONICS *cont.*

VACUUM TUBE - ELECTRONICS, ANTIQUE RADIO. Ed Romney's book, **FIXING UP NICE OLD RADIOS** is the best. 188p. 300+ schematics, illustrations. $29. Romney, Box 487, Drayton, SC 29333. Phone: 864-597-1882. www.edromney.com

VACUUM TUBES: We stock 1,000 varieties of new old stock made in the USA vacuum tubes. Write or fax address for free pricelist. Antique Triode, 653 Commercial Street, Farnham, NY 14061 Fax 716-549-3823

ANTIQUE RADIO CLASSIFIED. Free sample copy! Antique radio's largest-circulation monthly magazine. Old radios, TVs, ham equip., 40s & 50s radios, telegraph, books & more. Ads & articles. Free 20-word ad monthly. Subscribe today. Six-month trial: $19.95. Yearly rates: $38.95 ($55.95 by 1st Class). Foreign: write. ARC, PO Box 802-G20, Carlisle, MA 01741. Phone: 508-371-0512; Fax: 508-371-7129; Web: www.antiqueradio.com

CRYSTAL SETS. Parts, plans, books, kits. Largest source in the world. Catalog $2. MIDCO, PO Box 2288, Hollywood, FL 33022.

312 ± VAC. tube collection, untested. Best offer over $350. Money order payment only. Deadline 1/15/98. C. Raney, POB 85, Chaffee, MO 63740.

WESTERN ELECTRIC WANTED: 1920s-1960s. Amplifiers, mixers, pre-amps, speakers, tubes, etc. FREE OFFER 1-800-251-5454.

Looking for a great value? Subscriptions to *Nuts & Volts* are only $19 for a full year. Call *Toll Free* and use your Visa or MasterCard to order! 1-800-783-4624

ATTENTION INDUSTRIAL/ BROADCAST VIDEO EQUIPMENT HOBBYIST! Here's a great opportunity to own the top of the line (IVC) color HI band one-inch broadcast-capable rack-mount video tape machine at a great affordable price. Originally over $25K, it's going for $500. That includes around 50 x 10" reels (hermetically sealed) of 90 minute video tapes. Includes complete set of spare boards and documentation. Tape machine is on its own roll-around rotatable rack for easy maintenance. Machine makes pictures but may need some tweaking. Fax 415-821-7500 or Tel 415-821-3359. F.O.B. San Francisco.

AVIATION ELECTRONICS

BUY, SELL, Trade: Avionics equipment. Collins, King, test equipment IFR, any Litton inertial nav. equip. LTN series 33, 39, 51, 58, 72, 92. 941-575-0138 P, 947-575-2361 F.

AIRCRAFT SOLID-STATE INVERTER by Vicor. 28V in, 5V out @ 50 watts. 28V in, 48V out @ 100 watts, 80 pcs. of ea. avail. New $60 ea. Call Roger @ GS&E, 716-338-7001. VISA-MC available.

PUBLICATIONS

NOW HEAR THIS! ELECTRONIC EAVESDROPPING EQUIPMENT DESIGN by Winston Arrington. This revised edition contains 117 schematic diagrams and text of our production and prototype equipment consisting of: 29 crystal controlled transmitters of all types; 35 room battery and mains powered; 32 telephone leech and battery types; combination leech telephone and room transmitter; 15 subscarrier and carrier-current; infrared and receiver; high gain audio amplifier; high impedance recorder activator, counter-surveillance procedure chapter; countermeasures detection equipment and additional useful schematics. It is necessary to know electronics including building equipment from a schematic. Price: $65 plus shipping & handling US $6, Canada $8. Pay with US or Canadian Postal Money Order or Cashier's Check. Citibank money orders and regular checks require 21 days clearance. Sheffield Electronics Co., PO Box 377940-E, Chicago, IL 60637-7940. Tel. 773-324-2196.

UNUSUAL FREE catalog: Camera repair manuals, supplies, tools, old radio books, more! Send SASE. Romney, Box 487, Drayton, SC 29333. www.edromney.com

THE CASE AGAINST PATENTS. Don Lancaster's tested and proven alternatives that work in the real world. $28.50, Synergetics Press, 3860 West First Street, Box 809, Thatcher, AZ 85552. 520-428-4073. synergetics@tinaja.com VISA/MC.

"HOW TO CUT YOUR ELECTRIC BILL IN HALF - avoid high electric bills! You can reduce your bill by 50% using proven methods. Call **LORD/WYATT COMMUNICATIONS** for details 718-789-7329 press ext. 20.

ALL ELECTRONICS CORPORATION

QUALITY PARTS

FAST SHIPPING

DISCOUNT PRICING

CALL, WRITE, FAX or E-MAIL For A Free 96 Page CATALOG. Outside the U.S.A. send $3.00 postage.

60 Watt Switching Supply

Mfg. by Sony for Sun Microsystems # APS-28
Input: 100-240 vac.
Output: 5 vdc @ 4.5 A and 12 vdc @ 4 A



On/off switch. IEC power input receptacle. 9.5" x 2.56" x 2.5". UL, CSA listed.

CAT #PS-60 **$12.00 each**

Ferrite Bead

TDK # HF70RH 16X28X9
1.1" x 0.63" od x 0.35" id.
CAT # FB-24 $1.00 each
10 for $8.50 - 100 for $70.00

SUPER SAVINGS ON S-VHS TAPES (USED)

Super VHS tape users! Save a bundle on name-brand S-VHS, T-120 tapes. These tapes were used for a brief period, then bulk erased. The record-protect tabs have been broken out, so you will have to cover the notch with a piece of tape, but they work great and cost a fraction of the "new" price. Try some, you'll be back for more.

CAT #S-VHS **$3.00 each**

10 for $28.00 • 100 for $250.00

Shielded Woofer

Designed for use in Infinity center channel video sound systems. These well constructed woofers have shielded magnets to prevent interference with picture quality.

5 1/4" 6 OHM
1" voice coil. 8 oz. magnet. 50 watts max power. 3.125" deep.



CAT # SK-7346
$10.00 each

12 for $96.00

Low Power Audio Amp

Motorola MC34119P
Low power audio amplifier suitable for speaker phones or talking picture frames. The 8 pin DIP package requires only a few additional parts, operates on 2 - 16 volts and drives speakers of 8 ohms or greater. Output power exceeds 250 mW with 32 ohm speaker. Power-down option saves power in battery driven applications. Hook-up sheet.
Large quantity available.

CAT # MC34119P
50¢ each

50 for $20.00
500 for $150.00

3 Volt Lithium Coin Cell with PC Leads

Panasonic # BR2330-1GU
3 volt, 255 mAh coin cell. Lithium batteries have a very long shelf life and are great for memory back-up protection. 0.9" diameter x 0.12" thick. 0.7" between positive and negative pc leads.
VERY SPECIAL PRICE
LARGE QUANTITY AVAILABLE

75¢ each

CAT #LBAT-16

20 for $12.00
100 for $45.00
1000 for $300.00

High Brightness FLASHER LEDs

T 1 3/4 (5mm) high brightness RED LEDs with built-in flasher unit. 3-5 Vdc operation

CAT # LED-4 2 for 90¢
100 for $40.00
1000 for $300.00

12 Volt LEDs

T 1 3/4 (5mm) diffused LEDs. Connect directly to 12 Vdc (max. 15 Vdc). No resistor necessary.

RED CAT# LED-100
2 for $1.00 - 10 for $4.00

GREEN CAT# LED-200
2 for $1.00 - 10 for $4.00

YELLOW CAT# LED-300
2 for $1.20 - 10 for $5.00

Light Activated Intrusion Alarm

Leviton "Snapit-Alert"
830-51031
This handy light activated alarm buzzes intermittently when exposed to light. Use it in desk drawer, gun rack, medicine cabinet, refrigerator, school locker or file cabinet to prevent children or unwanted intruders from being where they don't belong. Red plastic case with self-adhesive Velcro backing. 2.5" x 3" x 0.84". Operates on 9 volt battery (not included). Good-looking retail packaging.

$2.50 each

CAT# SNA-2

10 for $20.00

ORDER TOLL FREE 1-800-826-5432

MAIL ORDERS TO:
ALL ELECTRONICS CORP.
P.O. BOX 567
VAN NUYS, CA 91408-0567

FAX (818) 781-2653 • INFO (818) 904-0524
INTERNET http://www.allcorp.com/
E-MAIL allcorp@allcorp.com

NO MINIMUM ORDER • All Orders Can Be Charged to Visa, Mastercard, American Express or Discover • Checks and Money Orders Accepted by Mail • Orders Delivered in the State of California must include California State Sales Tax • NO C.O.D • Shipping and Handling $5.00 for the 48 Continental United States - ALL OTHERS including Alaska, Hawaii, P.R. and Canada Must Pay Full Shipping • Quantities Limited • Prices Subject to change without notice.

MANUFACTURERS - We Purchase EXCESS INVENTORIES... Call, Write, E-MAIL or Fax YOUR LIST.

Write in 174 on Reader Service Card.

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.

WORLD'S MOST UNUSUAL Communications Books! Large selection covering Scanners, "confidential" frequency (HF/VHF) registries, wireless history, bugging, wiretapping, electronic surveillance, monitoring, etc. Big free catalog! CRB Research, Box 56-NV, Commack, NY 11725.

ROBOTICS

ROBOTS WANTED: dead or alive, whole or parts. HeathKit (HERO JR, HERO 1, HERO 2000, or Arm Trainer), and robots (Topo, BOB, FRED, Andromman), RB5X, Gemini, Hubot, Newton SynPet, Omnibots, Rhino, Marvin, Servitron, ITSABOX, Cyber I, MAXX STEELE, etc. Also looking for robot options, books, and literature. Will pay cash. Please E-Mail: rdoerr@bizserve.com Call 810-777-1313 or write to: Robert Doerr, 26308 Cubberness, St. Clair Shores, MI 48081.

HEXAPOD ROBOT, walks forward, reverse turns left and right. Comes with everything to build your own robot. Includes a counterfeit Basic Stamp with example code. $150 complete. Add $7.50 S&H USA. IL residents add 6.25%. VISA, MasterCard. Tel: 309-382-1816 Fax: 309-382-1254 Web: www.lynxmotion.com Free catalog with more robots



ROBOTIC ARM, 5 axis arm, including gripper. Control with any serial port. Very accurate and repeatable. Comes with everything to build your own robot. Includes a MiniSSC2 servo controller with software. $195 complete. Add $7.50 S&H USA. IL residents add 6.25%. VISA, MasterCard, Tel: 309-382-1816 Fax: 309-382-1254 Web: www.lynxmotion.com Free catalog with more robots.

ZAGROS ROBOTICS mobile robotic kits and parts. PO Box 460342, St. Louis, MO 63146-7342. 314-768-1328. http://walden.mo.net/~zagros/zagros.htm zagros@mo.net

ATTENTION DEALERS: WHOLESALE ONLY!

EXCLUSIVE:

NEW!
Wavemaster 99 Channel
• Sleep Timer • Std./HRC Switch • Parental Control

10+	20 +	50+
$57	52	45

JAMES' ELECTRONIC SERVICES, LTD.
Formerly JES, Inc.
BEST PRICES!
FAST SERVICE
SAME DAY SHIPPING

	5+	10+	20+
Panasonic 145	$72	65	60
Refurb. Panasonic 145	57	55	52
Panasonic 100	52	49	--
Panasonic 175	--- CALL! ---		
Starcomm DQN (99 ch; Refurb.)	49	45	39

TOLL FREE: 800-322-9690 VISA MasterCard **FAX: 516-246-5634**

Write in 96 on Reader Service Card.

MICROMOUSE ROBOT, can be used for line tracking, mazes, etc. Everything you need to build your own robot. Includes a Counterfeit Basic Stamp with example code. $95 complete. Add $7.50 S&H USA. IL residents add 6.25%. VISA, MasterCard, Tel: 309-382-1816 Fax: 309-382-1254 Web: www.lynxmotion.com Free catalog with more robots.

INDUSTRIAL ELECTRONICS bonanza: Collection of brand new General Electric machine tool quality switches, pilot lights, proximity sensors, motor starters, etc., includes green PB, reflex photo limit switch, proximity switch, lever limit switch, relay contacts, red light, green light, spring switch, accessory kit, red light, black PB, photo sensing head, polarized retroreflector, selector switch, green light, magnetic starter, DPST relay, renewal parts, aux connector kit, amber light, pneumatic timer, capacitance sensor, red PB, big barrel proximity switch, mini prox switch, overload relay, black switch photo limit switch, limit level, amber lamp, limit switch, armored cable, aux connector kit, magnetic contactor, more. In original boxes at 19 cents on the dollar. $249 for the lot. Synergetics Surplus, 3860 West First Street, Box 809, Thatcher, AZ 85552. 520-428-4073. synergetics@tinaja.com VISA/MC.

Sell Nuts & Volts in your store! Contact us for complete details.
phone 909-371-8497
fax 909-371-3052
E-Mail distributors@nutsvolts.com

UNIVERSAL MOTOR CONTROL KIT $29, computer interfaced, drives two, 3A. 4, 5, 6, or 8 wire, steppers or two 3A. DC motors. Linear interpolation software included, expandable. **FREE CATALOG**, kits, and surplus goodies. 510-582-6602, SVS_KITS@MSN.COM fax 510-582-6603.

20%-50% off sale! Autonomous, mobile, programmable, small robot vehicles for experimenting and fun! Call 1-888-Mr-Robot or visit http://www.mil.ufl.edu/novasoft

Visit Us On The Web! **http://www.nutsvolts.com**

PARAMAX INC.

800.473.8080

AVAILABLE SOON

New Products
MaxPhone...
Real-Time Internet telephone
Use the Internet to call long distance for just the cost of a local call.*
Full Duplex - no delayed audio - no dropouts.
MaxPhone.....$139
*excluding ISP costs

Data Acquisition
MaxData... PRELIMINARY
16 Bit data acquisition board
MaxData.....$229

Stepper Motor Controllers
MaxMover and MaxMover Pro
16 Bit Stepper Motor Controllers
The MaxMover Pro is a high output power model for more powerful stepper motors.
MaxMover.....$259
MaxMover Pro.....$359

Digital I/O Controller
MaxI/O... PRELIMINARY
MaxI/O is the ultimate peripheral connector that allows you to control up to 65,535 devices at 16 bits per device from a single parallel port. Now there is no limit to what you can control with your computer.
MaxI/O.....$229

Let Paramax develop, host and promote a web site for your company at a cost effective rate. Reach the market you've been missing.
webmaster@paramax.net

Also available at Ford Electronics
714.521.8080

www.paramax.net

Write in 135 on Reader Service Card.

Speech Recognition Kit



Explore leading edge technology with this stand alone speech recognition kit. The circuit recognizes 40 words (1 second length). You easily train the circuit to recognize words you say. Train the circuit in any language; English, Spanish, Swahili, Chinese, etc. The circuit is easily interfaced to the outside world to control appliances, robots, equipment and machinery using voice commands.

Speech Recognition Kit
Unassembled $ 100.00

Images Company
PO Box 140742
Staten Island NY 10314
(718) 698-8305

Visit us on the Internet
http://www.imagesco.com

SURPLUS SALE

200,000 WALL TRANSFORMERS

3.6 VDC	900 MA	2.25
12 VDC	100 MA	1.10
12 VDC	500 MA	1.75
12 VDC	800 MA	2.10
14 VAC	500 MA	1.75
16 VAC	1.25 A	2.95

Min 1000/type -- Call for other types

SURPLUS TRADERS
PO Box 276,
Alburg, Vt. 05440
Tel: 514-739-9328
Fax: 514-345-8303
FREE CATALOG

PROGRAMMERS OVER 50 MODELS

ADVANTECH EETOOLS NEEDHAMS DATA I/O ICE TECHNOLOGY HILO SYSTEM GENERAL CHROMA MODULAR CIRCUIT TECHNOLOGY XELTEK

PROMAX EMP-20 MEGAMAX MEGAMAX4 SIMM/SIP TESTER EMUPA

CALL ADVANTECH LABTOOL	599 EETOOLS SIMMAX
629 ICE TECH MICROLV	795 CHROMA SIMM/SIP
650 EETOOLS ALLMAX +	359 MOD-MCT-EMUPA/R
409 EETOOLS MEGAMAX	279 MOD-MCT-EMUP/R
509 EETOOLS MEGAMAX4	49 EPROM 1G TO 512K
369 XELTEK SUPERPRO II	69 EPROM 1G TO 1MEG
409 XELTEK SUPERPRO II P	99 EPROM 4G TO 1MEG
249 XELTEX SUPERPRO L	199 EPROM 16G TO 1 MEG
165 XELTEK ROMMASTER II	89 EPROM 1G TO 8MEG
479 MOD-MCT-EMUPA	129 EPROM 4G TO 8MEG
739 STAG ORBIT-32	250 EPROM 8G TO 8MEG

LABTOOL48 MICROMASTER SUPERPRO ALLMAX PLUS ROMMASTER2

General Device Instruments
Sales 408-241-7376 Fax 241-6375 BBS 983-1234
Web www.generaldevice.com E-Mail icdevice@best.com

BCD electro

We'll Buy your excess Inventory

IC's, Transistors, Diodes, capacitors, trimpots, etc. etc.

- *Purchase outright*
- *Consignment*
- *Partnering agreements*

Send your excess list for a quick offer!

Contact Bob Harris
Phone (214) 343-2170, FAX 1854
email - bcdelect@onramp.net
web - http://www.bcdelectro.com

Serial Problems???

Use your PC compatible desktop or laptop computer to debug serial communications problems with **Serial,** our test tool for serial communications.

Serial works with the standard data rates and asynchronous serial formats commonly found in modern office and industrial environments. Suitable for development, service work, and end-user problem diagnosis.

- Easy to Use
- Menu and Windows
- Highly Configurable
- Contextual Help
- Autobaud Detect
- Time Stamping
- Custom font editor for EGA/VGA Screens
- Saves Configurations
- Extensive Manual
- Block transmit ability
- CRC/LRC generation

Serial, with manual $99.95
Cable for full duplex monitoring $49.95

For Orders and Inquiries Call: 1-800-980-9806
Allison Technology Corporation
8343 Carvel, Houston, TX 77036
FAX and BBS 1-713-777-4746

SEND FOR FREE CATALOG



NEW! SLR 30M, 40M OR 80M RECEIVER KITS WITH ANTENNA. VERY SENSITIVE. HAS HIGH IMMUNITY TO LOCAL AM BROADCAST AN QRN. SEE QST 10/97 ..... $101.50 PP

CODE PRACTICE OSCILLATOR $23.45 PP
CURTIS KEYER KIT MARCONI ANTENNAS
VIBROPLEX® KEYS J- POLE ANTENNAS
JADE BOOK: HARD TO FIND ENGINEERING DATA, HUMOR, FOLKLORE ..... $ 6.00 PP

SMART BATTERY CONTROLLERS KITS
AC OR SOLAR 110/220
1/2, 1, 3, 5 OR 6 AMPS

BUY THE MODULE OR ENCLOSED VERSION

1-800 JADE PRO (523-3776)
www.jadeprod.com/
email: jadepro@jadeprod.com
JADE PRODUCTS INC. E. HAMPSTEAD NH 03826-0368

PCB's in Minutes From LaserPrint!*

8 1/2" x 11" Sheets

* Or Photocopier Use household Iron to apply.

PnP BLUE	or	PnP WET
For High Precision Professional PCB Layouts		Easy Hobby Quality PCB's
1. LaserPrint 2. Iron-On 3. Peel-Off 4. Etch		1. LaserPrint 2. Iron-On 3. Soak-Off w/ Water 4. Etch
Adds an Extra Layer of Resist for Super Fine Lines on Std Clad Bds		Transfers Laser Printer or Copier Toner as Resist to Std Clad Bds

20Sh$30/40Sh$50/100Sh$100 Blue/Wet (No Mix)
Sample Pack 5 Shts Blue + 5 Shts Wet $20
VISA/MC/PO/CK/MO $4 S&H -- 2nd Day Mail
Techniks Inc. P.O. Box 463 Ringoes NJ 08551
(908)788-8249
100% Money Back Guarantee!-Dealer Inquiries Invited

Convert RS-232 to RS-485 or TTL/CMOS for Only $49.00

Communicate up to 4,000 feet, at up to 1 MEGA--BPS, full or half duplex, up to 32 units on one serial link, with 31 jumper options for flexible configuration, LED indicators.



COMMUNICATIONS CONVERTER

- FULL SCHEMATIC AND DOCUMENTATION
- FULL FAMILY OF MODULAR DESIGNS
- RS-485/RS-422 REMOTE I/O MODULE KITS
- NETWORK SOFTWARE AND SOURCE CODE
- AUTOMATIC OR RTS UNITS AVAILABLE
- RJ-11/12 CONNECTORS OR TERMINAL STRIP
- TURN YOUR PC INTO A DISTRIBUTED DATA ACQUISITION AND CONTROL SYSTEM

R.E. SMITH
(513) 874-4796
4311 TYLERSVILLE RD. ■ HAMILTON, OHIO 45011
FAX (513) 874-1236

TV 85 PJ & TV 86 CABLE CONVERTERS VOLUME & NON-VOLUME CONTROL

SALES/SERVICE
VOICE 1-800-473-0506
FAX 1-800-488-0525

FOSS WAREHOUSE DISTRIBUTORS
285 Schenck St.
N. Tonawanda, NY 14120
www.fossw.com

TELEPHONE TEST DEVICES

2 Line Simulator	$185.00
7 Line Simulator	$399.00
Caller ID Simulator	$395.00
20 HZ Ringing Module	$49.95
9-1-1 Training System	$370.00

** * * And Much More * * **

Check out our Web Site for detailed info about our unique line of test equipment. The CID-max Caller ID Simulator is a stand alone test unit that generates 10 different Caller ID messages per the Bellcore Specs!

Call John Today!
http://www.infinet.com/~jectech

1-800-631-0349

Peltier Junction

While They Last!

1 3/16 "x 1 3/16" cooling area

Quantity Pricing Available

WITH HEATSINK AND LEADS
$10 EACH
OR THREE FOR $25

COMREX RGB Composite Display

*refurbished
**90-day warranty

ONLY $99!!
Great for studio or lab monitors!! 640x480 resolution

Shreve Systems
318-424-9777
Ask for Jake

Returns subject to a 15% restocking fee. Prices are subject to change without notice.
WE ACCEPT VISA, MASTERCARD, AMEX, DISCOVER
http://www.shrevesystems.com

SPECIAL

ALL MAJOR BRANDS · ALL GUARANTEED

MICRO-PROCESSORS	EPROM	MEMORY MODULES
PIC 16C54	2716	1MEGX32 SIMM
PIC 16C56	2732	2MEGX32 SIMM
PIC 16C57	27C64	4MEGX32 SIMM
PIC 6C58	27C512	
GAL 16V8LP	27C256	CONTROLLERS / PROCESSORS
GAL 20V8LP	27C128	8748 / 80C31
GAL 22V10LP	27C010	8749 / 8255
STATIC RAM	27C020	8751 / 8254
6116	27C040	87C51 / 8253
6264	27C080	8752 / 8284
62256		8275
628128		8259

AND MUCH MORE . . .

WE BUY YOUR EXCESS INVENTORY

SINACO ELECTRONICS 818-705-1880 FAX 818-705-1881

ADAPT-11 • 68HC11 Module for Solderless Breadboards & Embedded Applications

- compact (less than 2" x 3") • 24 I/O, 8 analog inputs, SCI, SPI
- reset circuit, pushbutton, & mode select switch
- RS-232 interface, 5V regulator & external power connector
- I/O lines brought out to solderless breadboard connector
- choice of 6 header styles for the ultimate in flexibility!

Starter Packages include module with microcontroller, serial cable for downloading code from your PC, Motorola Programming Reference Guide, User Manual, 68HC11 software & demo program.
AD11-SP (2K EEPROM + 256 bytes RAM).....US$74.95
AD11C75-SP (8K EEPROM + 512 bytes RAM).....US$87.00
ADAPT-11C75DX (8K EEPROM + 32K SRAM).....US$120.00

NEW! 68HC12 MODULE!!!
ADAPT-812 Similar to our popular ADAPT-11 modular design, this full-featured, flexible 68HC812A4 core module has all the necessary elements for standalone, single-chip operation (4K EEPROM + 1K RAM). All I/O and control signals are brought out to two standard 50-pin connectors-- one for dedicated I/O, the other for additional I/O or memory expansion (up to 4 MB program and 2 MB data). Has RS232 & RS485 interfaces, on-board 5V regulator, 16 MHz crystal, & reset circuitry. Works with all BDM interface pods (pod required for programming).
AD812-M module with documentation & software.....US$99

TECHNOLOGICAL ARTS
voice/fax: (416) 963-8996
www.io.org/~techart

Get up to speed *fast!*

Quick PIC Kid's Kits

under $50
Learning toys for kids of ages
Sensors, alarms, timers, sonar, robotics, remote control,
Ready-to-use
Software & Hardware
For more info, contact us at
http://www.QPIC.com
email: info@qpic.com
(603) 643-8243

Fast Solutions with

Quick PIC MicroBoards

Prefab, PIC-based, tiny, low power, industrial, building block solutions to
Data Acquisition,
Sensors, Interfacing,
Data Logging
Process Control
Time Measurement
Connect to each other and the outside with high speed RS232/485
cost effective and easy-to use
Many applications can be put together in less that 20 minutes.

Electronic Product Design and Manufacturing

Embedded Microprocessor and DSP Applications

FPGA, CPLD, and ASIC Designs

Apogee R&D Services
59 Seekonk St.
Norfolk, MA 02056
Tel. 508-520-9803
Fax. 508-520-9838



TOGGLE SWITCH SUPERMARKET WHOLESALE PRICES

FERTIK'S
5400 ELLA ST., PHILA., PA 19120
FREE LIST PH/FAX
215-455-2121

CCTV SPECIALS

Panasonic AG-TL500
168 Hour Time-Lapse VCR



Built-in RS-232C Interface NEW!
On-Screen Display
2hr-168 hour modes
Repeat Pass Indicator
$750

Panasonic AG-RT600
40 Hour Real Time VCR

8/24/40hr
Time/Date Generator
Auto Repeat Recording
Alarm Search • Alarm Input
$650

Detection Dynamics DDC-5000P
Color Pinhole w/Audio

9 vdc • Built-in audio
Small! 42mm x 42mm
400 TVL • 1.0 Lux
$239

Detection Dynamics DDLCD4
Active Matrix 4" Color LCD Monitor

Lightweight for easy mounting
Wide viewing angle
12 vdc • 380 mA
Pro Version $325
$239

DETECTION DYNAMICS

Call us for all types of security & industrial closed circuit television equipment
www.ddaustin.com

7801 N. Lamar, Suite D-84 • Austin, Texas 78752
(512) 345-8401 • FAX 926-0940
CCTV CATALOG $5.00 - REFUND W/PURCHASE

EPS

EPROMS AS LOW AS 25¢

27C256	27C040	27C1024	87C51
27C512	27C400	28F010	8751
2732A	27C4096	28F020	8755
27C32	574000	28F040	68705
27C128	574200	8749H	2564
27C64	27C402	8748H	2516
2716	27C020	8741	PROCESSOR
2708	27C210	8742	8255
27C512-90	27C010	8744	8254
STATIC RAM		MEMORY	80C31

THIS MONTH

SPECIAL 2764

TEL: (818) 774-9444 · FAX: (818) 774-0822
WE BUY EXCESS INVENTORY



FREE SAMPLE COPY!

ANTIQUE RADIO CLASSIFIED

Antique Radio's Leading Monthly Magazine

Articles – Classifieds – Ads for Parts & Services. Also: Ham Equip. – Books – Telegraph – 40's, 50's & 60's Radios – Early TV – Auction Reports & more...

1-Year: $38.95 ($55.95 by 1st Class)
6-Month Trial - $19.95. Foreign - Write.

A.R.C., P.O. Box 802-G19
Carlisle, MA 01741
Call: 508-371-0512 — Fax: 508-371-7129
Web: www.antiqueradio.com

EQUIPMENT FOR SALE

ELECTRONIC TEST	
Tektronix	EXT 330
Hewlett-Packard	EXT 331
Other Manufacturers	EXT 332
MEASURE & INSPECT	EXT 333
VIDEO PRODUCTS	EXT 370
SCIENTIFIC & LAB	EXT 335
LASERS	EXT 340
POWER SUPPLIES	EXT 334
COBWEB CORNER	EXT 380
MFG COMPLETE INDEX	EXT 300

To obtain information via FAX: A) Have your fax number ready. B) Dial 1-800-547-4636. C) Request above Extension Numbers.

DEXIS CORPORATION
(612) 944-7670 FAX (612) 942-9712
9749 HAMILTON ROAD
EDEN PRARIE, MN 55344

CUT MANUFACTURING COST!

CABLE TV CONVERTER BOXES

SHEET METAL
20 GAUGE
SILK SCREEN
PRINTED
WITH YOUR CO. NAME



ALSO PCB, SMT, PROTOTYPES, ASSEMBLY. PLASTIC MOLDS, INJECTION MOLDING.

USA Office: **V&V Mach. & Equipment, Inc.**
Ph: (713) 397-8101, Fax: (713) 397-6220.
Mexico Plant: **Marketing Tech.**
Ph: 011 (525) 361-3351, Fax: 011 (525) 361-5996.

ROBOTICS

ST-Stepper Motor Controller

- CONTROL OF 4 STEPPER MOTORS INDEPENDENTLY (NETWORKABLE UP TO 128 MOTORS)
- MOTOR DRIVING POWER UP TO 2 AMP, 50V (UPGRADABLE)
- ACCELERATION & DECELERATION MODES ARE SUPPORTED
- 8 TTL COMPATIBLE I/O LINES

For more information about this and other products contact us at:
RMV ELECTRONICS INC.
Tel: (604) 299-5173 • Fax: (604) 299-5174
http://rmv.com • customer@rmv.com

TOLL CALL RESTRICTOR BUILD A KIT

Bilocon's Toll Call Restrictor keeps your long distance charges under control. It can limit dialing sequences that start with a 1, 0, 411, or 976 and it can also limit the number of digits dialed. The owner can program long distance numbers or area codes that are to be allowed.

Kit - Our kit comes with some of the parts mounted to the PCB. The builder only needs to install one IC, a capacitor, and the RJ-11 jack. PCB soldering capability is required. Mechanical assembly is very simple. The cost of the kit is $39.95.

Assembled and Tested - Units start at $54.95. Quantity discounts are available.

Bilocon Corp.
800-736-5927
425-353-2276
www.bilocon.com

Seabird Technical
3580 Haven Ave.
Redwood City.CA
94063-4603
650/367-8320
Fax 365-5845
Visa / MC
5 year warranty

Magnification 10X &30X -dual lighting
ST201A $325.00 delivered USA

CONTROL • MEASURE • INPUT

MODEL 40–$109

- RS-232 interface
- 28 lines digital I/O
- Eight analog inputs
- PWM output
- Three stepper ports

MODEL 100–$279

- 12-bit 100KHz A/D • Four analog outputs
- Three timer counters • 24 digital I/O

PRAIRIE DIGITAL, INC.
920 SEVENTEENTH ST., INDUSTRIAL PARK
PRAIRIE DU SAC, WI 53578
TEL: (608) 643-8599 · FAX: (608) 643-6754

Discount Computer Systems

Intel Pentium II P266MMX MZH Multimedia System

SYSTEMS INCLUDE:

MID TW. CASE, MB W/P II CHIPS 512 CACHE, 64MB EDO RAM, 5.1 GB HARD DRIVE, 24X CD ROM, 4MB 64 BIT 3D VIDEO CARD, 3.5" 1.44MB FD, 16 BIT 3D SOUND CARD, 33.6 FAX MODEM WITH VOICE, WIN 95 MOUSE, WIN 95 104 KEYBOARD, 80 WATT SPEAKERS, WIN 95 REL. 2, 17" SVGA MONITOR INCLUDED

$2999

800-804-6552

PC ADAPTER FOR FIXED FREQUENCY

MING Graphics card will run a Fixed Frequency Monitor just like an SVGA monitor on a standard PC with virtually all colors, DOS text, and graphics up to 1600x1200 resolution.

Specifications — Controller: Tseng Lab 128-bit ET6000, support 4MB MDRAM, MPEG, 3D apps; Tseng Lab 64-bit ET400032P, support 2MG DRAM, PCI or VLB bus. Driver Supported: Windows 3.X/NT/95, AutoCAD, Lotus 123, WordPerfect, 3D, and others. Sync: sync on green (3 BNC conn.), composite sync (4 BNC conn.), separate sync (5 BNC conn.), HV (13W3 conn.). Manufacturers supported: Radius, Hitachi, Sun, HP, Sony, Tektronics, DEC, IBM, Mitsubishi, Ikegami, Appolo, and others.

Call us today at (909) 738-1416
or visit our web site at
http://www.riverside.quik.com/ming
Tech Support: (909) 372-0489
Fax: (909) 549-3628

WHOLESALE PRICING

- All Converter Boxes
- Universal Converters
- And Many More Cable Items

Free Catalog
(800) 676-6342
MEGA ELECTRONICS

CELLULAR PHONES BIG CLOSEOUT SALE

10,000+ units as low as
$39

Thousands of phones, both digital and analog. All major brand names and current models available. Like: Motorola, Nokia, Erickson, and many more.

Batteries, Leather Case, Car Charger **$4.95** Minimum qty. app.

1-800-328-7120
FAX 954-730-3326

Slot Machines $ 449.00

Free Shipping

Slot Machine Demo Video $ 5.99
40 - Minutes

33" High 20" Wide 14" Deep

Brochure $ 1.00

Filter Kits

Notch Filters

Video Media www.nutnet.com
P.O. Box 93/6025
Margate, Fl. 33093
(954)-752-9202

Weeder Technologies

Add $4 ship/hand **FREE CATALOG!** Visa MasterCard **Pro-Kit**

PO Box 2426, Ft. Walton Beach, FL 32549 850-863-5723

Stackable RS-232 Kits

Digital I/O - 12 I/O pins individually configurable for input or output. DIP switch addressable; stack up to 16 modules on same port for 192 I/O points. Turn on/off relays. Sense switch transistions, button presses, 4x4 matrix decoding using auto-debounce and repeat. **$32.00**

Analog Input - 8 input pins. 12-bit plus sign self-calibrating ADC. Returns results in 1mV steps from 0 to 4095. Software programmable alarm trip-points for each input. DIP switch addressable; stack up to 16 modules on same port for 128 single-ended or 64 differential inputs. **$49.00**

Home Automation (X-10) - Connects between a TW523 and your serial port. Receive and transmit all X-10 commands with your home-brewed programs. Full collision detection and auto re-transmission. **$38.50**

Caller ID - Decodes the caller ID data and sends it to your serial port in a pre-formatted ascii character string. Example: *12/31 08:45 850-863-5723 Weeder, Terry <CR>*. Keep a log of all incoming calls. Block out unwanted callers to your BBS or other modem applications. **$34.50**

Touch-Tone Input - Decodes DTMF tones used to dial telephones and sends them to your serial port. Keep a log of all outgoing calls. Use with the Caller ID kit for a complete in/out logging system. Send commands to the Home Automation or Digital I/O kits using a remote telephone. **$33.50**

IR Remote Control Receiver

Learns and records the data patterns emitted by standard infrared remote controls used by TVs, VCRs, Stereos, etc. Lets you control all your electronic projects with your TV remote. Seven individual I/O pins can be assigned to any button on your remote, and can be configured for either *toggle* or *momentary* action. **$32.00**

DTMF Decoder/Logger

Keep track of all numbers dialed or entered from any phone on your line. Decodes all touch-tones and displays them on a 16 character LCD. Holds the last 240 digits in a non-volatile memory which can be scrolled through. Connect directly to radio receiver's speaker terminals for off-air decoding of repeater codes, or numbers dialed on a radio program. **$54.50**

50 MHz Frequency Counter

Reads frequency from 1Hz to 50MHz and displays up to 7 digits on a 16 character LCD. Auto-range feature provides floating decimal point and automatic placement of suffix (Hz, KHz, or MHz). Microcontroller based provides for very small parts count, only 2" x 3" big. **$46.50**

Telephone Call Restrictors

Two modes of operation; either prevent receiving or placing telephone calls (or call prefixes) which have been entered into memory, or prevent those calls (or call prefixes) which have *not* been entered into memory.

Block out selected outgoing calls. Bypass at any time using your password. **$35.00**

Block out selected incoming calls. Calls identified using Caller ID data. **$46.00**

ABC ELECTRONICS 315 7TH AVE N. MPLS. MN. 55401
(612)332-2378 FAX (612)332-8481 E-MAILSURP1@VISI.COM
WE BUY TEST EQUIPMENT AND COMPONENTS.
VISIT US ON THE WEB AT WWW.ABCTEST.COM

TEK 7B15 1 GHZ DELAYING TIME BASE	$250.00	TEK 2245 100 MHZ 4 CHANNEL O-SCOPE	$1200.00
TEK 2465A 350 MHZ 4 CHANNEL O-SCOPE	$3200.00	TEK 7A19 600 MHZ SINGLE TRACE AMPLIFIER	$150.00
TEK 7A26 200 MHZ DUAL TRACE AMPLIFIER	$75.00	TEK 7B85 400 MHZ DELAYING TIME BASE	$125.00
TEK 7904 500 MHZ MAIN FRAME	$250.00	HP 1630D 25 MHZ LOGIC ANALYZER	$250.00
TEK 577/177 CURVE TRACER	$1500.00	TEK 7S11 SAMPLING PLUG IN	$200.00
TEK 7S12 GENERAL PURPOSE SAMPLER	$350.00	FLUKE 95 SCOPE METER NO PROBES	$600.00
TEK 453 50MHZ OSCILLOSCOPE	$200.00	FLUKE 97 SCOPE METER WITH PROBES	$1000.00
DRANETZ 626 DISTURBANCE ANALYZER	$1500.00	HP 8182A 50 MHZ PATTERN GENERATOR	$800.00
GENRAD 1657 RLC BRIDGE	$750.00	PHILLIPS PM3296 400 MHZ OSCILLOSCOPE	$1000.00
TEK 7D20 PROGRAMMABLE DIGITIZER	$500.00	EMI SCR 7.5-300 7.5V 300A POWER SUPPLY	$500.00
TEK 465 100 MHZ OSCILLOSCOPE	$400.00	HP 8558B SPECTRUM ANALYZER	$1500.00
TEK 465B 100 MHZ OSCILLOSCOPE	$450.00	WAVETEK 175 WAVE FORM GENERATOR	$500.00
TEK 2335 100 MHZ OSCILLOSCOPE	$1200.00	WAVETEK 157 PROG. WAVE FORM SYNTH.	$500.00
TEK 2215 60 MHZ OSCILLOSCOPE	$350.00	RACAL DANA 1901 100 MHZ COUNTER	$200.00
TEK 496P 1KHZ-1.8GHZ SPECTRUM ANALYZER	$5000.00	VALHALLA 2790B SYSTEM INTERFACE	$150.00
BRADLEY 132 SCOPE CALIBRATOR	$700.00	GENRAD 1683 RLC BRIDGE	$300.00
PHILLIPS PM3350A 60 MHZ DIG.STORAGE SCOPE	$1000.00	HP 3455A MULTIMETER	$300.00
HP 8601A 110 MHZ SWEEP/SIGNAL GENERATOR	$400.00	HP 3456A MULTIMETER	$450.00
TEK FG504 40 MHZ FUNCTION GENERATOR	$500.00	FLUKE 5200A AC CALIBRATOR	$1500.00
HP 54100A 1GHZ DIGITIZING OSCILLOSCOPE	$3000.00	TEK TM504 4 SLOT POWER FRAME	$125.00
HP 8170A LOGIC PATTERN GENERATOR	$150.00	HP 4955A PROTOCOL ANALYZER	$500.00
SYSTRON DONNER DPSD 50	$500.00	MAGTROL 4614 POLYPHASE POWER ANLZR.	$300.00
LEADER LSG215A 125 MHZ SIGNAL GENERATOR	$700.00	TEK CT-5 HIGH CURRENT TRANSFORMER	$500.00

SPECIAL THIS AD ONLY TEK 475 200 MHZ OSCILLOSCOPE REGULAR PRICE $500.00 SALE PRICE $400.00
SPECIAL THIS AD ONLY TEK DAS 9100 AS IS NO PROBES THESE UNITS ARE UNTESTED NOT REJECTS $150.00

Write in 57 on Reader Service Card.

ROBOTICS *cont.*

STEPPER MOTORS/encoder X & Y assembly intended for use on HP Draftmaster plotter. Quality, ball bearing, 10V 2A $30 ea., $50 pair. Qty's available. 619-632-9775.



MOVE AND MEASURE! Three channel RS232 stepper controller with three A/D channels. Simple to use. Metal enclosure. Complete with PSU, cables, example programs, three 12V steppers. $150 incl. S&H. Call 540-623-2372 or http://www.mounet.com/~rsmith

MOBILE ARM, 5 axis arm including gripper plus mobile base. Control with PC or microcontroller. Everything you need to build your own robot. Includes a MiniSSC2 servo controller with software. $250 complete. Add $7.50 S&H USA. IL residents add 6.25%. VISA, MasterCard, Tel: 309-382-1816 Fax: 309-382-1254 Web: www.lynxmotion.com Free catalog with more robots.

Closing Date For Next Issue – December 10th!

PLANS – KITS – SCHEMATICS

TEST EQUIPMENT kits. If you liked Heathkit, you will love Technology Systems, 4 Prospect Pl., Torrington, CT 06790.

HEATH COMPANY is selling photocopies of most Heathkit manuals. Only authorized source for copyright manuals. Phone: 616-925-5899, 8-4 ET.

HOBBY CATALOG: Broadcast, ham, CB transmitters, amplifiers, antennas. TV add-ons, descramblers, bugging devices, science projects, start your own radio station books and more. PAN-COM International, Box 130-V, Paradise, CA 95967. www.panaxis.com

LONGWAVE KITS AND PRODUCTS. Including 1750 meter license-free equipment. Catalog $1. CURRY COMMUNICATIONS, BOX 1884, Burbank, CA 91507-1884. WEB: http://www.fix.net/~jparker/currycom.htm



TEC 2000 FILM HIGH DEFINITION PROFESSIONAL STRENGTH. SCHEMATIC TO PCB IN SECONDS! CREATE, ENLARGE, REDUCE ANY CIRCUIT! COSTS PENNIES. (8.5" x 11" SHEETS). WHOLESALE: 20/$25, 50/$50, 100/$80. SAMPLE KIT (5) $10. S/H ALWAYS $4 (SHIPPED 2ND-DAY AIR!). CALL 1-888-430-7576 ext. 3135.

200+ ELECTRONIC PROJECTS. Build for pleasure or make 100% (or more) profits reselling printed plans. Loose 55¢ stamp for catalog & dealer info. MATCO-A4, POB 509, ROSEVILLE, MI 48066-0509.

MAKE PCBs from your HPGL plotter. Info. SASE. Roler, 349 N. Murphy Ave., Sunnyvale, CA 94086.

Converters ★ Remotes ★ Converters ★ Remotes ★ Converters ★ Remotes

Converters

Modern Communications • (405) 691-0594 TEL & FAX

Converters:	10	50	100+
Panasonic: TZPC145	$75.00	$69.00	$65.00
Centurion CF-3000	$65.00	$60.00	$55.00
DRZ-3 or DRX-3-105	$29.00	$25.00	$18.00
Remotes:			
Jerrold: 400, 450, 550	$4.50	$4.00	$3.75
CFT: 2XXX	$4.95	$4.50	$4.25
S/A: 075, 175, 475	$4.95	$4.50	$4.25
S/A: 8600 Original	$5.95	$5.50	$5.00
Zenith (ALL)	$4.95	$4.50	$4.25
Tocom 5503-VIP	$4.95	$4.50	$4.25
Pioneer (ALL)	$4.95	$4.50	$4.25
Pioneer: Made in Korea	$5.95	$5.50	$5.00

Parts, Parts, Parts

	50	200	500
18 VAC, 300 MA P/S	$3.00	$2.50	$2.00
65.8 MHz Saw Filters	$2.50	$2.35	$2.10
PIC16C54	$2.20	$2.10	$2.00
PIC16C56	$2.35	$2.30	$2.25
Micro 68H705C8P	$9.50	$9.00	$8.50
4 MHz (Resonance 2 pins)	$0.45	$0.40	$0.35

Call for FREE CATALOG
(405) 691-0594

Remotes

Converters ★ Remotes ★ Converters ★ Remotes ★ Converters ★ Remotes

Write in 33 on Reader Service Card.

EZ80/6V4 TUBE

New European-made! Amperex brand marked, "Made in France."
EZ80 **$4.00 each**



DIFFERENTIAL SCSI CABLE

Three feet long, DB50M to SCSI-II.
K-18DSC3 **$24.95 each**

16-BIT IDE CONTROLLER

Hard drive only.
96C012 **$2.99 each**

6.5536 MHz CRYSTAL

Tone dialer/baud rate generator. HC18U size.
97P020 **$1.00 each**

50-LB. CARE PACKAGE

Surplus goodies from Silicon Valley. This is not junk, just material we've acquired in quantities too small to catalog - electronic and mechanical subassemblies for everything from robots to rockets. Assortments may include ICs, caps, connectors, bearings, diodes, hardware, circuit boards, cables. Weird and wonderful stuff. Most folks are happy with the assortments we send and we often get re-orders. Try one.
92U034 **50 Lbs. for $49.95**

40VCT, 1.2A TRANSFORMER

97E024 **$7.95 each**

DUKE'S DELIGHT

Five pounds of assorted electronic hardware - fasteners, nuts, bolts, screws, brackets, springs, standoffs, arms, gears, pulleys, and indescribable metal stuff scrounged from Silicon Valley's surplus to complement your hardware hoard.
92Z009 **5 Lbs for $4.95**

"Semiuniversal" RCA 39-BUTTON REMOTE CONTROL

This versatile unit works on several products and brands. Just press desired function button and enter the 3-digit code provided. Requires four AAA batteries. Unused.
97V010 **$9.95 each**

PAN & TILT MECHANISM

Two stepper motors control azimuth and elevation. Ideal for robotics applications, targeting, or TV camera control> One motor is 5.6V, 4.2A, 200s/rev, 1.8°/step, with gear reduction box. The other stepper is 3V, 1A, 200 s/rev, with a right-angle gearbox. Try driving it with our L293D IC.
97M025 **$24.95 each**

ROTOR CABLE WITH 50-OHM COAX

25 feet of RG58 cable with BNC connectors, plus 8-conductor cable with Jones plugs (rotor cable) in one jacket.
96W014 **$5.95 each**



SNAP-TOGETHER TOROID CORE

Center hole: 5/16". Core size: 5/8" O.D. x 9/16" L. Case size: 1: O.D. x 1" L.
97P026 **95¢ each**

OPEN FRAME POWER SUPPLY

5VDC @ 6A, and ±15VDC @ 1.5A. Power One HCBB-701, unused.
97E028 **$19.95 each**

SONY WALKMAN NiCd BATTERY

6V, 900mAH, 2.75" x 1.75" x 0.75". Part No. BP-MZ1. *Sony list price $79.95.*
97E026 **Our price $19.95**

Many Other Wall Warts In Stock!



9VDC, 200mA WALL WART

2.5mm x 5.0mm 90° coaxial power connector, center positive.
96E013 **$4.95**

RESISTOR RIOT

1/8, 1/4, 1/2 Watt, power, precision, fixed, adjustable, etc. Thousands of pieces.
92P023 **5 Lbs. for $4.95**

TV AUDIO DEMODULATOR

Unused unit from cable TV box takes channel 3, 4 or 5 signal and demodulates the audio. Comes with documentation and schematics, plus additional schematics to build add-on video demodulator board.
92A028 **$9.95 each**

"RFI SNIFFER"

This useful kit is a wideband RF detector that indicates RF field strength in the 100KHz to 500MHz range at low levels. The kit includes an etched and drilled circuit board and all necessary components, except 9V battery. It also comes with a plastic case, antenna and an attractive analog meter.

The RF power reading is not linear and simply indicates the presence of RF and its relative level. However, it makes a great BUG detector or you can use it to test the output of any RF transmitter, including ham radios, cordless telephones and even car alarm transmitters! The circuit has an adjustable attenuator to handle everything from low to high power levels. Use during RFI/EMI precompliance testing.

The kit is easy to assemble and comes with schematic diagrams and complete instructions.
97K005 **$29.00 each**



RELAY BOX

This nifty metal 4" x 6" x 6" box contains an 8-position barrier strip, DPST 15A toggle switch, cable and three nice 10-Amp relays (SPDT 24VAC coil; DPDT 240VAC coil; SPDT 240VAC coil).
97B025 **$5.95 each**

TIP127

10 for $5.00



FOUR-WAY SWITCH BOX

Switch monitor and keyboard between four computers. HD-15 and DIN-5 connectors.
13-MK4155 **$18.00**

"HIGH-SPEED" GAMECARD

For use with PC, XT, AT, PS/2 (25 & 30) and 100% compatible computers with clock speeds up to 35 MHz.
97C049 **$2.95 each**

UNIPOLAR STEPPER MOTOR DRIVER IC

UCN5804. Drives a unipolar stepper in one of three operating modes: single phase, two phase or half step. Up to 1.25 Amps per phase. Step and direction input. Drive with a 555 timer, parallel port, etc. Build your own robot, anything that requires precision positioning.
93I002 **$4.50 each**

NIPPON PULSE MOTOR

7.5 deg./step, 48 s/rev, 5 V, stepper with brass gear mounted on shaft. NPM P/N PF42-48ES. With spec sheet.
92M010 **$3.95 each**

COMBO PACK!

One 93I002 IC and 92M010 motor (both described above), with schematics.
93I003 **$7.95/set**

ADJUSTABLE VOLTAGE BENCH POWER SUPPLY

Input voltage: 105-125 VAC 60 Hz. Output voltage: 0-20 VDC, front panel adjustable. Output current 10A maximum. Brand new!
95E020 **$159.95 each**

HEXADECIMAL DISPLAY WITH LOGIC

Solid-state with TTL circuit to accept, store and display 4-bit binary data. 0.2270" (6.858mm) character. Left- and right-hand decimals. Separate LED and logic power supplies may be used. Internal TTL MSI chip with latch, decoder and driver. Operates from 5V or 6V supply. Constant-current driver for hexadecimal characters. Easy system interface. Utilizes "active low" for enable.
LR1707 **$7.95 each**

TREADMILL DISPLAY

LCD display offers speed, time, distance and scan modes as well as readout for Kcal/min. Operates on 5VDC. Uses +5V pulses to operate readout. Many applications.
93U013 **$5.95 each**



"PNEUMATIC LOGIC"

Eight double-action TTL-controlled pneumatic solenoids with test buttons and activity LEDs. Drivers and suppression diodes on board. Sorry, No docs.
97T004 **$39.95 each**

HOLD-VAC® SURFACE MOUNT TOOL

This pen-style vacuum tool is delivered to you with four different size vacuum cups - ideal for handling and manipulating various surface mount components during assembly or repair operations.
HV-800 **$19.95 each**

12VDC MINI FAN

2.375" square by 0.75" thick.
94F004 **$4.95**

Hundreds of fans in stock!
Fax or email your needs today.

CARBON COMP RESISTOR ASSORTMENT

10% and 20% tolerance. Many individually packaged.
94P031 **5 Lbs. for $9.95**



100 FT. RG/58U CABLE

With BNC male connectors.
97W028 **$19.95 each**

ALLTRONICS

2300-D Zanker Road - San Jose, CA 95131-1114

World Wide Web: http://www.alltronics.com

(408) 943-9773 - Fax (408) 943-9776

Store Hours: 9-6 M-F & 10-3 Sat. - Pacific
Visa, M/C, AmEx Accepted.
All Sales Final.
California Residents Add Sales Tax.
Shipping Additional on All Orders.
Prices Good 60 Days from Date of Publication

Send $2.00 For Our Latest Catalog!
$4.00 Foreign. Refundable on First Order.

011297

New Company

Positive Filters

$7.50ea

Min Purchase 10pcs

Channels In Stock

2-24 and 95-99

Visa, Mastercard, Discover and UPS COD

24 hours a day 7 days a week. Same day Shipments

800-684-0539

Learn MICROCONTROLLERS EMBEDDED SYSTEMS and PROGRAMMING...



with the AES learning system/ embedded control system. Extensive manuals guide you through your development project. All programming and hardware details explained. Complete schematics. Learn to program the LCD, keypad digital, analog, and serial I/O. for your applications.

THREE MODELS AVAILABLE. Choose from an Intel 8051, Intel 8088, or Motorola 68HC11 based system. All models come with:

• 32K Byte ROM, 32K Byte RAM • 2 by 16 Liquid Crystal Display • 4 by 5 Keypad • Digital, Analog, and Serial I/O • Interrupts,timers, chip-selects • 26 pin expansion connector • Built-in Logic Probe • Power Supply (can also be battery operated) • Powerful ROM MONITOR to help you program • Connects to your PC for programming or data logging (cable included) • Assembly, BASIC, and C programming(varies with model) • Program disks with Cross Assembler and many, well documented, program examples • User's Manuals: cover all details(over 500 pages) • Completely assembled and ready to use • Source code for all drivers and MONITOR • Optional Text Book

Everything you need. From $279

Money Back Guarantee

Call for Free Info Pack, or see

WEB at http://www.aesmicro.com

714-550-8094, FAX 714-550-9941

Call 1-800 - 730-3232

AES

Advanced Educational Systems

AES 575 ANTON BLVD., SUITE 300, COSTA MESA, CA 92626, USA

BUILD A radar jammer out of your old radar detector. No electronic knowledge needed. Call 24 hr. for easy step-by-step plans. "GUARANTEED." New from "Image Master Publishing" 1-800-295-0953. Only $9.95, $2.50 S&H.

FREE CATALOG. Laser light show with software $139, computerized waveform generator and software $25. Stepper motor controller $12, plus other kits and surplus goodies. 510-582-6602, SVS_KITS@MSN.COM fax 510-582-6603.

CALLER-ID PHONELINE simulator. Test/demonstrate telephone devices without phoneline! Six direct dial extensions, Caller-ID, distinctive ringing. Authentic dial tone, busy signals, 20Hz ringing. "Party-Line" kit includes PCB, all components, microprocessor, documentation, $199.95. Custom enclosure $32.95. Fully assembled $425. Shipping $8. Checks, credit cards. Digital Products Company, 134 Windstar Circle, Folsom, CA 95630. 916-985-7219, Fax 916-985-8460, E-Mail: digprod@aol.com Web site: www.digitalproductsco.com

All New Products

Mini-Mods

Miniature Engineering Modules

Serial Motor Controller. Control DC motors, fans, and Peltier junctions!



The Motor Mind B only $29.95 qty. 1

1.2"x1.3" SIP module, up to 30V/2A DC motors, 254 speed steps, reverse, read tach(0-65,528Hz), auto-speed control, simple 1 or 2 pin serial communication.
(shown here without heat sink)

Serial RAM. Store all kinds of data with one i/o line!



The RAMPack B only $29.95 qty. 1

1.6"x1.6" SIP module, 8K bytes of RAM, expandable to 32K, 1.2K-19.2K auto-baud detect, addressable Write, Byte Read, and Block Read commands, new buffer mode needs no addressing, 1, 2, or 4 pin serial communication.

Serial Clock. Real time and your choice of 4 alarm types!



The Pocket Watch B only $24.95 qty. 1

1"x1" SIP module, real time clock accurate to the second, year 2000 compatible, standard, single shot, short astable, and long astable alarm types, simple 1 or 2 pin serial communication.

Store serial data automatically, and retrieve it when you're ready, using the RAMPack B FIFO buffer.



Solutions 3

www.solutions-cubed.com
phone (916) 891-8045
fax (916) 891-1643

3029 F Esplanade
Chico, CA 95973

Place your order by phone, fax, mail, or via our web site. We accept Visa and Mastercard. Shipping and handling are extra. COD is extra.
Ask about our consulting services! BASIC Stamp is a registered trademark of Parallax Inc.

Stamp Applications

Putting the Spotlight on BASIC Stamp Projects, Hints, and Tips

by Jon Williams

Last month, we built a working alarm clock with the Stamp 2 and the Dallas Semiconductor DS1302. While I've been able to port the heart of that code to the Stamp 1, there just isn't enough program space left to do anything practical. This month, we'll create an alarm clock with the Stamp 1 by using a recent addition to the list of serial saviors: the Pocket Watch B (PWB) from Solutions Cubed. And, of course, we'll call on our old friend — the Scott Edwards' serial LCD backpack — to provide the display for the clock.

It's Time To Get Real – Part 2

The Pocket Watch B is a pin-for-pin replacement of the original Pocket Watch that Scott reviewed in this column in April '97. Improvements include:

- Factory calibrated timebase
- User accessible timebase
- User calibration of timebase
- Three advanced alarms: single-shot, short astable, and long astable
- Year 2000 compliance
- PCB insertable SIP connector
- Streamlined communications protocol

Physically, the Pocket Watch B is a one-inch-squared circuit board with a five-pin SIP connector on one edge. I found the arrangement of the SIP connector very handy; I simply plugged the PWB into a solderless breadboard and started experimenting. In a permanent project, you could use Scott Edwards' connéctamúndos header-post jumper wires (I love those things!). Refer to the Oct. '95 installment of Stamp Applications for instructions on building your own connéctamúndos-type jumper wires.

The connections to the PWB are +5 volts, ground, transmit, receive, and alarm. Don't be worried about the separate transmit and receive pins. These pins are never active at the same time, so we can tie them together for use with the Stamp. The alarm output from the PWB is a real help in conserving our I/O resources. Last month, we used eight pins. This month, we only need five.

How It Works

The PWB is a stand-alone, time-keeping module with advanced alarm features. It contains separate registers for the time and alarm values. Last month, we were forced to synthesize an alarm with the DS1302. The PWB conveniently handles all those details for us. The PWB also differs from the DS1302 in that the registers are transmitted in straight binary. We don't need to worry about BCD conversions when using the PWB.

Like the LCD backpack, the PWB communicates with the Stamp through an asynchronous serial connection. When you examine the code, you'll notice that each command sequence begins with $55. This byte is necessary for the PWB to detect the baud rate being used. And, while 4800 and 9600 baud are supported, the standard speed of the Stamp 1 limits us to 2400 baud.

The PWB uses two different time modes: standard and extended. In extended mode, two bytes are used for the year. The high byte of the year contains the century value (i.e., 19). If you need year-2000 compliance, or want to use one of the advanced alarms, use extended mode. And keep in mind that the PWB operates strictly in 24-hour mode. That is, the hours will always be from zero to 23. In order to save space, we'll stick with that format for this project. If you'd like to have a 12-hour clock, refer to last month's code for the conversion routine.

In addition to the physical alarm output, the PWB has four distinct alarm types: standard, single-short, short astable, and long astable. The standard alarm is the easiest to understand, and yet, the least convenient to use. Once the standard alarm trips, it will not reset unless the PWB power is cycled or an "alarm off" command is sent to the PWB. Either case requires the Stamp to monitor the alarm output, using up another precious pin.

The single-shot alarm output causes the alarm output to be on for a user-specified number of seconds. The PWB accepts values $0000 to $FFFE (65,534) allowing for very long outputs (greater than 18 hours). A possible down side to the single-shot mode is that it is not automatically re-enabled once fired. This means that you have to reset the alarm after the single-shot output has activated. One last note: The PWB automatically adds one second to the time you download. Keep this in mind for precision applications.

As I pointed out earlier, the PWB has two astable alarms: short and long. They are similar in that you download a repetition rate and duration for the alarm output. In short mode ($17), repetition is specified in minutes, and duration is specified in seconds. In long mode ($18), repetition is specified in hours, and output is in minutes. And just as with the single-shot mode, the PWB increments each register (repetition and time) by one. Since our project is a standard alarm clock, we tell the PWB to turn on the alarm output for one minute every 24 hours with this command:

```
SEROUT ClkIO, ClkBaud, ($55, $18, 23, 0)
```

Our BS1 Alarm Clock

Aside from the different RTC and LCD hardware, our BS1 alarm clock is structurally similar to the BS2 version we built last month. The features of the PWB certainly simplify the code, allowing it to fit into the slim resources of the Stamp 1. Examining Listing 1, you'll see that the code reads the PWB, displays the time just read, and checks the time-set buttons. If either time-set button was pressed, the raw time value is updated and the



clock is reset with that value. Since the PWB handles the alarm processing, we simply need to connect our circuit to it.

There are no new tricks used in this program, however, there is one area that I feel could use a bit more explanation: the use of I/O pins as variables. If you look very carefully, you'll see that this program does not actually know what it's reading or setting (time or alarm). The program simply deals with a time value. What this value represents is determined by the state of the Time/Alarm input.

Within our definitions, we have a variable called TmAlrm that tracks the state of pin 2. This pin is normally pulled low through a 10K resistor. With the Time/Alarm switch in the Time position (open), a read of TmAlrm will return a value of zero. When the switch is in the Alarm position (closed), a read of TmAlrm will return a value of one. The value of TmAlrm is refreshed every time we use it since it is referencing pin 2.

Last month, we used this input (albeit inverted) as an array index for our rawTime variable. Since the PWB contains separate time and alarm registers, this month we're using TmAlrm variable to determine which set of registers are being retrieved or set. To read the time registers (standard mode is suitable for our project) from the PWB, we need to issue the command byte of $02. To read the alarm time registers, we need to issue a command byte of $03. No problem; we simply add the value of TmAlrm to $02 and use this as our command byte.

We use the same technique when setting the time or alarm. There is a bit of extra code in the SetTm routine to set up the long astable alarm and to enable the alarm output.

The PWB command set made the technique I just described pretty easy. But what would you do if the commands were, say, $03 and $15? This is still not a problem; it just requires a little extra math. If the code for "get time" was $03, and the code for "get alarm" was $15, we'd rewrite our command line like this:

```
temp1 = $12 * TmAlarm + $03
```

Run through the math so you understand how this works. Note that the order is important. Remember that the Stamp 1 evaluates math strictly from left to right — parenthesis are not allowed and there are no operator precedents. Do keep this one in your bag of tricks. It'll save you a couple of lines of code, which is always important when working with the Stamp 1.

True to our word, we built an alarm clock with the Stamp 1. It's not particularly fancy, but it is very functional and there's enough space left for a few bells and whistles. If you connect the PWB to a Stamp 2, you'll have plenty of code space to work with the date registers. Give it a try.

Once again, I'd like to thank those of you who have sent E-Mail. I sincerely appreciate your kind comments and your thoughtful ideas. And I'd like to thank the good folks at *Nuts & Volts* and my friend Scott Edwards for their faith in my first stint as a columnist. To each of you reading this, may God bless you, your families, and loved ones through this holiday season, and the coming new year. I'll see you in 1998! **NV**

Sources

For more information on the BASIC Stamp, contact:

Parallax, Inc.
3805 Atherton Road, #102, Rocklin, CA 95765
phone **(916) 624-8333**
Internet **http://www.parallaxinc.com**

Scott Edwards Electronics
P.O. Box 160, Sierra Vista, AZ 85636-0160
phone **520-459-4802**; fax **520-459-0623**
Internet archive *(catalog, user manuals, samples)*
located at **ftp.nutsvolts.com** in directory
/pub/nutsvolts/scott
E-Mail: **72037.2612@compuserve.com**

Jon Williams
1505 Grande Blvd., #1602
Tyler, TX 75703
(903) 509-1691
jonwms@aol.com
Internet: **http://members.aol.com/jonwms**
ftp://members.aol.com/jonwms/stamps

Solutions Cubed
3029-F Esplanade
Chico, CA 95973
(916) 891-8045
http://www.solutions-cubed.com

```
' Listing 1
' Stamp Applications: Nuts & Volts, December 1997

' —[ Title ]———————————————
'
' File..... BS1CLOCK.BAS
' Purpose... Stamp 1-based Alarm Clock
' Author.... Jon Williams
' E-mail.... jonwms@aol.com
' WWW..... http://members.aol.com/jonwms
' Started... 25 OCT 97
' Updated... 26 OCT 97


' —[ Program Description ]—————————————
'
' This program demonstrates basic timekeeping functions using the Pocket
' Watch B real-time clock module from Solutions Cubed. A Scott Edwards'
' Electronics serial backpack is used for the display


' —[ Revision History ]————————————————
'
' 26 OCT 97 : Completed and working


' —[ Constants ]———————————————
'
' ==================
' I/O Pin Definitions
' ==================
'
SYMBOLSetHr     = 0
SYMBOLSetMn     = 1
SYMBOLTmAlrm = Pin2

' ==============
' Pocket Watch B
' ==============
'
SYMBOLClkIO     = 3
SYMBOLClkBaud = T2400

' command set
SYMBOLWrTime  = $00     ' write time – standard
SYMBOLWrAlrm  = $01     ' write alarm – standard
SYMBOLRdTime  = $02     ' read time – standard
SYMBOLRdAlrm  = $03     ' read alarm – standard
SYMBOLAlrm1   = $04     ' alarm on
SYMBOLAlrm0   = $05     ' alarm off
SYMBOLWrXTm   = $10     ' write time – extended
SYMBOLWrXAlrm= $11      ' write alarm – extended
SYMBOLRdXTm   = $12     ' read time – extended
SYMBOLRdXAlrm= $13      ' read alarm – extended
SYMBOLAlrm1X  = $14     ' alarm on – extended
SYMBOLAlrm0X  = $15     ' alarm off – extended
SYMBOLSSAlrm  = $16     ' single-shot alarm
SYMBOLSAAlrm  = $17     ' short astable alarm
SYMBOLLAAlrm  = $18     ' long astable alarm
SYMBOLGetAlrm = $19     ' get alarm characteristics


' ==================
' SEE Serial Backpack LCD
' ==================
'
SYMBOLLcdIO     = 4
SYMBOLLcdBaud= N2400

SYMBOL I        = $FE   ' backpack instruction toggle
SYMBOL ClrLCD  = $01    ' clear the LCD
SYMBOL CrsrHm  = $02    ' move cursor to home position
SYMBOL CrsrLf  = $10    ' move cursor left
SYMBOL CrsrRt  = $14    ' move cursor right
SYMBOL DispLf  = $18    ' shift displayed chars left
SYMBOL DispRt  = $1C    ' shift displayed chars right
SYMBOL DDRam   = $80    ' Display Data Ram control
SYMBOL CGRam   = $40    ' Char Gen Ram control


SYMBOLBtnDly    = 35    ' delay for BUTTON loop


' —[ Variables ]———————————————
'
SYMBOLsecs      = B0
SYMBOLmins      = B1
SYMBOLhrs       = B2
```

Stamp

```
SYMBOLxx        = B3                    ' space holder for date registers
SYMBOLtemp1     = B4
SYMBOLtemp2     = B5
SYMBOLbutn      = B6                    ' BUTTON workspace
SYMBOLrawTm     = W4                    ' raw time (minutes past midnight)


' —[ EEPROM Data ]————————————————
'


' —[ Initialization ]—————————————
'
Init:   Dirs = %00011000
        Pins = %00001000
        PAUSE 1000                      ' let clock and LCD initialize


' —[ Main Code ]——————————————————
'
Start:  GOSUB GetTm                     ' get the clock
        GOSUB ShowTm                    ' show clock on backpack lcd

        butn = 0
ChkHr:  BUTTON SetHr,0,150,10,butn,0,ChkMn      ' is Set Hours pressed?
        GOSUB GetTm                     ' yes, get the clock
        rawTm = rawTm + 60 // 1440
        GOSUB SetTm                     ' set new time
        GOSUB ShowTm                    ' display the change
        PAUSE BtnDly                    ' pause between changes
        GOTO ChkHr                      ' still pressed?

ChkMn:  BUTTON SetMn,0,150,10,butn,0,Start      ' is Set Minutes pressed?
        GOSUB GetTm                     ' yes, get the clock
        rawTm = rawTm + 1 // 1440
        GOSUB SetTm                     ' set new time
        GOSUB ShowTm                    ' display the change
        PAUSE BtnDly                    ' pause between changes
        GOTO ChkMn                      ' still pressed?

        GOTO Start


' —[ Subroutines ]————————————————
'
GetTm:  temp1 = $02 + TmAlrm            ' time ($02) or alarm ($03)
        SEROUT ClkIO,ClkBaud,($55,temp1)
        ' note that we ignore day, month and year
        SERIN  ClkIO,ClkBaud,secs,mins,hrs,xx,xx,xx
        rawTm = hrs * 60 + mins         ' update raw time value
        RETURN

SetTm:  hrs = rawTm / 60                ' get hours from raw time
        mins = rawTm // 60              ' get minutes from raw time
        ' set the clock time
        ' (alarm if "TmAlrm" input is high)
        temp1 = $10 + TmAlrm            ' calculate command code
        SEROUT ClkIO,ClkBaud,($55,temp1,0,mins,hrs,10,18,97)
        IF TmAlrm = 0 THEN Done
        ' reset the alarm output duration
        ' every 24 hours for 1 minute
        ' (the Pocket Watch B increments each value by 1)
        SEROUT ClkIO,ClkBaud,($55,LAAlrm,23,0)
        ' enable the alarm
        SEROUT ClkIO,ClkBaud,($55,Alrm1X)
Done:   RETURN

ShowTm:         SEROUT LcdIO,LCDBaud,(I,ClrLCD)         ' clear the lcd
        temp1 = hrs / 10                ' get the hours 10s digit
        temp2 = hrs // 10               ' get the hours 1s digit
        SEROUT LcdIO,LCDBaud,(#temp1,#temp2,":")
        temp1 = mins / 10               ' get the mins 10s digit
        temp2 = mins // 10              ' get the mins 1s digit
        SEROUT LcdIO,LCDBaud,(#temp1,#temp2)
        ' remove next 3 lines to conserve code space
        temp1 = secs / 10               ' get the secs 10s digit
        temp2 = secs // 10              ' get the secs 1s digit
        SEROUT LcdIO,LCDBaud,(":",#temp1,#temp2)
        RETURN
```


Serial Display Modules

We offer top-quality LCDs that accept data through a serial interface at up to 9600 baud. Easy to use with computers and controllers (e.g., BASIC Stamps, PCs)—if you can send serial (RS-232), you can have a display working in minutes!

Contact us or download sample user manuals, catalogs, schematics and other docs from our FTP archive.

OEMs: serial-to-LCD chips and boards available at great quantity discounts

$45 *non-backlit*
$55 *LED backlit*

$89 *LED backlit*

$139 *non-backlit*
$159 *LED backlit*

Counterfeit Kits

Designed by the author of the *Stamp Applications* column, the Counterfeit is no fake! It's the **genuinely** easy, **truly** inexpensive kit equivalent to the BASIC Stamp I microcontroller. Get started with microcontrollers today with a $69 Counterfeit Development System, or add a Counterfeit to your Stamp collection for $29.



Mini Serial Servo Controller



$29 *kit*
$44 *assembled*

Control hobby servos with a Stamp or PC computer. Build robots, automated camera positioners, test equipment, etc. The Mini SSC generates precise, stable servo-control signals based on simple, serial instructions. Want to know more? Get our catalog or download info from our Internet archive.

Scott Edwards Electronics

We accept Visa, Mastercard, Discover, and American Express.
Personal/company checks OK for mail orders. CODs incur a handling fee.

Scott Edwards Electronics • PO Box 160 • Sierra Vista • AZ • 85636-0160
ph: 520-459-4802 • fax: 520-459-0623 • e-mail: 72037.2612@compuserve.com
Internet: ftp://ftp.nutsvolts.com/pub/nutsvolts/scott

BASIC Stamp is a registered trademark of Parallax Inc.

Write in 67 on Reader Service Card.

ATTENTION DEALERS

BUY DIRECT FROM THE WHOLESALER

GET THE BEST PRICES AND SERVICE

ALL UNITS ARE IN STOCK FOR IMMEDIATE SHIPMENT

CABLE CONVERTERS AND ACCESSORIES

CALL FOR PRICING ON ITEMS NOT LISTED

	QTY 5	QTY 10	QTY 25	QTY 50	QTY 100
NEW CONVERTERS					
CENTURY CT-3000	$68	$64	$60	$55	CALL
COMMERCIAL-11	$75	$70	$65	$62	CALL
PANASONIC-1003	$55	$49	$48	$46	CALL
DIGITECH-550 MHZ	$55	$49	$48	$46	CALL
NOVAVISIONS					
NV-5600	$175	$170	$165	$155	CALL
NV-5700	$175	$170	$165	$155	CALL
NV-5800	$175	$170	$165	$155	CALL
NV-6600	$269	$249	$239	$229	CALL
REFURBISHED CONVERTERS					
PANASONIC-145R	$55	$50	$42	$38	CALL

1-800-800-0766

KIMTRONIX

30 day money back guarantee. All shipping and handling at customers expense. Anyone implying theft of cable service will be denied sale. NO FLORIDA SALES.

WE WILL MEET OR BEAT ALL COMPETITOR'S PRICES IN THIS MAGAZINE

Write In 173 on Reader Service Card.

REFILL INKS FOR INKJET PRINTERS

Refill your old cartridge and save. All refill kits come with instructions and needed materials for refilling inkjet cartridges. Success guaranteed. Available for the following:

CANON BC-01, BC-02 CANON BJ10e, APPLE STYLEWRITER, BJ-200 Single, Black, $8.00. **CANON BJC-600** (BC-201) Single Black or Single Colors (3 refills) $8.00. **CANON BJ-130/300/330 & IBM Exec Jet** (Cart #BJI-481 & BJI-642) Black - 3-bottle kit $22.00. **CANON BJC-210/240** (BC-05 Cart) 3-color kit (3 refills each color for BC-05) $24.00. **CANON BJC-4000** and Apple Stylewriter 2400 Black 3-bottle kit (3 refills BC-20, 9 refills BCI-21 black, 30 refills BCI-11 black, 10 refills BCI-10) $19.00. **CANON BJC-4000/BJC70** and **Apple Stylewriter 2400** Tri-color kit - 6 refills each color for BCI-21 or 15 refills each color for BCI-11 $24.00. **CANON BJC-800/820/880** 3-bottle kit (for BJI-643B) $19.00. **CANON BJC-800/820/880** 3-bottle tri-color kit (Cart #BJI-643CMY) $24.00. **EPSON STYLUS COLOR PRINTER** - (Cart S020034) Single Triple black $19.00; Tri-color kit (Cart S020036) 2 refills each color $24.00. **EPSON STYLUS COLOR II** - (S020047) Triple Black $19.00 (S020049). Tri-color (2 refills each color) $24.00. **EPSON STYLUS COLOR 400, 500, & 600** (S020093) Triple black (7 refills total) $19.00; **EPSON STYLUS COLOR 200, 500** (S020097) Tri-color 3 refills each color $24.00. **EPSON STYLUS COLOR 800 & 1520** Triple Black (S020108) 5 refills total $19.00. **EPSON STYLUS COLOR 400, 600, 800, 1520** Tri-color (S020089) 3 refills each color $24.00. **EPSON STYLUS 800/1000** (S020025) 3-refill kit, black, $19.00. **HP DESKJET 500/550/560** (51608A, 51633A, 51626A) Black single refills $8.00. **HP DESKJET 500/550/560** (51626A). Black 3-bottle kit $19.00. **HP DESKJET 500C/550C/560C** (51625A) . Tri-color kit (5 refills each color) $24.00. **HP DESKJET 1200C, DESIGNJET 650** (Cart #HP 51640B) Black Three pack (3 refills) $19.00. **HP DESKJET 1200C/1600C, DESIGNJET 650** (Cart #HP 51640 C,M,Y). Tri-color kit (one refill each color) $24.00. **HP DESKJET 600/660** (HP 51629A) Black three pack $19.00. **HP DESKJET 600C/660C.** (HP 51649A) Tri-color (5 refills each color) $24.00. **HP DESKJET 855C/1600C** (HP 51645A) Black three pack $19.00. **HP DESKJET 855C** (HP 51641A) Tri-color kit (2 refills each color) $24.00. **HP PAINTJET** and **PAINTJET XL** (51606A) Black 3-bottle kit $19.00. **HP PAINTJET** and **PAINTJET XL** (51606C) Tri-color kit $24.00. **HP PAINTJET XL300** (C1645A & C1656A) Black 3-refill kit $19.00. **HP PAINTJET XL300** Tri-color kit (1 refill each color) HP 51639C,M,Y $24.00. **HP THINKJET, QUIETJET, KODAK DICONIX 150** (51604A or 92261A) black 5 refills $9.00. **IBM/Lexmark/Execjet/4076** (1380620) black 3-refill kit $19.00. **IBM/Lexmark ExecJet IIC, WinWriter 150 C** (Cart #1380619) 4 refills each color $24.00. **SNAP AND FILL SYSTEM** - Permits refilling HP 51626A (black for HP 500-series) and HP 51629A (black for HP 600-series) cartridges without making a hole in the cartridge. Consists of special cartridge holder, syringe, plastic tubing, and directions. $12.00. **BULK INK FOR SNAP AND FILL SYSTEM** - (black only) 4-oz bottle $18.00; 8-oz bottle $34.00. Specify whether for HP 51626A or HP 51629A.

HARD-TO-GET PRINTER RIBBONS

Gorilla Banana, Commodore 1525 **$8.00**; Adam Coleco **$12.00**; TI-850/855 **$6.00**; Centronics 700 Zip Pack **$5.00**; C. Itoh Prowriter Jr., Riteman C+/F+ **$6.00**; Riteman Inforunner **$8.00**; Commodore MPS-801 **$5.00**; MPS 803 **$5.00**; Decwriter LA30/36 **$4.00**; Apple Scribe **$4.00**; Mannisman Tally Spirit 80, Commodore 1526 **$5.00**; Epson JX-80 4-Color **$14.00**. Printronix P-1013 **$11.00**; Star SJ144 color 3-pack **$29.00**.

ALSO HEAT & TRANSFER RIBBONS AND PAPER FOR PRINTING T-SHIRTS.

Over 300 different ribbons in stock. All ribbons new, not re-inked. Fully guaranteed. Order directly or send SASE for complete list.

Add $2.00 per order shipping. California residents add 7.75% sales tax.
On ribbon orders over $50.00 deduct 10% discount.

H.T. ORR Computer Supplies

249 Juanita Way, Placentia, CA 92870-2216

714-528-9822 · 800-377-2023 · FAX 714-993-6216

http://www.extremeplay.com/occomp/orr.htm

Write In 213 on Reader Service Card.

Learn by Example!

The PRIMER 8085 Based Microprocessor Training and Control System shows you how to program by example. Examples & exercises in the Self Instruction manual take you from writing simple programs to controlling motors. Start out in Machine language, then move on to Assembler, & then continue on with optional C, Basic, or Forth Compilers. This trainer can be used stand alone via the keypad and display or connected to a PC with the optional upgrade ($49.95). The Upgrade includes: an RS232 serial port & cable, 32K of battery backed RAM, & Assembler/Terminal software.

Examples Include:

- Measuring Temperature
- Using a Photocell to Detect Light Levels
- Making a Waveform Generator
- Constructing a Capacitance Meter
- Motor Speed Control Using Back EMF
- Interfacing and Controlling Stepper Motors
- Scanning Keypads and Writing to LCD/LED Displays
- Bus Interfacing an 8255 PPI (new)
- Using the Primer as an EPROM Programmer

The PRIMER is only $119.95 in kit form. The PRIMER Assembled & Tested is $169.95. Please add $5.00 for shipping within the U.S. Picture shown with upgrade option and optional heavy-duty keypad ($29.95) installed.

EMAC, inc.

11 EMAC WAY, CARBONDALE, IL 62901
618-529-4525 Fax 457-0110 BBS 529-5708
World Wide Web: http://www.emacinc.com

1985 - 1997 OVER 12 YEARS OF SERVICE

Write In 95 on Reader Service Card.

When Visiting Disney World And Sea World. . .
Come To The World Of Electronic Surplus!

SKYCRAFT

PARTS & SURPLUS, INC.
ORLANDO, FLORIDA

Located At The Intersection Of I-4 And Fairbanks Avenue.

A Self-Service Retail Outlet Featuring Commercial And Government Electronic Surplus Including:

- ★ WIRE
- ★ SWITCHES
- ★ RESISTORS
- ★ TRANSISTORS
- ★ TRANSFORMERS
- ★ TEST EQUIPMENT
- ★ NI-CAD BATTERIES
- ★ COAX
- ★ RELAYS
- ★ HARDWARE
- ★ CAPACITORS
- ★ PANEL METERS
- ★ CIRCUIT BOARDS
- ★ INTEGRATED CIRCUITS

★ ★ ★ ★ ★ ★ ★ ★ ★

We Buy Surplus Electronic Parts — *FAX your list.*

HOURS:
Monday - Friday 8:30-6:00
Saturday 8:30-5:00

FAX 407/647-4831
PH 407/628-5634
P.O. BOX 536186
ORLANDO, FLA. 32853-6186

PLANS – KITS – SCHEMATICS *cont.*

SCHEMATICS AND DOCUMENTATION for remote control miniature encoded RF and IR transmitter and receiver boards. **$5** Inventive Solutions, PO Box 8, Stratford, NY 13470. E-Mail: **invent@klink.net**



CIRCUIT BOARDS. Single sided. No minimum. No set-up fees. No hidden costs. No per hole charge, up to 1,000 holes per panel. Complete price list available. Circuit Design, PO Box 5415, Central Point, OR 97502, 541-664-7904. Phone or Fax. http://www.medford.net/circuit/

HOME AUTOMATION via phone without expensive computers, furnace/air cond. on remotely, components locally. Minimal wiring. Money orders only. Plans $10.95. AMR Automate CTR, PO Box 1176, Waltham, MA 02254-1176.

Subscribe to Nuts & Volts! Call 1-800-783-4624

DEALER DIRECTORY

The dealers listed below carry the latest issue of Nuts & Volts, for your convenience.

ALABAMA

Little Professor Book Center
2717 S. 18th St.
Birmingham 35209

RT Systems Amateur Radio Supply
8207 Stephanie Dr.
Huntsville 35802

ARIZONA

Batteries, Batteries
3415 W. Glendale Ave. #4
Phoenix 85051

1829 E. Southern Ave.
Tempe 85282

6245 E. Bell Rd.
Scottsdale 85254

Elliott Electronic Supply
1251 S. Tyndall Ave.
Tucson 85713

Tower Records
3 E. 9th St.
Tempe 85281

CALIFORNIA

Abletronics
9155 Archibald Ave. Unit E
Cucamonga 91730

Advanced Computer Products, Inc.
1310 "B" E. Edinger Ave.
Santa Ana 92705

All Electronics
905 S. Vermont Ave.
Los Angeles 90006

14928 Oxnard St.
Van Nuys 91411

Allen's To Go
13461 Hwy. 88
Lockeford 95237

Alltronics
2300-D Zanker Rd.
San Jose 95131

Brand Newsstand
234-1/2 N. Brand Blvd.
Glendale 91203

Centerfold International
716 N. Fairfax Ave.
Los Angeles 90046

Computing Technology
251 Balsam St.
Ridgecrest 93555

Del Amo Books & News
3758 Sepulveda Blvd.
Torrance 90505

Digicity.Net
4549 Quail Lakes Dr.
Stockton 95207

Electro Mavin
2985 E. Harcourt St.
Rancho Dominguez 90221

Ford Electronics
8431 Commonwealth Ave.
Buena Park 90621

Harding Way News
113 W. Harding Way
Stockton 95204

Harold's Newsstand
524 Geary St.
San Francisco 94102

HdB Electronics
2860 Spring St.
Redwood City 94063

Hi-Fi Doctor
1814 E. Ball Rd.
Anaheim 92805

HSC Electronic Supply
4837 Amber Ln.
Sacramento 95841

3500 Ryder St.
Santa Clara 95051

5681 Redwood Dr.
Rohnert Park 94928

JK Electronics
6395 Westminster Ave.
Westminster 92683

Laurel Park News
4346 Laurel Canyon Blvd.
Studio City 91604

Lion Electronic Labs
4948 E. Townsend Ave.
Fresno 93727

Op Amp Technical Books
1033 N. Sycamore Ave.
Los Angeles 90038

Pace Electronics
369 Hampshire Rd.
Thousand Oaks 91361

Panorama Electronics
8737 Van Nuys Blvd.
Panorama City 91402

Porter Ranch News Stand
18473 Devonshire St.
Northridge 91325

Quantum Enterprises
1566 Simpson Way
Escondido 92029

Sandy's Electronics Supply, Inc.
20655 Soledad Cyn. Rd. #15
Santa Clarita 91351

Sav-On Electronics
13225 Harbor Blvd.
Garden Grove 92643

Springbok News
55 N. Baldwin Ave.
Sierra Madre 91024

Survival Books & Equipment
11106 Magnolia Blvd.
North Hollywood 91601

The Radio Place
5675-A Power Inn Rd.
Sacramento 95824

Tower Books
211 Main St.
Chico 95928

7840 Macy Plaza Dr.
Citrus Heights 95610

1280 E. Willow Pass Rd.
Concord 94520

630 San Antonio Rd.
Mountain View 94040

1600 Broadway
Sacramento 95818

5950 Florin Rd.
Sacramento 95823

2538 Watt Ave.
Sacramento 95812

2727 El Camino Real
San Mateo 94403

Tower Magazines/News
885 Riverside Pkwy.
West Sacramento 95605

Tower Records/Video
220 N. Beach Blvd.
Anaheim 92801

2520 Durant
Berkeley 94704

212 F St.
Davis 95616

5703 Christie Ave.
Emeryville 94608

5611 Blackstone
Fresno 93710

2052 Redwood Hwy.
Greenbrae 94904

6310 E. Pacific Coast Hwy.
Long Beach 90803

2280 Market St.
San Francisco 94114

3205 20th Ave.
San Francisco 94132

2525 Jones St.
San Francisco 94133

871 Blossom Hill Rd.
San Jose 95123

14570 Ventura Blvd.
Sherman Oaks 91403

1205 W. Covina Pkwy.
West Covina 91790

Valencia Newsstand
23164 W. Valencia Blvd.
Valencia 91355

Video Electronics
3829 University Ave.
San Diego 92105

CANADA

Com-West Radio Systems Ltd.
48 E. 69th Ave.
Vancouver, BC V5X 4K6

Muir Communications Ltd.
3214 Douglas St.
Victoria, BC V8Z 3K6

Norlink Communications & Consulting
428 E. Victoria Ave.
Thunder Bay, Ontario P7C 1A5

COLOMBIA

Roboti-K
Carrera 38 No. 10-60.
Local 258, Bogota

COLORADO

Fistell's Micro Electronics
7023 E. Colfax Ave.
Denver 80220

International Tesla Society
2220 E. Bijou St.
Colorado Springs 80909

TH Electronics
216 Commerce Dr., Unit 2
Fort Collins 80524

Tower Records/Video
2500 E. 1st Ave.
Denver 80206

Western Test Systems
530 Compton #C
Broomfield 80020

CONNECTICUT

Archway News
64 Bank St.
New Milford 06776

Derric Electronics
1660 Whitney Ave.
Hamden 06517

DISTRICT OF COLUMBIA

Tower Records
2000 Pennsylvania Ave.
Washington 20006

FLORIDA

Alfa Electronic Supply
1502 S. St. Rd. #7
Hollywood 33023

Bob's News & Books
1515 S. Andrew Ave.
Fort Lauderdale 33316

Clarks Out of Town News
303 S. Andrews Ave.
Fort Lauderdale 33301

Mike's Electronic Distributing Co.
1001 N.W. 52nd St.
Fort Lauderdale 33309

Skycraft Parts & Surplus, Inc.
2245 W. Fairbanks
Winter Park 32789

Sunny's At Sunset, Inc.
8260 Sunset Strip
Sunrise 33322

GEORGIA

Tower Records
3400 Around Lenox Dr.
Atlanta 30326

HAWAII

SolarWorks!
525 Lotus Blossom Ln.
Ocean View 96737

Tower Records
4211 Waialae Ave.
Honolulu 96816

611 Keeaumoku
Honolulu 96814

IDAHO

Hi-Tech Surplus
605 E. 44th St.
Boise 83714

The Current Source
5159 Glenwood
Boise 83714

ILLINOIS

City Newsstand
4018 N. Cicero
Chicago 60641

Pick's Electronics
Lewis Park Mall
Carbondale 62901

Tower Records/Video/Books
383 W. Army Trail Rd.
Bloomingdale 60108

2301 N. Clark St. #200
Chicago 60614

1209 E. Golf Rd.
Schaumburg 60173

KANSAS

Lloyd's Radio & Electronic, Inc.
220 W. Harry St.
Wichita 67213

LOUISIANA

Lakeside News
3323 Severn Ave.
Metairie 70002

Tower Records
408 N. Peter St.
New Orleans 70130

MARYLAND

Silicon Valley Electronics
2014-A Industrial Dr.
Annapolis 21401

Tower Records/Video
2566 Solomons Island Rd.
Annapolis 21401

1601 Rockville Pike #210
Rockville 20852

MASSACHUSETTS

Tower Records #172
360 Newbury St.
Boston 02115

MICHIGAN

Family Electronics
111 E. Superior St.
Alma 48801

Little Professors Book Center
22174 Michigan Ave.
Dearborn 48124

MW Electronics
229 E. Michigan Ave.
Paw Paw 49079

Purchase Radio Supply, Inc.
327 E. Hoover Ave.
Ann Arbor 48104

Tower Records
1214 S. University Ave.
Ann Arbor 48104

MINNESOTA

Radio City, Inc.
2633 County Road 1
Mounds View 55112

MISSOURI

Accurate Instruments
11201 E. 24 Hwy.
Independence 64054

Bob's Electronics
123 S. Main St.
Piedmont 63957

Electronics Exchange
8644 St. Charles Rock Rd.
St. Louis 63114

Stewart & Associates
204 Sonderen St.
O'Fallon 63366

NEVADA

Amateur Electronic Supply
1072 N. Rancho Dr.
Las Vegas 89106

Less Buster's Electronics
2930 N. Las Vegas Blvd. VSTG-22
North Las Vegas 89030

Radio World
1656 Nevada Hwy.
Boulder City 89005

Tower Records/Video
4580 W. Sahara Ave.
Las Vegas 89102

6450 S. Virginia
Reno 89511

NEW JERSEY

JR Tech Systems
1309 Hwy. 71
Belmar 07719

NEW YORK

All Phase Video Security, Inc.
70 Cain Dr.
Brentwood 11717

Ham Central
3 Neptune Rd.
Poughkeepsie 12601

Hirsch Sales Corporation
219 California Dr.
Williamsville 14221

Hi-Tech Repair, Inc.
270 Neelytown Rd.
Montgomery 12549

Tower Records/Video
105 Old Country Rd.
Carle Place 11514

350-370 Route 110
Huntington 11746

1961 Broadway
New York 10023

383 Lafayette St.
New York 10003

OHIO

Compustuff
241 Great Oaks Trl.
Wadsworth 44281

Digital One
7603 Mentor Ave.
Mentor 44060

Footsteps
4925 Jackman Rd. Store #58
Toledo 43613

Hosfelt Electronics, Inc.
2700 Sunset Blvd.
Steubenville 43952

Keyways, Inc.
611 S. Main St.
Miamisburg 45342

Leo's Book Shop
330 N. Superior St.
Toledo 43604

Magazines & More
26880 Brookpark Rd. Ext.
North Olmsted 44070

Powermaxx, Inc.
1587 U.S. Route 68 N.
Xenia 45385

OREGON

News & Smokes
2295 W. Main St.
Medford 97501

News & Smokes #8
259-C Barnett Rd.
Medford 97501

Norvac Electronics
7940 SW Nimbus Ave. Bldg. 8
Beaverton 97005

960 Conger
Eugene 97402

1545 N. Commercial NE
Salem 97303

Powell's Technical Bookstore
33 NW Park
Portland 97209

Tower Books
1307 NE 102nd Ave.
Portland 97220

PENNSYLVANIA

Business & Computer Bookstores
213 N. Easton Rd.
Willow Grove 19090

Lehman Scientific
2997-F Cape Horn Rd.
Red Lion 17356

Penn Electronics
2310 A Walnut St.
Harrisburg 17103

Surplus Al
RR 1 Box 337
Hunlock Creek 18621

Tower Books
425 South St.
Philadelphia 19147

Tower Records
340 W. Dekalb Pike
King of Prussia 19406

SOUTH CAROLINA

555 Electronics
5646 Farrow Rd.
Columbia 29203

TENNESSEE

Tower Books
204 W. End Ave.
Nashville 37203

TEXAS

BDL News, Inc.
809 Pierce
Houston 77002

Electronic Parts Outlet
3753-B Fondren Rd.
Houston 77063

Tanner Electronics
1301 W. Beltline #105
Carrollton 75006

The Communication Source
2713 Galleria Dr.
Arlington 76011

Tower Records
2403 Guadalupe
Austin 78705

VIRGINIA

Electronic Equipment Bank
323 Mill St. NE
Vienna 22180

Satellite Headquarters
7920 Timberlake Rd.
Lynchburg 24502

Tower Records/Video/Books
6200 Little River Tpk.
Alexandria 22312

4110 W. Ox Rd. #12124
Fairfax 22033

1601 Willow Lawn Dr.
Richmond 23230

8389 E. Leesburg Pike
Vienna 22182

WASHINGTON

A-B-C Communications, Inc.
17541 15th Ave. NE
Seattle 98155

Cody Books Ltd.
1122 Fir Ave.
Blaine 98230

Supertronix
18650 68th Ave. S.
Kent 98032

Tower Books
10635 NE 8th St.
Bellevue 98004

20 Mercer St.
Seattle 98109

WISCONSIN

Amateur Electronic Supply, Inc.
5710 W. Good Hope Rd.
Milwaukee 53223

News & Hobby Center
4758 Packard Ave.
Cudahy 53110

Low Cost SBC, ISA Data Acq Cards, Multi-Tasking PC WatchDog card...



Call for Flex51 SBC options and prices, starting as low as $99.

Flex51 is the Easiest 8051 SBC to program and use. Check out this sample configuration:

- 89C51 CPU running at 11 MHz
- Download program files from PC to on-board programmer via RS232 link
- 32K RAM, 64K E(E)PROM
- 2 Serial Ports: RS232 & RS485 suitable for creating a control network with multiple units
- 5 External Interrupts
- Prototype Area 4.75" X 3.15"
- Expandable w/plug in cards: 72 DI/O, 24 DO 500mA, 11 Analog in @12 bit, 4 D/A 8 bit, 2 D/A 12 bit, 3 Counters (16 bit), 2 X 40 LCD, 4 X 4 Keypad
- Program in Assembly, C, Basic, PL/M or Forth.
- FREE Assembler, Tools, Basic and C compilers, Manual, Application Examples, Tech Support.

MULTI-TASKING ISA BUS PC WATCHDOG
Unique ISA 8 bit card monitors up to 4 programs and alarms or resets PC if any one crashes. Has relay outputs and PC IRQ. Includes two 16 bit counters, 24 digital I/O and software. Only $80

8 BIT ISA DATA ACQ CARD, MODEL PCDA
24 user definable Digital I/O, 8 channel of 8 bit A/D, 12 bit counter. $65 w/o counter, $75 with. Call for catalog.

PRINTER PORT DATA ACQ, MODEL PPDA
8 channel of 8 bit A/D, 8 Digital In, 8 Digital Out. Bare board $87 With case & P/S, $130

WinDatAq software. Uses parallel port and Game port. 4 analog in, Auto calibration, Real time data collection, 12 D/O, 9 D/I, 8 bit pattern generator (for logic testing), Logs data to disk. **Dragonfly Software** used with PPDA or PCDA. Real-time A/D display, read and write to the D/ IO, Data-to-disk log. Only $35 Each

Send check, money order + o S&H CA add sales tax
Innovation West 2275 Huntington Drive
Suite 265, San Marino, CA 91108
phone (626) 309-6085 fax (626) 309-9972
E-Mail: inowest@aol.com

Write in 210 on Reader Service Card.

The RF Connection

The RF Connection
213 North Frederick Ave.
Suite 11NV
Gaithersburg, MD USA
20877
http://www.therfc.com/

Complete Selection of MIL-Spec Coax, RF Connectors and Relays

UG-21B/U N Male for RG-213/214.....$5.00
UG-21D/U N Male for RG-213/214.....$3.25

N Connectors for 9913/Flexi4XL/9096

UG-21B/9913.....$6.00 **Pins Only**.....$1.50
UG-21D/9913.....$4.00 **Extra Gasket**..... .75

Amphenol 83-1SP-1050 PL-259.....$0.90
UG-176/U Reducer RG-59/8X. .25 or 5/$1.00
UG-175/U Reducer RG-58/58A .25 or 5/$1.00
Silver Teflon PL-259/Gold Pin.....
.....$1.00 or 10/$9.00

MIL-Spec Coax Available (Teflon, PVC IIA)

New Product: Belden 9913F. 9913 with High Density PE Foam dielectric, stranded center cond. and Duobond III Jacket.....
..... .80/ft or $76.00/100ft
Also New: 9092, RG8X with Type II Jacket
Intro Price.....$23.00/100ft

Call for Specials of the Month

Full Line of Audio Connectors for Icom, Kenwood, and Yaesu

8 Pin Mike Female.....$2.50
8 Pin Mike Male Panel.....$2.50
13 Pin DIN for Kenwood.....$2.75
8 Pin DIN for Icom.....$1.00
8 Pin DIN for Kenwood.....$1.50

Prices Do Not Include Shipping

Orders 800/783-2666
Info 301/840-5477
FAX 301/869-3680

Write in 210 on Reader Service Card.

Write PIC programs in BASIC!

PicBasic Compiler

$99.95

BASIC makes it easy for you to program the fast and powerful Microchip PIC microcontrollers.

- Expanded BASIC Stamp 1 compatible instruction set
- True compiler provides faster execution & longer programs than BASIC interpreters
- In-line assembler & Call support
- *New Features!* Peek & Poke, I2Cin & I2Cout
- Supports PIC16C6x, 7x & 8x
- Use with most PIC programmers

PicBasic Compiler Bundle - $179.95
Includes: PicBasic Compiler, EPIC Programmer, AC Adapter, 25 Pin Cable, PICProto18 and PIC16F84

Also: PICProto Boards - $8.95-$17.95
EPIC Pocket PIC Programmer - $59.95

*BASIC Stamp is a trademark of Parallax, Inc.

microEngineering Labs, Inc.
Box 7532 Colorado Springs CO 80933
(719) 520-5323 FAX 520-1867
www.melabs.com

Write in 170 on Reader Service Card.

MANUALS – SCHEMATICS WANTED

WANTED: LATE MODEL TEST EQUIPMENT (Tektronix, HP, Fluke), and also, test equipment service manuals. Pepper Systems: 214-353-0257; 214-902-9511 FAX.

MISCELLANEOUS ELECTRONICS FOR SALE

IMPROVED: PHANTOM, POLICE LASER/RADAR JAMMER & DETECTOR: No more tickets or manufacturer pays them! Guaranteed lowest prices. Free brochures. 30-day money back guarantee, 3-yr. warranty. Visa/MC/COD. Kortesis Marketing, order 303-548-3995, FAX or messages 303-699-6660.

VARIAC-SUPERIOR - 240 input, output 0-240 @ 28A @ 7.8KVA. Used, in good condition at $200. Call Roger @ GS&E, 716-338-7001. VISA-MC available.

FREE FLYER on cable TV, phones, credit cards info, schematics, project boards, other misc. items. Bill 1-800-879-9657.

NUCLEAR ELECTRONICS (NIM, CAMAC), PMTs, optics, high vacuum, and high voltage components and equipment. Guaranteed quality at reasonable cost. For catalog, contact: OE Technologies, Box 703, La Madera, NM 87539. Ph: 505-583-2482, Fax: 505-583-9190, E-Mail: oetech@newmexico.com

ALL CABLE NEEDS
SE HABLAN ESPAÑOL

KDE ELECTRONICS CORP.

CONVERTERS
ALL BRANDS
WITH REMOTE

PARENTAL LOCKOUT AVAILABLE

COMPETITIVE PRICING

TOLL FREE ORDER LINE:
1-800-361-4586
ALSO
HOOK-UP HELP LINE:
1-630-889-0281

NO ILLINOIS SALES

ACCEPTED VISA MasterCard COD ACCEPTED

HOURS: Mon. thru Fri. 9-6, Sat. 10-2
30-DAY MONEY BACK GUARANTEE
1 YEAR WARRANTY

KDE ELECTRONICS CORP.
P.O. BOX 1494, ADDISON, IL 60101

Write in 56 on Reader Service Card.

ELECTRONICS Q & A

With TJ Byers

In this column, I answer questions about all aspects of electronics, including computer hardware and software. This column doesn't replace the Tech Forum that you've grown to love and support. Instead, it will supplement it, so feel free to participate as always with your questions and answers. You can reach me on America Online at TJBYERS, on the Internet at TJBYERS@aol.com or by snail mail at *Nuts & Volts Magazine, 430 Princeland Ct., Corona, CA 91719.*

What's Up:

Thanks for the lost memories: the story of a virus infection, two readers looking for part replacements, and specs on old monitors. A more ambitious telephone off-hook circuit, a sensitive IR detector, and a turntable vacuum tube preamplifier. Finally, two programs that convert Internet files to text.

Virus Concerns

Q. Will you shed some light on a subject that comes up around here quite often? Is it possible for a computer to become infected with a virus by merely reading an E-Mail message?

Charles E. Heisler K3VDB
via Internet

A. Not that I'm aware of. To become infected you need to download a file of *some kind – something that has encoding, such an EXE or MS-Word file. E-Mail messages are done in ASCII, which a virus can't attach to.*

While we're on the subject, I'd like to thank that reader who infected my system with a virus. As you know, I try my best to respond to your needs as quickly as possible, which is why my E-Mail box is always open. However, this open-door policy also leaves me vulnerable to all kinds of trash – including viruses. Well, this month, a reader slipped a StealthBoot.c virus through my defenses, with devastating consequences. StealthBoot is a very infectious virus that's undetectable by many virus checkers. Moreover, the longer it lingers, the more damage it does. Imagine an earth worm eating through your brain, gobbling up brain cells as it tunnels. That's StealthBoot. So, if you're the person who purposely infected me with that phoney "drawing" file, this is your 15 minutes of fame. I know who you are and if you try it again, expect a lawsuit and possible arrest.

I know what your next question is, so let me tell you how I discovered and rid myself of this virus. Because this particular strain is stealth and new, it was able to penetrate my first line of defense: a virus checker from Microsoft that I should have upgraded three years ago. All the really good virus-detection programs have some form of scheduled upgrading (usually quarterly) that adds new virus patterns to their scanning process. Well, I made a copy of a file and gave it to my girlfriend to print out. Guarding the gates of her computer is the Norton AntiVirus program. While it didn't identify the virus correctly, it flashed a message that the disk was infected. Puzzled, I ran a virus search and destroy (clean) operation using her virus program, only to discover that Norton had lost it. Oops! Big trouble! I took the diskette back to my PC and gave it a thorough screening. It wasn't until I downloaded the latest version of Dr. Solomon (http://www.drsolomon.com) that I discovered the true nature of the infection. A subsequent check with the newest version of McAfee VirusScan (http://www.mcafee.com) also located the virus. However, I used Dr. Solomon for the innoculation process, just because. This isn't to say McAfee VirusScan or Norton Anti-Virus are inferior. What I'm saying is that viruses are always a moving target. Like the hundreds of strains of Asian flu that plague us every year, no one vaccine works for all. From now on, I'll do my scheduled upgrades and daily scour my system for slimy bugs.

Are You Busy?

Q. On page 93 of the Oct. '97 issue you show how to build a line-in-use indicator for readers who have two phone lines. I built the indicator section of the circuit using parts from Radio Shack, but the light comes on only when the phone to which it is connected goes off-hook. If my wife picks up the extension in the next room, the light won't light. Is there a way to make your schematic work with extension phones, too, other than buying the Radio Shack "In-use Indicator" for $12.99 (plus a nine-volt battery)?

Bill Stitzer
Atascadero, CA

A. *The reason you can only detect your phone off-hook and not the extension is because the circuit is current operated. In other words, voltage is generated across the bridge rectifier only when current flows through the diodes – current triggered by your phone or any other device (fax, modem, etc.) going off-hook.*



When your wife picks up the extension, no current flows through your line, and the LED won't light. You need to insert this circuit in a line that feeds both phones, such as the building's main junction box, which isn't always practical. The solution is a voltage-sensitive off-hook detector, like the one below.

This circuit works by sensing the voltage status of the phone line. When the phone is on-hook, the line voltage is about 48 volts. This condition causes current to flow through the zener diode and turns on Q1 which, in turn, shunts the bias current of Q2 to ground and turns Q2 off. When the line goes off-hook, the voltage drops to 10 volts, which is below the triggering point of the zener. Q1 turns off, and restores bias current to Q2, which now turns on and lights the LED. If you have trouble detecting the off-hook, increase the value of the zener from 12 volts to 15 or 20 volts. The beauty of this device is that you can place it in any room and know if the line is being used by any device in the building – and you don't have to break the line. The disadvantage is the circuit has a higher part count and costs more to build.



Looking For A Substitute Part

Q. If you have your NTE cross-reference handy, could you please tell me what I can substitute for an NTE 379? I have one in an ancient Macintosh 512 power supply that has overheated and failed. I think it's a silicon power transistor, and I may have something in my attic that I could use – if I knew what to look for. However, my Radio Shack references don't show NTE numbers.

Miki Karner
via Internet

A. *Hmm, according to my crystal ball this is a very expensive ($8.00) silicon NPN power transistor with 12A @ 700V ratings in a TO220 case. The power dissipation is 100W. Let me see what Radio Shack has that's close ... how about a 2SC4274 (RSU 11426145). This is a special order part (via mail only) that lists for $5.39. Before you replace the transistor, though, make sure the diodes in the low-voltage section aren't shorted, or you'll be ordering another transistor. BTW, you can cross-reference NTE parts yourself from their Web site at http://www.nteinc.com*

Tube Preamp

Q. My friend recently gave me an old Pioneer PL-200 turntable, that sounds pretty amazing – but only after I run it through my four-track recorder before plugging it into the AUX input of my stereo. I would like to build a preamplifier to replace the tape recorder. After looking through several magazines, I noticed that old-style tube amps seem to be popular, but are way out of my

price range. Are there any books or articles out there that show you how to build a reasonably-priced tube amp for my turntable?

Dave Whiteford
via Internet

A. *There's no such thing as a cheap tube amp because the parts that go into making it are expensive. For example, a 12AX7 tube will cost you $10.00, not counting the socket. And the high-voltage capacitors cost many times more than their solid-state counterparts. Still interested? Then here's a typical turntable pre-amp that'll cost you about $20.00 per channel (you need two for stereo), plus the cost of a chassis, ventilated cabinet, and a power supply (about $40.00, minimum).*



The circuit is built around a 5751 twin-triode (two tubes in one envelope). This tube is a premium, low-noise 12AX7 with 70% lower gain which all but eliminates the need for negative feedback – the reason vacuum tubes are highly prized in high-end audio pre-amps. The pre-amp is RIAA-compensated to match the sound profile of a 33-RPM LP. However, the circuit isn't complete, as you see, on purpose. Missing from the drawing is the power supply, tube pin-outs, and the filament connections. If you don't know how to do this, get help from a local HAM radio operator. The high voltages and open construction can be a deadly combination. Good luck! Are you sure you don't want the op amp equivalent which you can construct for less than $20.00?

Converting HTML Files To Text

Q. I would like to find a simple program for stripping out format codes from downloaded Internet files. For example, <A>, <head>, <h5> would be deleted, and <ul> Nuts & Volts <\ul> would become simply Nuts & Volts.

Fred Chesson
via Internet

A. *The script you're talking about is called HTML (HyperText Markup Language), and is easily identified by its HTM extension, as in FILENAME.HTM. I combed through many HMTL-to-text conversion programs, and came up with two that I think are well-suited for our reader's needs. The first is HTMLCOM, a DOS-based file that runs from the DOS prompt. The second is a Windows program called HTMLASCI. Both files are available on our Web site (http://www.nutsvolts.com) under the names HTMLCOM.ZIP and HTMLASIC.ZIP, respectively. Both are shareware programs ($7.00 and $20.00), which you can try for free, and both are zipped files that need to be expanded using PKUNZIP (also available on our Web site under PKUNZIP.EXE for DOS and PK250W16.EXE for Windows). Be aware, these are conversion programs only; they won't let you edit HTML files. But you can edit the resulting ASCII files using any text editor or word processor.*

Future Scientist Needs Part

Q. I'm a junior at Greenwich High School currently working on an independent science research project. I'm trying to build an electronic circuit that I found in an article published in the *Journal of Chemical Education*. The detector in the schematic is a TIL413, which is no longer in production. I noticed your article on page 133 of the July '97 issue where you mentioned an infrared detector. Could this detector be substituted for the TIL413? If not, could you please suggest another detector that could be used in place of it?

Melissa Otero
via Internet

A. *You've taken on a very ambitious project, trying to measure vivo chlorophyll fluorescence. I wish you luck. The detector you seek has long ago been replaced with faster and more sensitive PIN diodes. An excellent replacement is the PN334PA PIN diode from Panasonic. This part is available from Digi-Key (800-344-4539; http://www.digikey.com) for just $1.40. While you're at it, I'd substitute a TL084C op amp for the LM324 shown in the original design, and move a couple of the controls so that the circuit is more stable. Here's the modified schematic.*



This circuit can also be used to measure other low-level infrared events. Detection of the weak IR light is achieved by amplifying the output from the PN334PA photodiode. This sensor has a response time of two nanoseconds and a peak sensitivity at 900 nanometers. To set the NULL, short out the sensor diode and adjust the 250K pot so that the output of IC1A is zero. The OFFSET control is used to position the recorder's pen, and the GAIN control is used to limit the pen's swing so that it doesn't bang against the sides.

Scratchy CD Drive

Q. I need help with my CD-ROM, which is rather dirty. Every time I play my CDs, the drive ends up leaving scratches on the disk. I paid only $29.00, but that was three months ago, so I can't return it. I'd like to convert the CD music files to MP3 or WAV format to save them from further damage. Any suggestions?

Alex Bel
via Internet

A. *Only $29.00? The CDs this drive is destroying cost more than that! Toss it and buy a new one. As for converting your music tracks to WAV files, most of today's sound cards and video capture boards have the ability to capture CD-quality audio and save them to a file. While we're on the subject, the video capture cards can capture both synchronized sound and graphics, but you'll probably want to edit both to refine them and then re-synchronize them. To do this, look into Animator (Autodesk) or Premiere (Adobe). These are two completely different types of software. Animator is for 2-D animation, paint, and sound synchronization. Premiere handles video editing and special effects. In Animator, you can create or alter digital video sequences and synchronize the sound. In Premiere, you can also edit video, create custom transitions and special effects, and even remix audio into a finalized playback sequence. Be careful, though, this hobby can be addictive.*

EGA Monitor Lives?

Q. I have a used color monitor that I purchased surplus, and I need to get more information on it. I wrote the company (Mitsubishi), and got nowhere. The monitor is an XC1412C. I believe it is an EGA or CGA monitor, but I'm not sure. It has a DB-9 connector, and I'd like to get it to work with a Tandy RSX computer (386SX), which has a DB-15 connector and an AVGA2 video card running DOS 5.0. I also have an old PC-XT that I'd like to upgrade for use with this monitor, too, and need to know what I have to add.

Dave Raycroft
va3rj@hotmail.com

A. *I can't find anything on this monitor either, but if memory serves me, it's an EGA monitor. Unfortunately, your Tandy PC has a VGA video controller, and the PC-XT has a monochrome or CGA adapter. So your first task is finding an EGA video card, which won't be easy. They disappeared from the planet over 10 years ago. You might still be able to find one at a hamfest or parking-lot sale. Or maybe one of our readers has one gathering dust, which is why I'm including your E-Mail address. If you locate one of these dinosaurs, make sure you get the cable, too. Now all you have to do is plug the card into an empty slot and plug in the monitor. You may have to change a switch on the PC-XT from mono to color; it's located somewhere in the middle of the motherboard. I wouldn't waste too much time or money on this project. For a couple hundred dollars you can put together a 486DX system with a 14-inch SVGA (super-VGA) monitor that'll run circles around either.*

More Old Monitors

Q. I have a little AT&T monitor which I suspect is monochrome. I don't know what PC it came off, but it has a single cable coming out of it terminating in a

(Continued on page 109)

MO-TECH DISTRIBUTORS
YOUR MIDWEST PANASONIC CONVERTER WHOLESALER

PANASONIC

	10 PC	20 PC	50 PC
TZPC1453G2	**$63-**	**$61-**	**$59-**

"Top of the line converter" featuring sleep timer, parental lock, standard/HRC switchable, last channel recall, favorite channel memory, and 83 channel capable.

TZPC1003	**$49-**	**$44-**	**$42-**

One of our best selling converters featuring sleep timer, parental lock, last channel recall, favorite channel memory, and 80 channel capability.

TZPC175DG2	**$89-**	**$85-**	**$82-**

Our "Top of the line" converter with volume control. Featuring sleep timer standard/HRC switchable, parental lock, last channel recall, favorite channel memory, and 83 channel capable.

PHONE (810) 739-2710
FAX (810) 739-3517

Nuts & Volts

SELL NUTS & VOLTS IN YOUR STORE AND EARN $$$
Contact us for details. 909-371-8497
E-Mail distributors@nutsvolts.com

Lowest Dealer Price Available

✣ RA-550E
CATV converter

- Parental lock
- STD/HRC switchable
- 85 channel capability
- Brand new

✣ R-8750
Volume control converter



- Parental control
- STD/HRC switchable
- 85 channel capability
- Brand New

✲ **Refurbished w/remote - from $29/ea**

✣ No decoder sales

Warranty included

METRO SURPLUS 310-515-5085

The Filter Company

Positive Notch Filters

Internet: www.gofilters.com

Large STOCK on all Available Channels
2 thru 30*, 95 thru 99
0,1,57,58,59,60,61,A1,A2,A3,A4,A5
ORDER BY SINGLE CHANNELS

We Specialize in Large Quantities on every Channel

Prices as low as $6.00ea

NOBODY BEATS OUR PRICES

Monday - Friday (8am to 5pm) Central Time
QUALITY METAL CYLINDER TYPE NON-TUNABLE
ABSOLUTELY NO DRIFTING PROBLEMS

Standard Positive Filters

1pc-$16.00 5pcs-$14.00 10pcs-$12.00
25pcs-$10.00 50pcs-$8.00

*Standard Positive Filters, Channels 26-30 add $3.00 more each.

Positive "G and S" Series Filters

1pc-$30.00 5pcs-$28.00 10pcs-$25.00

Tom G. - FL *Excellent Service, fast and quick. The only bad thing about this company is they don't sell Cable Boxes. We hope someday they will.....*

David P. - CA *We called around for help on filters and nobody had any answers except one, call the "THE FILTER COMPANY" we did and had an answer in a matter of seconds.....*

John B. - IL *Our company buys in the 100 quantities and needs a large selection of different channels. "The Filter Company" was the only one who was able to supply.....*

PHONE ORDERS:

1-800-235-8080

Visa, Mastercard and Discover
(UPS COD for established customers)

Anyone implying theft of Cable Service will be denied assistance
We do not sell Data Blockers, Bullets or FM Traps !!!!

A "TFC" Company

Give our 800 line a howl for the best service in the Country.....!!!!

ATTENTION DEALERS

BUY DIRECT FROM THE WHOLESALER

GET THE BEST PRICES AND SERVICE

ALL UNITS ARE IN STOCK FOR IMMEDIATE SHIPMENT

NOVAVISIONS

	QTY 10	QTY 20	QTY 50
NV-5600 (PIO)	$199	$185	$170
NV-5700	$199	$185	$170
NV-5800	$199	$185	$170
NV-5750 (JBB)	$275	$260	$245

NEW CONVERTERS

	QTY 10	QTY 20	QTY 50
CENTURY CT-3000	$65	$60	$55
PANASONIC 145	$79	$74	$69

ALL TYPES OF CABLE EQUIPMENT AVAILABLE. CALL FOR DETAILS.

CALL FOR THIS MONTH'S SPECIALS

1-800-808-3356

DIRECT CABLE SUPPLY

MISC. ELECTRONICS FOR SALE *cont.*

QUALITY ELECTRONIC Parts-Surplus prices! Gold plated dual 5-way binding post, low as $1.95 ea. Thermal cutouts, low as $0.40 ea. Gold plated banana jacks, low as $1.50 pr. LM340T-5.0, low as $0.40 ea. 3 amp, adj. V. reg IC, low as $1.65 ea. 20A/125V. Circuit breakers, low as $1.35 ea. VHF/UHF varactor tuners, low as $9.95 ea., MTH8N45 power MOSFETS $1.75 & up, other power MOSFETS $0.50 & up. We have many other items! Call, fax, E-Mail for free flyer. Hoffman Industries, 853 Dundee Ave., Elgin, IL 60120, Ph: 847-622-8201, toll free order line: 1-888-311-4248, fax: 847-622-8202, E-mail: hoffmanind@worldnet.att.net Visit our web site at: http://www.hoffind.com

ANAHEIM WIRE PRODUCTS. DISTRIBUTOR OF ELECTRICAL WIRE AND CABLE since 1973. Items available from our stock: Hook up wire, Automotive primary wire, GXL, SXL, Plenum cable, Teflon wire, Multi-conductor cable, Irradiated PVC, SO-CORD, Mil-Spec wire, Building wire, Welding cable, Battery cable, Telephone wire, Shrink tubing, Cable ties, Connectors. If interested, please call **1-800-626-7540**, FAX: 714-771-5043. Visa/MC/Amex. SEE US ON THE INTERNET: http://www.anaheimwire.com OR E-Mail: info@anaheimwire.com

ELECTRON TUBES: All types bought and sold. Daily Electronics, B-6 10914 NE 39th St., Vancouver, WA 98682. 1-800-346-6667, 360-896-5476 FAX.

SOLAR-POWERED FAN HAT. Baseball type hat with solar powered fan. Great for sports fans, golfers, etc. Available in red or blue. $19 plus $2.00 shipping. CA residents add 7.75% sales tax. Visa/MC/Disc/Amex OK. H.T. Orr Computer Supplies, 249 Juanita Way, Placentia, CA 92670. 714-528-9822, 1-800-377-2023, FAX 714-993-6216.

CALL FOR a **free electronics catalog** or visit our web site at **www.bgmicro.com/ B.G. Micro,** PO Box 280298, Dallas, TX 75228. Order line **1-800-276-2206**.

50Hz 65KW motor/gen. set $6,500 760-632-9775.

ELECTRONIC ASSEMBLY MACHINERY. We buy and sell assembly machinery including solder machines and board cleaners, insertion machines and lead formers. Petlock Inc., Rialto, CA. 909-877-8900, FAX 909-877-8902.

RADAR GUNS: MPH Industries, model K-55. Displays your speed & target speed. Comes w/case & instructions. Only $300. 1-800-539-2859.



QUICKEST PROTOBOARDS available. Unique design eliminates 90% of manual point-to-point wiring. Compatible with PIC, Motorola, Atmel, National, Parallax microcontrollers. Oricom Technologies, 303-444-9776, www.sni.net/~oricom

RFID TRANSPONDERS, only $1? RCA jacks, 1" speakers. Browse http://ourworld.compuserve.com/homepages/dvp or call 503-743-3194, fax 503-743-2095.

INDOOR RADIO CONTROLLED BLIMP. Christmas special $40.95. Radio controlled flying saucer READY TO FLY. Batteries and 4 cubic feet of helium not included. West Coast Blimps 760-375-2108. 713 Cottonwood Dr., Ridgecrest, CA 93555. Home Page: http://www.ridgecrest.ca.us/~jpiri

PCB DRILLS: 50 assorted tungsten-carbide bits in plastic cabinet, only $5. Jack 503-581-6654, fax: 503-581-4382.

MISCELLANEOUS ELECTRONICS WANTED

WESTERN ELECTRIC audio equipment wanted. 1927-1960's. Amplifiers, "receivers," speakers, x-overs, tubes, etc. 1-800-251-5454.

WESTERN ELECTRIC WANTED: 1920s-1960s. Amplifiers, mixers, pre-amps, speakers, tubes, etc. FREE OFFER 1-800-251-5454.

WANTED: BALANCING machines & vibration analyzing equipment manufactured by the following: Spectral Dynamics, Hofmann, Bentley Nevada, Schenck, IRD Mechanalysis, Gishott. Contact Mike Park at E.T. Balancing, 12823 Athens Way, Los Angeles, CA 90061. 310-538-9738, FAX: 310-538-8273.

EXCESS INVENTORY WANTED: Transistors, semiconductors, capacitors, PC boards, & diodes. We buy it all!! Contact: **SEMITECH, INC.,** 381 Roberts Road, Oldsmar, FL 34677. Phone 813-854-3311, FAX 813-854-3422.

HIGHEST PRICES paid for new and used tubes. $200+ for Western Electric 205D (tennis ball shape) used. $150+ for Western Electric 274A/B (engraved base) used. $450+ for Western Electric 252A and 300A/B (engraved base) used. $100+ for 2A3 (single plate) used and many more. Don Singerhouse tel/fax 715-246-3899.

Write in 74 on Reader Service Card.

TESTERS WANTED: Immediate offers made for Ultrasonic, Magnetic Particle, Eddy Current, X-Ray and Borescopes, 24hrs. Leave detailed message with make/model. 1-800-530-3371.

WANTED: ELECTRICAL materials, Allen-Bradley, Agastat, Appleton, Crouse-hinds, T&B, Square D, Pyle National, Russel & Stoll, circuit breakers, fuses, connectors. Call Beiner Sales, 805-376-9044, FAX 805-376-8207.

SS WHITE AIR ABRASIVE wanted. Model K, H, or similar. Call or fax Jack, 513-777-0800, 513-779-3931 (voice).

WANTED: ELECTRONIC OR VISUAL AUTOCOLLIMATORS, ALIGNMENT TELESCOPES, working or not. Taylor-Hobson, Hilger-Watts, Davidson or K&E products; optical instruments, components. METROPTICS, PO Box 726, Glendora, CA 91740. Phone: 626-335-5136, FAX 626-335-7896.

WANTED: TUBE HiFi, Tube theater/commercial amps, speakers etc. Corner speakers/coaxials/triaxials. Old guitars & guitar amps. Altec, McIntosh, Marantz, Western Electric, Scott, Fisher, Dynaco, Electrovoice, Jensen, Gibson, Fender, Vox etc. Sonny Goldson, 1413 Magnolia Ln., Midwest City, OK 73110. 405-737-3312. FAX 405-737-3355.

WANTED: ELECTRON tubes, ICs, semiconductors. Astral, PO Box 707NV, Linden, NJ 07036. Call 1-800-666-8467.

TUBES WANTED - paying cash for new 5U4GB, 5AR4/GZ34, 6L6GC, EL-34, 7027, 6550, 6V6GTA 610-767-9097.



WANTED: EXCESS ELECTRONIC INVENTORIES, ICs, MEMORY, EPROMs, PALs, LEDs, CIRCUIT BOARDS, DIODES, AND TRANSISTORS. CALL ACTIVE MICRO, 562-494-4851 OR FAX 562-494-4913.

WILL PAY cash for electronic related business. Inventory, machinery, or equipment. ISE 956-350-5555 FAX: 956-350-5574.

WANTED: AVIONICS test equipment, IFR 1200Y3, 40IL, 600A, 750B, also King, Collins, any Litton inertial nav. equipment, LTN series 33, 39, 51, 58, 72, 92. 941-575-0138 P, 941-575-2361 F.

BUYING NEW and used vacuum tubes. Write for bid sheet showing prices we pay. Antique Triode, 653 Commercial Street, Farnham, NY 14061. Fax 716-549-3823.

WANTED: WAWASEE MODEL JB 1001 SFC/M CB TEST STATION, 916-451-7530 10am-5pm PST.

WANT USED or surplus DC motor controls or adjustable frequency AC drives, 1/2 HP and up. DC motors fractional to 3 HP. C. Woodruff, 5507 55th Ave. So., Seattle, WA 98118. Voice/Fax 206-723-8487.

BBS & ONLINE SERVICES

VISIT DON Lancaster's **GURU'S LAIR** website at **http://www.tinaja.com** PICs, pseudoscience, PostScript, patents, Tinaja quests, flutterwumpers, book-on-demand, magic sinewaves, money machines, Navicubes, tramways, wavelets, and Webmastering. Online reprints, consultants net, forums, annotated hot links, surplus bargains, great heaping bunches more.

EDUCATION

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.

DON LANCASTER'S ACTIVE FILTER COOKBOOK is back in print. Autographed copies of the seventeenth(!) classic printing $28.50. **SYNERGETICS PRESS**, Box 809-N, Thatcher, AZ 85552. 520-428-4073. Visa/MC.

BUSINESS OPPORTUNITIES

MILLIONS IN scrap gold are about to hit the market in the form of old computer junk. I'm making a bundle recycling this material and you can join me. Call 24-hour message: 603-645-4776.

24 Hr. Shipping

To Order Call 1-800-292-7711 Fax: (847) 541-9904

Quality Kits for Hobbyist and Students

All Kits include PCB, all parts, and detailed assembly manuals.

TOOL KITS

Technicians Tool Kit
TK-2000
$42.95

Contains 25 tools
An electronic technician tool kit designed for the educational field. Heavy-duty deluxe Plano tool box comes with two cantilever trays having 18 component trays. Deep bottom storage area for bulky items. Quality array of tools meets most educational requirements.

Deluxe Tool Kit
TK-3000
$79.95

Contains 25 tools plus a special meter stand
A professional technician service tool kit in a metal reinforced tool case with heavy-duty handle and locks. A removeable pallet handles most of the tools listed with more room for tools and parts in the lower half.

Hobbiest Tool Kit
TK-1000
All the tools you'll need to build these kits. 25 tools contained in a heavy-duty carrying case.
$39.95

Call for a FREE 64 page catalog! (800) 445-3201

SOLDERLESS KITS NEW

TALKING CLOCK KIT
$14.95 AK-220

- Dual analog/digital
- Rooster crows every hour.
- Easy-to-build

No Soldering Required

35mm Camera Kit
AK-540 $14.95

Learn all about Photography

No Soldering Required

ELECTRONIC KEYBOARD KIT
AK-900
$24.95

- 37 mini-size keys
- 8 tempo rhythms
- 4 custom drums



REMOTE CONTROL CAR KIT
AK-870

- 7 functions
- Remote control included

$24.95
No Soldering Required

Stereo Cassette Player Kit
AK-200
$14.95

- Transparent Case
- Belt Clip
- High Resolution
- Includes Headphones

M-1005K
Digital Multimeter Kit

Low cost, 3 1/2 digit LCD, 18 ranges, transistor test, diode test, overload protection and pocket-size. $19.95

AM/FM-108K
AM/FM Radio Kit and Training Course
14 Transistors and 5 Diodes

$29.95

AM Radio Kit and Training Course
7 Transistors and 1 Diode $19.95

FO-30K
Fiber Optics Technology with Training Course $24.95

Learn the basics of fiber optics data communications while you build this exciting kit. Comes complete with all necessary components.

Telephone Kit
Model AK-700
Build this high-tech see-thru plastic telephone. Learn theory on how telephones work and then proudly show off your work with the transparent phone case. Complete with all parts and manual. Neon lamps flash when the phone rings.

$15.95

AR-2N6K
2 meter / 6 meter Amateur Radio Kit



$34.95

Talking Clock Kit Model AK-210

Features:
- LCD time display
- One button instant time report
- Hourly time announcements
- 3 alarm sound choices rooster crow, buzzer, cuckoo

Requires two (2) "AA" batteries (not included)
$14.95

Robotic Arm
Model OWI-007
The Movit Robotic Arm is an educational kit that teaches the fundamentals of a basic robotic arm as well as your own motor skills.

$59.95

AK-300 Digital Roulette Kit

This Digital Roulette Kit is just like the real thing. With a push of a button, the LEDs spin round and round. Where they stop is anybody's guess. It's unique design includes "pop out" chips of different values. Enjoy hours of fun with this game of chance. Requires one (1) 9V battery.

$14.95

Telephone Hold Button
Model K-18
Put all incoming and outgoing calls on hold at the press of a button.

$7.95

Telephone Bug
Model K-35
Size of a dime, yet transmits both sides of a phone conversation to any FM radio. No battery needed.

$7.95

Motion Detector Kit
Model AK-510
Simple and fun to build. Compact, portable, and adds safety to your home or office. Requires one (1) 9V battery.

$14.95

Guaranteed Lowest Prices
UPS SHIPPING: 48 STATES 5%
OTHERS CALL FOR DETAILS
IL Residents add 8.25% Sales Tax

C&S SALES, INC.
150 W. CARPENTER AVENUE
WHEELING, IL 60090
FAX: (847) 541-9904 • (847) 541-0710
http://www.elenco.com/cs_sales

15 DAY MONEY BACK GUARANTEE
FULL FACTORY WARRANTY
PRICES SUBJECT TO CHANGE WITHOUT NOTICE

Questions & Answers
TECH FORUM

This is a READER TO READER Column. All questions AND answers will be provided by *Nuts & Volts readers* and are intended to promote the exchange of ideas and provide assistance for solving problems of a technical nature. All questions submitted are subject to editing and will be published on a space available basis if deemed suitable to the publisher. All answers are submitted by readers and *NO GUARANTEES WHATSOEVER* are made by the publisher. The implementation of any answer printed in this column may require varying degrees of technical experience and should only be attempted by qualified individuals. Always use common sense and good judgement!

QUESTIONS

Does anyone know how I can modify my Radio Shack DX-390 digital shortwave radio so that it doesn't mute while tuning?

12971 **Mike Elcsisin**
Winters, CA

I would like to make a 50 LED panel controlled by a number pad where the LED will come on when the respective number is pressed in on the number pad. I want to use high emitting green LEDs.

12972 **Sal Lieata**
Brooklyn, NY

I need a schematic/parts list to build a good bandpass filter and I need to pass 42 to 50 MHz on a receive antenna.

12973 **KF6NID**
Essex, CA

I need to get as much information as I can on kits for music. Such as drum machines or drum tone boards, synthesizer modules, tone generators, electronic bass emulators, sounders, and etc. It doesn't matter if it is company producers and schematics or person-built emulators, etc., resources, web sites, magazines, books, schematics, copies of these things of information will help me in educating myself.

12974 **Troy Thomas Day**
Longwood, FL

I am looking for a supplier of SMPTE time code generator and reader ICs. Does anyone know if PIC source code is available for this purpose?

12975 **Mike Uschak**
Loyalhanna, PA

In the past few years, I have designed several analog type measurement instruments that operate through the parallel port (with ADCs of course). These have all used QBASIC as the programming language. QBASIC addresses the port with the simple OUT- - - - for output on the port's eight output lines/pins, or INP- - - - for input so as to look at whatever is present on at least four of the port's input lines/pins.

I just purchased the PRO version of VISUAL BASIC 5 and discovered that it will not respond to "OUT- - - -" and "INP- - - -," even though it does respond to other QBASIC words. Actually it does respond with the dreaded "Compile error - - - Sub or Function not defined," but does not do anything useful.

My question boils down to: What commands (or words or lines or routines or something) are equivalent to "OUT - - - "and "INP - - - ?"

12976 **Richard Schroeder**
r.f.schroeder@juno.com

I'm making lighthouse models for gifts. I need a flashing light to operate off a nine-volt battery, flashing three to five seconds or so, with a switch.

Can you suggest a circuit? Where can I get the components? Is it possible to keep the cost to $1.00 or less (without the battery)? I will need about 125-150 total.

12977 **Andy Osborne**
South Walpole, MA

I have an AM/FM broadcast band radio aboard my boat. I find that the safety rails (attached to the fiberglass deck) make a fairly good reception aerial for it and the small portable TV. How can I make a better set-up using both rails (about 12 feet long each)? A hookey jumper works fair, but would like other and better ideas.

12978 **Cliff Steele**
Rockford, IL

My problem is finding any service information, schematic, or similar circuitry for a ADC model LT 60 linear tracking turntable. Maybe 10-years-old or more. The company address was 71 Chapel St., Newton, MA. This was made in Taiwan. If possible maybe a place to get service, arm travels only backwards to home. Would like schematic if possible.

12979 **James Marvel**
Rensselaer, NY

How can I make a battery operated TV using a signal amplifier (small but strong)? I have a TV set with regular rabbit ears for reception, and because of my location my reception is poor.

129710 **Anthony E. Smith**
Camden, NJ

I would like to get information on a good and reliable school-to-train in the field of RF technician.

129711 **Luis Diaz**
Paterson, NJ

I need to build a count down counter with a three or four digit LCD display keyed with a microswitch or reed switch. Then at "0" key, a relay to shut the system off. Maybe thumb wheel or rotary switches to set each digit, or maybe a key pad. Cost is important so I must build one. I need a schematic and parts list. This is to help our local school.

129712 **Mel Goodwin**
Terrell, TX

I have a IC-2F and IC-3P made by Inoue Communication Equipment of Oaska, Japan. I need information on two diodes D11 and D12 in IC-2F, manufactured in 1970. The diode is marked TCG110. What is the JEDEC number or what is the replacement number? Is this the first ICOM equipment made and sold in the USA?

129713 **Jerome F. Musialowski**
Cheektowaga, NY

I have a Toshiba T3100 model PA7037U laptop computer with a non-working screen. I would like to attach an outboard monitor to this computer, but I don't know how to toggle from the computer's built-in screen to the outboard monitor.

129714 **Ray Gilbert**
Sequim, WA

I was given a Hewlett Packard printer model number 2934A. It also has four plug-in slots in the back. In one of the slots is a module Courier 92188A. What is that for?

I would like to connect it to my Directwave PT 5M166B Pentium PC with Windows 95. In my printer wizard under HP selection, there are no choices for that model number. And I don't have a disk for it. What do I need to do to connect and make it work on my PC? I have called many different departments at "HP" and the best they could do is to give me another number to find out how much of a trade-in allowance I would get if I purchased a new HP printer. I have a good laser printer. I would like to use this one, because it has the wide carriage to run business forms.

129715 **Albin Bauer**
via Internet

A friend of mine bought a used 486SX computer from one of the local dealers. We (and I helped) could not get the 1.4 meg drive to format, coming back with the "Invalid media or track 0 bad - disk unusable. When I put the disk in my machine it would give me an empty directory and a serial number of 0000-0000. I put a NEW 1.44 MHz drive in and received the same results.

Both of the drives would format a 720K, giving the serial number 0000-0000. The dealer thought it was a defective power supply, but after a few days replaced the machine, with a 486 DXL4 100 MHz with an Award Modular Bios V4.50G. Same thing. The drive will format a 720K disk with no problem, giving it the same serial number, 0000-0000! The 5-1/2 drive works okay on both 360 and 1.2 Meg disks, giving the same serial #0000-0000.

ANSWER INFO

- Include the question number that appears directly below the question you are responding to.
- Payment of $25.00 will be paid within four weeks of publication if your answer is printed.
- Only one answer per question will be printed.
- If you do not want your name, address, or phone number available to the reader please so indicate or it will be assumed that you have no objection.
- In the event that more than one person submits the same solution, the choice will be made at the discretion of the publisher.
- Due to space limitations, we can not reprint the original questions with the answer. The question number and the issue it appeared in are printed above the answer.
- Unanswered questions from a past issue may still be responded to.

QUESTION INFO
TO BE CONSIDERED FOR PUBLICATION

All questions should relate to one or more of the following:
1) Circuit Design 3) Problem Solving
2) Electronic Theory 4) Other Similar Topics

INFORMATION/RESTRICTIONS
- No questions will be accepted that offer equipment for sale or equipment wanted to buy.
- Selected questions will be printed one time on a space available basis.
- Questions may be subject to editing.

HELPFUL HINTS
- Be brief but include all pertinent information. If no one knows what you're asking, you won't get any response (and we probably won't print it either).
- Write legibly (or type). If we can't read it, we'll throw it away.
- Include your Name, Address and Phone Number. Only your name will be published with the question, but we may need to contact you.

TECH FORUM

ANSWER TO #109713 - OCT. 1997

CAUTION! Timing lights can have up to 1 KV inside them. Use a shorting lead with a 50 ohm, 2W resistor in series on all high voltage capacitors inside the light as soon as you open it, and each time you make changes if you test it while opened up.

I am assuming the light runs off the vehicle 12V and has a third trigger wire that has to be directly connected to a spark plug wire. Some of the parts you need can be found in a junked photoflash unit trigger coil, SCR, small high-voltage film capacitor. The inductive pickup itself can be made from a ferrite U-1 core set with 10 turns of #26 wire on the "u." I used Ferroxcube (now called Phillips) 376U250 and 376B250 cores when I converted an old Sears timing light. There will be a lot of mechanical work involved:

1. Wrap a thin trigger wire around the flashtube, three-five turns of fine wire (#28-34 GA will do) wound over the length of the tube except the last 1/4"-3/8" near each end. **2.** Make a clamp housing for the inductive pickup cores. It will have a hinged, spring-loaded jaw with the "1" core in it and an opening big enough to pass the largest wire you want it to fit. The cable from the pickup to the timing light can be several feet of coaxial cable. The coax enters the light housing the same way the "direct connected" HV wire did. **3.** Add a small circuit board inside the timing light to hold the trigger cirucuit and possibly some added circuitry to be discussed below.

The trigger circuit is fairly simple.

The +HV and ground connections are to the two ends of the large high- voltage film capacitor which is wired across the ends of the flashtube. USE THE SHORTING WIRE before touching this part. It can have high voltage on it.

What is not simple is that the +HV varies a lot with engine RPM and can get very high if the timing light is turned on when no trigger is present. Usually all that happens is that the trigger circuit "free runs" as a relaxation oscillator. If it does this at low RPM (setting timing at idle speed, etc.) a high-voltage regulator circuit will have to be added to limit voltage at the SCR. This can be done various ways. The most efficient way controls the converter circuit that makes the high voltage. The simplest way is to stack up 300-500V of zeners in series and connect them across the SCR. Use a 68K 2W resistor instead of the 68K 1W shown in the drawing if this is done. If a better SCR is needed, try a C106M or any other 600V sensitive gate SCR.

Timing lights are fairly cheap, so I assume this is being done for fun. If so, trace the voltage converter circuit and find a way to add a controller to make it regulate. Set it for 80% of the voltage rating on the large high-voltage film capacitor.

Jonathan Wexler
Los Angeles, CA



When using another format utility, it would format the disk and give a directory, both in this machine and mine. I cannot understand how this could happen. Could you enlighten me?

129716 **B. J. Baum**
Decatur, IL

I have an LCD clock and thermometer module that can be set on any given temperature within specified limits. (High or low.) If for example, I set the high limit for 75 degrees and when the ambient temperature reaches 75 degrees, the module opens one output port for connecting additional circuitry for an alarm buzzer, etc. This output offers a 1.5 volt positive. What simple circuit could I use to energize a 12-volt relay?

129717 **Mike McFarlane**
via Internet

Is there a machine that allows you to copy cartridges like Genesis or Nintendo 64?

129718 **Internet**

I have an old, small multi-band (3 to 30 MHz) "adapter" for an automobile radio (similar to many sold over the years by Blaupunkt, Phillips, Telefunken, Grundig, etc., but this one is a Japanese copy). It has push buttons for different meter bands; a 12-volt power connection, is solid-state, has an on-off push button, and connects between the antenna and the car radio. Once the band is selected, then the car radio's analog tuning knob tunes that band. It is a quite-satisfactory-at-night poor man's automobile shortwave receiver. (My income is limited to my monthly social security check.)

Is there a way to use this little gadget with newer digital (PLL) automobile radios? (They seem to be limited to the frequency spacing of regular US AM

Continued on page 100

ANSWER TO #109715
OCT. 1997

The circuit you requested is easily implemented using a 4017 CMOS decade counter and a 4049 inverter to drive the LEDs. The 4000 series CMOS will operate between 3 to 18 volts and are ideally suited to the battery power as they use very little current.

Kevin Goodwin
Oceanside, CA



Quality ELECTRONICS

Yes, we can help with all your cable needs

QUALITY PRICES
QUALITY SERVICE
QUALITY PRODUCTS

1-800-394-3043

9am-5pm M-S • Same Day Shipping
1 FULL YEAR GUARANTEE
CALL TODAY! NO NV SALES

Don Lancaster's

RESOURCE BIN

number seventy one

My secrets of web-based research

Our usual reminder here that the *Resource Bin* is now a two-way column. You can get tech help, consultant referral, and off-the-wall networking on nearly any electronic, *tinaja questing*, personal publishing, money machine, or computer topic by calling me at (520) 428-4073 weekdays 8-5 Mountain Standard Time.

Web Research Secrets

I sure do get a lot of helpline calls asking about the basic tools you will need to locate stuff on the web. So, I thought we might once again review just where you can go to instantly get stuff electronically ...

Search Engines

A *search engine* is a good starting point to find anything on the web. My favorite search engine is the *Hotbot* you'll find at www.hotbot.com — Besides the usual searches for exact phrases or "any" and "all" words, this site also lets you find people and even links to your own website.

The latter sure is a great ego trip. Finding out who knows about you is one useful way to see how well your web promotion efforts are working. Url links are also a means to find out what others think about a site.

Or to find related sites on a linked list third party collection.

Another popular search engine is *Alta Vista* at *www.altavista.digital.com*

This one appears to find almost as much as Hotbot almost as well. But Hotbot lets me view more results at once. And lets you restrict by date. The "find url" feature on Alta Vista is somewhat hidden. You have to prefix your search with *link:*.

As in *link:www.tinaja.com*

A hint: To find an exact phrase or a name, put the words in quotes. This will miss a lot and give you less hits, but can be fast and accurate.

Some 70 or so of the popular search engines are gathered together at *www.wp.com/resch/search.htm* — One brand new *inference* engine is offered at *www.inference.com/infind* — This one does not appear to be able to find all that much, but it sure arranges what it is able to find very nicely.

Ezines, Newsgroups, and Newsletters

These are all special interest online publications, each having their own strengths and weaknesses.

An *ezine* could be any electronically published magazine. Some have print companions; others do not. Examples of my own ezines include the *Blatant Opportunist*, *Tech Musings*, *Guru's Lair*, *Resource Bin*, and *Hardware Hacker*.

All on *www.tinaja.com*

The best ezine directory seems to be John Labovitz's *www.meer.net/~johnle-zine-list* — Some other useful locators are found at *www.dominis.com/Zines* or *www.edoc.com/ejournal*

My favorite printed zine and web ezine commentary is Seth Friedman's *Factsheet Five* at *www.well.com/conf/f5/f 5index2.html* — There's something here to offend everyone.

A *NewsGroup* is a Usenet forum to which anyone can post and anyone can subscribe. There are many tens of thousands of these which target most any imaginable special interest topic. The nice thing about newsgroups is that you might visit these only when and where you want, actually reading only those threads and the authors of current interest to you.

The bad thing about newsgroups is that their quality can get really poor. Many newsgroups are not moderated, so anyone can say anything. There's a lot of naive and misinformed posting here, scads of hidden agendas, plus great heaping bunches of invective insults. So much so that all the real experts in most fields won't put up with such time-wasting nonsense.

And are promptly driven away.

Newsgroups are also the home of *trolls*. A troll is an life-challenged and clue-challenged individual who posts in such a tone as to totally infuriate the other users into making irrational responses. Troll skill levels can range from immature juvenile newbies to diabolical fiends. Your surest way to spot any troll is whenever they flame *themselves* on slow days. Some even conjure carefully crafted *Sock Puppet* alter egos. Needless to say, you *never* respond to any troll in any manner. Ignore them and they'll go away.

Or else Bozo filter them.

You can access these newsgroups through the *news server* at your local ISP. Most include news access in their basic rate; others will charge a little extra. The news service will include a listing and a search service.

NEXT MONTH:
Don looks into new microwave and wireless developments.

The usual starting point to find out all about newsgroups is *Deja News* at *www.dejanews.com/home_ps.shtml* — This one also lets you scope out those *other* groups a given responder is posting to. Thus, you're able to quickly run a credibility and background check. But I like the *Usenet* search feature of *Alta Vista* better. It finds more stuff.

I've put a hot linked newsgroup list to *www.tinaja.com/text/newslist.html*

"FAQ" is short for *Frequently Asked Questions*. Better newsgroups do try to answer all of the obvious queries that newcomers ask in downloadable files. A master directory for the FAQ sites appears as *www.faqlib.com*

Three newsgroup rules: *Always lurk before you post.* Preferably for several weeks. Always carefully read *all* the other responses before posting. And *never* post anything to a newsgroup without *at least* a 24 hour delay for thinking out your message.

A *newsletter* (or *mailing list*) can be thought of as a "subscription only" newsgroup. The postings are usually moderated, thoroughly stomping all the garbage, the flames, and the trolls. The people here are usually far more knowledgeable, infinitely more polite, and the content quality is often much higher. Membership might be strictly limited, and charges may apply.

You've got a choice of receiving dozens (and possibly hundreds) of E-Mail newsletter messages daily. Or of receiving a few humongous and hard to search *digest* files. Either way, newsgroups could provide you with useful information and contacts. But normally do so in an annoying and obnoxiously intrusive way.

new from
DON LANCASTER

ACTIVE FILTER COOKBOOK
The sixteenth (!) printing of Don's bible on analog op-amp lowpass, bandpass, and highpass active filters. De-mystified instant designs. **$28.50**

CMOS AND TTL COOKBOOKS
Millions of copies in print worldwide. **THE** two books for digital integrated circuit fundamentals. About as hands-on as you can get. **$28.50** each.

RESEARCH INFOPACKS
Don's instant cash-and-carry flat rate consulting service. Ask any reasonable technical question for a detailed analysis and complete report. See www.tinaja.com/info01 for specifics. **$75.00**

INCREDIBLE SECRET MONEY MACHINE II
Updated 2nd edition of Don's classic on setting up your own technical or craft venture. **$18.50**

LANCASTER CLASSICS LIBRARY
Don's best early stuff at a bargain price. Includes the CMOS Cookbook, The TTL Cookbook, Active Filter Cookbook, PostScript video, Case Against Patents, Incredible Secret Money Machine II, and Hardware Hacker II reprints. **$119.50**

LOTS OF OTHER GOODIES

Tech Musings V or VI	$24.50
Ask the Guru I or II or III	$24.50
Hardware Hacker II, III or IV	$24.50
Micro Cookbook I	$19.50
PostScript Beginner Stuff	$29.50
PostScript Show and Tell	$29.50
Intro to PostScript Video	$29.50
PostScript Reference II	$34.50
PostScript Tutorial/Cookbook	$22.50
PostScript by Example	$32.50
Understanding PS Programming	$29.50
PostScript: A Visual Approach	$22.50
PostScript Program Design	$24.50
Thinking in PostScript	$22.50
LaserWriter Reference	$19.50
Type 1 Font Format	$16.50
Acrobat Reference	$24.50
Whole works (all PostScript)	$380.00
Technical Insider Secrets	FREE

BOOK-ON-DEMAND PUB KIT
Ongoing details on Book-on-demand publishing, a new method of producing books only when and as ordered. Reprints, sources, samples. **$39.50**

THE CASE AGAINST PATENTS
For most individuals, patents are virtually certain to result in a net loss of sanity, energy, time, and money. This reprint set shows you Don's tested and proven real-world alternatives. **28.50**

BLATANT OPPORTUNIST I
The reprints from all Don's Midnight Engineering columns. Includes a broad range of real world, proven coverage on small scale technical startup ventures. Stuff you can use right now. **$24.50**

RESOURCE BIN I
A complete collection of all Don's Nuts & Volts columns to date, including a new index and his master names and numbers list. **$24.50**

FREE SAMPLES
Check Don's Guru's Lair at *http://www.tinaja.com* for interactive catalogs and online samples of Don's unique products. Searchable reprints and reference resouces, too. Tech help, hot links to cool sites, consultants. email: *don@tinaja.com*

FREE US VOICE HELPLINE VISA/MC

SYNERGETICS
Box 809-NV
Thatcher, AZ 85552
(520) 428-4073

FREE Catalog: http://www.tinaja.com



RESOURCE BIN

A FEW USEFUL WEB RESEARCH SITES

Acrobat newsgroup	comp.text.pdf
Adobe Acrobat Reader	www.adobe.com/prodindex/acrobat/readstep.html
Alta Vista search engine	www.altavista.digital.com
Alternate ezine directory	www.dominis.com/Zines
Alternate ezine directory	www.edoc.com/ejournal
Basic Stamp support	www.parallaxinc.com
Bed and breakfast directory	www.homearts.com/affil/ahi/main/ahihome.htm
Best book info	www.amazon.com
Best ezine directory	www.meer.net/~johnl/e-zine-list
Bizarre Pseudoscience	www.tinaja.com/scweb01.html
Black Range Lodge	www.zianet.com/blackrange/lodge.html
Blond Aggie redneck lawers	www.winn.com/pwinn/humor/index/html
Car trader	www.traderonline.com
Cattle Moo Tillations	www.qtm.net/~geibdan/framest.html
Church of the SubGenius	sunsite/unc.edu/subegnius
Classified shopper	www.classifieds2000.com
Dilbert and Dogbert	www.unitedmedia.com/comics/dilbert
Don Lancaster's Guru's Lair	www.tinaja.com
Emory University MedWeb	www.gen.emory.edu/medweb
Factsheet Five on zines	www.well.com/conf/f5/f5index2.html
FM radio station finder	wmbr.mit.edu/stations/locate.html
Four11 people finder	www.Four11.com
Free catalogs	catalog.savvy.com
Free energy forum	www.eskimo.com/~bilb/freenrg/frng
Free Medline medical info	www.healthy.net
Electronic auctions	www.bentleysauction.com
Electronic engineer links	www.tinaja.com/eeweb01.html
Hotbot search engine	www.hotbot.com
Inference search engine	www.inference.com/infind
InfoPack research services	www.tinaja.com/info01.html
Interesting site links	www.persiankitty.com
Internet country codes	www.Four11.com/cgi-bin/Four11Main?Country
Internet Service Providers	thelist.iworld.com
Jerry Decker's Keelynet	www.keelynet.com
Job listing links	www.datamation.com/PlugIn/jobs/jobs.html
Kelly Blue Book	www.kbb.com
Lindsay Publications	www.keynet.net/~lindsay
Lookup USA phone directory	www.lookupusa.com
Ma Bell 800 numbers	attnet/dir800
Mapquest map drawing site	www.mapquest.com
Master FAQ directory	www.faqlib.com
Master PIC directory	www.tinaja.com/pic500
Meta search engine site	www.wp.com/resch/search.htm
Microchip Technology	www.microchip.com
Mo Hotta Mo Betta	www.mohotta.com
More Acrobat support	www.tinaja.com/acrob01.html
Movie reviews & info	us.imdb.com
Online published books	www.cs.cmu.edu/books.html
Oxbridge Media Finder	www.mediafinder.com
PAML newsletter directory	www.NeoSoft.com/Internet/paml
Patent repository	patent/womplex.ibm.com
Periodical elements table	www2.shef.ac.uk/~chem?web-elements
PIC reprints & support	www.tinaja.com/picup01.html
Random cyberspace jump	www.yahoo.com/bin/top2?122.25
Real time Arizona floods	wwwdaztcn.wr.usgs.gov/rt-cgi/gen_tbl_pg
Saucer Smear magazine	www.mcs.com/~kvg/smear.htm
Scott Edwards	www.seetron.com
Science Hobbyist	www.eskimo.com/~billb
Shepard Engineering	home.att.net/~dennis.shepard
Surplus bargains	www.tinaja.com/barg01.html
Switchboard phone directory	www.switchboard.com/cgiqa.dll?MG=
Technical electronics	techweb.cmp.com/eet/docs
US Government surplus	131.87.1.51
USPS zip code directory	www.usps.gov/ncsc
Volkswagen Van newsletter	Vanagon@gerry.sdsc.edu
Wall Street investment net	wsm.com
Web site free promotion	www2com.com/~upfront/launch
Web site free promotion	www.ep.com/faq/webannounce.html
Web site name finder	www.internic.net/cgi-bin/whois
Web site registration	www.internic.net
Webmastering secrets	www.tiaja.com/weblib01.html
WhoWhere people finder	www.whowhere.com

Newsgroups are tightly targeted. E-Mail *Vanagon@gerry.sdsc.edu* with a message of *subscribe vanagon* or else *subscribe vanagon digest*, and you'll be placed on their fine mailing list for a newsletter on 1987 Synchro 4WD vans with diff locks.

You subscribe to other newsgroups in pretty much the same manner. By E-Mailing them your requests. *PAML* is one newsletter directory service.

At *www.NeoSoft.com/Internet/paml*

Finding People

Online phone directories are your obvious place to start people finding. These do include *Lookup USA* at, of all places, *www.lookupusa.com*; competitor *Switchboard* at *www.switchboard.com/cg iqa.dll?MG=*; and the Ma Bell toll free 800 number directory *attnet/dir800.*

Lookup USA also can provide maps. A second useful map site is *Mapquest* at *www.mapquest.com*

If the individual is active online, try finding them by way of *WhoWhere* at *www.whowhere.com* or else use *Four11* at *www.Four11.com*

If the person you are looking for is active in newsgroups, Deja News is once again a powerful access choice.

Basic Research Tools

Here is one quick rundown of the research sites on the web that I use most for my own consulting:

Books in Print does not seem to be online just yet. But *Amazon Books* at *www.amazon.com* is a useful alternate that works even better. Similarly, that *Ulrich's Periodicals Dictionary* also does not seem to be available online. Their *Oxbridge Media Finder* competitor is now completely blowing them out of the water at *www.mediafinder.com*

Surprisingly, the complete and free *Thomas Registry of Manufacturers* is now available online at *www.thomasre gister.com/index.html* — You do have to register and remember a password. This is a great place to go to find out stuff about old line companies who are not yet web-literate.

A great selection of technical books (many involving historical or "lost" art) can be located through *Lindsay* at *www.keynet.net/~lindsay/* — A directory of online published books is available through *www.cs.cmu.edu/books.html*

I've got a whole page of electrical engineering links uploaded for you at *www.tinaja.com/eeweb01.html* — Other superb electronics access can be found at *techweb.cmp.com /eet/docs*

Government surplus electronics are found at *131.87.1.51*, while one leading surplus electronics auction house is Bentley at *www.bentleysauction.com*

Other surplus bargains can often be gotten at *www.tinaja.com/barg01.html*

A USPS zip code directory can be found at *www.usps.gov/ncsc*

A great periodical table of the elements is at www2.shef.ac.uk/~chem?web-elements

A fully searchable patent repository resides at the *patent/womplex.ibm.com* — But do remember that winners appear in the marketplace and losers appear in the patent directories. More on this in my *Case Against Patents* package or at *www.tinaja.com/patnt01.html*

You can find the darndest stuff on the web if you dig deep enough. For instance, you can track Arizona floods real-time with the live stream gauge satellite monitors at wwwdaztcn.wr.usgs.gov/rt-cgi/gen_tbl_pg

Betcha you don't already have this one bookmarked.

Investments, Medicine, Jobs, and Movies

Let's quickly look at a few of my favorite non-technical sites. The best investment links I've found are the superb *Wall Street Research Network* at *wsrn.com*

The place doctors go to get info is the fee-based *Medline* service. One free medline link is *www.healthy.net*

Another very useful medical link is *www.gen.emory.edu/medweb*

One extensive job listing source is *www.datamation.com/plugin/jobs*

A leading movie review site is the *Internet Movie Database* at /us.imdb.com

Places to buy and sell stuff include *www.classifieds2000.com* and the *Trader Online* people at *www.traderonline.com*

Car apprasial is best done through the *Kelly Blue Book* at *www.kbb.com*

Thousands of free catalogs are now offered by *catalog.savvy.com*

Essential hacker nutrients are at *Mo Hotta Mo Betta* (*www.mohotta.com*) One good bed and breakfast directory is *www.homearts.com/affil/ahi/main/ahihome.htm* while our favorite B & B is the *Black Range Lodge* at *www.zianet.com/blackrange/lodge.html*

A really great FM station finder is at *wmbr.mit.edu/stations/locate.html*

Check this one out.

Adobe Acrobat

Typical web technical information (especially electronic data sheets) is now presented in *Adobe Acrobat* or .PDF format. In *one* fast-loading single file, Acrobat can give you a "perfect" camera ready image, having exactly and only what your provider wants you to see in precisely the way they want you to see it. With all fonts and artwork and images and text fully and perfectly preserved. Magnifiable, and with text smoothing, even.

If you know the secret insider trick, Acrobat gives you instant online and hot linked *full screen* displays. Just click on your PDF selection and let it autoload into Netscape. Then enter ctrl-shift-L followed by ctrl-K. Presto. Your full screen "just like the printed page" display. Easily navigated with the usual keys or mouse moves. And printable on any newer printer.

A hint: Set your Acrobat full screen preferences to activate escape, apply vertical wipe, set cursor hidden after delay, and use loop wraparound. But unclick your auto advance.

You can get the latest free Acrobat 3.01 reader from *www.adobe.com/prodindex/acrobat/readstep.html* — Always do install Netscape first and Acrobat 3.01 second, so your plug-ins get properly placed into your browser.

There's an acrobat newsgroup at *comp.text.pdf* and more Acrobat info at *www.tinaja.com/acrob01.html*

Web-Related

Your usual place to go to register your personal website is Internic at *www.internic.net* — They also have their *whois* at *www.internic.net/cgi-bin/whois* that lets you find if a domain name is in use and who owns it.

Useful locations to promote your website at no charge now do include *www2com.com/~upfront/launch* plus *www.ep.com/faq/webannounce.html*

A handy listing for the internet country codes appears at *www.Four11.com/cgi-bin/Four11Main?Country*, while the master directory of ISP *Internet Service Providers* is at *thelist.iworld.com*

A few more webmastering access tools: /www.tinaja.com/webwb01.html

PIC-Related

The horse's whatever on PIC info is *Microchip*

at *www.microchip.com* — Other great PIC sites include the *BASIC Stamp* people at *www.parallaxinc.com*, *Shepard Engineering* at *home.att.net/~dennis.shepard*, or the Scott Edwards Electronics at *www.seetron.com*

A master directory of PIC websites is at *www.tinaja.com/pic500*, while PIC reprints and other useful content are found both at my */picup01.html* and at */picwb01.html* on the same site.

Pseudoscience

One of my very favorite activities is pseudoscience bashing. Besides being mesmerizingly awful fiction, this can give me unique directions to present fundamental electronic, chemical, and physical principles.

I also have this goal of piling up all of pseudoscience in the middle of a big stage somewhere, shining a bright light on it, and getting all of you to conclude "Yup, that sure is a really big pile allright."

Only tiny problem is that a lot of it keeps leaking out of the bottom.

My favorite source for this sort of thing is *www.keelynet.com* — Bill Beatty runs his superb *Science Hobbyist* site at *www.eskimo.com/~billb* which combines both real science and pseudoscience file downloads. He also hosts a bizarre free energy forum at *www.eskimo.com/~bilb/freenrg/frng*. But watch out for all the "not even wrong" labwork here.

And, of course, Mosley's old *Saucer Smear* at *www.mcs.com/~kvg/smear.htm* uses "in your face" journalism to slam UFO friend and foe alike.

Now in their 43rd year!

Cattle *Moo Tillations* are covered by *www.qtm.net/~geibdan/framest.html*

Lots more pseudoscience site links are at *www.tinaja.com/scweb01.html*

Just For Fun

Those Guru's and Swami's Union local #204 rules do demand that all technical Internet sites have a Dilbert and Dogbert link. You'll find them at *www.unitedmedia.com/comics/dilbert* — To pick up all of the latest blonde Aggie redneck lawer jokes, try *www.winn.com/pwinn/humor/index/html* — I really do like the one here where Wiley Coyote is filing a product liability suit against *Acme* manufacturing.

An interesting variety of site links is offered by *www.persiankitty.com*

If you want to go completely off the planet in your web explorations, do check out the *Church of the SubGenius* at *sunsite/unc.edu/subgenius*

One ultimate for-fun venture is to make a random jump somewhere in cyberspace and see where you land. One good way to do this is by using *www.yahoo.com/bin/top2?122.25* — Since this link is now "hidden" by its host, it might not stay around forever.

For More Help

The best way to find things on the web is to jump in with both feet and start doing it. If you do not yet have a web account with the local ISP, try borrowing a friend's Internet access. Or go to your local library to begin picking up experience. Or sign up for a community college course.

Hands-on is everything!

Hot links to all of these mentioned research tools appear on my *Guru's Lair* website at *www.tinaja.com* — Start with all of those *Web Related Links* at *www.tinaja.com/webwb01.html* — Then try those seven other link buttons.

Additional insider web tricks and techniques in the *Webmaster Library* at *www.tiaja.com/weblib01.html* — The hot linked version of this column is up at *http://www.tinaja.com/glib/resbn71.pdf* — Just click on any blue text to instantly go anywhere mentioned. By using Acrobat's online full screen feature.

Finally, if you don't want to do your own web research, I'd be most happy to do most of it for you. Full details all about my unique *InfoPack* consulting service can now be found at *www.tinaja.com/info01.html*

This Month's Contest

For our contest this month, just tell me about any useful and unusual web site I don't already know about. Tell me what it does. And why you like it.

There should be a largish pile of my new *Incredible Secret Money Machine II* books going to the dozen or so better entries, plus an all-expense-paid (FOB Thatcher, AZ) *tinaja quest* for two that will go to the very best of all.

Send all your *written* entries to me here at *Synergetics*, rather than to *Nuts & Volts* editorial. **NV**

Microcomputer pioneer and guru Don Lancaster is the author of 33 books and countless tech articles. Don maintains his no-charge US tech helpline found at ***(520) 428-4073****, besides offering all of his own books, reprints, and consulting services. Don also offers a free catalog full of his unique products and resource secrets. The best calling times are 8-5 on weekdays, Mountain Standard Time.*

Don is in the process of setting up his Guru's Lair at ***http://www.tinaja.com***

Full reprints and preprints of all Don's columns and ongoing tech support appear here. You can reach Don at Synergetics, Box 809, Thatcher, AZ 85552. Or send any messages to his US Internet address of ***don@tinaja.com***

Looking for the right crowd to promote your electronic products to?

RENT OUR LIST!

FOR ORDERING OR MORE INFORMATION, PLEASE CONTACT:

Response Media Products, Inc.

2323 Perimeter Park Drive, Suite 200, Atlanta, Georgia 30341-1335

(770) 451-LIST · FAX (770) 451-4929

BUSINESS OPPORTUNITIES *cont.*

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.

FOR SALE: TV/VCR/STEREO/APPLIANCE sales & service center. 2 locations. Located in sunny south Florida. Est. over 40 years. Authorized service for over 45 companies. Part inventory & service literature in excess of $100,000. Office is fully computerized. Owner retiring. Must sell ASAP. Offers accepted. Day 305-632-1267, evening 305-227-9854, E-Mail: repair4less@worldnet.att.net

THE CASE AGAINST PATENTS. Thoroughly tested and proven alternatives that work in the real world, $28.50. **SYNERGETICS PRESS**, Box 809-N, Thatcher, AZ 85552. 520-428-4073. Visa/MC.

ELECTRONICS BUSINESSES, home based. Part/full time. 250 pg. comprehensive guidebook, insider information **$19.95**. 24 hr. recording **1-800-326-4560** x151.

DYNAMIC Technologies

Booth #3752 at CES in the LVCC

Advanced Cable Products for a Competitive World

1 - 4 0 2 - 7 3 1 - 9 5 5 5

Suite 541064 • Boystown, NE 68154

Stargate Elite

- Slim Line Remote
- 550MHz / 83 Channel
- Parental Control
- Unlimited Favorite Channel
- HRC / Standard Switchable
- Auto Fine Tune
- Manual Tune Override
- 1 Year Warranty

As Low As $38.50

Stargate Elite Plus

- Volume Control
- Audio/Video Out
- Slim Line Remote
- 550 MHz / 83 Channel
- Parental Control
- Unlimited Favorite Channel
- HRC / Standard Switchable
- Auto Fine Tune
- Manual Tune Override
- 1 Year Warranty

$59.95

Infinity 3000

- SHARP 125 Channel Tuner
- Dynamic Memory Recall
- Parental Control
- Last Channel Recall
- Unlimited Favorite Channels
- Slim Line Remote
- Automatic Fine Tune
- Micro Card Slot
- Volume Control
- Audio /Video Outputs
- Sleep Timer
- Automatic Low Signal Enhancer

$89.95

SHARP's™ New Premium Dynamic Tuner
No Other Cable Box Gives a Sharper Picture

Stargate Infinity 3000A

NEW

- Advanced Addressable Base Band Decoder
- Upgradeable Micro Decoder Card
- 125 Chnnel / 800 MHz
- Volume Control
- Audio/Video Outputs
- Sleep Timer
- Automatic Low Signal Enhancer
- Dynamic Memory Recall
- Parental Control
- Last Channel Recall
- Unlimited Favorite Channels
- Slim Line Remote
- Automatic Fine Tune

$169.00

The *Ultimate* Navigator Series

Starting at $219.00

- Advanced Baseband Replacement
- Interactive On Screen Display
- 250 Channel Capable
- Watch One Premium While Recording Another
- Parental Control *with timed lock/unlock schedules*
- Watch and Record
- Easy Read Clock
- Preloaded Channel Labels
- Unique Favorite Channel Theme System
- V-Chip Ready
- Audio/Video Input and Output
- Addressable/Programmable
- Electronic Program Guide Available*





*StarSight Electronic Program Guide
Exclusive to the Navigator Series

- One Touch Recording
- Eliminates Complicated VCR Programming
- Current, Future or Series Recording
- Categorizes All Programming
- Displays Time, Date, Rating, Starring Actors, and More
- Seven Day Programming Schedule
- Free Ninety Day Subscription

All products are FCC approved and comply with the 1996 Telecommunications Act Section 304, Subsection 629 entitled Navigation Equipment. In accordance with the 1996 Telecommunications Act, all Everquest products with decoding functions are addressable and must be activated by an authorized cable system.



Your choice has got to be...

M.F.M. COMMUNICATIONS.

for...

CELLULAR PROGRAMMING

New ... "Full Plans & Codes to Build Your Own."

Build your own... **Motorola Magic Boxes.** "A Small and Neat Box that Programs via the phones own keypad." Does EE1,2,3 & StarTAC to and including version 964F. Full Plans and Code, including five fully built units with leads. **Only $9,999.**

Build your own... **Motorola Copy-Kats.** Does EE1,2,3 & StarTAC to and including version 964F. Full Plans and Code, including two fully built & tested units with leads. **Only $6,999.**

Build your own... **NEC Programming Clips.** Full Plans and Code, including a fully built & tested unit. **Only $1,499.**

Build your own... **Ericsson Programming Clips.** Full Plans and Code, including a fully built & tested unit. **Only $999.**

Cellular Products built & tested, ready to use.

Magic Box & Leads. Motorola EE1,2 3 and StarTAC, only **$699.**

Copy-Kat & Leads. Motorola EE1,2 3 and StarTAC, only **$699.**

NEC Clip, only **$149.** **Ericsson Clip**, only **$119.**

ESN Reader (also tracks calls and decodes DTMF), only **$1699.**

New... **Copy-Cat (4way).** Motorola, Ericsson, NEC & Sony, only **$899.**

***Call Us Now on...* 01144-188-333-0060**

Email: MFMCOM123@aol.com

M.F.M. COMMUNICATIONS.

57 Addison Road, Caterham. CR3-5LU. UK.

"This advert is For Information Purposes Only"

Please note: When Purchasing the ESN reader, proof of Cellular dealership will be required.

Write in 187 on Reader Service Card.

Mr. NiCd ***E.H. Yost & Co.*-YOUR SOURCE FOR** **Mr. NiCd**

★ BATTERIES! ★

☆ AMATEUR / COMMERCIAL / AVIATION RADIO ☆
☆ LAPTOP COMPUTERS ☆ VIDEO CAMCORDERS ☆
☆ CELLULAR & CORDLESS TELEPHONES ☆
☆ SEALED LEAD ACID ☆ PHOTOGRAPHY ☆
☆ MEDICAL EQUIPMENT ☆ TESTING EQUIPMENT ☆

CALL OR WRITE TODAY FOR OUR FREE CATALOG!

Phone (608) 831-3443 / Fax (608) 831-1082

E.H. Yost & Company **2211-D Parview Rd., Middleton, WI 53562**

BUSINESS OPPORTUNITIES *cont.*

HOME AUTOMATION DEALERS WANTED. Free information. Call 1-800-838-4051 or fax name, address, and telephone to 402-729-3863.

REPAIRS — SERVICES

ENGINEERING CONSULTING. Product development from conceptual to manufacturing stages. Digital, analog, and RF expertise. Microcontroller designs for HC05xx, HC11xx, PIC16C5x. Software design for IBM PC. ASIC design using XILINX. In-house schematic capture and PWB. Steve Hicks, DiaSystems Electronics, 7508 E. Granada Rd., Scottsdale, AZ 85257. 602-970-3162. E-Mail: diasys@cyberhighway.net website: www.cyberhighway.net/~diasys

(E)EPROM PROGRAMMING done quickly and economically. One day turn around typical. Simple copy $3 per device. Also prototyping, design, and consulting services available. Call or send SASE to: **Luzer Electronics, 4023 North Bayberry, Wichita, KS 67226. 316-687-4759, FAX 316-687-3103.**

CATV REPAIR, most models, great prices, warranty included. Please call 573-363-0402.

20,000 + TECHNICAL REPAIRS for **TVs, VCRs, PROJECTION TVs, CAMCORDERs, AUDIO** on disk. COMPONENT/BOARD LEVEL REPAIRS. Installs on your hard drive. Easy look-up by model/chassis number. **ADD** your own tech repairs. **PRINT** out repairs. **FREE DEMO. HIGHER INTELLIGENCE SOFTWARE, 60 FARMINGTON LANE, MELVILLE, NY 11747. 1-800-215-5081.**



SEMICONDUCTOR CROSS-REFERENCE Library (SCRL) software for the PC. 250,000+ devices, with descriptions, lead and case drawings for most. $69 plus $6 S&H. We will include the **ELECTRONIC REPAIR TIPS** (26,000+) for additional $20, **FCC ID CODES** for additional $10. Checks & credit cards accepted. E-Mail: customsoftware@usa.net web: http://www.electronic-repair.com Custom Software Creators, PO Box 1092, St. Bethlehem, TN 37155. 931-647-6120.

PICS, GALS READ if you've lost your masters. Programming service available. Call for info. Network Sales, 616-683-0500.

WORLD OF SAVINGS FROM I.E.S.

We can help with all your cable needs.
One stop source for converter parts, tools, and accessories.

- **Low Prices**
- **Quality Service**
- **Quality Products**

*Call now for your **FREE** catalog.*

Tel: 405-634-1535
Fax: 405-634-1587

Feature Of The Month
PIC16C54: $1.95 EACH
PIC16C56: $1.90 EACH
Micro 40 pin Motorola
68H705C8P: $8.50 EACH
Minimum 100 lot

E-Mail: intek8111@aol.com

We are looking for New Distributors for Nuts & Volts Magazine.

If you would be interested in selling Nuts & Volts in your store or on your newsstand, we have a great deal for you!

For complete information, ask for our New Distributor flyer.

Nuts & Volts Magazine
430 Princeland Court
Corona, CA 91719
phone 909-371-8497
fax 909-371-3052
E-Mail
distributors@nutsvolts.com

Write in 30 on Reader Service Card.

DSS Digital Satellite Systems

ONE STOP SUPPLIER

"One call does it all" 1-888-426-9787 Toll Free



Tri 550 Converter
$59.00

Millennium Converter
$69.00

NovaVision Converter
$199.00



Panasonic Converters
$179.00

MasterCard AMERICAN EXPRESS VISA

A DOZEN OTHER CONVERTERS AVAILABLE!

Call for Quantity Prices We accept: MasterCard, Visa, American Express

Open Monday - Friday 10:00 a.m. - 5:00 p.m. Saturdays 10:00 a.m. - 2:00 p.m.

REMOTES!

No Florida Sales • We ship same Day • 90 Day Limited Warranty • Visit us at our website www.onestopcable.com • E-Mail: Info@onestopcable.com

Write in 212 on Reader Service Card.

Events CALENDAR

Continued from page 39

MAY 9

CA - FONTANA - Inland Empire ARC Amateur Radio & Electronics Swapmeet. A B Miller High School. Bill 909-822-4138 eves

MAY 15-16-17

OH - DAYTON - HamVention. Dick Miller N8CBU, 937-276-6930. E-Mail: chair@hamvention.org Web: http://www.hamvention.org/

MAY 16

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052

MAY 17

MA - CAMBRIDGE - Flea Market. Kendall Square area. MIT. Nick Alternbernd KA1MQX, 617-253-3776

MAY 29-30

NE - SOUTH SIOUX CITY - Midwest/Dakota Div. Convention. Mike Nickolaus NF0N, 402-494-6070

MAY 29-30-31

NY - ROCHESTER - Atlantic Division Convention. Harold Smith K2HC. 716-424-7184. E-Mail: rochfst@frontiernet.net Web: http://www.rochesterhamfest.org

OR - SEASIDE - Northwestern Division Convention. Randy Stimson KZ7T. 503-297-1175

MAY 31

CA - SANTA ANA - Swapmeet. ACP parking lot. Mary Russo 714-558-8813

JUNE 1998

JUNE 6

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052

JUNE 7

IL - PRINCETON - Starved Rock RC Hamfest. Debbie Burton N9DRU, 815-795-2201

JUNE 12-13

GA - ALBANY - ARC Hamfest. Arthur Shipley N4GPJ, 912-439-7055

ATTENTION CABLE VIEWERS

CABLE VIEWERS . . . get back to your BASIC Cable Needs

Call 1-800-577-8775

For information regarding all of your **BASIC** cable needs.

5 GOOD REASONS TO BUY OUR FAR SUPERIOR PRODUCT

- PRICE
- EFFICIENT SALES AND SERVICE
- WE SPECIALIZE IN 5, 10 LOT PRICING
- ALL FUNCTIONS (COMPATIBLE WITH ALL MAJOR BRANDS)
- ANY SIZE ORDER FILLED WITH SAME DAY SHIPPING

We handle NEW equipment ONLY – Don't trust last years OBSOLETE and UNSOLD stock!

COMPETITIVE PRICING — DEALERS WELCOME

BASIC ELECTRICAL SUPPLY & WAREHOUSING CORPORATION

It is not the intent of B.E.S.W. to defraud any pay television operator and we will not assist any company or individual in doing the same.

*Refer to sales personnel for specifications.

P.O. BOX 8180 · BARTLETT, IL 60103-8180 · 847-584-2099

Write In 131 on Reader Service Card.

New Product News

Our readers are always looking for new and interesting electronic items. Showcase your NEW PRODUCTS here to help stimulate your product's success. Submit all news releases, product information, and/or photos to:

NUTS & VOLTS MAGAZINE
NEW PRODUCT EDITOR,
430 PRINCELAND CT., CORONA, CA 91719

250CT CURRENT TRANSDUCER



Ideal for industrial monitoring and control, Shoreline Electronics introduces the 250CT, an AC/DC current transducer. The 250CT monitors both AC and DC current with ±1.0% accuracy at 20°C ±5°C and ±2.0% accuracy at 45°C. This Hall-Effect current sensor allows a user simply to place a positive or negative cable through the sensor and measures up to 250 amps.

Requiring merely a single DC 10-12 volt power supply, the 250CT has a rise time of <3 microS, operates up to 400 Hz, and weighs <100G. Packed into a sleek 58 x 91 x 45 mm frame, the 250CT operates over a wide temperature range (-10° to 55° C) with 0.5% linearity over 0 to 250 amps.

Pricing begins at $59.95.

For more information, contact:

SHORELINE ELECTRONICS
2098B WALSH AVE., DEPT NV
SANTA CLARA, CA 95050
408-987-7733 FAX: 408-987-7735
E-MAIL: ShoreElec@aol.com

MOTOR MIND B



Motor control is simplified to a serial communication stream with the Motor Mind B. Serial commands can be sent via a one- or two-wire interface. The short instruction set designed into the Motor Mind B allows the user to implement complex control algorithms quickly and with little effort. Bi-directional or uni-directional DC motors with operating voltages as great as 30 VDC, can be used with the Motor Mind B.

This module can handle peak currents as large as 3.5 amps and continuous currents of 2 amps. Package power dissipation must not be exceeded during use.

Features include the ability to read a motor's tachometer frequency (0-65,528 Hz), automated speed control, 254 discrete steps of speed control, and motor direction changes.

The Motor Mind B comes complete with a watchdog timer to eliminate the possibility of a system firmware failure.

The Motor Mind B's small size and connection scheme allow the device to be inserted directly into circuit boards for production runs, or into breadboards for easy prototyping. Complete data sheets and application notes are available at "www.solutions-cubed.com"

The Motor Mind B comes in a 1.2" x 1.3" SIP module, and sells for $29.95.

For more information, contact:

SOLUTIONS CUBED
3029 ESPLANADE STE. F
DEPARTMENT NV
CHICO, CA 95973
530-891-8045 FAX: 530-891-1643
E-MAIL:
lon@solutionscubed.com
URL: www.solutions-cubed.com

CIRCULAR CONNECTOR

Hirose offers the JR-W series of high-performance water-proof circular connectors, developed for interfaces of a variety of electronic equipment, including machine tools and communications equipment.

The JR-W connector was also developed to be corrosion resistant in order to be utilized even in adverse environments.

Plated with black chromium, the JR-W series offers smooth connections, provided by five guide points, and is provided in variable shell sizes and core numbers.

Cost of the JR-W is $33.50 in lots of 500.

For more information, contact:

HIROSE ELECTRIC, INC.
2688 WESTHILLS CT., DEPT. NV
SIMI VALLEY, CA 93065
805-522-7958 FAX: 805-522-3217

PEI FILTER PROBE



This new and unique probe is designed to locate phone, data, security, and alarm, HVAC and building control, and de-energized electrical wiring without picking up the hum generated by AC wiring.

It works with any PEI tone generator and speeds cable tracing.

It has volume control, a conductive tip, momentary on-switch, and terminals for connection to a test set.

It is weather-resistant and has an easy access battery compartment.

For more information, contact:

JENSEN TOOLS INC.
7815 S. 46TH ST., DEPT. NV
PHOENIX, AZ 85044-5399
602-968-6241 FAX: 602-438-1690

BNC T-CONNECTORS



Trompeter Electronics has added a BNC coaxial T-connector to its telecom, and audio and video broadcast lines in two versions: a 50-ohm connector (BN23) and a 75-ohm version (UBN23).

The new BNC T-adapters include Teflon dielectric and beryllium copper contacts, at a cost of $5.00 at 100 quantity.

For more information, contact:

TROMPETER ELECTRONICS
31186 LABAYA DR., DEPT. NV
WESTLAKE VILLAGE, CA 91362
818-707-2020 FAX: 818-706-1040
1-800-982-2629
www.trompeter.electronics.industry.net

NX1 PC CARD FRAME KITS

Hirose Electric, Inc., provides NX1 snap-together-type PC card frame kits, ideal for a wide variety of PC card I/O applications. Versions for standard 16-bit and CardBus are available.

The NX1 reduces the number of steps needed for PC card frame assembly eliminating the need for heat fusion and cooling of covers.

With the NX1, assembly of the frame kit is possible with a simple jig tool. The NX1's two-piece construction enables fast, efficient assembly. The spring quality of the metal also maintains stable conduction between the panels of the NX1.

The frame kits are available with board offsets of 0.3 mm and 0.9 mm. Back connectors with 15, 25 and 32 contacts are available.

Costs of the NX1 for 15 positions is $1.99 in lots of 1,000 or more.

For more information, contact:

HIROSE ELECTRIC, INC.
2688 WESTHILLS CT. DEPT. NV
SIMI VALLEY, CA 93065
805-522-7958 FAX: 805-522-3217

MENTALMAX™



Selling for $549.00, mentalMAX is a new all-in-one circuit design package featuring schematic entry, printed circuit board layout with autorouting, and both analog (SPICE) and digital simulation.

The package is designed for small companies, individual engineers, students, and others who

New Product News

want a complete design capability for a very low cost.

MentalMAX includes the easy-to-use SuperCAD schematic entry software. This software allows you to draw circuit diagrams on A through E size sheets which can be printed on any Windows compatible printer. SuperCAD has nearly 2,000 part symbols including most TTL and CMOS logic, op amps, discrete symbols, and others, plus you can easily add custom symbols. SuperCAD serves as the front end to the other mentalMAX software and seamlessly interfaces to them directly through menus and display windows, including the oscilloscope window for SPICE and the analyzer window for digital simulation. Output from SuperCAD includes a netlist report and a bill of materials. You can also output drawings to AutoCAD®.

MentalMAX comes with the popular SuperPCB program for doing layouts on printed circuit boards up to 32" x 32". SuperPCB features 1 mil (.001") resolution, four signal layers, silkscreen, paste, and solder mask layers. It includes industry-standard Gerber and Excellon outputs, and you can print your artwork on laser and other printers.

The mentalMAX tools will run under Windows 3.1, 3.11, Windows 95, and Windows NT. You need about 10M of disk space and at least 4M of memory.

For more information, contact:

MENTAL AUTOMATION, INC.
5415 136TH PL., S.E., DEPT. NV
BELLEVUE, WA 98006
425-641-2141 FAX: 425-649-0767
http://www.mentala.com

ULTRASONIC LEVEL CONTROLLER



The SONA-TROL® Ultrasonic Level Controller features a sensor head which can detect changes down to .006" over a 48" distance or within 1" up to 20' over the surface. Eliminating floats, switches, and hardware subject to wear and corrosion, this non-contacting level controller can provide digital or analog readouts, 0 to 10 VDC or 4 to 20 mA outputs, and be equipped with circuits to detect false signals and compensate for surface rippling.

Ideal for use with liquids, slurries, and solids, the SONA-TROL® Ultrasonic Level Controller has a electrically isolated sensor, adjustable gain and receiver sensitivity, and distance zero offset. Incorporating a standard oil-tight JIC enclosure, sensors can be constructed from stainless steel or fiberglass and be equipped with a purge box for hazardous environments.

The SONA-TROL® Ultrasonic Level Controller is priced from $799.00 (list).

For more information, contact:

WADDINGTON ELECTRONICS, INC.
25 WEBB ST., DEPT. NV
CRANSTON, RI 02920
401-781-3904 FAX: 401-781-1650
E-MAIL: johnwn@ids.net

HIGH-PERFORMANCE RECEIVER



Neulink is now shipping its DCL-VHF-RX and DCL-UHF-RX, a high-performance, synthesized, digital receiver operating in the VHF band, 153 MHz to 173 MHz and 450 MHz to 470 MHz band, respectively. They are currently being used in the National Broadcast Emergency Alert Systems and Law Enforcement applications.

The receivers support digital data, and have excellent audio output that out-performs many high-end commercial radios. The band spread is 10 MHz in the receivers and can be tuned to any frequency in the selected band.

For more information, contact:

RF NEULINK
7610 MIRAMAR RD., DEPT. NV
SAN DIEGO, CA 92126
619-549-6340 FAX: 619-549-6345
1-800-233-1728
E-MAIL: rfneulink@aol.com

PROTOTYPING SYSTEM



AWC announces the ASP-1 prototyping system for developing hardware based on Parallax's BASIC Stamp microcontrollers. The system consists of a high-quality solderless breadboard, a power source, and two integrated programming cables (one for the Stamp I and another for the Stamp II).

Using this system, designers can easily try circuits, tear them apart, and try something different. There is no soldering or wirewrapping required. The ASP-1 is perfect for professional designers, hobbyists, and it is ideal for educational use, too.

For more information, contact:

AWC
310 IVY GLEN CT., DEPT. NV
LEAGUE CITY, TX 77573
281-334-4341
alw@al-williams.com

AUTOMATIC WIRE CUTTER



RF Industries announces the release of the RFA-4090, automatic wire and tubing cutter. Lengths from .01" to 9999" and cuts up to 9,999 pieces can be programmed and stored into the microprocessor. Pieces will run out of the calibrated machine, pre-measured and cut at the rate of 1,000 feet per hour.

For more information, contact:

RF INDUSTRIES
7610 MIRAMAR RD., DEPT. NV
SAN DIEGO, CA 92126-4202
619-549-6340 FAX: 619-549-6345
1-800-233-1728
E-MAIL: rfi@rfindustries.com

FLEXPORT™ MODULAR SERIAL I/O SYSTEM



Dataforth Corporation introduces the new FlexPort™ PC5000 Series of high-performance, serial input/output boards, and accessories for industrial PC/XT/AT ISA bus applications.

The PC5000 Series makes it easy to interface RS-232 and/or RS-485 data acquisition, control, or data lines.

The new FlexPort PC5000 System consists of two main boards that plug into the PC/XT/AT ISA bus and provide two or four serial ports; two "daughter" interface SimmPort™ modules that plug into SIMM sockets on the main cards and provide two channels each of RS-232 or RS-485 communications; RS-485 transmit and receive lines are transient protected to ANSI/IEEE C37.90-1-1989; a software driver compatible with Windows 3.1; and a special connector cable for four-channel configurations.

Prices for PC5000 FlexPort Serial I/O Systems start at $166.00.

For more information, contact:

DATAFORTH CORP.
3331 E. HEMISPHERE LOOP
DEPARTMENT NV
TUCSON, AZ 85706
520-741-1404 FAX: 520-741-0762
1-800-444-7644
E-MAIL: techinfo@dataforth.com
WEB: www.dataforth.com

WIRELESS REMOTE DATA ACQUISITION AND CONTROL SYSTEMS

Skyline base stations and remote platforms contain high speed, two watts, synthesized, transceiver modems that have 65,000 unique ID codes, error detection/correction, 64 programmable RF channels, and a repeater capability. Skyline comes in both UHF and VHF versions and has its own propriety over-the-air protocol with several options that can be configured by the user. This over-the-air protocol is transparent to the devices on either end and is configured by hooking the Skyline up to a computer through the RS232 serial port.

Continued on page 110

Continued from page 91

520-1710 KHz band, which I think is 10 KHz instead of the 5 KHz or less spacing of the shortwave bands.)

129719 **Bernard A. McIlhany**
Lebanon, GA

ANSWERS

ANSWER TO #11971 - NOV. 1997

What you mentioned will not work without some major modifications. The original pulse width for the throttle body injectors that you mentioned are computed by that analog computer and are calibrated by pulse width for a given motor and its unique conditions.

Its mixture is a formulae made up from varied input signals such as motor temperature, RPM, vacuum, oxygen sensor, and throttle settings. If this set-up comes off an eight-cylinder, two-injector throttle body set up, and you direct the signal to eight separate injectors without any pulse width modification, then the fuel pulse duration will be four times too long, making your mixture far too rich to run. Even if your computer assembly is from a four-cylinder engine. The signal length, hence the mixture quantity, will still be incorrect for any V-8 engine.

If you have a gas analyzer and scope, and add an optical sensor to your motor with four positions firing each sequence into two opposing cylinder injectors at the same time, one of the cylinders being at the intake position of the firing sequence and the other at its exhaust sequence (that cylinder will have a closed intake valve and this injection will act as a precharge), you will still need to modify all of the sensor inputs and the pulse width inside the computer so that the injector's "On Time" is correct for the exact amounts of fuel necessary for that motors exact requirements. The value variance of each input signal coming from such things as the throttle sensor or temperature gauge may also not be compatible with that computer.

Most computers are linked to an oxygen sensor that compensates for incorrect mixtures, but according to federal law they are only allowed to compensate for a minute amount of error of around two to five percent overall mixture which won't compensate for all of the errors you will run into by mismatching the motor to that computer.

It can be done, but basically you will need to completely overhaul the entire system just to get it to operate. A better way might be to start with a eight-cylinder computer off of a newer car and slightly modify it to suit your needs.

Chris
Bieber, CA

ANSWER TO #11973 - NOV. 1997

If you were able to calibrate successfully two variacs to give you a perfect out- put, then it should be easy for you to modify two commercial light dimmers to simplify your needs.

Using a double gang rotary switch you replace both of the potentiometers that normally control the light dimmer circuit with matched and calibrated value precision resistors.

You set up using the original potentiometers and reach your desired goal or phase/voltage on each dimmer and then measure each of the values off of the potentiometer on each dimmer. Copy that down because each of the dimmers potentiometers will have a slight variance between them. Measure accurately.

Do this at the three positions of your choosing and then replace the potentiometers with the switch and exact value resistors. You must use one percent tolerance resistors and even after assembling this circuit you may still find that you have to add a trimmer pot to one or more of the positions on the switch to fine tune the slight error that still occurs. The overall variance shouldn't exceed two percent depending on load, or overheating will occur.

Chris
Bieber, CA

ANSWER TO #11972 - NOV. 1997

The connection you need can be across the tip/ring connection, or

Continued on page 102

HOME PAGE: www.hamboree.org

38th ANNUAL

TROPICAL HAMBOREE® & ARRL FLORIDA STATE CONVENTION

E-MAIL: edg@elink.net

FEBRUARY 7 - 8, 1998

TALK IN: 146.925

DADE COUNTY FAIR & EXPOSITION CENTER
S.W. 112 AVENUE & CORAL WAY (S.W. 24 ST.)
MIAMI, FLORIDA
• Sponsored by Dade Radio Club of Miami, Inc.

ON-SITE EARLY-BIRD EVENTS

FEBRUARY 5 – NOVICE/TECHNICIAN EXAM THEORY REVIEW BY GORDON WEST
WITH LIVE DEMONSTRATIONS AND WORKING EQUIPMENT
9:00 A.M. - 5:00 P.M. (One Hour Lunch Break) $25.00

FIVE WPM CODE TEST PREPARATION REVIEW – 6 P.M. - 9 P.M. – $10.00

FEBRUARY 6 – GENERAL TEST CODE AND THEORY REVIEW BY GORDON WEST
9:00 A.M. - 5:00 P.M. (One Hour Lunch Break) $25.00

These will be Mr. West's only Southeast Coast classes, so sign up now and begin your home-study with ARRL or West materials. Contact Hamboree Chairman for full details.

FEBRUARY 6 – ARRL RF SAFETY WORKSHOP by Ed Hare W1RFI, ARRL Laboratory Supervisor
$20.00 ARRL Members, $25.00 Non-Members. Sign up with ARRL Education Dept., 225 Main St. Newington, CT 06111

FEBRUARY 7 - 8
RFI PRESENTATION • INTRODUCTION TO AMATEUR RADIO DISPLAY • LEGAL & FREQUENCY CHALLENGES • AMATEUR RADIO FOR THE HANDICAPPED • APRS • VHF TRANSMITTER HUNT • YOUTH FORUM • PROGRAMS BY AMSAT, ARRL, DXPEDITIONS, AND MORE • COMMERCIAL EXHIBITS • THREE SWAP AREAS • TWO ON-SITE EXAM SESSIONS • FIELD CHECKING FOR DXCC AND CQ AWARDS • NEW CRAFT SECTION & ALTERNATIVE INTEREST PROGRAMS

AIR-CONDITIONED FACILITY • ON-SITE CAMPING FOR 300 RVs • FREE PARKING FOR 15,000 VEHICLES • ATM IN MAIN BUILDING • WHEELCHAIR & STROLLER RENTALS • ADDITIONAL REFRESHMENT AREAS

Registration: $5.00 Advance (deadline Feb. 3) – Door: $7.00
Campsites: 3 days (Fri., Sat., Sun.) $45.00 • 4 days (Thur., Fri., Sat., Sun.) $60.00
Swap Tables: $28.00 each* plus reg. ticket • Power: $10.00 per user.
(Ticket price includes tax. Camping, tables and power are subject to 6.5% tax.)

HEADQUARTERS HOTELS: (All at same location/facilities & rates to meet your needs)
1201 N.W. LeJuene Road (N.W. 42nd Avenue)
MIAMI AIRPORT MARRIOTT: $140 single, double - plus tax – Tel: 800-228-9290
COURTYARD AIRPORT SOUTH: $105 single, double - plus tax – Tel: 800-321-2211
AIRPORT FAIRFIELD INN SOUTH: $72 single, double - plus tax – Tel: 800-228-2800
Mention "Tropical Hamboree" Cutoff date is January 22, 1998

TICKET, CAMP, TABLE PAYMENTS **PAYABLE TO: DADE RADIO CLUB OF MIAMI, INC.**
Mail to: Evelyn Gauzens, W4WYR, 2780 N.W. 3 St., Miami, FL 33125-5059
BOOTH & TABLE INQUIRIES: email: edg@elink.net, Tel: 305-642-4139, Fax: 305-642-1648
HOMEPAGE: www.hamboree.org

★ CopyCat ★ Software Sale!!

NOW!! BUILD And SELL your own CopyCat

Software does...1. *MOTOROLA* (includes Elite EE3 & StarTac) 2. *NEC* P100, P200, P300, P400, P600, P700! 3. *AUDIOVOX* (includes new 800)! 4. *GE-ERICSSON* (includes new version)! 5. *PANASONIC*! 6. *SONY* and 7. *MITSUBISHI/DIAMONDTEL*!

ALSO AVAILABLE...

Preloaded circuit boards, circuit board cases with display and keypad & programming cables! For pricing information, call (770) 973-8474 TODAY or visit us on the web at www.celltec.com

Circuit Boards..

7-Way StarTac as low as $495!

ABOUT US

**Midnight Communications (a division of Cellular Technology Group) was one of the first importers/distributors of the "stand alone" programmer (i.e. "black box", "copy cat", "kopy cat", etc..) WE ARE PARTICIPANTS IN THE BBB's CARE PROGRAM AND DO NOT OPERATE OUT OF A LETTER SUITE OR USE A P.O. BOX. You are invited to call or visit us at 434 Old Mill Place, Cartersville (Atlanta) GA. 30062. Purchaser of any product agrees to comply with all local, state and federal laws, including all FCC rules and regulations. All products are sold solely for EDUCATIONAL PURPOSES ONLY. VISIT US ON THE WEB `http://www.celltec.com` *NO GEORGIA SALES..*

CALL US TODAY AT 770.973.8474 or e-mail ctg@mindspring.com

MO-TECH DISTRIBUTORS
YOUR MIDWEST PANASONIC CONVERTER WHOLESALER

PANASONIC

	10 PC	20 PC	50 PC
TZPC1453G2	**$63-**	**$61-**	**$59-**

"Top of the line converter" featuring sleep timer, parental lock, standard/HRC switchable, last channel recall, favorite channel memory, and 83 channel capable.

TZPC1003	**$49-**	**$44-**	**$42-**

One of our best selling converters featuring sleep timer, parental lock, last channel recall, favorite channel memory, and 80 channel capability.

TZPC175DG2	**$89-**	**$85-**	**$82-**

Our "Top of the line" converter with volume control. Featuring sleep timer standard/HRC switchable, parental lock, last channel recall, favorite channel memory, and 83 channel capable.

PHONE (810) 739-2710
FAX (810) 739-3517

Spectrum Research

Your Design and Manufacturing Source

Electronics is our Specialty

- Complete Product Engineering
- RF Circuit Design
- Computerized Testing Lab
- Parts Acquisition
- Complete Assembly Facility
- REVERSE Engineering
- Prototype Design
- Printed Circuit Boards
- Gal and Pic Read, Program
- Local and International

(941) 921-3484

Visit our WEB SITE WWW.SPECTRES.COM

Write in 53 on Reader Service Card.

TECH FORUM

Continued from page 100

direct connect to the microphone in the handset.

In either case, get an audio transformer from Radio Shack. The transformer should be impedence 8-ohm to 600-ohm.

Optionally, get a 2-MFD capacitor, this should be a Mylar or other non-polarized (not an electrolytic, tantilum, etc., do not use a capacitor with + or - labeled). Then connect the 8-ohm side to the audio output of your voice device. Place the 2-MFD capacitor in series with the 600-ohm output. This will give you a 600-ohm output with DC blocking so it can connect directly across the phone line, or can be connected to the handset microphone.

You will also need a way to keep the line "off Hook." This can be the phone itself, but doing this, the phone handset may pick up ambient noise in the room. Also, if you use it directly across the phone line, disconnect the device when not in use.

The 2-MFD capacitor and the DC resistance of the transformer across the phone line will cause the circuit to answer an incoming call. The 20 Hz ringing voltage will cause the 2-MFD capacitor to conduct ringing voltage, and will exceed the ring trip current, and go off hook for the duration of the ring cycle. The phone will ring part of one time, then the line would go back on hook.

The effect to the caller would be picking up the phone during the first ring, and immediatly putting it back on hook.

You could optionally place a 220-ohm, 2-watt resistor in parallel with the 2-MFD capacitor.

This would provide a DC path for the line current, and the circuit would provide off-hook conditions, and audio coupling into the phone line. It would act as a telephone in this configuration.

Ed Pruitt
Keller, TX

ANSWER TO #11979 - NOV. 1997

Home Shop Machinist magazine had a six-part series (ending with the Mar./Apr. '96 issue) on building one that included circuit diagrams and parts lists. However, its stepper motor was not computer-controlled like you want. *Nuts & Volts* had an excellent article on building a three-axis stepper motor controller rig that was computer-controlled about three years ago (I've got it, but it is loaned out), more recently, *Electronics Now* had one called "Build the PC Drill" in the Feb. and Mar. '97 issues that uses two-axis computer-controlled stepper motors.

If you can't locate someone who has the HSM issues, the series has been reprinted in a single volume as "Build an EDM" by Robert Langlois. It is a bit pricey at $17.00 plus $4.50 shipping. Their address is **Village Press Publications**, P.O. Box 629, Traverse City, MI 49685-0629 or call **1-800-447-7367**. I have the issues (around here some place) if you want to correspond. Hope this helps.

Frank Nally
Louisville, KY

Continued on page 109

ACP's 84th GIANT COMPUTER SWAP MEET

Orange County's Original!

Sunday, 8am-2pm
Jan 25th

Be a Seller! ...for space call Mary...

FREE Admission & Parking
Shop 100's of Sellers

in ACP's Giant Parking Lot

Advanced Computer Products, Inc.

ACP SUPER STORE
Since 1976

1310 E.Edinger
Santa Ana, CA
714-558-8813

CopyCat

7-WAY EE3 STARTAC

*Pocket Size

*Operates on 9-volt Battery

*Easy to read LCD Display

*Easy to Operate



*We manufacture our own units

*We repair and upgrade all other units

$995

219-744-4788

Write in 94 on Reader Service Card.

(Part 3)

Encyclopedia of Electronic Circuits: PCB Layout

by TJ Byers

This unique CD-ROM contains 1,000 circuits that can be knitted together to create virtually any project imaginable. In this three-part series, I show you how to use this CD to go from concept to copper, and build a karaoke amplifier in the process.

In case you missed the first two parts of this series, let me bring you up to speed. It began with an innocent enough query from readers like you who asked, "Where do you get the answers for your Electronics Q & A column?" Well, some of the answers come from years of experience, but mostly they're the result of searching through countless stacks of trade journals and application notes. One of my many sources is the "Encyclopedia of Electronic Circuits," which I refer to as the CD-ROM of 1,000 circuits. You can buy this CD-ROM from any well-stocked software house for just $99.00.

In addition to sporting over 1,000 circuits, the CD-ROM contains the entire catalog of EDA (Electronic Design Automation) software from Mental Automation. The software lets you import a circuit from the CD-ROM and convert it into a printed circuit board. Well, that's what this series is about — going from schematic to copper clad to finished project using the CD-ROM. For this tutorial, I chose a karaoke amplifier as an example. So far, we've covered circuit capture, project design, and design modification. All this was done using SuperCAD ($99.00), the schematic capture program.

In this installment, I'll show you how to convert our schematic (Figure 1) into a printed circuit board.

Parsing The Pieces

Once you have a SuperCAD schematic on the screen, it's usually a simple process to convert it into a circuit board using the SuperPCB software. However, the transfer from schematic to copper clad isn't always seamless. For example, our schematic won't translate into a functional circuit board the way it stands. Changes have to be made to the drawing — changes that translate it from a schematic to a bill of materials drawing, so to speak.

Let's start with the power supply. First off, I don't want to have 110VAC applied to any part of the board. It presents a shock hazard, and it's not a good engineering practice to mix line voltage with low voltage. So let's remove S1, F1, T1, and the power cord from the schematic. This way they won't appear in the netlist — or on the circuit board. Instead, these parts are mounted in the cabinet and hand-wired together. In place of T1, we install a five-pin berg connector. The Power LED (D3) needs to be replaced with a berg connector, too (Figure 2).

The microphone also needs to be removed and replaced with an audio jack (Figure 3). While we're at it, let's replace J1 and J2 with a stereo phone jack (Figure 4), which will let you patch into the earphone jack of your CD, stereo, or boombox. Finally, we need to replace the speaker with a berg connector.

The potentiometers can be replaced with berg connectors, too, because (except for one) they're not on the circuit board either. They mount on the front panel. However, this isn't a wise thing to do because the symbol changes from a potentiometer to a connector — which is quite unacceptable. Fortunately, the hole spacing is identical to that of a berg con-

1



nector — 0.100 inches — so we can leave the symbol as-is.

Missing Footprints

The next order of business is to see if SuperCAD's component outlines are available in SuperPCB. Not all schematic symbols have a physical equivalent in SuperPCB. For example, SuperCAD assigns a TO5B outline to the LM383 chip — an outline that's specific to National Semiconductor and not listed in the SuperPCB library.

When the CD-ROM was cobbled, the editors had to draw the circuits by hand from the pages of the book so that they ended up in SuperCAD format. However, several of the circuits use parts that weren't in the SuperCAD component libraries at the time — parts that had to be created from scratch. Obviously, some of the editors drew their information from National Semiconductor data sheets, unaware that the TO5B outline wasn't in the SuperPCB libraries. Since most data sheets list this package as a TO220a5, I went back to SuperCAD, gave the LM383 a new outline, and saved it in the SuperCAD analog library (see Part 2 of this series for details).

Also not found in the SuperPCB library is the TO220u footprint of U3. This time, I decided that the outline is popular enough that it had to be added to the SuperPCB library. You may wonder why I sometimes refer to a SuperPCB library and other times I say libraries. It's because there are two libraries. The first is labeled L1 and the other is L2. L1 is the default library, and the only one that SuperPCB searches for footprints. Library L2 is in a separate directory, appropriately enough labeled L2. Here's where I found the TO220u footprint. A simple copy command places this footprint in the primary library.

Sizing It Up

But these are nothing compared to the capacitor footprint folly. SuperCAD assigns all electrolytic capacitors with a lead spacing of 0.600 inches and all small coupling capacitors with a 0.250-inch spacing. Obviously, changes have to be made because a 10,000uF electrolytic doesn't have the same footprint as a 10uF tantalum. What you have to do is sort through the schematic and change each capacitor's outline to match its pin spacing.

You can switch the package type on the schematic using the Custom option under the Edit menu. However, you'll need a table listing the various case styles (Figure 5) within eye shot, because the package names are somewhat confusing. After matching the capacitor to its footprint, you enter the new package style in the Package/User Defined dialog box (Figure 6) and click on OK. The schematic symbol won't change, but the resulting netlist will.

Alternatively, you can make the package changes by editing the netlist (Table 1), which is what I





did. Editing the netlist (listed under *filename*.ref) is a lot faster and simpler than hopping around the schematic from capacitor to capacitor, because it can be done using a text (ASCII) editor or word processor. Of course, you still need a copy of the package outline list.

From Ink To Copper

We are now ready to convert the squiggly lines and circles on the modified schematic (Figure 7) into copper traces and solder pads. Start by generating a circuit board using the Printed Circuit Board command under the Utilities menu (Figure 8). The dialog box gives you several options. If this is the first attempt, check the "Generate new netlist option." After that, you'll want to turn this option off, otherwise it'll overwrite any changes you may have made to the netlist.

There are three versions of the SuperPCB program to accommodate users with different needs. Table 2 lists the differences between the versions.

For this project, I used the full version of SuperPCB ($499.00) because it has an autorouter and automatic parts placement. The decision was made on the size of the project and the component count. A smaller project, such as a wireless microphone or digital thermometer, doesn't require this much power, and can be easily fabricated using one of the cheaper versions of SuperPCB.





Part Placement

With my version of SuperPCB, the parts are placed on the circuit board in what it thinks is a logical pattern (Figure 9). It never is. Notice how the autoplace algorithm placed C20 atop U1. The other versions of SuperPCB simply stack the parts in a big heap that you have to distribute. In either case, you're gonna shuffle around most of the parts by hand before you find a layout that works.

What I did first is move the jacks and berg connectors to the edge of the circuit board, where they belong. In fact, it's always a good idea to move wires and cables to the perimeter of the board whenever possible for servicing purposes. Then I looked at the schematic, and guessed where the remaining components would fit best. When moving parts, pay careful attention to the placement of the bypass capacitors — they must be kept as close as possible to their respective IC.

A useful tool for part placement is a *ratsnest* — which is listed as Rats Nest under the Process menu. This utility draws lines — not traces — between all the parts on the circuit board. If you see a long line connecting two parts, it means they should be closer together than they are (Figure 10).

Unfortunately, SuperPCB's ratsnest isn't the best I've used. It doesn't have rubber-banding — a feature that lets the lines move as the part moves. With SuperPCB, you have to move the part, erase the lines, and generate a new ratsnest. Another annoyance, albeit a common complaint with PCB layout software and not exclusive to SuperPCB, is that Rats Nest can't find the shortest path between common links, such as ground wires. What looks like a long reach may actually be a short hop.

Design Verification

The ratsnest is also a useful tool for design verification. For example, SuperCAD assigns pin 5 of the LM383 to a power source labeled V+. All the other power sources are labeled VCC. When SuperCAD generates the netlist, it doesn't catch the fact that we want V+ to be the same as VCC, so no error is generated. As far as the SuperCAD design verification is concerned, pin 5 has a connection.

But we know better. In real life, it's a dangling lead with no place to go. I didn't realize this until I looked at the ratsnest and discovered pin 5 had no connection (Figure 10). I fixed the problem by editing the netlist and moving pin 5 to the VCC

u2 ANALOG\LM383 1 TO220a5
c9 HCAPE 1 CAXL0P6
c10 VCAP 1 C47E4P
r17 VRES 1 RES4W
r18 VRES 1 RES4W
c11 VCAPE 1 CAXL0P6
r16 DEVICE\VAR_RES 1 B3292W
c8 HCAPE 1 CAXL0P6
r10 HRES1 1 RES4W
r11 HRES1 1 RES4W
r12 VRES 1 RES4W
r13 VRES 1 RES4W
q1 NPN 1 TO92
r14 VRES 1 RES4W
r15 VRES 1 RES4W
c7 VCAPE 1 CAXL0P6
r8 DEVICE\VAR_RES 1 B3292W
r7 DEVICE\VAR_RES 1 B3292W
r9 DEVICE\VAR_RES 1 B3292W
r19 VRES 1 RES4W
r21 HRES 1 RES4W
c13 VCAPE 1 CAXL0P6
c16 VCAP 1 C47E4P
r27 DEVICE\VAR_RES 1 B3292W
r20 VRES 1 RES4W
c14 HCAPE 1 CAXL0P6
c15 VCAP 1 C47E4P
r23 DEVICE\VAR_RES 1 B3292W
r25 VRES 1 RES4W
r26 VRES 1 RES4W
r28 VRES 1 RES4W
c19 HCAP 1 C47E4P
r22 HRES 1 RES4W
r24 HRES 1 RES4W
c17 VCAP 1 C47E4P
c12 HCAP 1 C47E4P
r2 HRES 1 RES4W
r6 DEVICE\VAR_RES 1 B3292W
c1 HCAPE 1 CAXL0P6
r1 VRES 1 RES4W
r5 VRES 1 RES4W
r4 VRES 1 RES4W
c3 VCAPE 1 CAXL0P6
c4 HCAP 1 C47E4P
r3 HRES 1 RES4W
c2 HCAPE 1 CAXL0P6
c18 HCAPE 1 CAXL0P6
d1 DIODE 1 DO7
d2 DIODE 1 DO7
c20 VCAPE 1 CAXL1P0
c21 VCAPE 1 CAXL0P6
c22 VCAPE 1 CAXL0P6
c5 HCAPE 1 CAXL0P6
c6 HCAPE 1 CAXL0P6
r29 VRES 1 RES4W
u3 7812 1 TO220u
u1 TL082 2 DIP8
j4 CONN5 1 WSIP5
j1 DEVICE\PJACK3 1 pjack
j2 CONN2 1 WSIP2
j5 CONN5 1 WSIP5
j3 DEVICE\PJACK 1 pjack

TABLE 1. Karaoke Netlist

line. I've since made a change to the SuperCAD library, so it won't happen again. However, you can see the trouble I would have had if it weren't for the ratsnest.

Making Tracks

The next task is to replace the ratsnest with copper tracks, or traces. Yes, you can do this by hand one track at a time, if you have the patience, but why? Spend the extra bucks and buy one of the versions that has a batch router.

Batch routing, commonly called

	SuperPCB/I	SuperPCB/R	SuperPCB (full)
Version	MA8500	MA8505	MA8510
Signal Layers	2	2	16
Router	incremental	incremental/batch	incremental/batch
Placement	manual	manual	manual/automatic
Library Parts	90	90	320
Verify Checking	manual	manual	manual/batch
Net Selection	no	no	yes
Netlist Extraction	no	no	yes
Grids	Cartesian	Cartesian	Cartesian and Polar
Max. Work Area	8" x 8"	16" x 8"	32" x 32"
Drawing Elements (traces, vias, parts)	16,000	16,000	32,000
Price	$149.00	$299.00	$499.00

SuperPCB Features

You can update at any time from SuperPCB/I/R to the SuperPCB package by paying the price difference plus shipping.

autorouting, is supported by two of the three SuperPCB programs. In the batch operation, the traces are automatically routed on one or more layers. If the router hits a roadblock, it looks for an alternate path. Sometimes it's successful, and sometimes it's not. The rate of success depends on component density, track width, and pad size and shape. In really tight spots, you can use the necking feature. Necking down is the process of narrowing a trace skinny enough to squeak between the pads of an IC's footprint.

A board can be routed using a 25-, 50-, or 100-mil grid, and component pads don't have to fall on the grid (1 mil is a thousandth of an inch). However, traces follow the grid pattern as closely as possible. So even though there may be a more direct path between two pads, the traces will hug the grid the best they can, which results in traces like you see in Figure 11. As tracks are added, they stack one atop the other, separated by a space defined in the Setup table, usually 10 mils.

In general, if you're routing a board with mostly DIP packages, then a 50-mil grid is adequate. However, I find the 50-mil grid too coarse for most layouts. My preference is 25 mils, which, oddly enough, happens to be the default spacing.

The default trace width is just 8 mils, which I find too narrow for hobby use. Instead, I prefer to use 20 mils for the track width because it's easier to work with using home etching methods.

Autorouting

To autoroute a board, click on the Batch Route option in the Process menu. A dialog box will appear (Figure 12), from which you set the trace width, routing grid, and the active layers. The Max length option (measured in mils) is used to







control the maximum length of traces on a board, which is useful for high-frequency layouts. After the router parameters are set, click on the Route button and watch the traces magically appear as the algorithm ripples through the possible combinations.

The autorouter relies heavily on vias to achieve 100 percent completion. A via is a "jumper" wire that connects the trace from one layer to another. Vias are useful for getting around roadblocks, such as an existing track. Think of them as tunnels or freeway underpasses. Unfortunately, vias are prone to failure because the hole has to be filled with a metal plating to make the connection — metal plating that's subject to physical and thermal stress. So the fewer vias you have, the better. The Optimize utility under the Process menu scours a routed board and removes unnecessary vias.

Because most readers don't have access to through-hole metal plating, my goal was to design a PC board with no vias, which I was able to do after much trial and error. All my layer-to-layer connections are made through component leads.

A Smoothing Massage

Once the traces are in place, the corners should be rounded, a process called smoothing. The smooth operation replaces 90-degree trace bends with either arcs or 45-degree bends. Smoothing has two benefits: it improves PC board yield because there's less risk of shorted traces, and it reduces RFI radiation (sharp corners are notorious for emitting noise).

The smooth operation is applied only after a board has been both routed and optimized. To initiate the smoothing, click on Smooth under the Process menu and select the type of smoothing (Figure 11).

A Sound Message

The last item on this long list of things to do is to identify the components for both fabrication and repair. Fortunately, every component has a built-in reference — the same reference found on the schematic. However, I took it a step further, and so should you.

This project, for example, has quite a few sound processing controls, specifically several tone and volume adjustments. To make things clearer, I used the Draw Text feature to identify the purpose

of these potentiometers on the PC board. Other nomenclature can be added to the board as well, such as the project's name, the date, and, most importantly, settings of DIP switches. The more information you put on the board, the less documentation it needs. The nomenclature is placed on the PC board via a silkscreen mask or by etching the message directly into a copper layer; the choice is yours.

It's A Wrap

That does it for this project, and for our review of the Encyclopedia of Electronics Circuits CD-ROM — the CD-ROM of 1,000 circuits. Of course, not all projects have to be as complex as the karaoke amplifier. I'm sure you'll find many of them suited to your needs as is. But like I pointed out, you may have to make adjustments to the artwork or components before you





can turn it into a finished project.

Next time, I'll describe the construction of the circuit board and fabrication of the karaoke amplifier. Meanwhile, you can download the PCB layout artwork from our Web site (http://www.nutsvolts.com); it's under the name KARAOKE.ZIP. **NV**

Encyclopedia of Electronic Circuits: CD-ROM – $99.00

Available from:
Mental Automation
206-641-2141 http://www.mentala.com

Includes the viewer needed to *display* the schematics on the screen. To edit the circuits or make a printed circuit board, you need the Mental Automation CAD software, which is also on the CD-ROM, but requires the purchase of a password to unlock. *(Also available at major CD-ROM outlets.)*

The Pocket Programmer



The portable programmer that uses the printer port of your PC instead of a internal card. Easy to use software that programs E(E)prom, Flash & Dallas Ram. 27(C)/28(C)/28F/ 29F/29CXXXX & 25XX series from 16K to 8 Megabit with a 32 pin socket. Adapters available for Pic, MCU's 874X, 875X, 40-Pin X 16 & Serial Eprom's, PLCC, 5-Gang and Eprom Emulator to 32K X 8. **Only $129.95**

Same Name, Address & Phone Number for 13 Years..... Now isn't that Amazing ?

Intronics, Inc.
Box 13723 / 612 Newton St.
Edwardsville, KS 66113 **Add $4.75 COD**
Tel. (913) 422-2094 **Add $4.00 Shipping**
Fax (913) 441-1623 **Visa / Master Charge**

LA PAZ
ELECTRONICS INTERNATIONAL
COMPUTER PARTS

DRAM SIMM

1MX9-70 SIMM	$12.00
4Mx9-70 SIMM	$25.00
1Mx32/36-70 72-pin SIMM (4MB)	$12/$26
2Mx32/36-70 72-pin SIMM (8MB)	$20/$39
4Mx32/36-70 72-pin SIMM (16MB)	$39/$55
8Mx32/36-80 72-pin SIMM (32MB)	$79/99
256Kx4 DIP DRAM	$3.00
1Mx1 DIP DRAM	$2.50
1Mx4-80 DIP/ZIP DRAM	$15/$14
256Kx8-60 VIDEO SOJ DRAM	$8.00
256Kx16-70 VIDEO SOJ (2CAS)	$6.00
256Kx16-70 VIDEO ZIP (2CAS/2WE)	$18/$20

CACHE SRAM

64Kx1-15ns 22-DIP	$5.50
32Kx8-15/20ns 28-DIP	$2.50/$2.00
64Kx8-15ns 32-DIP	$6.00
128Kx8-15/20ns 32-DIP Narrow	$19/$18
128Kx8-15/20/25ns 32-DIP Wide	$19/18.50/18

We carry a complete line of memory for AST, Apple, Compaq, DEC, IBM, HP, Notebooks, and printers. CALL for current prices.

✧ International Sales & Shipping ✧

CPU & CO-PROCESSORS

NE2000 NET COMBO CARD	$25.00
INTEL 486DX2-66 (5v) CPU	$39.00
INTEL 486DX4-100 (5v) CPU	$75.00
INTEL PENTIUM 133/166 CPU	$99/149
80387SX/DX CO-PROCESSOR	$19/32

MISCELLANEOUS

486 M/B+256K CACHE+100MHz CPU+8MB RAM **$129.00**

PENTIUM M/B 133MHz, 256K CACHE, 16MB RAM **$249.00**

MMX ADAPTOR *allows your M/B to accept MMX CPUs.* **$35.00**

AMD 486DX4-100+5v ADAPTOR+CPU FAN *This kit will allow you to upgrade your old M/B to a faster CPU* **$65.00**

LBA CARD *upgrade your hard drive beyond 540MB without the expense of upgrading your present BIOS* **$29.95**

SPECIALTIES
PACKARD BELL UPGRADES
CPU, CACHE, VIDEO, SIMM, & MOTHERBOARDS
CALL

* OTHER PARTS AVAILABLE, CALL FOR QUOTE * VOLUME DISCOUNTS OFFERED
* PRICES SUBJECT TO CHANGE WITHOUT NOTICE * TERMS:COD (CASH),VISA/MC
MINIMUM ORDER $20 * SHIPPING & HANDLING: $6 MIN.
ORDER LINE (800) 586-4199

P.O. BOX 261095, San Diego CA 92196
TEL (619) 586-7610 FAX (619) 586-1482
e-mail: lapazusa@pobox.com

Are you sponsoring a Hamfest, Computer Show, or Convention?

PROMOTE YOUR EVENT IN THE NUTS & VOLTS EVENTS CALENDAR

Send or fax your flyer to:
Nuts & Volts Magazine
Events Coordinator
430 Princeland Court
Corona, CA 91719
FAX
(909) 371-3052
Phone
(909) 371-8497

Write in 55 on Reader Service Card.

DB-25 male connector. By any chance, do you have the pinouts for it so I can make an adapter? Also, I have an old Amiga 1000 with what is supposed to be an RGB output on the back of it. The problem is it uses a DB-23 (yes, I said 23 pins) connector. I would like to use it with a nine-pin RGB from my PC. I don't regularly subscribe to *Nuts & Volts Magazine*, so an E-Mail reply would be appreciated.

Gary Depietro
FL

A. *What, you aren't a regular subscriber! Why not? Fortunately, you don't have to be a subscriber to get answers, and here they are (your answer is in the E-Mail, too).*

AT&T PC6300

Pin	Function	Comment
1	Horizontal sync	
2	ID0 (monitor ID)	Logic high for color; nothing for mono
3	Vertical sync	
4	Red	
5	Green	
6	Blue	
7	???	
8, 9	N/C	
10	ID1 (monitor ID)	Logic high for color; nothing for mono
11	Mode 0	
12	N/C	
13	-Degauss	I'd use a push button
14-21	GND	
22, 23	N/C	
24, 25	+15V	

Amiga *500, 1000, 2200, 2500, 3000, 3500, 4000*

Pin	Function
3	Red
4	Green
5	Blue
11	Horizontal sync
12	Vertical sync
16-20	GND

MAILBAG

In reading your response in the Oct. '97 Electronics Q & A column regarding the 400-volt vacuum tube power supply, I noted your concern that it might be difficult to locate a two-megohm, two-watt resistor. Indeed, it might — but the resistor in the circuit shown can't dissipate more than 0.08 watts at 400 volts (or 0.125 watts at 500), so a one-watt, or even a one-half watt resistor should be plenty. I suspect you specified a two-watt resistor because of its higher insulation breakdown voltage — actually a longer leakage path and more space between leads. But this is clearly overkill. In circuits operating at up to 500 volts, one watt composition resistors are routinely used, and one-half watt resistors are not uncommon with 300-400 volt drops across them. I have a suggestion which may satisfy all requirements without requiring a two-megohm, two-watt resistor: Use two one-megohm, one-half-watt resistors in series.

Michael
via Internet

Response:

I wholeheartedly agree with this conclusion. I remember when one-half watt resistors were 3/4 inches long, not the puny 1/4 inches they measure today. Nice analysis!

TJ Byers
Q & A Editor

TECH FORUM

Continued from page 102

ANSWER TO #11974 - NOV. 1997

To provide DC power to a camera is pretty simple. You can build the following circuit at the TV where you wish to monitor the activity in the baby's room, and run RG 59 or RG 6. Use RG 6 for longer runs over 100'. You will need a capactor. Typically, .001 will work fine, and a 100 Uh choke. The choke is placed in series with typically, the positive side of your 12-volt supply the other end of the choke is connected to the center conductor of the RG 59 or RG 6. The other lead of the power supply will be connected to the shield of the coax. This will provide the needed 12-volts on the line with center conductor positive, if you need opposite polarity reverse the power leads. Then connect the .001 MFD capacitor from the same point as the choke, and then to the connection to the TV. The capacitor will be a DC block to keep the DC voltage from flowing into the TV. The capacitor will provide a path for the video on channel three or four to pass. Many of these cameras have this same circuit built-in the design to allow a power/video connection in one. If your camera requires separate DC input, then build an identical circuit for the camera end of the coax, and connect the DC out at the choke.

Ed Pruitt
Keller, TX

ANSWER TO #11978 - NOV. 1997

To put video into the computer, you need a video capture board. The board can have either a composite video hack, or some have tuners that allow you to tune any channel available. You can watch the video on screen typically with any super VGA monitor, 1 meg or more.

The capture is typically any frame. rather than full motion video. The storage of full motion video takes so much space it is not practical for most computers. Even storing it on CD-ROM 650 MB you could likely get 10-15 minutes of full motion video. There are DVD Players on the market, They use CD-ROM-type media, and have typically two or more hours per DVD Disk. Currently, I am not aware of any writeable CD drives that can handle the density required for the DVD Technology. With developments in the industry, it should be available in the near future.

Ed Pruitt
Keller, TX

ANSWER TO #11975 - NOV. 1997

James Waite may already have all the stuff he needs to get a stereo theater in his living room. If he has a cable that broadcasts stereo, a TV with mono audio, a stereo amplifier, and an MTS stereo VCR.

Take the channel three out of the cable box for premiums to stereo VCR, feed the left and right audio to the stereo amplifier and the channel three RF to the TV with mono audio. For non-premiums, the cable can go directly to the cable ready MTS VCR. Place the stereo speakers on either side of the TV to suit and adjust the volume controls to suit. The TV audio can be used to fill the middle or turned down as one prefers.

In the event that one inserts a splitter in the cable and feeds the extra output to the antenna input of the FM of the stereo system, most cable companies have a whole spectrum of FM stereo programming that this arrangement will play. Just leave the TV off.

Travis Brackeen
Fayetteville, GA

reader FeedBack

Continued from page 5

are notated with the aid of multiplier values of R (= Resistance 'units' or 'ohms'), K (= 1000 ohms), or M (= 1000,000 ohms); if the component's value contains a decimal point, the point is replaced by the appropriate multiplier symbol in the actual abbreviation. For example, 510R (= 510 ohms), 47K (= 47,000 ohms), 4K7 (=4.7K = 4,700 ohms), 4M7 (= 4.7M = 4,700,000 ohms), 8R0 (= 8.0 ohms), 2R7 (= 2.7 ohms), 0R1 (= 0.1R = 0.1 ohms).

Schematic capacitance values are usually notated with the aid of multiplier values of µ (pronounced microfarad, = 1 millionth of a Farad), N (pronounced nanofarad, = 1 thousandth of a microfarad), or P (pronounced picofarad, but usually abbreviated to 'puff,' = 1 thousandth of a nonofarad). Thus, 1N0 = 1000P = 0.001µ, and 1 µ0 = 1000N = 1,000,000P.

Typical examples of capacitance values are 100P (= 0N1 = 0.1N = 0.0001µ), 47N (= 47,000P = 0.047µ), 0µ1 (= 100N = 100,000P = 0.1 µF), and 47µ (= 47,000N = 47,000,000P).

Schematic inductance values are usually notated with the aid of multiplier values of µ (pronounced microhenry, = 1 millionth of a Henry), M (pronounced millihenry, = 1 thousandth of a Henry, or H (= 1 inductive unit or 'Henry'). Thus, 1M0 = 1000µ = 0.001H.

Ray Marston

Dear Nuts & Volts:

I really enjoyed the article by Brian Mork on Disposable Cameras. I have torn everything else apart to salvage parts and to learn how they are constructed. This was a great article.

John B. Stuart
via Internet

Dear Nuts & Volts:

I was suprised to open my latest issue of N & V today and find the same article it took me two hours to search for on the Internet last night.

The article on disposable cameras was excellent. I've been hobbying in robotics for the past several months and one of the articles suggested getting the cameras for their 160 uF caps. I've been meaning to stop by the camera store for weeks. When I finally did, they gave me six or seven the first day. I was astounded to find all the useful components in something that would have been thrown away. At first, I was going to just tear out the caps and trash the rest, but my curiousity got the better of me and since I'm more of a digital electronics tech I was curious to find out how the circuit worked. Brian's article not only showed me how a flash circuit worked, he also enlightened me in the basics of charge pump power supplies. Great work. Thanks for an excellent magazine.

Biff Wheeler
via Internet

Continued from page 99

New Product News

Skyline can be used to monitor and control physical devices through a variety of I/O modules. These modules inside digital I/O, analog I/O, and various of I/O relay configurations. Up to eight I/O modules can be connected to a single remote Skyline platform. Skyline can also be configured to mimic an operation.

For more information, contact:

RF NEULINK
7610 MIRAMAR RD., DEPT. NV
SAN DIEGO, CA 92126
619-549-6340 FAX: 619-549-6345
1-800-233-1728
E-MAIL: rfneulink@aol.com

ID1 SOCKET SERIES



Hirose introduces the surface mount ID1 socket series for SIM (Subscriber Identity Module) cards.

Ultra-compact and thin, the ID1 is the world's smallest socket for SIM cards: only 2.75 mm in height, 30.6 mm in length, and 17.4 mm in width.

The ID1 series of sockets complies with the requirements of plug-in SIM cards meeting the GSM Standard. Applications include GSM Standard portable terminals and portable equipment.

The sockets are available in standard tray packaging or embossed type packaging for automatic mounting. The cost of the ID1 is $1.39 in lots of more than 500.

For more information, contact:

HIROSE ELECTRIC, INC.
2688 WESTHILLS CT., DEPT. NV
SIMI VALLEY, CA 93065
805-522-7958 FAX: 805-522-3217

COMPACT POWER SUPPLY CONNECTORS

Hirose introduces the MQ172 series of compact power supply connectors that also doubles as an I/O connector for small handheld devices.

Applications for the three-position MQ172 series include handheld devices such as cellular phones, handheld computers, and PDAs.

The lightweight MQ172 is not only space-saving (it is about 60% smaller than a typical pin jack connector), it also uses a stable two-point mating contact and a snap latch with a positive "click" connection. Durability is assured through 5,000 insertions. S-shape spring contacts prevent stressing of solder joints.

The contacts have 3 amp capacity and accommodate 24-32 AWG wiring and a choice of three keyings. Tape and reel packaging are available.

Cost of the MQ172 series is $1.20 per mated pair in lots of 1,000.

For more information, contact:

HIROSE ELECTRIC, INC.
2688 WESTHILLS CT., DEPT. NV
SIMI VALLEY, CA 93065
805-522-7958 FAX: 805-522-3217
1-800-879-8071

ACDC-620T CLAMP-ON METER



Amprobe Instrument, announces the release of their new Clamp-On meter, model ACDC-620T. The ACDC-620T is the first clamp-on meter to contain true RMS AC and DC amperage, true RMS AC and DC voltage, temperature and differential temperature, capacitance, and resistance measurement capabilities.

The circuitry allows recording to maximum, minimum, and average values of all parameters possible.

Peak values of AC voltage and current can also be measured, typically for motor inrush current applications.

The ACDC-620T comes complete with DTL-3000 test leads, CC-ACDC carrying case, MN-1604 nine-volt battery, and instruction manual.

For more information, contact:

AMPROBE INSTRUMENT
630 MERRICK RD., P.O. BOX 329
DEPARTMENT NV
LYNBROOK, NY 11563
516-593-5600 FAX: 516-593-5682

MICRO POSITIONING SYSTEM



CST, Inc. introduces the new Micro Positioning System (patents pending) for its DM718 Automatic SIMM/DIMM Handler.

This system assures a perfect match between contactors and the module tabs and helps eliminate costly retest and quality uncertainty.

This new Micro Positioning System references the modules to the JEDEC specified tooling holes instead of the variable outer edges. The module is first carried to the test site and stopped at this proximity. The center-seeking micro positioning pins lower into the two tooling holes on the module to perfectly align the module tabs to the contactors. The Micro Position is the only way to eliminate fallout on automatic memory module testing.

For more information, contact:

CST, INC.
2336 LU FIELD RD., DEPT. NV
DALLAS, TX 75229
214-241-2662 FAX: 214-241-2661
E-MAIL: cst_inc@ix.netcom.com
WEB: http://www.simmtester.com

VHF FM EXCITERS AND RECEIVERS



Hamtronics® has a new line of VHF FM transmitters and receivers.

The new T301 exciter and R301 receiver provide high-quality NBFM and FSK operation on 144-148 MHz (and 148-174 MHz for export and government services). Features include DIP switch frequency selection, low-noise synthesizer for repeater service, commercial grade TCXO for tight frequency accuracy in wide range of environmental conditions, and fast delivery with no wait for channel crystals.

The T301 exciter has exceptional modulation for voice and sub-audible tones. It uses direct FM modulation, which allows FSK transmission of data up to 9600 baud. Power output is 2-3 watts and it is rated for continuous duty in demanding applications, such as repeater service.

The T301 and R301 are available either in kit form or factory wired and tested. The T301 exciter is only $109.00 for the kit or $189.00 wired/tested. The R301 receiver is $139.00 for the kit or $209.00 wired/tested. Kits use a crystal (supplied) to generate the reference frequency, and a TCXO is optional at $40.00. Factory built units include a TCXO as standard equipment.

For more information, contact:

HAMTRONICS, INC.
65-N MOUL RD., DEPT. NV
HILTON, NY 14468-9535
716-392-9430 FAX: 716-392-9420
E-MAIL: jv@hamtronics.com
WEB: http://www.hamtronics.com

DIGITAL PAGING TRANSMITTERS

Sonik Technologies Corporation announces the introduction of its new PagePro family of low-powered digital paging transmitters. These units are designed for low-powered on-site and local area paging and are also ideal for use as exciters with high-powered power amplifiers to provide wide area coverage.

The PagePro family provides synthesized coverage in the 136-174, 218-230, 260-280, 450-470, and 470-490 MHz frequency bands. Output power is adjustable at 1-5 watts in the 136-174 MHz band and 0.5-2 watts in the other bands.

The PagePro units are packaged in compact fully-shielded metal OEM enclosures with a large heatsink to permit continuous duty operation. Rack mounting is available as an option. An RS-232 port provides convenient programming of the operating frequency and other parameters.

For more information, contact:

SONIK TECHNOLOGIES
310 VIA VERA CRUZ, STE. 111
DEPARTMENT NV
SAN MARCOS, CA 92029
760-752-1011 FAX: 760-752-1411
E-MAIL: sales@sonik.com
WEB: http://www.sonik.com

Nuts & Volts Magazine

Exploring Electronics
And Technology For The Hobbyist
And Professional

Robotics
Lasers
Communications
Computers
Microcontrollers
Automation
Alternative Energy
Much More!

Only $19 for 12 issues!

Subscribe Today!
1 800 783-4624
909 371-3052 Fax
URL — http://www.nutsvolts.com

Looking for the right crowd to promote your electronic products to?

RENT OUR LIST!

- Nuts & Volts Magazine has its mailing list available for rent to qualified electronic firms.
- The list is comprised of approximately 225,000 electronic enthusiasts in the computer, ham radio, and related fields.
- Complete or partial rentals are available.

FOR ORDERING OR MORE INFORMATION, PLEASE CONTACT:
Response Media Products, Inc.
2323 Perimeter Park Drive, Suite 200
Atlanta, Georgia 30341-1335
(770) 451-LIST · FAX (770) 451-4929

Become A Nuts & Volts Distributor!

Sell copies of Nuts & Volts to your customers

For information, write or call:

Nuts & Volts Magazine
430 Princeland Court
Corona, CA 91719

(909) 371-8497
FAX (909) 371-3052

distributors@nutsvolts.com

HOW TO PLACE A CLASSIFIED AD

TYPE or PRINT your **ELECTRONICALLY RELATED** ad copy **CLEARLY (not all caps)** on a separate piece of paper. Spell out words when submitting handwritten copy. Calculate the number of words and multiply it by the appropriate rate (see RATE PER WORD section). Include any charges for **bold** and/or CAPPED words, any artwork costs that would be applicable, and/or costs for boxing your ad (explained below). Choose the appropriate classification for your ad(s) to appear in (see below). If no classification is indicated, it will be placed in Misc. Electronics or wherever we deem most suitable. **Enclose your name, address, phone number, and *Nuts & Volts* account number from your mailing label** (if available) for identification purposes. Include full payment — **CLASSIFIEDS RUN ON A PRE-PAID BASIS ONLY** — and mail your completed order to:

NUTS & VOLTS MAGAZINE, 430 Princeland Ct., Corona, CA 91719.

RATE PER WORD

The ad rate for **current PAID subscribers** is **60¢** per word. All others pay **$1.20** per word. There is a **$9.00 minimum** charge per ad per insertion.

WORDS IN BOLD AND/OR ALL CAPS

Words to be set in **bold** or CAPS are each 10¢ extra PER WORD. **BOLD CAPS** are 20¢ extra per word. The first two words of each ad are bold capped at no charge. Indicate bold words by underlining. Words normally written in caps (e.g., IBM) and accepted abbreviations such as VAC or MHz are NOT charged as all cap words. Use a two-letter abbreviation for states.

PHOTOS, DRAWINGS, AND BOXES

A photo or drawing may be run at the top of your classified ad for an additional **$10.00** (1" depth max.) for camera-ready art. No wording is allowed in this area. Add a one-time charge of **$5.00** to enlarge, reduce, or duplicate line art, or **$8.00** for halftone of photographs. To **BOX** your ad, include an additional **$50.00** for copy-only ads, or **$75.00** for ads with art or photos.

FAXING IN AD COPY

You may fax in ad copy or changes before the closing date (5:00pm on the 10th) at 909-371-3052 using MasterCard or Visa. Include credit card expiration date, the name that appears on the card, a daytime phone number, and your *Nuts & Volts* account number. Ads without credit card information will not be listed as received until payment is received in full. **WE DO NOT CALL OR FAX BACK VERIFICATION OR QUOTES OF FAXED-IN ADS.** For verification of faxed-in ads, please call 909-371-8497.

DEADLINE

Prepaid ads received by 5:00pm on the closing date (10th of the month) will appear in the following month's issue. Ads postmarked through the 10th, but received after the closing date, will be placed in the next available issue. No cancellations or changes after the 10th. Cancellations and changes must be submitted in writing.

IMPORTANT INFORMATION

All classified ads are running copy only. No special positioning, centering, dot leaders, extra space, etc. is allowed. All advertising in *Nuts & Volts* is limited to **electronically related items ONLY**. All ads are subject to approval by the publisher. We reserve the right to reject or edit any ad submitted. We do not take ad copy or changes over the phone. We do not bill for classified ads. Repeat ads or ads run in multiple classifications within the same issue are allowed. Paid subscribers may run ads at the 60¢ rate only through their subscription expiration date. **NO REFUNDS**. Credit only. No credit for typesetting errors will be issued unless you *clearly* print or type your ad copy.

Choose a category for your ad from the classifications listed below.

10. Ham Gear For Sale
20. Ham Gear Wanted
30. CB/Scanners
40. Music & Accessories
50. Computer Hardware
60. Computer Software
70. Computer Equipment Wanted
80. Test Equipment
85. Security
90. Satellite Equipment
95. Military Surplus Electronics
100. Audio/Video/Lasers
110. Cable TV
115. Telephone/Fax
120. Components
125. Microcontrollers
130. Antique Electronics
135. Aviation Electronics
140. Publications
145. Robotics
150. Plans/Kits/Schematics
155. Manuals/Schematics Wanted
160. Misc. Electronics For Sale
170. Misc. Electronics Wanted
175. BBS & Online Services
180. Education
190. Business Opportunities
200. Repairs/Service

ADVERTISER'S INDEX

24DOT7, Inc. 49
Abacom Technologies 43
ABC Electronics 76
Ace Computers 17
ACP Super Store....102
Advanced Educational Systems 78
Alfa Electronics 36
All Electronics Corporation 72
Allison Technology Corporation 51, 74
Alltech Electronics 48
Alltronics 77
AM Research, Inc. 31
ANA Instruments 40
Andromeda Research....5
Antique Radio Classified 75
Apogee R & D Services 75
Basic Electrical Supply & Warehousing Corporation 97
Battery-Tech, Inc. 64
Baylin Publications....39
BCD Electro 74
Bell Electronics 65
Bilocon Corp. 75
Bisme Computer, Inc. 66
Brigar Electronics 16
C & S Sales, Inc. 10, 89
C and H Sales Company 68
Capital Electronics, Inc. 14, 65
CARL'S ELECTRONICS. 49
CED, Inc. 44
Cellular Technology Group 101
Chenesko Products, Inc. 50
Circuit Specialists, Inc. 114
Communications Electronics, Inc. 29
Consumertronics....41
Corporate Systems Center 2
Cruising Equipment 37
C-Tech 94
Cunard Associates....37
Danbar Sales Company 11
Detection Dynamics 75
Dexis 67, 75
Direct Cable Supply 88
DYNAMIC Technologies 95
Earth Computer Technologies....31
E.H. Yost & Co. 96
ELECTRO MAVIN....43
Electro Tool, Inc. 37
Electronic Rainbow Ind., Inc. 9
Electronix Express 66
EMAC, Inc. 82
EPS 75
Excalibur Engineering, Inc. 50
Fair Radio Sales 47
Fertik's....75
Foss Warehouse Distributors....74
Gateway Electronics, Inc. 57
General Device Instruments 74
General Science & Engineering 32
Global Connections 33
Greenleaf Electronics....59
Graymark 60
Halted Specialties Co. 3
H.T. Orr Computer Supplies....82
I.E.S. 96
Images Company 74
Information Unlimited 15
Innovation West 84
Intronics, Inc. 108
J & M Microtek, Inc. 42
Jade Products, Inc. 74
James' Electronic Services, Ltd. 73
Javanco....49
Jectech 74
JR Communications....60
KDE Electronics Corp. 84
Kimtronix 82
La Paz Electronics Int'l. 108
M2L Electronics 51
Mega Electronics 75
Metric Equipment Sales, Inc. 47
Metro Surplus....87
M.F.M. Communications 96
microEngineering Labs 84
Micro Circuits, Inc. 39
Micromint 68
Midwest Electronics 31
MING 75
Modern Communications 76
Mo-Tech Distributors 87, 102
Motron Electronics....32
Mr. NiCd 96
Netcom 5
New Company 78
One Stop Supplier 97
Optoelectronics 115
Parallax, Inc. ....Back Cover
PARAMAX, INC. 73
Phelps Instruments 22
Pioneer Hill Software 22
Point Six, Inc. 35
Polaris Industries 51
Prairie Digital, Inc. 75
Prime Electronic Components, Inc. 32
QB VIDEO 22
QTRONICS 67
Quality Electronics 91
R & S Surplus 40
Ramsey Electronics, Inc. 28
R.B. USA 42
Resources Un-Ltd. 7
R.E. Smith 74
RMV Electronics, Inc. 75
Roger's Systems Specialist....30
S & N Cellular 42
Sam's Electronics....40
Scott Edwards Electronics 81
Seabird Technical 75
Shreve Systems 74
Sinaco Electronics 74
Skycraft Parts & Surplus, Inc. 82
Solutions Cubed 78
Spectrum Research 102
Square 1 Electronics 31
Street Smart Security 6
Sun Equipment Corporation 8
Surplus Sales of Nebraska 21
Surplus Traders 74
Synergetics 92
Techniks, Inc. 74
Technological Arts 74
Teleview Distributors....58
Test Equipment Plus 43
The Filter Company, Inc. 87
The RF Connection....84
Timeless Products 65
Timeline, Inc. 21
Tornado Communications 67
Tropical Hamboree & ARRL Florida State Convention 100
Unicorn Electronics 60
USI Corp. 68
V&V Mach. & Equipment, Inc. 75
ValueTronics International, Inc. 6
VersaTech Electronics 44
Video Media 75
Viking International 33
Visitect, Inc. 68
Weeder Technologies 76
Western Test Systems 26, 27
White-Star Electronics 21
Wholesale Cable 44

ADVERTISERS INDEX



AMATEUR RADIO & TV

Abacom Technologies 43
Alltronics 77
Communications Electronics, Inc. 29
Jade Products, Inc. 74
Ramsey Electronics, Inc. 28
The RF Connection 84

BATTERIES/CHARGERS

Battery-Tech, Inc. 64
Cruising Equipment 37
Cunard Associates 37
E.H. Yost & Co. 96
Jade Products, Inc. 74
Mr. NiCd 96
Solutions Cubed 78

BUSINESS OPPORTUNITIES

24DOT7, Inc. 49
Chenesko Products, Inc. 50

BUYING ELECTRONIC SURPLUS

ABC Electronics 76
Alltech Electronics 48
Bell Electronics 65
C and H Sales Company 68
Dexis 67, 75
Earth Computer Technologies 31
Metric Equipment Sales, Inc. 47
Roger's Systems Specialist 30
Skycraft Parts & Surplus, Inc. 82

CABLE TV

Basic Electrical Supply & Warehousing Corporation 97
CARL'S ELECTRONICS 49
C-Tech 94
Direct Cable Supply 88
DYNAMIC Technologies 95
Foss Warehouse Distributors 74
Greenleaf Electronics 59
I.E.S. 96
James' Electronic Services, Ltd. 73
KDE Electronics Corp. 84
Kimtronix 82
Mega Electronics 75
Metro Surplus 87
Modern Communications 76
Mo-Tech Distributors 87, 102
New Company 78
One Stop Supplier 97
QB Video 22
QTRONICS 67
Quality Electronics 91
R.B. USA 42
Sam's Electronics 40
Teleview Distributors 58
The Filter Company, Inc. 87
Timeless Products 65
Tornado Communications 67
Video Media 75
White-Star Electronics 21
Wholesale Cable 44

CB/SCANNERS

Communications Electronics, Inc. 29
USI Corp. 68

CCD CAMERAS/VIDEO

Detection Dynamics 75
Images Company 74
Polaris Industries 51
Ramsey Electronics, Inc. 28
Resources Un-Ltd. 7
Seabird Technical 75
Timeline, Inc. 21
USI Corp. 68

COMPONENTS

BCD Electro 74
Capital Electronics, Inc. 14, 65
Electronix Express 66
Images Company 74
Javanco 49
MING 75
Skycraft Parts & Surplus, Inc. 82
Surplus Sales of Nebraska 21
Unicorn Electronics 60
Visitect, Inc. 68

COMPUTER

Hardware

Ace Computers 17
ACP Super Store 102
Allison Technology Corp. 51, 74
Alltech Electronics 48
AM Research, Inc. 31
Bisme Computer, Inc. 66
Consumertronics 41
Corporate Systems Center 2
Earth Computer Technologies 31
ELECTRO MAVIN 43
EPS 75
General Device Instruments 74
Halted Specialties Co. 3
Innovation West 84
La Paz Electronics Int'l. 108
Midwest Electronics 31
MING 75
Prime Electronic Components, Inc. 32
Roger's Systems Specialist 30
Shreve Systems 74
Techniks, Inc. 74

Software

AM Research, Inc. 31
Bisme Computer, Inc. 66
Innovation West 84
Pioneer Hill Software 22

Microcontrollers / I/O Boards

Abacom Technologies 43
Advanced Educational Systems 78
AM Research, Inc. 31
Bisme Computer, Inc. 66
EMAC, Inc. 82
J & M Microtek, Inc. 42
Micro Circuits, Inc. 39
Micromint, Inc. 68
MING 75
Motron Electronics 32
Parallax, Inc. .....Back Cover
PARAMAX, INC. 73
Point six, Inc. 35
Prairie Digital, Inc. 75
R.E. Smith 74
RMV Electronics, Inc. 75
Scott Edwards Electronics 81
Solutions Cubed 78
Square 1 Electronics 31
Technological Arts 74
VersaTech Electronics 44

Printers/Printer Supplies

Chenesko Products, Inc. 50
H.T. Orr Computer Supplies 82

DESIGN/ENGINEERING SERVICES

Apogee R&D Services 75
Capital Electronics, Inc. 14, 65
J & M Microtek, Inc. 42
Spectrum Research 102
V&V Mach. & Equipment, Inc. 75

EDUCATION

Advanced Educational Systems 78
EMAC, Inc. 82
Sun Equipment Corporation 8

EVENTS/SHOWS

ACP Super Store 102
Tropical Hamboree & ARRL Florida State Convention 100

KITS

Alltronics 77
C & S Sales, Inc. 10, 89
CARL'S ELECTRONICS 49
Earth Computer Technologies 31
Electronic Rainbow Ind., Inc. 9
EMAC, Inc. 82
Gateway Electronics, Inc. 57
Information Unlimited 15
Jade Products, Inc. 74
Ramsey Electronics, Inc. 28
Scott Edwards Electronics 81
USI Corp. 68
Weeder Technologies 76

LASERS

Information Unlimited 15
Resources Un-Ltd. 7
Unicorn Electronics. 60
All Electronics Corporation. 72
Alltech Electronics 48
Brigar Electronics 16
C and H Sales Company 68
Circuit Specialists, Inc. 114
Consumertronics 41
Electronic Rainbow Ind., Inc. 9
Fair Radio Sales 47
Fertik's 75
Gateway Electronics, Inc. 57
General Science & Engineering 32
Halted Specialties Co. 3
Javanco 49
Prime Electronic Components, Inc. 32
Resources Un-Ltd. 7
Shreve Systems 74
Skycraft Parts & Surplus, Inc. 82
Surplus Traders 74
Unicorn Electronics 60
Viking International 33
Visitect, Inc. 68
Weeder Technologies 76

PROGRAMMERS

Andromeda Research 5
General Device Instruments 74
Intronics, Inc. 108
J & M Microtek, Inc. 42
M2L Electronics 51
microEngineering Labs 84
Sinaco Electronics 74

PUBLICATIONS

Antique Radio Classified 75
Consumertronics 41
Netcom 5
Square 1 Electronics 31
Surplus Sales of Nebraska 21
Synergetics 92

ROBOTICS

Abacom Technologies 43
Images Company 74
Graymark 60
PARAMAX, INC. 73
RMV Electronics, Inc. 75
Solutions Cubed 78

SATELLITE

Baylin Publications 39
CARL'S ELECTRONICS 49

SECURITY

Information Unlimited 15
Polaris Industries 51
Street Smart Security 6
USI Corp. 68
Visitect, Inc. 68

SOLAR EQUIPMENT

Cruising Equipment 37

STEPPER MOTORS

Alltronics 77
PARAMAX, INC. 73

TELEPHONE/CELLULAR

Bilocon Corp. 75
Cellular Technology Group 101
Communications Electronics, Inc. 29
Jectech 74
JR Communications 60
M.F.M. Communications 96
S & N Cellular 42
Weeder Technologies 76

TEST EQUIPMENT

ABC Electronics 76
Alfa Electronics 36
Allison Technology Corp. 51, 74
ANA Instruments 40
Bell Electronics 65
C & S Sales, Inc. 10, 89
C and H Sales Company 68
CED, Inc. 44
Cruising Equipment 37
Danbar Sales Company 11
Dexis 67, 75
Electro Tool, Inc. 37
Excalibur Engineering, Inc. 50
Intronics, Inc. 108
Metric Equipment Sales, Inc. 47
Optoelectronics 115
Phelps Instruments 22
Pioneer Hill Software 22
R & S Surplus 40
Seabird Technical 75
Sun Equipment Corporation 8
Test Equipment Plus 43
ValueTronics International, Inc. 6
Western Test Systems 26, 27

TOOLS

Electro Tool, Inc. 37
Intronics, Inc. 108
Sun Equipment Corporation 8
The RF Connection 84
White-Star Electronics 21

WIRE/CABLE & CONNECTORS

Global Connections 33
Javanco 49
Roger's Systems Specialist 30
The RF Connection 84

Fantastic DMM Offer!!!

Don't let the price fool you. This meter is a digital multimeter designed for engineers and hobbyists. Equipped with 5 functions and 19 ranges. Each test position is quickly and easily selected with a simple turn of the FUNCTION/RANGE selector rotary switch.

Rubber Boot Included

Our Best Offer Ever on a High Quality Full Sized DMM

$19.00 any qty

General

Display: 3-1/2 Digit LCD, 21mm Figure Height with Automatic Polarity
Overrange Indication: 3 Least Significant Digits Blank
Temperature for Guaranteed Accuracy: 23°C±5°C RH<75%
Temperature Ranges:
Operating: 0°C to 40°C (32°F to 104°F)
Storage: -10°C to 50°C (14°F to 122°F)
Power: 9V Alkaline or Carbon-Zinc Battery(NEDA1604)
Low Battery Indication: BAT on Left of LCD Display
*Dimensions:*188mm long x 87mm wide x 33mm thick
Net Weight: 400g

DC Voltage (DCV)

Range:	*Resolution:*	*Accuracy:*
200mV	100µV	
2000mV	1mV	
20V	10mV	±(1%rdg+2dgts)
200V	100mV	
1000V	1V	

Maximum Allowable Input: 1000V DC or Peak AC.

DC Current (DCA)

Range:	*Resolution:*	*Accuracy:*
200µA	100nA	
2000µA	1µA	±(1.2%rdg+2dgts)
20mA	10µA	
200mA	100µA	
10A	10mA	±(1.2%rdg+2dgts)

Overload Protection: mA Input. 2A/250V fuse.

AC Voltage (ACV)

Range:	*Resolution:*	*Accuracy:*
200V	100mV	±(1.2%rdg+10dgts)
750V	1V	

Resistance (Ω)

Range:	*Resolution:*	*Accuracy:*
200Ω	100mΩ	
2000Ω	1Ω	
20KΩ	10Ω	±(1.2%rdg+2dgts)
200KΩ	100Ω	
2000KΩ	1KΩ	
20MΩ	10KΩ	±(2%rdg+10dgts)

Maximum Open Circuit Voltage: 2.8V

Diode Test
Measures forward voltage drop of a semiconductor junction in mV test current of 1.5mA Max.

ohFE Test
Measures transistor hFE.

Frequency Range: 45Hz-450Hz
Maximum Allowable Input: 750V rms
Response: Average Responding. Calibrated in rms of a Sine Wave.

CAT NO	DESCRIPTION	PRICE
9300G	Rugged High Quality DMM with Rubber Boot	$19.00

Switchable Scope Probe Sets

(Selectable X1/Ref/X10)
These high quality scope probe sets are for oscilloscopes up to 60MHz (model HP 9060) or 150MHz (model HP9150). Both sets include a handy storage pouch and include an IC test-hook adapter for the probe. The BNC connector rotates to avoid cable tangle or kink. Cable length is 1.4 meters.

CAT NO	DESCRIPTION	PRICE EACH 1	10	100
HP-9060	Scope Probe Set DC~60MHz	$16.49	$14.49	$11.58
HP-9150	Scope Probe Set DC~150MHz	24.95	21.95	18.62

CCD Camera - IR Responsive

As Low As $85!!

This black and white monochrome CCD Camera is totally contained on a PCB (70mm x 46mm). The lens is the tallest component on the board (27mm high from the back of the PCB) and it works with light as low as 0.1 lux. It is IR Responsive for use in total darkness. It comes with six IR LED's on board. It connects to any standard monitor, AUX or video input on a VCR or through a video modulator to a TV. Works with a REGULATED 12V power supply (11V-13V). Hooks up by connectiong three wires: red to 12V, black to ground (power & video) and brown to video signal output.

Power Supply Regulating Kit for CA-H34 This simple kit is designed to fit onto the back of the CA-H34 CCD camera. It resolves the problem of hooking up the camera to an UNREGULATED supply (which damages the camera) by providing safe regulated power from any 12V-14V DC supply. It also provides regulated 12V DC from a 12V AC source.

CAT NO	DESCRIPTION	PRICE EACH 1	5
CA-H34A	PCB Mounted IRCCD Camera	$99.00	$85.00
A34	Power Supply Regulating Kit	$6.95	----

PM-128: 3-1/2D LCD Digital Panel Meter; PM-129: 3-1/2D LED Digital Panel Meter

Features
- 200mV Full Scale Input Sensitivity
- PM-128 - Single 9VDC Operation
- PM-129 - Single 9VDC Operation
- Decimal Point Selectable
- PM-128 - 13mm Figure Height
- Automatic Polarity Indication
- Guaranteed Zero Reading for 0 Volt Input
- High Input Impedance (>100Mohm)

Specifications - PM-128/PM-129

Maximum Input	: 199.9mV DC
Maximum Display	: 1999 counts (3-1/2 Digits) w/Automatic Polarity Indication
Indication Method	: PM-128 - LCD Display PM-129 - LED Display
Measuring Method	: Dual-Slope Integration A/D Converter System *(cont.)*
(cont.)	
Overrange Indication	: "1" Shown in the Display
Reading Rate Time	: 2-3 Readings per sec.
Input Impedance	: >100 Mohm
Accuracy	: +-0.5% (23+-5°C, <80% RH)
Power Dissipation	: PM-128 - 1mA DC PM-129 - 60mA DC
Decimal Point	: Selectable w/Wire Jumper
Supply Voltage	: PM-128 - 9V DC PM-129 - 9V DC
Size	: 67mm x 44mm

Applications Include:
- Voltmeter
- Thermometer
- pH Meter
- dB Meter
- Watt Meter
- Current Meter
- Capacitance Meter
- LUX Meter
- LCR Meter
- Other Industrial & Domestic Uses

Positive Photo Resist Pre-Sensitized Printed Circuit Boards

These pre-sensitized printed circuit boards are ideal for small production runs. They provide high resolution and excellent line width control. High sensitive positive resist coated on 1oz. copper foil allows you to go direct from your computer plot or art work layout. No need to reverse art.

Single-Sided, 1oz. Copper Foil on Paper Phenolic Substrate

CAT NO	DESCRIPTION	PRICE EACH 1	10	50
PP101	100mm x 150mm/3.91" x 5.91"	$2.55	$1.90	$1.70
PP114	114mm x 165mm/4.6" x 6.6"	2.98	2.45	1.98
PP152	150mm x 250mm/5.91" x 9.84"	5.40	3.98	3.60
PP153	150mm x 300mm/5.91" x 11.81"	6.15	4.48	4.10
PP1212	305mm x 305mm/12" x 12"	12.78	10.65	8.52

Single-Sided, 1oz. Copper Foil on Fiberglass Substrate

CAT NO	DESCRIPTION	PRICE EACH 1	10	50
GS101	100mm x 150mm/3.91" x 5.91"	$ 3.90	$2.98	$2.60
GS114	114mm x 165mm/4.6" x 6.6"	4.80	3.49	3.20
GS152	150mm x 250mm/5.91" x 9.84"	8.69	5.98	5.78
GS153	150mm x 300mm/5.91" x 11.81"	10.20	7.20	6.80
GS1212	305mm x 305mm/12" x 12"	18.88	15.73	12.59

Double-Sided, 1oz. Copper Foil on Fiberglass Substrate

CAT NO	DESCRIPTION	PRICE EACH 1	10	50
GD101	100mm x 150mm/3.91" x 5.91"	$ 5.07	$3.68	$3.38
GD114	114mm x 165mm/4.6" x 6.6"	5.95	4.29	3.99
GD152	150mm x 250mm/5.91" x 9.84"	10.47	7.39	6.98
GD153	150mm x 300mm/5.91" x 11.81"	11.95	8.69	8.30
GD1212	305mm x 305mm/12" x 12"	22.09	18.35	14.68

Developer

This product is used as the developer on our positive photo-resist printed circuit boards. Includes instructions. 50 gram package, mixes with water, makes 1 quart.

CAT NO	DESCRIPTION	PRICE EACH 1	10	25
POSDEV	Positive Developer	$ .95	$ .80	$ .50

Etching Tank

This handy etching system will handle PC boards up to 8" x 9", two at a time. Ideal for etching your PCB's! System includes an air pump for etchant agitation, a thermostatically controlled heater for keeping etchant at optimum temperature and a tank that holds 1.35 gallons of etchant. A tight fitting lid is also supplied to prevent evaporation when system is not being used. Typical etching time is reduced to 4 minutes on 1oz. copper board!

CAT NO	DESCRIPTION	PRICE
12-700	Etch Tank System	$37.95

REDUCES ETCHING TIME!

Etching Chemicals/Ferric Chloride

A dry concentrate that mixes with water to make 1 pint of etchant, enough to etch 400 sq. inches of 1oz board.

CAT NO	DESCRIPTION	PRICE EACH 1	5
ER-3	Makes 1 pint	$3.50	$2.75

Digital Panel Meters (LCD & LED)

3-1/2 Digit LCD 3-1/2 Digit LED 4-1/2 Digit LCD

PM-328: 4-1/2D LCD Digital Panel Meter

Don't let the prices fool you. These digital panel meters are not surplus, so even if you design them into an ongoing manufactured product, you can be assured of continued availability. These high quality digital panel meters are decimal point selectable with guaranteed zero reading at zero volts input.

Specifications - PM-328

Maximum Input	: 199.99mV DC
Maximum Display	: 19999 counts (4-1/2 Digits) w/Automatic Polarity Indication
Indication Method	: LCD Display
Overrange Indication	: "1" Shown in the Display
Input Impedance	: >100 Mohm
Accuracy	: +-0.05% (23+-5°C, <80% RH)
Power Dissipation	: 1mA DC
Decimal Point	: Selectable w/Wire Jumper
Supply Voltage	: 9V DC
Size	: 67mm x 44mm

Features:
- 200.00mV Full Scale Input Sensitivity
- Single 9V DC Operation
- Decimal Point Selectable
- 11mm LCD Figure Height
- Automatic Polarity Indication
- Low Battery Detection and Indication
- High Input Impedance (>100 Mohm)

CAT NO	DESCRIPTION	PRICE EACH 1	10	25	100	250
PM-128	3-1/2 Digit LCD Panel Meter	$ 9.90	$ 7.09	$ 6.40	$ 5.86	$ 5.25
PM-129	3-1/2 Digit LED Panel Meter	11.49	9.54	8.67	7.95	6.95
PM-328	4-1/2 Digit LCD Panel Meter	19.88	16.40	14.90	13.66	11.93

!!!!!!!!!! SEE OUR ON-LINE CATALOG AT www.cir.com !!!!!!!!!!

Circuit Specialists Inc. www.cir.com

SINCE 1971
CIRCUIT SPECIALISTS, INC.
800-811-5203
602-464-2485
602-464-5824(FAX)

WE ACCEPT: VISA MasterCard NOVUS

RECEIVE OUR LATEST 132 PAGE CATALOG!

It's chock full of all types of electronic equipment and supplies. We've got I.C.'s. capacitors, resistors, pots, inductors, test equipment, breadboarding supplies, PC supplies, industrial computers, data acquisition products, personal computers and computer parts, plus much, much more. FAX us your name and address or call 800-811- 5203, ext. 5, to leave a message on our catalog request line. ***www.cir.com***

SALE PRICE

$349

DB32 Antenna Optional

Pat. No. 5,471,408

Capture the Savings

Limited time only

SAVE

$100

Sale ends January 31, 1998
No Dealer Sales

The Scout® is the latest advancement in hand-held frequency counters; a frequency recorder that excels at finding and recording frequencies. The Scout frequency recorder is a revolutionary device that can **record up to 400 unique frequencies and store them in memory.**

FEATURES

- Stores 400 Frequencies in memory
- Records up to 255 hits per frequency
- 10 digit LCD display with 16 segment RF bargraph
- Reaction Tune with AR8000, ICOM R7000, R7100, R8500, R9000, ICR10, Optoelectronics New R11 Test Receiver, and the Radio Shack Pro 2005/6 with the OS456 or OS456Lite installed or the Radio Shack Pro 2035/42 with the OS535 installed
- Download recorded frequencies to a PC using the optional OPTOLINX
- Beeper and Vibrator function will alert you when a frequency has been captured
- 10MHz - 1.4GHz frequency range
- Supplied with rapid charge NiCad batteries (8 hour discharge time)
- Recall mode: View all 400 frequencies and number of hits stored in memory
- Patented Digital Auto Filter and Digital Auto Capture
- Nearfield reception: Up to 300 feet distance with 5 watt UHF transmitter

Reaction Tune with the R11

Reaction Tune with the AR8000

Reaction Tune with the ICR10

© 1997, Optoelectronics, Inc.

FACTORY DIRECT ORDER LINE 800•327•5912

OPTOELECTRONICS®

5821 NE 14th Avenue • Ft. Lauderdale, FL 33334

Visa • MasterCard • C.O.D. • Prices and Specifications are subject to change without notice

Telephone: 954•771•2050 Fax: 954•771•2052 Email: sales@optoelectronics.com

www.optoelectronics.com

MADE IN USA

Write in 124 on Reader Service Card.

PARALLAX™

888.512.1024 (toll free)
916.624.8333
916.624.8003 fax
Monday-Friday 7 am to 5 pm PST

Tiny computers run PBASIC programs

BASIC Stamps are small computers programmed in Parallax BASIC (PBASIC), a simple programming language with powerful I/O instructions. The Parallax web site (http://www.parallaxinc.com) provides free software, manuals, and application notes.

BASIC Stamp® Modules

BS1-IC Module (#BS1-IC) $34
8 I/O lines; 80 PBASIC instr max; 2000 instr/sec; 2400 baud serial I/O; 14-pin SIP module. PBASIC language with I/O instructions including BUTTON, HIGH, INPUT, LOW, OUTPUT, POT, PULSIN, PULSOUT, PWM, REVERSE, SERIN, SEROUT, SOUND, and TOGGLE.

BS2-IC Module (#BS2-IC) $49
16 I/O lines; 500 PBASIC instr max; 4000 instr/sec; 50k baud serial I/O; 24-pin DIP module. Similar language as BS1-IC, plus DTMF, FREQOUT, SHIFTIN and SHIFTOUT, XOUT (X-10 powerline control), etc. I/O function have a higher resolution on the BS2-IC, due to its faster clock speed.

Starter Kits

BASIC Stamp I Starter Kit (#27205) $99
BASIC Stamp II Starter Kit (#27203) $149
Starter Kits include BS1-IC or BS2-IC module, carrier board w/prototype area & 9V battery clip, manual, application notes, software,and free tech support.

NEW! **BASIC Stamp Activity Board (#27905) $79**
is used to learn and experiment with BS1-IC and BS2-IC modules. All components and current limit resistors are prewired to BASIC Stamp I/O pins. Board doubles as a "carrier board" with strip header access to I/O pins. Features include LEDs, pushbuttons, piezospeaker, an RC network for changing PWM into a smooth analog output, and an X-10 interface via RJ-11. Sample source code and power supply included!

2-line x 16 character LCD Display (#27910) $54
4-line x 20 character LCD Display (not shown #27919) $109
Use the BASIC Stamp's SEROUT instruction (requires one I/O line, ground and power) to communicate with the Serial LCD display.

Using the PBASIC **HIGH** command and a 470 ohm resistor, BASIC Stamps can **electrify BLUE LEDs!** A stamper necessity! **(#27355) $8**

BASIC Stamp Bug (#27922) $129
(pictured above near Parallax Inc logo)
The BASIC Stamp Bug is a walking robot with 6 legs that is controlled by the BASIC Stamp I interpreter chip. Antennas under the LED eyes attatch to switches which detect obstacles and inform the robot to maneuver around them.

Kevin Kelm is an anthropomorphic enthusiast in Denver, CO. "Sir Karl" is a full size knight costume that uses a BASIC Stamp module to control ear, eye, and facial movements. See Sir Karl's construction and PBASIC code at http://www.xvt.com/users/kevink/furry/build.html

Milford Instruments of the UK uses 3 networked BS2-IC modules in their Laser Velocity and Imaging equipment, which measures the speed of projectiles travelling at up to 10km/sec. One BS2-IC looks after the user interface, another manages the steering logic, and the third gives additional I/O capabilities.

•**Australia** +61 67 722 777, +61 39 338 3306 •**Austria** +49 5232 8171 •**Belgium** +32 4 377 5151 •**Bulgaria** +359 2 72 77 50 •**Brazil** +55 11 453 5588, +55 11 801 0045 •**Canada** (514) 336-9426 •**Czech Republic** +42 49 5813 252 •**Finland** +358 31 266 1885 •**France** +33 328 550 328 •**Germany** +49 5232 8171 •**Greece** +30 1 902 0115 •**Hungary** +36 1270 7680 •**India** +91 422 232 561 •**Ireland** +44 1 977 683 665, +35 31 821 5060 •**Israel** +972 3 498 543 •**Italy** +39 0542 55400 •**Japan** +81 3 3251 1779 •**Netherlands** +31 10 450 4949 •**New Zealand** +64 947 82323 •**Poland** +48 34 648 882 •**Slovak Republic** +42 7 580 2574 •**South Africa** +27 11 493 6242 •**Sweden** +46 431 41 00 88 •**Switzerland** +49 241 918 900 •**Taiwan** +886 2 647 1978 •**Thailand** ++66 2 739 1181 •**United Kingdom** +44 1 977 683 665 •**United States** 818 882-7621, 800 344-4539 **(Digi-Key)**, 800 831-4242 **(Jameco)**, 800 538-5000 **(JDR)**, 800 652-6733 **(Marlin P. Jones)**, 415 491-4600 **(Mondo-Tronics)**, 800 843-7422 **(Radio Shack Unlimited)**, 303 512-2060 **(TechAmerica)**

the Parallax Inc logo and BASIC Stamp are registered trademarks of Parallax Inc

Write in 194 on Reader Service Card.

NUTS & VOLTS MAGAZINE
430 PRINCELAND COURT
CORONA, CA 91719

ADDRESS CORRECTION REQUESTED

BULK RATE
U.S. POSTAGE
PAID
V.Q.S.
ENTERPRISES